Unit: mm

TOSHIBA Transistor Silicon PNP Triple Diffused Type (Darlington power transistor)

2SB1682

- O Power Amplifier Applications
- High-Power Switching Applications
- High-breakdown voltage: $V_{CEO} = -160 \text{ V (min)}$
- Complementary to 2SD2636


Maximum Ratings (Tc = 25°C)

Characteristic Sy		mbol	Rating	Unit	
Collector-base voltage		V_{CBO}	-160	V	
Collector-emitter voltage		V_{CEO}	-160	V	
Emitter-base voltage		V _{EBO}	-5	V	
Collector current	DC I	С	-8	А	
	Pulse I	СР	− 15		
Base current		ΙΒ	-1	Α	
Collector power dissipation		PC	100 W		
Junction temperature		Tj	150	°C	
Storage temperature range		T _{stg}	-55 to 150	°C	

15.9MAX. Ø3.2±0.2 2.0±0.3 1.0=0.25 5.45±0.2 XYWW 1.Base 2.Collector(heatsink) 3.Emitter JEDEC JEITA TOSHIBA 2 -16C1A

Weight: 4.7 g (typ.)


Equivalent Circuit




Electrical Characteristics (Tc = 25°C)


Characteristic S		ymbol	Test Conditions	Min	Тур.	Max	Unit
Collector cut-off current		I _{CBO}	V _{CB} = -160 V, I _E = 0	_	_	-10	μА
Emitter cut-off current		I _{EBO}	V _{EB} = -5 V, I _C = 0	_	_	-10	μА
Collector-emitter breakdown voltage		V (BR) CEO	$I_C = -10 \text{ mA}, I_B = 0$	-160	_	_ V	
DC current gain		h _{FE (1)}	V _{CE} = -4 V, I _C = -1 A	500	_	_	
		h _{FE (2)}	V _{CE} = -4 V, I _C = -7 A	5000	— 1	5000	
Collector-emitter saturation voltage		V _{CE (sat)}	I _C = -7 A, I _B = -7 mA	_	_	-3.0 V	
Base-emitter voltage		V _{BE}	V _{CE} = -4 V, I _C = -7 A	_	_	-3.0 V	
Transition frequency		f _T	V _{CE} = -10 V, I _C = -1 A	— 35		— MI	l z
Switching Time	Turn-on Time	t _{on}	$ B1 \longrightarrow B2 $ $ B1 \longrightarrow B2 $ $ B1 \longrightarrow B1 $ $ B1 \longrightarrow B2 $ $ B2 \longrightarrow B2 $ $ B1 \longrightarrow B2 $ $ B2 \longrightarrow B2 $ $ B2 \longrightarrow B2 $ $ B3 \longrightarrow B2 $ $ B4 \longrightarrow B4 \longrightarrow B2 $ $ B4 \longrightarrow B4 \longrightarrow$	— 0.	7	_	
	Storage Time	t _{stg}		— 1.	3	-	μS
	Fall Time	t _f		— 0.	7	ı	


Marking





2 2005-07-27















3 2005-07-27

Safe Operating Area



Collector-emitter voltage -V_{CE} (V)

4 2005-07-27

RESTRICTIONS ON PRODUCT USE

Handbook" etc..

030619EAA

• The information contained herein is subject to change without notice.

document shall be made at the customer's own risk.

- The information contained herein is presented only as a guide for the applications of our products. No responsibility
 is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from
 its use. No license is granted by implication or otherwise under any patent or patent rights of TOSHIBA or others.
- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
 In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and

conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability

- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this
- TOSHIBA products should not be embedded to the downstream products which are prohibited to be produced and sold, under any law and regulations.