

AS3695A

16 channel white LED driver for LCD backlight

Product Specification, Confidential



General Description

The AS3695A is a 16 channels precision LED driver for use in LCD-backlight panels.

Dynamic power feedback controls the external power supply to guarantee best efficiency. Build in safety features include thermal shutdown as well as open and short LED detection. The device is programmable via serial interface.


- 16 Channel LED driver
- Output voltage max. 30V
- Output current 120mA
- Linear current setting using 10-bit DAC
- Current accuracy $\pm 0.5\%$ @ VDAC=250mV
- Channel to Channel current accuracy $\pm 0.2\%$
- Output slew rate programmable
- Current programmable with external resistor
- Digital current control with 16 independent PWM generators
- Free programmable 12 bit resolution (period, high time and delay)

- PWM-generator clock
 - Internal RC-oscillator
 - External Clock
- H-Sync, V-Sync inputs to synchronize with TV-set
- Direct PWM mode
- Undervoltage detection (open LED)
- Undervoltage auto-turnoff
- Overvoltage detection (short LED)
- Overvoltage auto-turnoff
- Temperature shutdown
- Register lock/unlock function
- Fault interrupt output
- 2 configurable supply regulation feedback outputs
- SPI interface
- 6kV ESD at current sink inputs
- 2kV ESD at all other pins
- Package QFN48 7x7mm, 0.5mm pitch


Applications

LED backlighting for LCD – TV sets and monitors

1 Block diagram



2 Typical application



3 Electrical Characteristics

3.1 Absolute Maximum Ratings

Stresses beyond those listed may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions beyond those indicated in Section "Electrical Characteristics" is not implied.

Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

| Symbol | Parameter | Min | Max | Unit | Note |
|---------|--|-------|-----------|------|--|
| VDDMAX | Supply voltage | -0.3 | 7 | V | Applicable for pin VDD |
| VIN_5V | Maximum voltage | -0.3 | VDD +0.3V | V | Applicable for 5V pins ⁽¹⁾ |
| VIN_30V | Maximum voltage | -0.3 | 30 | V | Applicable for 30V pins ⁽²⁾ |
| Ilatch | Latch-Up immunity | -100 | +100 | mA | Norm: EIA/JESD78 |
| TSTRG | Storage Temperature Range | -55 | 150 | °C | Maximum Junction Temperature |
| | Humidity | 5 | 85 | % | Non condensing |
| VESD_LV | Electrostatic Discharge on all 5V pins ⁽¹⁾ | -2000 | 2000 | V | Norm: MIL 883 E Method 3015 Human body model |
| VESD_HV | Electrostatic Discharge on 30V pins ⁽²⁾ against GND | -6000 | 6000 | V | Norm: MIL 883 E Method 3015 Human body model |
| TBODY | Body Temperature during Soldering | | 260 | °C | according to IPC/JEDEC J-STD-020C |

Note: (1) Pins xRES, SDI, SCLK, SDO, xCS, VSYNC, HSYNC, VDD, xFault, FB1, FB2, RES1-RES16, V2_5

(2) Pins CURR1 – CURR16

3.2 Operating Conditions

3.2.1 General

| Symbol | Parameter | Conditions | Min | Typ | Max | Unit |
|--------|---------------------------------------|------------|-----|-----|-----|------|
| Rthja | Thermal resistance junction – ambient | QFN48 | | 30 | | °C/W |
| Tcase | Case Temperatur | | -20 | | 85 | °C |
| Tj | Junction Temperature | | -20 | | 115 | °C |

3.2.2 Power supply

| Symbol | Parameter | Conditions | Min | Typ | Max | Unit |
|---------|--------------------------|---|-----|-----|-----|------|
| VDD | Supply Voltage | | 4.0 | | 5.5 | V |
| VDD_POR | Power on reset level | Circuit stays in power down until VDD_POR is reached. | 2.4 | | 2.9 | V |
| IDD_q | Quiescent current | VDD= 5V, Default setting, PWM = 0 | | 20 | | mA |
| IDD_r | Supply current | VDD = 5V, HSYNC = 1MHz, Duty = 50% | | 30 | | mA |
| V2_5 | Voltage regulator output | | | 2.5 | | V |

3.2.3 Current outputs

| Symbol | Parameter | Conditions | Min | Typ | Max | Unit |
|--------------|-------------------------------------|---|-----------|-----|-----------|----------|
| Vcurrx | Output voltage pins CURRx | | | | 30 | V |
| Icurrx | Output current | VDAC = 0.25V Vcurr = 0.6V | | | 120 | mA |
| Rcurrx | Input resistance in CURRx | PWM = 0 PWM = 1 | 10 0.1 | | | MΩ MΩ |
| IResx | Input current pin RESx | URESx = 0.5V URESx = 0.8V | | | 10 100 | uA |
| Iled_250 | Trimmed Current accuracy | Trimmed during production ILED = 100mA, Temp = 25 °C, DACref=800mV, VDAC = 250mV ⁽¹⁾ (excluding error of external Rset) | -0.5 | | +0.5 | % |
| Iled_all_FET | Current accuracy External FET | Temp = 25 °C, DACref=800mV, VDAC = 200mV to 800mV ⁽²⁾ (excluding error of external Rset) | -1.4 | | +1.4 | % |
| Ich_250 | Channel to channel Current accuracy | ILED = 100mA, Temp = 25 °C, DACref=800mV, VDAC = 250mV ⁽¹⁾ (excluding error of external Rset) | | 0.2 | | % |
| Iled_all_FET | Current accuracy | Tjunction = -20 °C to +100 °C, DACref=800mV, VDAC = 200mV to 800mV ⁽²⁾ (excluding error of external Rset) | -1.5 | | +1.5 | % |

Note: (1) It is recommended to use DACref = 800mV in order to achieve specified accuracy

(2) It is not recommended to use DAC-voltages < 200mV in order to minimize influences from PCB-layout and noise.

3.2.4 Feedback circuit, fault detectors

| Symbol | Parameter | Conditions | Min | Typ | Max | Unit |
|--------|---------------------------------------|--|--|-----|-----|------|
| IFBmax | Feedback current maximum | | | 200 | | uA |
| RFBmin | Minim output resistance | VCURRx = 0.2V | 200 | 500 | | Ω |
| IFB_g | FB transconductance | IFB_g = ΔI _{FB} / ΔV _{CURRx} | -2 | | | mA/V |
| VFB | Feedback voltage trip point | Programmable, Tolerance ±10% | 0.6 0.8 1.0 VDAC +0.35 | | | V |
| Vshort | Short LED detection voltage at Pin Dx | Programmable, Tolerance ±1.2V | 2 3 4 5 6 7 8 9 10 11 12 | | | V |

| Symbol | Parameter | Conditions | Min | Typ | Max | Unit |
|---------|--------------------------------------|---------------------------------------|-----|-----------------------------|-----|---------------------|
| Vopen | Open LED detection Voltage at Pin Sx | Programmable, Tolerance $\pm 10\%$ | | 50 100 200 VDAC /2 | | mV mV mV V |
| Tovtemp | Over temperature limit | | 130 | 140 | 150 | °C |
| Thyst | Over temperature hysteresis | | | 10 | | °C |

3.2.5 PWM-generators

| Symbol | Parameter | Conditions | Min | Typ | Max | Unit |
|--------|------------------------|------------|-----|-----|------|------|
| fosc | Internal Clock for PWM | | 400 | 500 | 600 | kHz |
| fHSYNC | HSYNC frequency | | 100 | | 2000 | kHz |
| fVSYNC | VSYNC frequency | | 60 | | 480 | Hz |


3.2.6 Digital pins

| Symbol | Parameter | Min | Typ | Max | Unit | Note |
|--------|---|---------|-----|---------|------|------|
| VIH | High Level Input voltage | 1.3 | | VDD | V | |
| VIL | Low Level Input voltage | -0.3 | | 0.8 | V | |
| VoH | High Level output voltage | VDD-0.3 | | | V | I=mA |
| VoL | Low Level output voltage | | | VDD-0.3 | V | I=mA |
| VoL_PD | Low level output voltage open drain outputs | | | VDD-0.3 | V | I=mA |
| R_pu | Input resistance PullUp inputs | | 300 | | kΩ | |
| R_pd | Input resistance PullDown inputs | | 300 | | kΩ | |


3.2.7 SPI-timings

| Symbol | Parameter | Min | Typ | Max | Unit | Note |
|--------|----------------------------|-----|-----|-----|------|------|
| fsclk | SCLK frequency | 0 | | 10 | MHz | |
| t1 | xCS setup time | 50 | | | ns | |
| t2 | xCS hold time | 100 | | | ns | |
| t3 | xCS disable time | 100 | | | ns | |
| t4 | SDI setup time | 5 | | | ns | |
| t5 | SDI hold time | 5 | | | ns | |
| t6 | SCLK rise time | 5 | | | ns | |
| t7 | SCLK fall time | 5 | | | ns | |
| t8 | SCLK low time | 40 | | | ns | |
| t9 | SCLK high time | 40 | | | ns | |
| t10 | output valid from SCLK low | 10 | | | ns | |

SPI-input timing



SPI-output timing




3.3 Pins equivalent circuit

| | |
|---------------------------|--|
| VDD | <p>VDD is connected to a 7V power source through a diode and to GND through another diode.</p> |
| Digital inputs | <p>Digital inputs are connected to VDD through a diode and to GND through a diode. An inverter symbol is shown between the inputs and the connection to VDD.</p> |
| Digital inputs Pull up | <p>Digital inputs are connected to VDD through a diode and to GND through a diode. A pull-up resistor is connected between the inputs and VDD, and an inverter symbol is shown between the inputs and the connection to VDD.</p> |
| Digital inputs Pull Down | <p>Digital inputs are connected to VDD through a diode and to GND through a diode. A pull-down resistor is connected between the inputs and GND, and an inverter symbol is shown between the inputs and the connection to VDD.</p> |
| Digital outputs push/pull | <p>Digital outputs are connected to VDD through a diode and to GND through a diode. A switch symbol is shown between the outputs and the connections to VDD and GND.</p> |
| Digital output open drain | <p>Digital outputs are connected to VDD through a diode and to GND through a diode. An open-drain symbol is shown between the outputs and the connections to VDD and GND.</p> |

4 Detailed Block description

4.1 Current outputs



4.1.1 Precision current sink

All current sinks are built with an internal error amplifier A1 and an internal power transistor. For low EMI radiation the slew rate of the amplifier output voltage can be adjusted between 1us and 9us

4.1.2 Power supply feedback

The voltage on the pins "CURRx" is monitored to adjust the DCDC output voltage. If this voltage is lower than "FBvoltage" a comparator turns on a NMOS transistor which is able to control the output voltage of the external power supply via pin FB1 or pin FB2. The feedback comparator can be assigned to either FB1 or FB2. The power supply feedback can be turned off for all channels by the flag "FBen". If an output is turned off with the corresponding bit in the CUR_ON_1/2-registers, the feedback function of this output is also automatically turned off.


4.1.3 Open LED detection

If a LED-string is broken the voltage at the current setting resistor goes below "OPENvoltage". This status is detected by a comparator and if this status lasts longer than 100ms a fault is indicated and optionally the output and the corresponding power feedback function is turned off. This feature can also be used for external resistor short detection during production. For proper detection the PWM high time has to be longer than 50us.

4.1.4 Short LED detection

Shorted LEDs in a LED-string will cause higher voltage at pin "CURRx". A higher voltage during PWM=1 is detected by a comparator and will trigger a "short LED detection" fault. The duration of the fault is accumulated and if the time exceeds 100ms a fault is indicated and optionally the output is turned off. If the high-time of the waveform is shorter than 100ms it will take more periods to trigger this fault. For proper detection the PWM high time has to be longer than 50us.


4.1.5 Fault detection



If a Open-LED or Short-LED condition is detected the fault-signal is debounced with an internal 100ms clock. This means that the fault will be indicated in the OPENLED or SHORTLED registers between 100ms and 200ms. In order to clear the bit in these registers a "1" has to be written.

4.1.6 DAC

The reference voltage for the output stage is generated by an internal 10-bit DAC. The DAC reference can be selected between 500mV and 800mV depending on register settings. The DAC is trimmed during production with $DACref = 800mV$ to guarantee an output current accuracy of $\pm 0.5\%$ on every current output.



The DAC output voltage can be calculated with:

$$VDAC = \frac{DACref}{1024} * DAC$$

DAC...10bit data value

DACref...DAC reference voltage 500mV to 800mV

4.1.7 Registers in current output stage

| RegAddr: 0x01 | | CUR_ON_1 | Default | Access |
|---------------|---------------|---|----------|--------|
| Bit | Name | Description | | |
| 7:0 | CURR1 - CURR8 | Enables or disables current outputs 0...output OFF. Pulldown resistor to GND 1...output ON. | 00000000 | r/w |

| RegAddr: 0x02 | | CUR_ON_2 | Default | Access |
|---------------|----------------|---|----------|--------|
| Bit | Name | Description | | |
| 7:0 | CURR9 - CURR16 | Enables or disables current outputs 0...output OFF. Pulldown resistor to GND 1...output ON. | 00000000 | r/w |

| RegAddr: 0x03 | | Fault_1 | Default | Access |
|---------------|------------|--|---------|--------|
| Bit | Name | Description | | |
| 7:3 | | Not used | 00000 | r/w |
| 2 | Toff_OverT | Automatic Output turn off at overtemperature 0...Do not turn off current outputs on overtemperature 1... Turn off current outputs on overtemperature | 1 | r/w |
| 1 | Toff_Short | Automatic Output turn off on short LED detection 0...Do not turn off current outputs on short LED detection 1... Turn off current outputs on short LED detection | 0 | r/w |
| 0 | Toff_Open | Automatic Output turn off on open LED detection 0...Do not turn off current outputs on open LED detection 1... Turn off current outputs on open LED detection | 0 | r/w |

| RegAddr: 0x04 | | Fault_2 | Default | Access |
|---------------|--------------|---|---------|--------|
| Bit | Name | Description | | |
| 7:6 | OPENvoltage | Trigger voltage for OPEN LED detection 00...50mV 01...100mV 10...200mV 11...VDAC/2 | 00 | r/w |
| 5:2 | SHORTvoltage | Trigger voltage for SHORT LED detection 0000...2V 0001...3V 0010...4V 0011...5V 0100...6V 0101...7V 0110...8V 0111...9V 1000...10V 1001...11V 1010...12V 1011 to 1111 ...do not use | 0000 | r/w |
| 1 | SHORTen | Enable short LED detection 0...SHORT detection OFF 1...SHORT detection ON | 0 | r/w |
| 0 | OPENen | Enable open LED detection 0...OPEN detection OFF 1...OPEN detection ON | 0 | r/w |

| RegAddr: 0x05 | | Feedback | Default | Access |
|---------------|-----------|---|---------|--------|
| Bit | Name | Description | | |
| 7:6 | | Not used | 00 | r/w |
| 5:4 | FBvoltage | Feedback regulator trip voltage. This voltage has to be adjusted if current is larger than 70mA or VDAC is higher than 0.25V 00...0.6V 01...0.8V 10...1.0V 11...V-DAC + 0.35V | 00 | r/w |

| | | | | | |
|---|---------|--|--------------------------|---|-----|
| 3 | FBboost | Feedback boost option. | FUNCTION DISABLED | 0 | r/w |
| 2 | | Not used | | 0 | r/w |
| 1 | | Not used | | 0 | r/w |
| 0 | FBen | Enable Feedback function for all current outputs. 1...Feedback function enabled 0...Feedback function disabled Note: If a current output is disabled its Feedback function is automatically disabled. | | 0 | r/w |

| RegAddr: 0x06 | | FB_SEL1 | | |
|----------------------|-------------|---|----------------|---------------|
| Bit | Name | Description | Default | Access |
| 7:0 | | Select FB-channel for current outputs 1 to 8 0...select FB channel FB1 1... select FB channel FB2 | 00000000 | r/w |

| RegAddr: 0x07 | | FB_SEL2 | | |
|----------------------|-------------|--|----------------|---------------|
| Bit | Name | Description | Default | Access |
| 7:0 | | Select FB-channel for current outputs 9 to 16 0...select FB channel FB1 1... select FB channel FB2 | 00000000 | r/w |

| RegAddr: 0x08 | | CURRctrl | | |
|----------------------|-------------|--|----------------|---------------|
| Bit | Name | Description | Default | Access |
| 7:6 | | Not used. | 00 | r/w |
| 5:4 | | DAC reference voltage 00...500mV 01...600mV 10...700mV 11...800mV this reference is used at factory trimming | 00 | r/w |
| 3:2 | | Not used | 00 | r/w |
| 1:0 | | Select slew rate of output drivers 00...9us 01...6us 10...3us 11...1us | 00 | r/w |

| RegAddr: 0x09 | | SHORTLED1 | | |
|----------------------|-------------|---|----------------|---------------|
| Bit | Name | Description | Default | Access |
| 7:0 | | Indicates short LED condition on outputs 1 to 8 0...no short LED detected 1... short LED detected | 00000000 | r/w |


| RegAddr: 0x0A | | SHORTLED2 | | |
|----------------------|-------------|--|----------------|---------------|
| Bit | Name | Description | Default | Access |
| 7:0 | | Indicates short LED condition on outputs 9 to 16 0...no short LED detected 1... short LED detected | 00000000 | r/w |

| RegAddr: 0x0B | | OPENLED1 | | |
|----------------------|-------------|--|----------------|---------------|
| Bit | Name | Description | Default | Access |
| 7:0 | | Indicates open LED condition on outputs 1 to 8 0...no open LED detected 1... open LED detected | 00000000 | r/w |

| RegAddr: 0x0C | | OPENLED2 | | |
|----------------------|-------------|---|----------------|---------------|
| Bit | Name | Description | Default | Access |
| 7:0 | | Indicates open LED condition on outputs 9 to 16 0...no open LED detected 1... open LED detected | 00000000 | r/w |

| RegAddr: | | DAC | | |
|----------|------|---|------------|--------|
| 0x0E | 0x0D | | | |
| Bit | Bit | Description | Default | Access |
| 1:0 | 7:0 | DAC[9:0] defines DADC output voltage $DACvoltage = DAC[9:0]*DACref/1024$ | 1000000000 | r/w |

4.2 PWM-generators




4.2.1 Clock and reset


The clock for the build in PWM-generators can be one of two different sources.

1. Internal RC oscillator with 500KHz +20%
2. External Clock signal. This is usually the HSYNC signal of the TV.

4.2.2 PWM-counter




Each PWM-generator is build with a 12bit counter and digital comparators. The counter is counting up with t_{clk} until the value stored in "PWMper" is reached. This resets the counter and starts the next period. While the counter value is below "PWMxHT" the PWM-singal is "1", the rest of the period the PWM-signal is "0". The output of each PWM-generator can also be inverted by means of the "PWMrev".



4.2.3 SPI data update, UPDATERmode bit

The PWM-settings that are programmed via the SPI-Interface take effect depending on the status of the "UPDATERmode"-bit.

If UPDATERmode =1 new data from the serial interface are stored at the next rising edge of VSYNC
If UPDATERmode =0 new data from the serial interface are stored immediately after xCS goes high and will take effect after current PWM cycle is finished. In this mode the values in the PWMxdel registers are ignored. There will be no Delay on the PWM signals.



The PWMxHT-values are double buffered. HighTime values for the next VSYNC can be written even when the current HighTime is not finished.

4.2.4 PWM direct control

The internal signals PWMx can also be direct applied at the VSYNC input if the bit PWMext=1.

4.2.5 VSYNC detect

The VSYNCDet=1 the VSYNC detector monitors the presence of a VSYNC signal. If the VSYNC signal is missing for more than 100ms the current outputs are temporary turned off.

4.2.6 VSYNC duration

Since the VSYNC input is connected to an edge detector, there is no restriction on the duration of the VSYNC pulse.

4.2.7 Registers in PWM-generators

| RegAddr: 0x11 | | PWMREV1 | | |
|---------------|-----------------|--|----------|--------|
| Bit | Name | Description | Default | Access |
| 7:0 | PWMrev 1 - 8 | Selects PWM inverted operation for outputs 1 to 8 0...PWM normal 1... PWM inverted | 00000000 | r/w |

| RegAddr: 0x12 | | PWMREV2 | | |
|---------------|------------------|---|----------|--------|
| Bit | Name | Description | Default | Access |
| 7:0 | PWMrev 9 - 16 | Selects PWM inverted operation for outputs 9 to 16 0...PWM normal 1... PWM inverted | 00000000 | r/w |

| RegAddr: 0x13 | | PWMCTRL | Default | Access |
|----------------------|-------------|---|----------------|---------------|
| Bit | Name | Description | | |
| 7 | FaultDetDly | Sets delay time between PWM=1 and fault detection start 0...40us 1...20us | 0 | r/w |
| 6 | DelayStart | Defines when new PWM-Delay value takes effect 0...Delay values are updated every VSYNC pulse 1...Delay values are updated on the next VSYNC pulse only if HighTime or Delay value has been changed. | 0 | r/w |
| 5 | | | 0 | r/w |
| 4 | VSYNCdet | Enable VSYNC detection 0...VSYNC-detection OFF 1... VSYNC-detection ON. All current outpts are turned off if VSYNC signal is missing for 100ms | 0 | r/w |
| 3 | VSYNCedge | Defines VSYNC trigger edge 0...VSYNC trigger on rising edge 1...VSYNC trigger on falling edge | 0 | r/w |
| 2 | PWMext | Select external or internal PWM signal 0...PWM signal is generated internally 1...PWM signal is applied externally at pin VSYNC | 0 | r/w |
| 1 | UpdateMode | Defines when internal registers are updated 0...Registers updated with rising edge of xCS 1...Registers updated with next VSYNC-edge | 0 | r/w |
| 0 | ClockSrc0 | Clock source for internal PWM-generators 0..internal RC oscillator 1...External Pin HSYNC | 0 | r/w |

| RegAddr: | | PWMperiod | Default | Access |
|-----------------|-------------|------------------------------|----------------|---------------|
| 0x15 | 0x14 | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWMper[11:0] sets PWM period | 0x00, 0x00 | r/w |

| RegAddr: | | PWM1delay | Default | Access |
|-----------------|-------------|-------------------------------|----------------|---------------|
| 0x17 | 0x16 | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWM1del[11:0] sets PWM1 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM2delay | Default | Access |
|-----------------|-------------|-------------------------------|----------------|---------------|
| 0x19 | 0x18 | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWM2del[11:0] sets PWM2 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM3delay | Default | Access |
|-----------------|-------------|-------------------------------|----------------|---------------|
| 0x1B | 0x1A | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWM3del[11:0] sets PWM3 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM4delay | Default | Access |
|-----------------|-------------|-------------------------------|----------------|---------------|
| 0x1D | 0x1C | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWM4del[11:0] sets PWM4 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM5delay | Default | Access |
|-----------------|-------------|-------------------------------|----------------|---------------|
| 0x1F | 0x1E | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWM5del[11:0] sets PWM5 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM6delay | Default | Access |
|-----------------|-------------|-------------------------------|----------------|---------------|
| 0x21 | 0x20 | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWM6del[11:0] sets PWM6 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM7delay | Default | Access |
|-----------------|-------------|-------------------------------|----------------|---------------|
| 0x23 | 0x22 | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWM7del[11:0] sets PWM7 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM8delay | Default | Access |
|-----------------|------------|-------------------------------|----------------|---------------|
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM8del[11:0] sets PWM8 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM9delay | Default | Access |
|-----------------|------------|-------------------------------|----------------|---------------|
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM9del[11:0] sets PWM9 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM10delay | Default | Access |
|-----------------|------------|---------------------------------|----------------|---------------|
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM10del[11:0] sets PWM10 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM11delay | Default | Access |
|-----------------|------------|---------------------------------|----------------|---------------|
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM11del[11:0] sets PWM11 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM12delay | Default | Access |
|-----------------|------------|---------------------------------|----------------|---------------|
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM12del[11:0] sets PWM12 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM13delay | Default | Access |
|-----------------|------------|---------------------------------|----------------|---------------|
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM13del[11:0] sets PWM13 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM14delay | Default | Access |
|-----------------|------------|---------------------------------|----------------|---------------|
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM14del[11:0] sets PWM14 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM15delay | Default | Access |
|-----------------|------------|---------------------------------|----------------|---------------|
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM15del[11:0] sets PWM15 delay | 0x00, 0x00 | r/w |

| RegAddr: | | PWM16delay | Default | Access |
|-----------------|-------------|---------------------------------|----------------|---------------|
| Bit | Name | Description | | |
| 3:0 | 7:0 | PWM16del[11:0] sets PWM16 delay | 0x00, 0x00 | r/w |

| RegAddr: 0x36 | | LOCKUNLOCK | Def | Acc |
|----------------------|-------------|---|-------------|------------|
| Bit | Name | Description | ault | ess |
| 7:0 | LOCKUNLOCK | <p>Writing into register:</p> <p>0xCX...unlock register Group1. Writing enabled 0XA...unlock register Group2. Writing enabled 0xCA...unlock register Group1 and Group2. Writing enabled</p> <p>0xA...lock register Group1. Writing disabled 0XC...lock register Group2. Writing disabled 0xAC...lock register Group1 and Group2. Writing disabled</p> <p>X...don't care. All other values do not change the status of lockunlock.</p> <p>Reading from register:</p> | 0x00 | r/w |

| | | | | |
|--|--|--|--|--|
| | | 0x00.... Group1 and Group2 are locked 0x01...Group1 is unlocked 0x02...Group2 is unlocked 0x03...Group1 and Group2 are unlocked | | |
|--|--|--|--|--|

| RegAddr: | | PWM1hightime | Default | Access |
|-----------------|-------------|----------------------------------|----------------|---------------|
| 0x38 | 0x37 | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM1HT[11:0] sets PWM1 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM2hightime | Default | Access |
|-----------------|-------------|----------------------------------|----------------|---------------|
| 0x3A | 0x39 | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM2HT[11:0] sets PWM2 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM3hightime | Default | Access |
|-----------------|-------------|----------------------------------|----------------|---------------|
| 0x3C | 0x3B | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM3HT[11:0] sets PWM3 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM4hightime | Default | Access |
|-----------------|-------------|----------------------------------|----------------|---------------|
| 0x3E | 0x3D | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM4HT[11:0] sets PWM4 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM5hightime | Default | Access |
|-----------------|-------------|----------------------------------|----------------|---------------|
| 0x40 | 0x3F | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM5HT[11:0] sets PWM5 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM6hightime | Default | Access |
|-----------------|-------------|----------------------------------|----------------|---------------|
| 0x42 | 0x41 | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM6HT[11:0] sets PWM6 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM7hightime | Default | Access |
|-----------------|-------------|----------------------------------|----------------|---------------|
| 0x44 | 0x43 | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM7HT[11:0] sets PWM7 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM8hightime | Default | Access |
|-----------------|-------------|----------------------------------|----------------|---------------|
| 0x46 | 0x45 | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM8HT[11:0] sets PWM8 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM9hightime | Default | Access |
|-----------------|-------------|----------------------------------|----------------|---------------|
| 0x48 | 0x47 | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM9HT[11:0] sets PWM9 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM10hightime | Default | Access |
|-----------------|-------------|------------------------------------|----------------|---------------|
| 0x4A | 0x49 | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM10HT[11:0] sets PWM10 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM11hightime | Default | Access |
|-----------------|-------------|------------------------------------|----------------|---------------|
| 0x4C | 0x4B | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWM11HT[11:0] sets PWM11 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM12hightime | Default | Access |
|-----------------|-------------|------------------------------------|----------------|---------------|
| 0x4E | 0x4D | | | |
| Bit | Bit | Description | | |
| 3:0 | 7:0 | PWMHT12[11:0] sets PWM12 high time | 0x00, 0x00 | r/w |



| RegAddr: | | PWM13hightime | | |
|-----------------|-------------|------------------------------------|----------------|---------------|
| 0x50 | 0x4F | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWM13HT[11:0] sets PWM13 high time | 0x00, 0x00 | r/w |


| RegAddr: | | PWM14hightime | | |
|-----------------|-------------|------------------------------------|----------------|---------------|
| 0x52 | 0x51 | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWM14HT[11:0] sets PWM14 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM15hightime | | |
|-----------------|-------------|------------------------------------|----------------|---------------|
| 0x54 | 0x53 | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWM15HT[11:0] sets PWM15 high time | 0x00, 0x00 | r/w |

| RegAddr: | | PWM16hightime | | |
|-----------------|-------------|------------------------------------|----------------|---------------|
| 0x56 | 0x55 | | | |
| Bit | Bit | Description | Default | Access |
| 3:0 | 7:0 | PWM16HT[11:0] sets PWM16 high time | 0x00, 0x00 | r/w |

4.2.8 PWM examples





4.3 Power supply

4.4 Safety features

4.4.1 Temperature shutdown

If OTurnoff = 1 the outputs of the device are turned off when the die temperature reaches 140 °C. If the die temperature goes below 130 °C the outputs are turned on again.

4.4.2 xRES input

In addition to the build in power on reset circuit there is an external reset input "xRES" available. This gives the possibility to keep the outputs turned off until all blocks of the LED-driver circuits are fully working (DCDC, MCU ...)

4.4.3 Register Lock/Unlock


To prevent wrong writing to registers due to noise on the serial interface a lock/unlock mechanism is implemented.

Register 0x01, 0x02, 0x03, 0x04, 0x05, 0x06, 0x07, 0x08, 0x13 belong to Group1 and can only be written if Group1 is unlocked by the "LOCKUNLOCK"-byte (Reg: 0x36)

Register 0x0D, 0x0E, 0x11, 0x12, 0x14, 0x15 belong to Group2 and can only be written if Group2 is unlocked by the "LOCKUNLOCK"-byte (Reg: 0x36)

The default value of the Groups is locked.

4.5 Reference circuit



The reference circuit generates an internal supply voltage of 2.5V for the digital logic.

| RegAddr: 0x60 | | STATUS | Default | Access |
|---------------|------------|---|---------|--------|
| Bit | Name | Description | | |
| 7 | STATnosync | Sync detector status 0...no sync fault 1...sync fault. VSYNC was missed for > 100ms | 0 | r |
| 6 | STATOT | Overtemperature status 0...no overtemperature 1...overtemperature | 0 | r |
| 5 | STATopen | Status open LED detection 0...no open LED detected 1...opdn LED detected | 0 | r |
| 4 | STATshort | Status short LED detection 0...no short LED detected 1...short LED detected | 0 | r |
| 3 | | Not used | 0 | |


| | | | | |
|-----|-----------|--|----|---|
| 2 | STATUVLO | Status under voltage lockout detector 0...supply OK 1...supply voltage is to low | 0 | r |
| 1:0 | STATpower | Status of power supply monitor 00...no power supply 01...power supply is ramping up 10...power supply good 11...not used | 10 | r |

ams AG
Technical Content Still Valid

4.6 Dynamic feedback control


The output of pins “FB1” and “FB2” can be used to control any external power supply for best power efficiency. Every power supply senses its output voltage with a resistive voltage divider. This voltage divider can be modified to set the output voltage between a minimum output voltage VMIN and a maximum output voltage VMAX. The design of the dynamic feedback control is done in 3 steps.

Step 1: Set the resistors R1,R2 in the power supply according to the minimum output voltage




$$V_{out MIN} = \frac{(R1+R2)}{R2} * V_{sense}$$

Step 2: Add the Resistors R3 in the power supply according to the maximum output voltage




$$V_{out MAX} = \frac{(R1+R2||R3)}{R2||R3} * V_{sense}$$

Step 3: Connect R3 to the feedback pin “FB”.
C1 should be chosen according to the speed requirements of the feedback loop.



The characteristic of the feedback function can be seen in the following diagram. The final output voltage Vdcdc is determined by the setting of “FBvoltage” and the current flowing into the FB pin.




5 SPI interface

For the data transfer a serial peripheral interface (SPI) is used. The SPI is configured to work only as SPI slave. If more than one driver is connected to a SPI master, they can be connected in a “Daisy Chain”-structure or a parallel structure.


5.1 SPI daisy-chain structure

All SPI slaves share the same clock (SCLK) and chip select (xCS) signal. In that configuration all devices can be treated as one big shift register. The devices are automatically enumerated as described in the next section.



5.2 SPI parallel structure

All SPI slaves share the same input (SDI) output (SDO) and clock (SCLK) signal. Every single device can be addressed via the chip select (xCS) signal. In this configuration every device has DevAddr = 0x01.



5.3 SPI device address enumeration

The device address of each driver is automatically set by the position of the device in the chain. The first device has DevAddr = 0x01, the second device has DevAddr = 0x02 and so on. Device Addresses 0x00 and 0x3F are used for special broadcast writing commands described below.

5.4 SPI protocol

5.4.1 Data types

When xCS=0 all slaves will be activated. The addressing and data section is organized in byte packages. Each message can be built with the following Bytes:

| | | | |
|------------------------|---|---|--------------|
| Device address: | B | S | DevAddr[5:0] |
|------------------------|---|---|--------------|

Addresses a specific driver and defines protocol information

| Bit | Meaning | Value |
|--------------|----------------|--|
| B | Broadcast | B=1...Broadcast message to all devices B=0...Normal message to one single device |
| S | Singlebyte | S=0...Block data read or write S=1...Single data transmission (only one byte) |
| DevAddr[5:0] | Device Address | 0x00 Write same data to same register of all devices (B=1) 0x01 to 0x3E. Device addresses for device 1 to 62 0x3F Write different data to same register of all devices (B=1) |

| | |
|--------------------|---------------|
| Nr_of_data: | NrOfdata[7:0] |
|--------------------|---------------|

Defines the number of data bytes in the data frame if S=0

| Bit | Meaning | Value |
|---------------|-------------------------------|--------------|
| NrOfdata[7:0] | Number of data bytes in frame | 0x00 to 0xFF |

| | | |
|--------------------------|----|--------------|
| Register_address: | RW | ReqAddr[6:0] |
|--------------------------|----|--------------|

Register address to be read or written

| Bit | Meaning | Value |
|--------------|-------------------------|---|
| RW | Read/xWrite | RW=0 write to reg address RW=1 read from reg address |
| RegAddr[6:0] | Select register address | 0x00 to 0x60 |


| | |
|--------------|-----------|
| Data: | data[7:0] |
|--------------|-----------|

Data


| Bit | Meaning | Value |
|-------------|---------|--------------|
| data [7:0], | Data | 0x00 to 0xFF |

5.4.2 Timings

Write single data into single device





Read single data from single device




DA...DevAddr
RA...RegAddr
D.....Data

5.5 SPI protocol examples

5.5.1 Write single data




5.5.2 Write N data




5.5.3 Write different data in same register of all devices (single byte)

Set DevAdd = 0x3F



5.5.4 Write different data in same register of all devices (multiple bytes)



Set DevAdd = 0x3F



5.5.5 Write same data in same register of all devices (single byte)

Set DevAdd = 0x00



Write to Reg0x02 of Dev0x01 – Dev0x03



5.5.6 Write same data in same register of all devices (multiple bytes)



Set DevAdd = 0x00

Write to Reg0x02 - Reg0x04 of Dev0x01 – Dev0x03




5.5.7 Read single data

Read from Reg0x02 of Dev0x01





Read from Reg0x02 of Dev0x03



5.5.8 Read N data

Read from Reg0x02-Reg0x04 of Dev0x03



6 Register map

| | |
|--|---|
| | Registers can only be written if Group1 is UNLOCKED. Default = LOCKED |
| | Registers can only be written if Group2 is UNLOCKED. Default = LOCKED |

| Addr | Name | D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | Def ault |
|------|--------------|-----------------|----------------|---------------|------------------|---------------|---------------|----------------|---------------|-------------|
| 0x00 | | | | | | | | | | |
| 0x01 | CUR_ON_1 | Curr8 | Curr7 | Curr6 | Curr5 | Curr4 | Curr3 | Curr2 | Curr1 | 0x00 |
| 0x02 | CUR_ON_2 | Curr16 | Curr15 | Curr14 | Curr13 | Curr12 | Curr11 | Curr10 | Curr9 | 0x00 |
| 0x03 | FAULT_1 | | | | | Toff Otemp | Toff short | Toff open | | 0x04 |
| 0x04 | FAULT_2 | OPEN voltage | | | SHORT voltage | | SHORT en | OPEN en | | 0x00 |
| 0x05 | FEEDBACK | | | FB voltage | FB boost | | | FB enable | | 0x00 |
| 0x06 | FB_SEL1 | FBsel8 | FBsel7 | FBsel6 | FBsel5 | FBsel4 | FBsel3 | FBsel2 | FBsel1 | 0x00 |
| 0x07 | FB_SEL2 | FBsel16 | FBsel15 | FBsel14 | FBsel13 | FBsel12 | FBsel11 | FBsel10 | FBsel9 | 0x00 |
| 0x08 | CURRctrl | | | DAC ref | | | | Slew rate | | 0x00 |
| 0x09 | SHORTLED1 | Short8 | Short7 | Short6 | Short5 | Short4 | Short3 | Short2 | Short1 | 0x00 |
| 0x0A | SHORTLED2 | Short16 | Short15 | Short14 | Short13 | Short12 | Shor11 | Shor10 | Short9 | 0x00 |
| 0x0B | OPENLED1 | Open8 | Open7 | Open6 | Open5 | Open4 | Open3 | Open2 | Open1 | 0x00 |
| 0x0C | OPENLED2 | Open16 | Open15 | Open14 | Open13 | Open12 | Open11 | Open10 | Open9 | 0x00 |
| 0x0D | DACLSB | DAC7 | DAC6 | DAC5 | DAC4 | DAC3 | DAC2 | DAC1 | DAC0 | 0x00 |
| 0x0E | DACMSB | | | | | | | DAC9 | DAC8 | 0x20 |
| 0x0F | | | | | | | | | | 0x00 |
| 0x10 | | | | | | | | | | 0x00 |
| 0x11 | PWMREV1 | PWM Rev8 | PWM Rev7 | PWM Rev6 | PWM Rev5 | PWM Rev4 | PWM Rev3 | PWM Rev2 | PWM Rev1 | 0x00 |
| 0x12 | PWMREV2 | PWM Rev16 | PWM Rev15 | PWM Rev14 | PWM Rev13 | PWM Rev12 | PWM Rev11 | PWM Rev10 | PWM Rev9 | 0x00 |
| 0x13 | PWMCTRL | Fault DetDly | Delay Start | | VSYNC det | VSYNC edge | PWM ext | Update Mode | Clock Src0 | 0x00 |
| 0x14 | PWMperiodLSB | PWM Per7 | PWM Per6 | PWM Per5 | PWM Per4 | PWM Per3 | PWM Per2 | PWM Per1 | PWM Per0 | 0x00 |
| 0x15 | PWMperiodMSB | 0 | 0 | 0 | 0 | PWM Per11 | PWM Per10 | PWM Per9 | PWM Per8 | 0x00 |
| 0x16 | PWM1delLSB | PWM1 Del7 | PWM1 Del6 | PWM1 Del5 | PWM1 Del4 | PWM1 Del3 | PWM1 Del2 | PWM1 Del1 | PWM1 Del0 | 0x00 |
| 0x17 | PWM1delMSB | 0 | 0 | 0 | 0 | PWM1 Del11 | PWM1 Del10 | PWM1 Del9 | PWM1 Del8 | 0x00 |
| 0x18 | PWM2delLSB | PWM2 Del7 | PWM2 Del6 | PWM2 Del5 | PWM2 Del4 | PWM2 Del3 | PWM2 Del2 | PWM2 Del1 | PWM2 Del0 | 0x00 |
| 0x19 | PWM2delMSB | 0 | 0 | 0 | 0 | PWM2 Del11 | PWM2 Del10 | PWM2 Del9 | PWM2 Del8 | 0x00 |
| 0x1A | PWM3delLSB | PWM3 Del7 | PWM3 Del6 | PWM3 Del5 | PWM3 Del4 | PWM3 Del3 | PWM3 Del2 | PWM3 Del1 | PWM3 Del0 | 0x00 |
| 0x1B | PWM3delMSB | 0 | 0 | 0 | 0 | PWM3 Del11 | PWM3 Del10 | PWM3 Del9 | PWM3 Del8 | 0x00 |
| 0x1C | PWM4delLSB | PWM4 Del7 | PWM4 Del6 | PWM4 Del5 | PWM4 Del4 | PWM4 Del3 | PWM4 Del2 | PWM4 Del1 | PWM4 Del0 | 0x00 |
| 0x1D | PWM4delMSB | 0 | 0 | 0 | 0 | PWM4 Del11 | PWM4 Del10 | PWM4 Del9 | PWM4 Del8 | 0x00 |
| 0x1E | PWM5delLSB | PWM5 Del7 | PWM5 Del6 | PWM5 Del5 | PWM5 Del4 | PWM5 Del3 | PWM5 Del2 | PWM5 Del1 | PWM5 Del0 | 0x00 |
| 0x1F | PWM5delMSB | 0 | 0 | 0 | 0 | PWM5 Del11 | PWM5 Del10 | PWM5 Del9 | PWM5 Del8 | 0x00 |
| 0x20 | PWM6delLSB | PWM6 Del7 | PWM6 Del6 | PWM6 Del5 | PWM6 Del4 | PWM6 Del3 | PWM6 Del2 | PWM6 Del1 | PWM6 Del0 | 0x00 |
| 0x21 | PWM6delMSB | 0 | 0 | 0 | 0 | PWM6 Del11 | PWM6 Del10 | PWM6 Del9 | PWM6 Del8 | 0x00 |
| 0x22 | PWM7delLSB | PWM7 Del7 | PWM7 Del6 | PWM7 Del5 | PWM7 Del4 | PWM7 Del3 | PWM7 Del2 | PWM7 Del1 | PWM7 Del0 | 0x00 |
| 0x23 | PWM7delMSB | 0 | 0 | 0 | 0 | PWM7 Del11 | PWM7 Del10 | PWM7 Del9 | PWM7 Del8 | 0x00 |
| 0x24 | PWM8delLSB | PWM8 Del7 | PWM8 Del6 | PWM8 Del5 | PWM8 Del4 | PWM8 Del3 | PWM8 Del2 | PWM8 Del1 | PWM8 Del0 | 0x00 |
| 0x25 | PWM8delMSB | 0 | 0 | 0 | 0 | PWM8 Del11 | PWM8 Del10 | PWM8 Del9 | PWM8 Del8 | 0x00 |
| 0x26 | PWM9delLSB | PWM9 Del7 | PWM9 Del6 | PWM9 Del5 | PWM9 Del4 | PWM9 Del3 | PWM9 Del2 | PWM9 Del1 | PWM9 Del0 | 0x00 |
| 0x27 | PWM9delMSB | 0 | 0 | 0 | 0 | PWM9 | PWM9 | PWM9 | PWM9 | 0x00 |

| | | | | | | Del11 | Del10 | Del9 | Del8 | |
|------|-------------|---------------|---------------|---------------|---------------|----------------|----------------|---------------|---------------|------|
| 0x28 | PWM10delLSB | PWM10 Del7 | PWM10 Del6 | PWM10 Del5 | PWM10 Del4 | PWM10 Del3 | PWM10 Del2 | PWM10 Del1 | PWM10 Del0 | 0x00 |
| 0x29 | PWM10delMSB | 0 | 0 | 0 | 0 | PWM10 Del11 | PWM10 Del10 | PWM10 Del9 | PWM10 Del8 | 0x00 |
| 0x2A | PWM11delLSB | PWM11 Del7 | PWM11 Del6 | PWM11 Del5 | PWM11 Del4 | PWM11 Del3 | PWM11 Del2 | PWM11 Del1 | PWM11 Del0 | 0x00 |
| 0x2B | PWM11delMSB | 0 | 0 | 0 | 0 | PWM11 Del11 | PWM11 Del10 | PWM11 Del9 | PWM11 Del8 | 0x00 |
| 0x2C | PWM12delLSB | PWM12 Del7 | PWM12 Del6 | PWM12 Del5 | PWM12 Del4 | PWM12 Del3 | PWM12 Del2 | PWM12 Del1 | PWM12 Del0 | 0x00 |
| 0x2D | PWM12delMSB | 0 | 0 | 0 | 0 | PWM12 Del11 | PWM12 Del10 | PWM12 Del9 | PWM12 Del8 | 0x00 |
| 0x2E | PWM13delLSB | PWM13 Del7 | PWM13 Del6 | PWM13 Del5 | PWM13 Del4 | PWM13 Del3 | PWM13 Del2 | PWM13 Del1 | PWM13 Del0 | 0x00 |
| 0x2F | PWM13delMSB | 0 | 0 | 0 | 0 | PWM13 Del11 | PWM13 Del10 | PWM13 Del9 | PWM13 Del8 | 0x00 |
| 0x30 | PWM14delLSB | PWM14 Del7 | PWM14 Del6 | PWM14 Del5 | PWM14 Del4 | PWM14 Del3 | PWM14 Del2 | PWM14 Del1 | PWM14 Del0 | 0x00 |
| 0x31 | PWM14delMSB | 0 | 0 | 0 | 0 | PWM14 Del11 | PWM14 Del10 | PWM14 Del9 | PWM14 Del8 | 0x00 |
| 0x32 | PWM15delLSB | PWM15 Del7 | PWM15 Del6 | PWM15 Del5 | PWM15 Del4 | PWM15 Del3 | PWM15 Del2 | PWM15 Del1 | PWM15 Del0 | 0x00 |
| 0x33 | PWM15delMSB | 0 | 0 | 0 | 0 | PWM15 Del11 | PWM15 Del10 | PWM15 Del9 | PWM15 Del8 | 0x00 |
| 0x34 | PWM16delLSB | PWM16 Del7 | PWM16 Del6 | PWM16 Del5 | PWM16 Del4 | PWM16 Del3 | PWM16 Del2 | PWM16 Del1 | PWM16 Del0 | 0x00 |
| 0x35 | PWM16delMSB | 0 | 0 | 0 | 0 | PWM16 Del11 | PWM16 Del10 | PWM16 Del9 | PWM16 Del8 | 0x00 |
| 0x36 | LOCKUNLOC | MagicByte | | | | | | | | 0x00 |
| 0x37 | PWM1htLSB | PWM1 HT7 | PWM1 HT6 | PWM1 HT5 | PWM1 HT4 | PWM1 HT3 | PWM1 HT2 | PWM1 HT1 | PWM1 HT0 | 0x00 |
| 0x38 | PWM1htMSB | 0 | 0 | 0 | 0 | PWM1 HT11 | PWM1 HT10 | PWM1 HT9 | PWM1 HT8 | 0x00 |
| 0x39 | PWM2htLSB | PWM2 HT7 | PWM2 HT6 | PWM2 HT5 | PWM2 HT4 | PWM2 HT3 | PWM2 HT2 | PWM2 HT1 | PWM2 HT0 | 0x00 |
| 0x3A | PWM2htMSB | 0 | 0 | 0 | 0 | PWM2 HT11 | PWM2 HT10 | PWM2 HT9 | PWM2 HT8 | 0x00 |
| 0x3B | PWM3htLSB | PWM3 HT7 | PWM3 HT6 | PWM3 HT5 | PWM3 HT4 | PWM3 HT3 | PWM3 HT2 | PWM3 HT1 | PWM3 HT0 | 0x00 |
| 0x3C | PWM3htMSB | 0 | 0 | 0 | 0 | PWM3 HT11 | PWM3 HT10 | PWM3 HT9 | PWM3 HT8 | 0x00 |
| 0x3D | PWM4htLSB | PWM4 HT7 | PWM4 HT6 | PWM4 HT5 | PWM4 HT4 | PWM4 HT3 | PWM4 HT2 | PWM4 HT1 | PWM4 HT0 | 0x00 |
| 0x3E | PWM4htMSB | 0 | 0 | 0 | 0 | PWM4 HT11 | PWM4 HT10 | PWM4 HT9 | PWM4 HT8 | 0x00 |
| 0x3F | PWM5htLSB | PWM5 HT7 | PWM5 HT6 | PWM5 HT5 | PWM5 HT4 | PWM5 HT3 | PWM5 HT2 | PWM5 HT1 | PWM5 HT0 | 0x00 |
| 0x40 | PWM5htMSB | 0 | 0 | 0 | 0 | PWM5 HT11 | PWM5 HT10 | PWM5 HT9 | PWM5 HT8 | 0x00 |
| 0x41 | PWM6htLSB | PWM6 HT7 | PWM6 HT6 | PWM6 HT5 | PWM6 HT4 | PWM6 HT3 | PWM6 HT2 | PWM6 HT1 | PWM6 HT0 | 0x00 |
| 0x42 | PWM6htMSB | 0 | 0 | 0 | 0 | PWM6 HT11 | PWM6 HT10 | PWM6 HT9 | PWM6 HT8 | 0x00 |
| 0x43 | PWM7htLSB | PWM7 HT7 | PWM7 HT6 | PWM7 HT5 | PWM7 HT4 | PWM7 HT3 | PWM7 HT2 | PWM7 HT1 | PWM7 HT0 | 0x00 |
| 0x44 | PWM7htMSB | 0 | 0 | 0 | 0 | PWM7 HT11 | PWM7 HT10 | PWM7 HT9 | PWM7 HT8 | 0x00 |
| 0x45 | PWM8htLSB | PWM8 HT7 | PWM8 HT6 | PWM8 HT5 | PWM8 HT4 | PWM8 HT3 | PWM8 HT2 | PWM8 HT1 | PWM8 HT0 | 0x00 |
| 0x46 | PWM8htMSB | 0 | 0 | 0 | 0 | PWM8 HT11 | PWM8 HT10 | PWM8 HT9 | PWM8 HT8 | 0x00 |
| 0x47 | PWM9htLSB | PWM9 HT7 | PWM9 HT6 | PWM9 HT5 | PWM9 HT4 | PWM9 HT3 | PWM9 HT2 | PWM9 HT1 | PWM9 HT0 | 0x00 |
| 0x48 | PWM9htMSB | 0 | 0 | 0 | 0 | PWM9 HT11 | PWM9 HT10 | PWM9 HT9 | PWM9 HT8 | 0x00 |
| 0x49 | PWM10htLSB | PWM10 HT7 | PWM10 HT6 | PWM10 HT5 | PWM10 HT4 | PWM10 HT3 | PWM10 HT2 | PWM10 HT1 | PWM10 HT0 | 0x00 |
| 0x4A | PWM10htMSB | 0 | 0 | 0 | 0 | PWM10 HT11 | PWM10 HT10 | PWM10 HT9 | PWM10 HT8 | 0x00 |
| 0x4B | PWM11htLSB | PWM11 HT7 | PWM11 HT6 | PWM11 HT5 | PWM11 HT4 | PWM11 HT3 | PWM11 HT2 | PWM11 HT1 | PWM11 HT0 | 0x00 |
| 0x4C | PWM11htMSB | 0 | 0 | 0 | 0 | PWM11 HT11 | PWM11 HT10 | PWM11 HT9 | PWM11 HT8 | 0x00 |
| 0x4D | PWM12htLSB | PWM12 HT7 | PWM12 HT6 | PWM12 HT5 | PWM12 HT4 | PWM12 HT3 | PWM12 HT2 | PWM12 HT1 | PWM12 HT0 | 0x00 |
| 0x4E | PWM12htMSB | 0 | 0 | 0 | 0 | PWM12 HT11 | PWM12 HT10 | PWM12 HT9 | PWM12 HT8 | 0x00 |
| 0x4F | PWM13htLSB | PWM13 HT7 | PWM13 HT6 | PWM13 HT5 | PWM13 HT4 | PWM13 HT3 | PWM13 HT2 | PWM13 HT1 | PWM13 HT0 | 0x00 |
| 0x50 | PWM13htMSB | 0 | 0 | 0 | 0 | PWM13 HT11 | PWM13 HT10 | PWM13 HT9 | PWM13 HT8 | 0x00 |
| 0x51 | PWM14htLSB | PWM14 | PWM14 | PWM14 | PWM14 | PWM14 | PWM14 | PWM14 | PWM14 | 0x00 |

| | | HT7 | HT6 | HT5 | HT4 | HT3 | HT2 | HT1 | HT0 | |
|------|------------|-------------|-----------|-----------|------------|------------|------------|------------|-----------|------|
| 0x52 | PWM14htMSB | 0 | 0 | 0 | 0 | PWM14 HT11 | PWM14 HT10 | PWM14 HT9 | PWM14 HT8 | 0x00 |
| 0x53 | PWM15htLSB | PWM15 HT7 | PWM15 HT6 | PWM15 HT5 | PWM15 HT4 | PWM15 HT3 | PWM15 HT2 | PWM15 HT1 | PWM15 HT0 | 0x00 |
| 0x54 | PWM15htMSB | 0 | 0 | 0 | 0 | PWM5 HT11 | PWM15 HT10 | PWM15 HT9 | PWM15 HT8 | 0x00 |
| 0x55 | PWM16htLSB | PWM16 HT7 | PWM16 HT6 | PWM16 HT5 | PWM16 HT4 | PWM16 HT3 | PWM16 HT2 | PWM16 HT1 | PWM16 HT0 | 0x00 |
| 0x56 | PWM16htMSB | 0 | 0 | 0 | 0 | PWM16 HT11 | PWM16 HT10 | PWM16 HT9 | PWM16 HT8 | 0x00 |
| 0x57 | ASICIDLSB | A | | | | Rev Nr. | | | | 0xA |
| 0x58 | ASICIDMSB | 9 | | | | 5 | | | | 0x95 |
| 0x59 | Not used | | | | | | | | | 0x00 |
| 0x60 | STATUS | STAT Nosync | STAT OT | STAT Open | STAT Short | 0 | STAT UVLO | STAT power | | |

ADDRESSES ABOVE 0x60 ARE FOR FACTORY TEST ONLY. DO NOT WRITE !

7 Pinout and Packaging


7.1 Pinout

| Pin Nr | Pin Name | Pin Type | Description |
|--------|-----------|----------|--|
| 1 | CURR1 | AIO | Current source output 1 |
| 2 | RES1 | AIO | Current setting resistor 1 |
| 3 | V2_5 | AIO | Digital supply output. Connect 2.2uF bypass capacitor to GND |
| 4 | XFAULT | DO- OD | Fault output. Open drain. Connect pullup to VDD |
| 5 | XRES | DI | Reset input active low |
| 6 | FB1 | AIO | Power supply feedback output1 |
| 7 | FB2 | AIO | Power supply feedback output2 |
| 8 | VSSA | AIO | GND |
| 9 | VDD | AIO | Power supply. Connect 4.7uF bypass capacitor to GND |
| 10 | VSS_SENSE | AIO | VSS sense input. Keep this node noise free |
| 11 | RES16 | AIO | Current setting resistor 16 |
| 12 | CURR16 | AIO | Current source output 16 |
| 13 | RES15 | AIO | Current setting resistor 15 |
| 14 | CURR15 | AIO | Current source output 15 |
| 15 | RES14 | AIO | Current setting resistor 14 |
| 16 | CURR14 | AIO | Current source output 14 |
| 17 | RES13 | AIO | Current setting resistor 13 |
| 18 | CURR13 | AIO | Current source output 13 |
| 19 | CURR12 | AIO | Current source output 12 |
| 20 | RES12 | AIO | Current setting resistor 12 |
| 21 | CURR11 | AIO | Current source output 11 |
| 22 | RES11 | AIO | Current setting resistor 11 |
| 23 | CURR10 | AIO | Current source output 10 |
| 24 | RES10 | AIO | Current setting resistor 10 |
| 25 | CURR9 | AIO | Current source output 9 |
| 26 | RES9 | AIO | Current setting resistor 9 |
| 27 | VDD | AIO | Supply |
| 28 | VSSA | AIO | GND |
| 29 | VSYNC | DI-PD | Vertical sync frequency |
| 30 | HSYNC | DI-PD | Clock input for PWM generators |
| 31 | xCS | DI-PU | SPI interface chip select |
| 32 | SDO | DO | SPI interface data output. Tristate output |
| 33 | SCL | DI-PD | SPI interface clock |
| 34 | SDI | DI-PD | SPI interface data input |
| 35 | RES8 | AIO | Current setting resistor 8 |
| 36 | CURR8 | AIO | Current source output 8 |
| 37 | RES7 | AIO | Current setting resistor 7 |
| 38 | CURR7 | AIO | Current source output 7 |

| | | | |
|----|-------|-----|------------------------------|
| 39 | RES6 | AIO | Current setting resistor 6 |
| 40 | CURR6 | AIO | Current source output 6 |
| 41 | RES5 | AIO | Current setting resistor 5 |
| 42 | CURR5 | AIO | Current source output 5 |
| 43 | CURR4 | AIO | Current source output 4 |
| 44 | RES4 | AIO | Current setting resistor 4 |
| 45 | CURR3 | AIO | Current source output 3 |
| 46 | RES3 | AIO | Current setting resistor 3 |
| 47 | CURR2 | AIO | Current source output 2 |
| 48 | RES2 | AIO | Current setting resistor 2 |
| EP | VSSA | AIO | Exposed PAD. Connect to VSSA |

| | |
|-------|---------------------------------------|
| AIO | Analog Pin |
| DI | Digital input |
| DI-PU | Digital input with pull up resistor |
| DI-PD | Digital input with pull down resistor |
| DO | Digital output |
| DO-OD | Digital output open drain |

7.2 Package Drawing QFN48





8 Thermal characteristic

The thermal characteristics of the devices were measured at 25°C ambient temperature. The device was mounted on a double sided FR4 PCB with the bottom layer used as cooling area.

8.1 QFN48

PCB FR4, 1cm distance from ground



9 Ordering information

| Part Number | Marking | Package Type | Delivery Form | Description |
|--------------|---------|--------------|------------------------------|--|
| AS3695A-ZMFT | AS3695A | QFN48 | Tape and Reel in Dry Pack | Package size = 7x7mm, Pitch = 0.5mm, Pb-free; |

Copyright

Copyright © 1997-2009, austriamicrosystems AG, Schloss Premstaetten, 8141 Unterpremstaetten, Austria-Europe. Trademarks Registered ®. All rights reserved. The material herein may not be reproduced, adapted, merged, translated, stored, or used without the prior written consent of the copyright owner.

All products and companies mentioned are trademarks or registered trademarks of their respective companies.

Disclaimer

Devices sold by austriamicrosystems AG are covered by the warranty and patent indemnification provisions appearing in its Term of Sale. austriamicrosystems AG makes no warranty, express, statutory, implied, or by description regarding the information set forth herein or regarding the freedom of the described devices from patent infringement. Austriamicrosystems AG reserves the right to change specifications and prices at any time and without notice. Therefore, prior to designing this product into a system, it is necessary to check with austriamicrosystems AG for current information.

This product is intended for use in normal commercial applications. Applications requiring extended temperature range, unusual environmental requirements, or high reliability applications, such as military, medical life-support or life-sustaining equipment are specifically not recommended without additional processing by austriamicrosystems AG for each application. For shipments of less than 100 parts the manufacturing flow might show deviations from the standard production flow, such as test flow or test location. The information furnished here by austriamicrosystems AG is believed to be correct and accurate. However, austriamicrosystems AG shall not be liable to recipient or any third party for any damages, including but not limited to personal injury, property damage, loss of profits, loss of use, interruption of business or indirect, special, incidental or consequential damages, of any kind, in connection with or arising out of the furnishing, performance or use of the technical data herein. No obligation or liability to recipient or any third party shall arise or flow out of austriamicrosystems AG rendering of technical or other services.



Contact Information

Headquarters
austriamicrosystems AG
A-8141 Schloss Premstätten, Austria

T. +43 (0) 3136 500 0
F. +43 (0) 3136 5692

For Sales Offices, Distributors and Representatives, please visit:

<http://www.austriamicrosystems.com/contact>