

Self-Capacitive Touch Panel Controller

INTRODUCTION

The FT6X36 Series ICs are single-chip capacitive touch panel controller IC with a built-in 16 bit enhanced Micro-controller unit (MCU). They adopt the self-capacitance technology, which supports single point and gesture touch or two points. In conjunction with a self-capacitive touch panel, The FT6X36 Series ICs implement the user-friendly input function and are widely used in various portable devices, such as smart phones, MID's and GPS.

The FT6X36 series ICs include FT6236/FT6336/FT6436L/FT6436, the difference of their specifications will be listed individually in this datasheet.

FEATURES

- Self-Capacitive Sensing Techniques support single point touch and gesture or two point touch
- Absolute X and Y coordinates or gesture
- 1 point and gestures / 2 points supported
- High immunity to RF and power Interferences
- Auto-calibration: Insensitive to Capacitance and Environmental Variations
- Built-in Enhanced MCU
- FT6236 supports up to 22 or 28 channels of sensors /drivers
- FT6336 supports up to 36 channels of sensors /drivers
- FT6436L supports up to 42 channels of sensors /drivers
- FT6436 supports up to 46 channels of sensors /drivers
- Report Rate: Up to 100Hz
- Support Interfaces :I2C
- Support single film material TP and triangle pattern without additional shield
- Internal accuracy ADC and smooth filters
- Support 2.8V to 3.6V Operating Voltage
- Support independent IOVCC
- Built-in LDO for Digital Circuits
- High efficient power management with 3 Operating Modes
 - Active Mode
 - Monitor Mode
 - Hibernation Mode
- Operating Temperature Range: -40°C to +85°C
- ESD:HBM≥7000V,MM≥350V

TABLE OF CONTENTS

INTRODUCTION	I
FEATURES.....	I
1 OVERVIEW	1
1.1 TYPICAL APPLICATIONS	1
2 FUNCTIONAL DESCRIPTION.....	1
2.1 ARCHITECTURAL OVERVIEW.....	1
2.2 MCU.....	2
2.3 OPERATION MODES.....	2
2.4 SERIAL INTERFACE.....	3
2.4.1 I2C.....	3
3 ELECTRICAL SPECIFICATIONS.....	4
3.1 ABSOLUTE MAXIMUM RATINGS.....	4
3.2 DC CHARACTERISTICS	4
3.3 AC CHARACTERISTICS	5
3.4 I/O PORTS CIRCUITS.....	6
3.5 POWER ON/RESET/WAKE SEQUENCE.....	6
4 PIN CONFIGURATIONS	9
5 PACKAGE INFORMATION	12
5.1 PACKAGE INFORMATION OF QFN-4X4-32L PACKAGE.....	12
5.2 PACKAGE INFORMATION OF QFN-5X5-40L PACKAGE.....	12
5.3 PACKAGE INFORMATION OF QFN-6X6-48L PACKAGE.....	12
5.4 PACKAGE INFORMATION OF QFN-6X6-56L PACKAGE.....	15
5.5 ORDER INFORMATION	16

1 OVERVIEW

1.1 Typical Applications

FT6X36 accommodate a wide range of applications with a set of buttons up to a 2D touch sensing device, their typical applications are listed below.

- Mobile phones, smart phones
- GPS
- Game consoles
- POS (Point of Sales) devices
- Portable MP3 and MP4 media players
- Digital cameras
- MIDs

FT6X36 series ICs support up to 5.5 inch Touch Panel; users may find out their target IC from the specs listed in the following table,

Model Name	Panel	Package			Touch Panel Size
	Channel	Type	Pin	Size	
FT6236HMg	22	QFN4*4	32	0.5-P0.4	≤3.0"
FT6236GMA	28	QFN5*5	40	0.6-P0.4	≤4.0"
FT6336DMB	36	QFN6*6	48	0.6-P0.4	≤4.5 inch
FT6436LDQb	42	QFN6*6	56	0.6-P0.35	≤5.0 inch
FT6436DQf	46	QFN6*6	56	0.6-P0.35	≤5.5 inch

2 FUNCTIONAL DESCRIPTION

2.1 Architectural Overview

Figure2-1 shows the overall architecture for the FT6X36.




Figure 2-1 FT6X36 System Architecture Diagram

The FT6X36 is comprised of five main functional parts listed below,

THIS DOCUMENT CONTAINS INFORMATION PROPRIETARY TO FOCALTECH SYSTEMS CO.,LTD., AND MAY NOT BE REPRODUCED, DISCLOSED OR USED IN WHOLE OR PART WITHOUT THE EXPRESS WRITTEN PERMISSION OF FOCALTECH SYSTEMS CO.,LTD.

- Touch Panel Interface Circuits

The main function for the AFE and AFE controller is to interface with the touch panel. It scans the panel by sending AC signals to the panel and processes the received signals from the panel. So it supports both driver and Sensor functions. Key parameters to configure this circuit can be sent via serial interfaces.

- Enhanced MCU

For the Enhanced MCU, larger program and data memories are supported. Furthermore, A Flash ROM is implemented to store programs and some key parameters.

Complex signal Processing algorithms are implemented by MCU to detect the touches reliably and efficiently.

Communication protocol software is also implemented on this MCU to exchange data and control information with the host processor.

- External Interface

- I2C: an interface for data exchange with host
- INT: an interrupt signal to inform the host processor that touch data is ready for read
- RSTN: an external low signal reset the chip.

- A watch dog timer is implemented to ensure the robustness of the chip.

- A voltage regulator to generate 1.8V for digital circuits from the input VDDA supply.

2.2 MCU

This section describes some critical features and operations supported by the Enhanced MCU.

Figure 2-2 shows the overall structure of the MCU block. In addition to the Enhanced MCU core, we have added the following circuits,

- Memory:32KB Flash
- Data Memory: 4KB SRAM
- Timer: A number of timers are available to generate different clocks
- Master Clock:17.5MHz from a 35MHz RC Oscillator
- Clock Manager: To control various clocks under different operation conditions of the system




Figure 2-2 MCU Block Diagram

2.3 Operation Modes

FT6X36 operates in the following three modes:

- Active Mode

In this mode, FT6X36 actively scans the panel. The default scan rate is 60 frames per second. The host processor can configure FT6X36 to speed up or to slow down.

- Monitor Mode

In this mode, FT6X36 scans the panel at a reduced speed. The default scan rate is 25 frames per second and the host processor can increase or decrease this rate. When in this mode, most algorithms are stopped. A simpler algorithm is being executed to determine if there is a touch or not. When a touch is detected, FT6X36 shall enter the Active mode immediately to acquire the touch information quickly. During this mode, the serial port is closed and no data shall be transferred with the host processor

- Hibernation Mode

In this mode, the chip is set in a power down mode. It shall respond to the “RESET” or “Wakeup” signal from the host processor. The chip therefore consumes very little current, which help prolong the standby time for the portable devices.

Host Interface Figure 2-3 shows the interface between a host processor and FT6X36. This interface consists of the following three sets of signals:

- Serial Interface
- Interrupt from FT6X36 to the Host
- Reset Signal from the Host to FT6X36




Figure 2-3 Host Interface Diagram

The serial interface of FT6X36 is I2C. The details of this interface are described in detail in Section 2.5. The interrupt signal (/INT) is used for FT6X36 to inform the host that data are ready for the host to receive. The RSTN signal is used for the host to reset FT6X36. After resetting, FT6X36 shall enter the Active mode.

2.4 Serial Interface

FT6X36 supports the I2C interfaces, which can be used by a host processor or other devices.

2.4.1 I2C

The I2C is always configured in the Slave mode. The data transfer format is shown in [Figure 2-4](#).




Figure 2-4 I2C Serial Data Transfer Format




Figure 2-5 I2C master write, slave read




Figure 2-6 I2C master read, slave write

Table 2-1 lists the meanings of the mnemonics used in the above figures.

Table 2-1 Mnemonics Description

Mnemonics	Description
S	I2C Start or I2C Restart
A[6:0]	Slave address
R/W	READ/WRITE bit, '1' for read, '0' for write
A(N)	ACK(NACK)
P	STOP: the indication of the end of a packet (if this bit is missing, S will indicate the end of the current packet and the beginning of the next packet)

I2C Interface Timing Characteristics is shown in Table 2-2.

Table 2-2 I2C Timing Characteristics

Parameter	Min	Max	Unit
SCL frequency	10	400	KHz
Bus free time between a STOP and START condition	4.7	\	us
Hold time (repeated) START condition	4.0	\	us
Data setup time	250	\	ns
Setup time for a repeated START condition	4.7	\	us
Setup Time for STOP condition	4.0	\	us

3 ELECTRICAL SPECIFICATIONS

3.1 Absolute Maximum Ratings

Table 3-1 Absolute Maximum Ratings

Item	Symbol	Value	Unit	Note
Power Supply Voltage	VDDA - VSSA	-0.3 ~ +3.6	V	1, 2
Power Supply Voltage2	VDD3 - VSS	-0.3 ~ +3.6	V	1, 3
I/O Digital Voltage	IOVCC	1.8~3.6	V	1
Operating Temperature	Topr	-40 ~ +85	°C	1
Storage Temperature	Tstg	-55 ~ +150	°C	1

Notes

1. If used beyond the absolute maximum ratings, FT6X36 may be permanently damaged. It is strongly recommended that the device be used within the electrical characteristics in normal operations. If exposed to the condition not within the electrical characteristics, it may affect the reliability of the device.
2. Make sure VDDA (high) ≥ VSSA (low).
3. Make sure VDD(high) ≥ VSS(low).

3.2 DC Characteristics

Table 3-2 DC Characteristics (VDDA=2.8~3.6V, Ta=-40~85°C)

THIS DOCUMENT CONTAINS INFORMATION PROPRIETARY TO FOCALTECH SYSTEMS CO.,LTD., AND MAY NOT BE REPRODUCED, DISCLOSED OR USED IN WHOLE OR PART WITHOUT THE EXPRESS WRITTEN PERMISSION OF FOCALTECH SYSTEMS CO.,LTD.

Item	Symbol	Test Condition	Min.	Typ.	Max.	Unit	Note
Input high-level voltage	VIH		0.7 x IOVCC	-	IOVCC	V	
Input low -level voltage	VIL		-0.3	-	0.3 x IOVCC	V	
Output high -level voltage	VOH	IOH=-0.1mA	0.7 x IOVCC	-	-	V	
Output low -level voltage	VOL	IOH=0.1mA	-	-	0.3 x IOVCC	V	
I/O leakage current	ILI	Vin=0~VDDA	-1	-	1	μA	
Current consumption (Normal operation mode)	Iopr	VDDA =VDD3= 2.8V Ta=25°C MCLK=17.5MHz	-	4	-	mA	
Current consumption (Monitor mode)	Imon	VDDA =VDD3= 2.8V Ta=25°C MCLK=17.5MHz	-	1.5	-	mA	
Current consumption (Sleep mode)	Islp	VDDA =VDD3= 2.8V Ta=25°C MCLK=17.5MHz	-	50	-	uA	
Step-up output voltage	VDD5	VDDA = VDD3=2.8V	-	5	-	V	
Power Supply voltage	VDDA VDD3		2.8	-	3.3	V	

3.3 AC Characteristics

Table 3-3 AC Characteristics of Oscillators

Item	Symbol	Test Condition	Min	Typ.	Max	Unit	Note
OSC clock 1	fosc1	VDDA= 2.8V; Ta=25°C	34.65	35	35.35	MHz	

Table 3-4 AC Characteristics of sensor

Item	Symbol	Test Condition	Min	Typ.	Max	Unit	Note
Sensor acceptable clock	ftx	VDDA= 2.8V; Ta=25°C	0	100	300	KHz	
Sensor output rise time	Ttxr	VDDA= 2.8V; Ta=25°C	-	100	-	nS	
Sensor output fall time	Ttxf	VDDA= 2.8V; Ta=25°C	-	80	-	nS	
Sensor input voltage	Trxi	VDDA= 2.8V; Ta=25°C	-	5	-	V	

3.4 I/O Ports Circuits




Figure 3-1 Digital In/Out Port Circuit




Figure 3-2 Reset Input Port Circuits

3.5 POWER ON/Reset/Wake Sequence

The GPIO such as INT and I2C are advised to be low before powering on. Reset should be pulled down to be low before powering on. INT signal will be sent to the host after initializing all parameters and then start to report points to the host. If Power is down, the voltage of supply must be below 0.3V and Trst is more than 5ms.




Figure 3-7 Power on time



Figure 3-8 Power Cycle requirement




Figure 3-9 Power on Sequence

Reset time must be enough to guarantee reliable reset, the time of starting to report point after resetting approach to the time of starting to report point after powering on.




Figure 3-10 Reset Sequence

Table 3-5 Power on/Reset/Wake Sequence Parameters

Parameter	Description	Min	Max	Units
-----------	-------------	-----	-----	-------

THIS DOCUMENT CONTAINS INFORMATION PROPRIETARY TO FOCALTECH SYSTEMS CO.,LTD., AND MAY NOT BE REPRODUCED, DISCLOSED OR USED IN WHOLE OR PART WITHOUT THE EXPRESS WRITTEN PERMISSION OF FOCALTECH SYSTEMS CO.,LTD.

Tris	Rise time from 0.1VDD to 0.9VDD	-	3	ms
Tpon	Time of starting to report point after powering on	300	-	ms
Tprt	Time of being low after powering on	1	-	ms
Trsi	Time of starting to report point after resetting	300	-	ms
Trst	Reset time	5	-	ms

FOCALTECH CONFIDENTIAL

4 PIN CONFIGURATIONS


Pin List of FT6X36

Table 4-1 Pin Definition of FT6X36


Name	Pin No.					Type	Description
	FT6236H Mg	FT6236G MA	FT6336D MB	FT6436D Qf	FT6436L DQb		
VREF	1	1	47	56	53	PWR	Generated internal reference voltage. A 1 μ F ceramic capacitor to ground is required.
S1	2	2	48	1	54	I/O	Capacitance sensor /driver channel
S2	3	3	1	2	55	I/O	Capacitance sensor /driver channel
S3	4	4	2	3	56	I/O	Capacitance sensor /driver channel
S4	5	5	3	4	1	I/O	Capacitance sensor /driver channel
S5	6	6	4	5	2	I/O	Capacitance sensor /driver channel
S6	7	7	5	6	3	I/O	Capacitance sensor /driver channel
S7	8	8	6	7	4	I/O	Capacitance sensor /driver channel
S8	9	9	7	8	5	I/O	Capacitance sensor /driver channel
S9	10	10	8	9	6	I/O	Capacitance sensor /driver channel
S10	11	11	9	10	7	I/O	Capacitance sensor /driver channel
S11	12	12	10	11	8	I/O	Capacitance sensor /driver channel
S12	13	13	11	12	9	I/O	Capacitance sensor /driver channel
S13	14	14	12	13	10	I/O	Capacitance sensor /driver channel
S14	15	15	13	14	11	I/O	Capacitance sensor /driver channel
S15	16	16	14	15	12	I/O	Capacitance sensor /driver channel
S16	17	17	15	16	13	I/O	Capacitance sensor /driver channel
S17	18	18	16	17	14	I/O	Capacitance sensor /driver channel
S18	19	19	17	18	15	I/O	Capacitance sensor /driver channel
S19	20	20	18	19	16	I/O	Capacitance sensor /driver channel
S20	21	21	19	20	17	I/O	Capacitance sensor /driver channel
S21	22	22	20	21	18	I/O	Capacitance sensor /driver channel
S22	23	23	21	22	19	I/O	Capacitance sensor /driver channel
S23	24	22	22	23	20	I/O	Capacitance sensor /driver channel
S24	25	23	23	24	21	I/O	Capacitance sensor /driver channel
S25	26	24	24	25	22	I/O	Capacitance sensor /driver channel
S26	27	25	25	26	23	I/O	Capacitance sensor /driver channel
S27	28	26	26	27	24	I/O	Capacitance sensor /driver channel
S28	29	27	27	28	25	I/O	Capacitance sensor /driver channel
S29			28	29	26	I/O	Capacitance sensor /driver channel
S30			29	30	27	I/O	Capacitance sensor /driver channel
S31			30	31	28	I/O	Capacitance sensor /driver channel
S32			31	32	29	I/O	Capacitance sensor /driver channel
S33			32	33	30	I/O	Capacitance sensor /driver channel
S34			33	34	31	I/O	Capacitance sensor /driver channel
S35			34	35	32	I/O	Capacitance sensor /driver channel
S36			35	36	33	I/O	Capacitance sensor /driver channel
S37				37	34	I/O	Capacitance sensor /driver channel

THIS DOCUMENT CONTAINS INFORMATION PROPRIETARY TO FOCALTECH SYSTEMS CO.,LTD., AND MAY NOT BE REPRODUCED, DISCLOSED OR USED IN WHOLE OR PART WITHOUT THE EXPRESS WRITTEN PERMISSION OF FOCALTECH SYSTEMS CO.,LTD.

S38				38	35	I/O	Capacitance sensor /driver channel
S39				39	36	I/O	Capacitance sensor /driver channel
S40				40	37	I/O	Capacitance sensor /driver channel
S41				41	38	I/O	Capacitance sensor /driver channel
S42				42	39	I/O	Capacitance sensor /driver channel
S43					40	I/O	Capacitance sensor /driver channel
S44					41	I/O	Capacitance sensor /driver channel
S45					42	I/O	Capacitance sensor /driver channel
S46					43	I/O	Capacitance sensor /driver channel
VDD5	24	30	36	43	44	PWR	High voltage power supply from the charge pump LDO generated internally. A 1µF ceramic to ground is required.
VSSA		31	37			GND	Analog ground
VDDA	25	32	38	44	45	PWR	Analog power supply, A 1µF ceramic capacitor to ground is required.
VSS		33	39			GND	Analog ground
VDDD	26	34	40	45	46	PWR	Digital power supply. A 1µF ceramic capacitor to ground is required.
VSSD						GND	Analog ground
RSTN	27	36	42	46	47	I	External Reset, Low is active
IOVCC	28	37	43	47	48	PWR	I/O power supply
SCL	29	38	44	48	49	I/O	I2C clock input
SDA	30	39	45	49	50	I/O	I2C data input and output
INT	31	40	46	52	51	I/O	External interrupt to the host




FT6236HMg Package Diagram




FT6236GMA Package Diagram


THIS DOCUMENT CONTAINS INFORMATION PROPRIETARY TO FOCALTECH SYSTEMS CO.,LTD., AND MAY NOT BE REPRODUCED, DISCLOSED OR USED IN WHOLE OR PART WITHOUT THE EXPRESS WRITTEN PERMISSION OF FOCALTECH SYSTEMS CO.,LTD.



FT6336DMB Package Diagram




FT6436LDQb Package Diagram



FT6436DMf Package Diagram

5 PACKAGE INFORMATION


5.1 Package Information of QFN-4x4-32L Package



Item	Symbol	Millimeter		
		Min	Type	Max
Total Thickness	A	0.45	0.5	0.55
Stand Off	A1	0	0.035	0.05
Mold Thickness	A2	----	0.3	----
L/F Thickness	A3	0.203 REF		
Lead Width	b	0.15	0.20	0.25
Body Size	D	4 BSC		
	E	4 BSC		
Lead Pitch	e	0.4 BSC		
EP Size	J	2.6	2.7	2.8
	K	2.6	2.7	2.8
Lead Length	L	0.25	0.3	0.35
Package Edge Tolerance	aaa	0.1		
Mold Flatness	bbb	0.1		
Co Planarity	ccc	0.08		
Lead Offset	ddd	0.1		
Exposed Pad Offset	eee	0.1		

THIS DOCUMENT CONTAINS INFORMATION PROPRIETARY TO FOCALTECH SYSTEMS CO.,LTD., AND MAY NOT BE REPRODUCED, DISCLOSED OR USED IN WHOLE OR PART WITHOUT THE EXPRESS WRITTEN PERMISSION OF FOCALTECH SYSTEMS CO.,LTD.


5.2 Package Information of QFN-5x5-40L Package



Item	Symbol	Millimeter		
		Min	Type	Max
Total Thickness	A	0.5	0.55	0.6
Stand Off	A1	0	0.035	0.05
Mold Thickness	A2	----	0.4	0.425
L/F Thickness	A3	0.152 REF		
Lead Width	b	0.15	0.20	0.25
Body Size	D	5 BSC		
	E	5 BSC		
Lead Pitch	e	0.4 BSC		
EP Size	J	3.3	3.4	3.5
	K	3.3	3.4	3.5
Lead Length	L	0.35	0.4	0.45
Package Edge Tolerance	aaa	0.1		
Mold Flatness	bbb	0.1		
Co Planarity	ccc	0.08		
Lead Offset	ddd	0.1		
Exposed Pad Offset	eee	0.1		

THIS DOCUMENT CONTAINS INFORMATION PROPRIETARY TO FOCALTECH SYSTEMS CO.,LTD., AND MAY NOT BE REPRODUCED, DISCLOSED OR USED IN WHOLE OR PART WITHOUT THE EXPRESS WRITTEN PERMISSION OF FOCALTECH SYSTEMS CO.,LTD.


5.3 Package Information of QFN-6x6-48L Package



Item	Symbol	Millimeter		
		Min	Type	Max
Total Thickness	A	0.5	0.55	0.6
Stand Off	A1	0	0.035	0.05
Mold Thickness	A2	----	0.4	0.425
L/F Thickness	A3	0.152 REF		
Lead Width	b	0.15	0.20	0.25
Body Size	D	6 BSC		
	E	6 BSC		
Lead Pitch	e	0.4 BSC		
EP Size	J	4.52	4.62	4.72
	K	4.52	4.62	4.72
Lead Length	L	0.35	0.4	0.45
Package Edge Tolerance	aaa	0.1		
Mold Flatness	bbb	0.1		
Co Planarity	ccc	0.08		
Lead Offset	ddd	0.1		
Exposed Pad Offset	eee	0.1		

THIS DOCUMENT CONTAINS INFORMATION PROPRIETARY TO FOCALTECH SYSTEMS CO.,LTD., AND MAY NOT BE REPRODUCED, DISCLOSED OR USED IN WHOLE OR PART WITHOUT THE EXPRESS WRITTEN PERMISSION OF FOCALTECH SYSTEMS CO.,LTD.


5.4 Package Information of QFN-6x6-56L Package



Item	Symbol	Millimeter		
		Min	Type	Max
Total Thickness	A	0.5	0.55	0.6
Stand Off	A1	0	0.035	0.05
Mold Thickness	A2	----	0.4	----
L/F Thickness	A3	0.152 REF		
Lead Width	b	0.13	0.18	0.23
	b1	0.07	0.12	0.17
Body Size	D	6 BSC		
	E	6 BSC		
Lead Pitch	e	0.35 BSC		
EP Size	J	4.6	4.7	4.8
	K	4.6	4.7	4.8
Lead Length	L	0.35	0.4	0.45
Package Edge Tolerance	aaa	0.1		
Mold Flatness	bbb	0.1		
Co Planarity	ccc	0.08		
Lead Offset	ddd	0.1		
Exposed Pad Offset	eee	0.1		

THIS DOCUMENT CONTAINS INFORMATION PROPRIETARY TO FOCALTECH SYSTEMS CO.,LTD., AND MAY NOT BE REPRODUCED, DISCLOSED OR USED IN WHOLE OR PART WITHOUT THE EXPRESS WRITTEN PERMISSION OF FOCALTECH SYSTEMS CO.,LTD.

5.5 Order Information

Package Type	QFN
	32Pin(4*4)/40Pin(5*5)/48Pin(6*6)/56Pin(6*6)
	0.5-P0.4/0.6-P0.4/0.6-P0.4/0.6-P0.35
Product Name	FT6236HMg/FT6236GMA/FT6336DMB/FT6436LDQb/FT6436DQf
<p>Note:</p> <p>1). The last two letters in the product name indicate the package type and thickness and lead pitch.</p> <p>2). The three last letter indicates the package type.. H : QFN-4*4 ; G : QFN-5*5 ; D : QFN-6*6</p> <p>3). The second last letter indicates the thickness and lead pitch. M : 0.6-P0.4 ; Q : 0.6-P0.35</p> <p>4). The last letter indicates the numbers of sensors. g : 22 ; A : 28 ; B : 36 ; b : 42 ; f : 46</p>	
<p>T: Track Code F/R:"F" for Lead Free process, "R" for Halogen Free process Y: Year Code WW: Week Code S: Lot Code</p>	
V: IC Version	

Product Name	Package Type	Pannel Channels
FT6236HMg	QFN-32L(4*4)	22
FT6236GMA	QFN-40L(5*5)	28
FT6336DMB	QFN-48L(6*6)	36
FT6436LDQb	QFN-56L(6*6)	42
FT6436DQf	QFN-56L(6*6)	46

END OF DATASHEET

THIS DOCUMENT CONTAINS INFORMATION PROPRIETARY TO FOCALTECH SYSTEMS CO.,LTD., AND MAY NOT BE REPRODUCED, DISCLOSED OR USED IN WHOLE OR PART WITHOUT THE EXPRESS WRITTEN PERMISSION OF FOCALTECH SYSTEMS CO.,LTD.