

600k/1.2MHz TFT-LCD Step-Up DC-DC Converter

Features

- 90% Efficiency
- Adjustable Output from V_{IN} to 22V
- 4A, 0.125 Ω , 22V Power MOSFET
- 2.5V to 5.5V Input Range
- 600kHz/1.2MHz Switching Frequency
- TDFN3X3-10 Package

Applications

- LCD Displays
- Portable Applications
- Hand-Held Devices

General Description

The G5110 boost converter incorporate high-performance, current-mode, and frequency selectable pulse width modulation (PWM) circuitry with a built-in N-channel MOSFET to provide a highly efficient regulator.

The G5110's frequency can be selected by user to operate at either 600kHz or 1.2MHz. High switching frequency allows easily filtering and faster loop performance. An external compensation pin provides the user flexibility in determining loop dynamics, allowing the use of small, low ESR ceramic output capacitors. The current-mode architecture provides fast transient response to pulsed loads.

The internal N-channel MOSFET can produce output voltage as high as 22V. User programmed soft-start with an external capacitor determines the input current ramp rate.


The G5110 is available in a 10-pin TDFN3X3 package.

Ordering Information

ORDER NUMBER	MARKING	TEMP. RANGE	PACKAGE (Green)
G5110RE1U	5110	-40°C to 85°C	TDFN3X3-10

Note :RE: TDFN3X3-10
 1: Bonding Code
 U: Tape & Reel

Pin Configuration



Note: Recommend connecting the Thermal Pad to the Ground or let it keep floating.

Typical Application Circuit

