

## Bias Resistor Transistor

### PNP Silicon Surface Mount Transistor with Monolithic Bias Resistor Network

**LDTA123JLT1G**

- Applications

Inverter, Interface, Driver



- Features

- 1) Built-in bias resistors enable the configuration of an inverter circuit without connecting external input resistors (see equivalent circuit).
- 2) The bias resistors consist of thin-film resistors with complete isolation to allow positive biasing of the input. They also have the advantage of almost completely eliminating parasitic effects.
- 3) Only the on/off conditions need to be set for operation, making the device design easy.

- We declare that the material of product compliance with RoHS requirements.

● Absolute maximum ratings ( $T_a=25^\circ\text{C}$ )

Parameter	Symbol	Limits	Unit
Supply voltage	$V_{CC}$	-50	V
Input voltage	$V_{IN}$	-12 to +5	V
Output current	$I_o$	-100	mA
	$I_C(\text{Max.})$	-100	mA
Power dissipation	$P_D$	200	mW
Junction temperature	$T_j$	150	°C
Storage temperature	$T_{STG}$	-55 to +150	°C



#### DEVICE MARKING AND RESISTOR VALUES

Device	Marking	R1 (K)	R2 (K)	Shipping
LDTA123JLT1G	A6M	2.2	47	3000/Tape & Reel
LDTA123JLT3G	A6M	2.2	47	10000/Tape & Reel

● Electrical characteristics ( $T_a=25^\circ\text{C}$ )

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Input voltage	$V_{I(\text{off})}$	—	—	-0.5	V	$V_{CC}=-5V, I_o=-100\mu\text{A}$
	$V_{I(\text{on})}$	-1.1	—	—		$V_O=-0.3V, I_o=-5\text{mA}$
Output voltage	$V_{O(\text{on})}$	—	-0.1	-0.3	V	$I_o/I_i=-5\text{mA}/-0.25\text{mA}$
Input current	$I_I$	—	—	-3.6	mA	$V_I=-5V$
Output current	$I_{O(\text{off})}$	—	—	-0.5	$\mu\text{A}$	$V_{CC}=-50V, V_I=0V$
DC current gain	$G_I$	80	—	—		$V_O=-5V, I_o=-10\text{mA}$
Input resistance	$R_I$	1.54	2.2	2.86	k $\Omega$	—
Resistance ratio	$R_2/R_1$	17	21	26	—	—
Transition frequency	$f_T$ *	—	250	—	MHz	$V_{CE}=-10V, I_E=5\text{mA}, f=100\text{MHz}$

\* Characteristics of built-in transistor

**LDTA123JLT1G**

### ●Electrical characteristic curves




Fig.1 Input voltage vs. output current  
(ON characteristics)




Fig.2 Output current vs. input voltage  
(OFF characteristics)




Fig.3 DC current gain vs. output current





Fig.4 Output voltage vs. output current

**LDTA123JLT1G**
**SOT-23**
**NOTES:**

1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M,1982
2. CONTROLLING DIMENSION: INCH.



DIM	INCHES		MILLIMETERS	
	MIN	MAX	MIN	MAX
A	0.1102	0.1197	2.80	3.04
B	0.0472	0.0551	1.20	1.40
C	0.0350	0.0440	0.89	1.11
D	0.0150	0.0200	0.37	0.50
G	0.0701	0.0807	1.78	2.04
H	0.0005	0.0040	0.013	0.100
J	0.0034	0.0070	0.085	0.177
K	0.0140	0.0285	0.35	0.69
L	0.0350	0.0401	0.89	1.02
S	0.0830	0.1039	2.10	2.64
V	0.0177	0.0236	0.45	0.60

