

SANYO Semiconductors DATA SHEET



Bi-CMOS IC Low power consumption and high efficiency Step-down Switching Regulator Controller

Overview

LV5068V is 1ch step-down switching regulator. The operation current is about 80µA, and low power consumption is achieved.

Functions

- 1ch SBD rectification controller IC
- Maximum value of light load mode current is 80µA.
- Built-in OCP circuit with P-by-P method
- When P-by-P is generated continuously, it shifts to the HICCUP operation.
- If connect C-HICCUP to GND pin, then latch-off when over current.
- The oscillatory frequency can be set by the external pin. The oscillatory frequency is 300 kHz to 2.2MHz
- Built-in UVLO, TSD
- Synchronous driving with external signal

Specifications

Maximum Ratings at $Ta = 25^{\circ}C$

Parameter	Symbol	Conditions	Ratings	Unit
Input voltage	V _{IN} max		45	V
Allowable pin voltage	PDR,HDRV,RSNS, ILIM,EN,PG		V _{IN}	V
	V _{IN} -PDR		6	V
	REF		6	V
	SS,FB,COMP,RT C-HICCUP,SYNC		REF	V
Allowable power dissipation	Pd max	Specified substrate *1	0.74	W
Operating temperature	Topr		-40 to +85	°C
Storage temperature	Tstg		-55 to +150	°C

*1: Specified substrate 114.3mm×76.1mm×1.6mm³ glass-epoxy

- Any and all SANYO Semiconductor Co.,Ltd. products described or contained herein are, with regard to "standard application", intended for the use as general electronics equipment (home appliances, AV equipment, communication device, office equipment, industrial equipment etc.). The products mentioned herein shall not be intended for use for any "special application" (medical equipment whose purpose is to sustain life, aerospace instrument, nuclear control device, burning appliances, transportation machine, traffic signal system, safety equipment etc.) that shall require extremely high level of reliability and can directly threaten human lives in case of failure or malfunction of the product or may cause harm to human bodies, nor shall they grant any guarantee thereof. If you should intend to use our products for applications outside the standard applications, please consult with us prior to the intended use. If there is no consultation or inquiry before the intended use, our customer shall be solely responsible for the use.
- Specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.

SANYO Semiconductor Co., Ltd. http://semicon.sanyo.com/en/network

LV5068V

Recommended Operating Conditions at $Ta = 25^{\circ}C$

Parameter	Symbol	Conditions	Ratings	Unit
Input voltage range	VIN		4.5 to 40	V

Electrical Characteristics at $Ta = 25^{\circ}C$, $V_{IN} = 15V$

Deremeter	Cumbol	Symbol	Ratings			Linit	
Parameter	Symbol Conditions		min	typ	max	Unit	
Reference voltage							
Internal reference voltage	Vref		1.241	1.260	1.279	V	
Pch drive voltage	V _{PDR}	I _{OUT} =0 to -5mA	V _{IN} -5.5	V _{IN} -5.0	V _{IN} -4.5	V	
Saw wave oscillator							
Oscillatory frequency	Fosc	RT=470kΩ	280	330	380	kHz	
ON/OFF circuit							
IC start-up voltage	VCNT_ON		1.5		VIN	V	
Disable voltage	VCNT_OFF		0		0.3	V	
Soft start circuit							
Soft start source current	I _{SS} _SC	EN>1.5V	1.3	2.0	2.7	μA	
Soft start sink current	I _{SS} _SK	EN<0.3V, SS=4V	1.0	1.6	2.2	mA	
UVLO circuit			•		•		
UVLO release voltage	VUVLON	FB=COMP	3.3	3.7	4.1	V	
UVLO lock voltage	VUVLOF	FB=COMP	2.5	2.9	3.3	V	
Error amplifier	•						
Input bias current	I _{EA} _IN		-100	-50	100	nA	
Error amplifier gain	G _{EA}		100	250	400	μA/V	
Output sink current	I _{EA} OSK	FB=1.75V	-40	-20	-10	μA	
Output source current	I _{ES} _OSC	FB=0.75V	10	20	40	μA	
Over current limit circuit							
Reference current	I _{LIM} 1		48.4	55	61.6	μA	
Over current detection	VLIM OFS		-5		+5	mV	
comparator offset voltage							
RSNS pin input range	VRSNS		V _{IN} -0.175		VIN	V	
HICCUP timer start-up cycle	NLCYCLES			15		cycle	
HICCUP comparator threshold	V _{tHIC}		1.2	1.26	1.32	V	
voltage				0	2	•	
	HIC		1	Z	3	μΑ	
			05				
	D max		95			%	
Power good "L" sink current	IPWRGD_L	PG=5V	4	5	6	mA	
Power good "H" leakage current	IPWRGD_H	PG=5V	0		1	μΑ	
Power good threshold voltage	VtPG		1.0	1.1	1.2	V	
Power good hysteresis	VPG_H		40	50	60	mV	
Output on-resistance (High)	RONH			3		Ω	
Output on-resistance (Low)	RONL			3		Ω	
Output on-current (High)	IONH		500			mA	
Output on-current (Low)	IONL		500			mA	
The entire device							
Stand-by current	Iccs	EN<0.3V	0		1	μA	
Light load mode consumption	ISLEEP ¹	EN>1.5V,	30	55	80	μA	
Thermal shutdown	TSD	*2	150	170	100	്റ	
	100	-	150	170	190		

*2: Design certification

Package Dimensions

unit : mm (typ)



Block Diagram



Pin Assignment



Pin Descriptions

Pin No.	Pin name	Descriptions	Equivalent circuit
1	PG	Power good pin. Connect to open drain of MOS-FET in ICs inside. Setting output voltage to "L", when FB voltage is 1.05V or less	PG § 1kΩ GND
2	EN	ON/OFF pin	
3	ILIM	For current detection. Sink current is about 55μ A. The current limiter comparator works when an external resistor is connected between this pin and V _{IN} , and if the voltage of this resistor is less than the voltage of RSNS then Pch MOS is turned off. This operation is reset each PWM pulse.	
4	VIN	Supply voltage pin. It is observed by the UVLO function. When its voltage becomes 3.7V or more, ICs startup in soft start.	VIN GND
5	RSNS	Current detection resistor connection pin. Resistor is connected between $V_{\mbox{\rm IN}}$ and this pin, and the current flows to MOSFET are measured.	

Continued on next page.

Continued from preceding page.						
Pin No.	Pin name	Descriptions	Equivalent circuit			
6	HDRV	The external high-side MOSFET gate drive pin.	VIN ₹130kΩ HDRV PDR			
7	PDR	Gate drive voltage of the external Pch MOSFET. Meanwhile, the bypass capacitor is connected between ${\rm V}_{\rm IN}$ and this pin.	1.3MΩ \$ 1.5MΩ \$ 10kΩ \$ 10kΩ \$ 10kΩ \$ GND			
8	GND	Ground Pin. Ground pin voltage is reference voltage.	VIN GND			
9	SYNC	Pin of using combined of external synchronous signal input pin				
10	RT	Oscillation frequency setting pin. Resistor is connected between this pin and GND.				
11	C-HICCUP	It is capacitor connection pin for setting re-startup cycle in HICCUP mode. If connect it to GND pin, then latch-off when over current.	C-HICCUP			
12	SS	Capacitor connection pin for soft start. About 2µA current charges the soft start capacitor.				
13	NU	no più.				

Continued on next page.

Continued from preceding page.						
Pin No.	Pin name	Descriptions	Equivalent circuit			
14	COMP	Error Amplifier Output Pin. The phase compensation network is connected between GND pin and COMP pin. Thanks to current-mode control, COMP pin voltage would tell you the output current amplitude. COMP pin is connected internally to an int.comparator which comparators with 0.9V reference. If COMP pin voltage is larger than. 0.9V, IC operates in "continuous mode". If COMP pin voltage is smaller than 0.9V, IC operates in "discontinuous mode (low consumption mode)".	VIN			
15	FB	Error amplifier reverse input pin. ICs make its voltage keep 1.26V. Output voltage is divided by external resistors and it across FB.	$\begin{array}{c} V_{IN} & 10k\Omega \\ & 10k\Omega \\ & 1k\Omega \\ & 1k\Omega \\ & 1k\Omega \\ & 1k\Omega \\ & 00000 \\ & 0000 \\ &$			
16	REF	Reference voltage.	$\begin{array}{c} V_{\text{IN}} & 10\Omega \\ 10\Omega \\ 10\Omega \\ 51k\Omega \\ 51k\Omega \\ 51k\Omega \\ 51k\Omega \\ 6ND \\ 6$			

- SANYO Semiconductor Co.,Ltd. assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein.
- SANYO Semiconductor Co.,Ltd. strives to supply high-quality high-reliability products, however, any and all semiconductor products fail or malfunction with some probability. It is possible that these probabilistic failures or malfunction could give rise to accidents or events that could endanger human lives, trouble that could give rise to smoke or fire, or accidents that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO Semiconductor Co.,Ltd. products described or contained herein are controlled under any of applicable local export control laws and regulations, such products may require the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written consent of SANYO Semiconductor Co.,Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO Semiconductor Co.,Ltd. product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production.
- Upon using the technical information or products described herein, neither warranty nor license shall be granted with regard to intellectual property rights or any other rights of SANYO Semiconductor Co.,Ltd. or any third party. SANYO Semiconductor Co.,Ltd. shall not be liable for any claim or suits with regard to a third party's intellectual property rights which has resulted from the use of the technical information and products mentioned above.

This catalog provides information as of November, 2010. Specifications and information herein are subject to change without notice.