


The RF Line 550 MHz CATV Amplifier

. . . designed specifically for 550 MHz CATV applications. Features ion-implanted arsenic emitter transistors with 7.0 GHz f_T and an all gold metallization system.

- Specified for 77 Channel Performance
- Broadband Power Gain — @ $f = 40\text{--}550$ MHz
 $G_p = 14$ dB (Typ) @ 50 MHz
 14.5 dB (Min) @ 550 MHz
- Broadband Noise Figure
 $NF = 7.5$ dB (Max)
- Superior Gain, Return Loss and DC Current Stability with Temperature
- All Gold Metallization
- 7.0 GHz Ion-Implanted Transistors

MHW6142

**14 dB GAIN
550 MHz
77-CHANNEL
CATV INPUT/OUTPUT
TRUNK AMPLIFIER**



CASE 714-06, STYLE 1

ABSOLUTE MAXIMUM RATINGS

Rating	Symbol	Value	Unit
RF Voltage Input (Single Tone)	V_{in}	+70	dBmV
DC Supply Voltage	V_{CC}	+28	Vdc
Operating Case Temperature Range	T_C	-20 to +100	°C
Storage Temperature Range	T_{stg}	-40 to +100	°C

ELECTRICAL CHARACTERISTICS ($V_{CC} = 24$ Vdc, $T_C = +30^\circ\text{C}$, 75 Ω system unless otherwise noted)

Characteristic	Symbol	Min	Typ	Max	Unit	
Frequency Range	BW	40	—	550	MHz	
Power Gain — 50 MHz	G_p	13.5	14	14.5	dB	
Power Gain — 550 MHz	G_p	14.5	—	—	dB	
Slope	S	0.2	—	1.5	dB	
Gain Flatness (Peak To Valley)	—	—	0.2	0.5	dB	
Return Loss — Input/Output ($Z_0 = 75$ Ohms)	IRL/ORL	18	—	—	dB	
Second Order Intermodulation Distortion ($V_{out} = +46$ dBmV per ch., Ch 2, M13, M22) ($V_{out} = +44$ dBmV per ch., Ch 2, M30, M39)	IMD	—	-78 -75	— -72	dB	
Cross Modulation Distortion ($V_{out} = +46$ dBmV per ch.) ($V_{out} = +44$ dBmV per ch.)	60-Channel FLAT 77-Channel FLAT	XMD ₆₀ XMD ₇₇	— —	-64 -65	-62	dB
Composite Triple Beat ($V_{out} = +46$ dBmV per ch.) ($V_{out} = +44$ dBmV per ch.)	60-Channel FLAT 77-Channel FLAT	CTB ₆₀ CTB ₇₇	— —	-62 -65	-59	dB
Noise Figure ($f = 550$ MHz)	NF	—	6.5	7.5	dB	
DC Current	I_{DC}	—	210	240	mA	

