

## LOW VOLTAGE VIDEO AMPLIFIER WITH LPF

### ■GENERAL DESCRIPTION

The NJW1350 is a Low Voltage Video Amplifier with LPF circuit. By the internal charge pump circuit, output capacitor is unnecessary.

The NJW1350 features low power and small package, and is suitable for low power design on downsizing of portable video system and system with video output.

Moreover, the following voltage gain variations are arranged.

- NJW1351(Gain=6dB)
- NJW1352(Gain=9dB)
- NJW1353(Gain=16dB)

### ■PACKAGE OUTLINE



NJW1350RB1




NJW1350KK1

### ■FEATURES


- Operating Voltage                    2.5 to 3.45V
- Unnecessary output coupling capacitor
- 12dB amplifier
- Internal 75Ω Driver Circuit (2-system drive)
- Internal LPF                            -38dB at 19MHz typ
- Power Save Circuit
- Bi-CMOS Technology
- Package Outline                        TVSP8, SON10

### ■PIN CONFIGURATION



NJW1350RB1(TVSP8)


- 1: CP1
- 2: V+
- 3: VIN
- 4: Power Save
- 5: VOUT
- 6: GND
- 7: V-
- 8: CP2



NJW1350KK1(SON10)

- 1: CP1
- 2: V+2
- 3: V+1
- 4: VIN
- 5: Power Save
- 6: VOUT
- 7: GND1
- 8: GND2:
- 9: V-

### ■BLOCK DIAGRAM



(NOTE)

TVSP8: V+1 and V+2 are the same pins, and GND1 and GND2 are the same pins.

# NJW1350

www.DataSheet4U.com

## ■ABSOLUTE MAXIMUM RATINGS (Ta=25°C)

| PARAMETER                   | SYMBOL         | RATINGS                | UNIT |
|-----------------------------|----------------|------------------------|------|
| Supply Voltage              | V <sup>+</sup> | 3.55                   | V    |
| Power Dissipation           | P <sub>D</sub> | TVSP8:320<br>SON10:250 | mW   |
| Operating Temperature Range | Topr           | -40 to +85             | °C   |
| Storage Temperature Range   | Tstg           | -55 to +125            | °C   |

## ■RECOMMENDED OPERATING CONDITION(Ta=25°C)

| PARAMETER         | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|-------------------|--------|----------------|------|------|------|------|
| Operating Voltage | Vopr   |                | 2.5  | -    | 3.45 | V    |

## ■ELECTRICAL CHARACTERISTICS (V<sup>+</sup>=3.0V,R<sub>L</sub>=150Ω,Ta=25°C)

| PARAMETER                       | SYMBOL               | TEST CONDITION   | MIN.  | TYP.  | MAX.           | UNIT |
|---------------------------------|----------------------|--|-------|-------|----------------|------|
| Operating Current               | I <sub>CC</sub>      | No Signal  | -     | 14.0  | 20.0           | mA   |
| Operating Current at Power Save | I <sub>save</sub>    | No Signal, Power Save Mode   | -     | 0     | 1.0            | uA   |
| Maximum Output Voltage Swing    | V <sub>om</sub>      | f=100kHz, THD=1%   | 4.5   | 5.2   | -              | Vp-p |
| Voltage Gain                    | G <sub>v</sub>       | V <sub>in</sub> =100kHz, 0.5Vp-p,<br>Input Sine Signal                                   | 11.6  | 12.0  | 12.4           | dB   |
| Low Pass Filter Characteristic  | G <sub>fy</sub> 4.5M | V <sub>in</sub> =4.5MHz/100kHz, 0.5Vp-p  | -0.75 | -0.05 | 0.25           | dB   |
|                                 | G <sub>fy</sub> 8M   | V <sub>in</sub> =8MHz/100kHz, 0.5Vp-p  | -7.0  | -3.0  | -1.0           |      |
|                                 | G <sub>fy</sub> 19M  | V <sub>in</sub> =19MHz/100kHz, 0.5Vp-p   | -     | -38   | -23            |      |
| Differential Gain               | DG                   | V <sub>in</sub> =0.5Vp-p, 10step Video Signal  | -     | 0.5   | -              | %    |
| Differential Phase              | DP                   | V <sub>in</sub> =0.5Vp-p, 10step Video Signal  | -     | 0.5   | -              | deg  |
| S/N Ratio                       | SN <sub>v</sub>      | 100kHz to 6MHz, V <sub>in</sub> =0.5Vp-p<br>100% White Video Signal, R <sub>L</sub> =75Ω | -     | +70   | -              | dB   |
| Switching Noise Level           | N <sub>swpl</sub>    | R <sub>L</sub> =75Ω,<br>V <sub>out</sub> =10% White Video Signal                         | -     | 4.0   | 7.0            | mVpp |
| 2nd. Distortion                 | H <sub>v</sub>       | V <sub>in</sub> =0.5Vp-p, Sine Signal ,<br>3.58MHz, R <sub>L</sub> =75Ω                  | -     | -60   | -              | dB   |
| SW Change Voltage High Level    | V <sub>thPH</sub>    | Active   | 1.25  | -     | V <sup>+</sup> | V    |
| SW Change Voltage Low Level     | V <sub>thPL</sub>    | Non-active   | 0     | -     | 0.45           |      |

## ■CONTROL TERMINAL

| PARAMETER  | STATUS | NOTE            |
|------------|--------|-----------------|
| Power Save | H      | Power Save: OFF |
|            | L      | Power Save: ON  |
|            | OPEN   | Power Save: ON  |



\*Please refer to the NJW1351 data sheet for the example of the characteristic.

Ver.2

*New Japan Radio Co., Ltd.*

www.DataSheet4U.com

## TEST CIRCUIT



**[CAUTION]**  
 The specifications on this databook are only given for information, without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.