

## High Voltage Very low current consumption $I_o=100\text{mA}$ Regulator

### ■ GENERAL DESCRIPTION

The NJW4181 is a high input voltage and low current consumption 100mA series regulator low current consumption  $I_q=9\mu\text{A}$  and small package.

It has two package lineup. SOT-89 is able to direct replace to 3-terminal 78L series. ESON6, tiny DFN package, corresponds to a demand on miniaturization of sensor application and so on.

Due to the low current consumption of  $9\mu\text{A}$ , the NJW4181 is suitable for light load and continuously running applications such as power management microprocessor, RTC, protection circuit, security system and so on.

### ■ PACKAGE OUTLINE



NJW4181KG1



NJW4181U3

### ■ FEATURES


- Wide Operating Voltage Range 35V (max.)
- Low Current Consumption 9 $\mu\text{A}$  (typ.)
- Correspond to Low ESR capacitor (MLCC)
- Output Current  $I_o(\text{min.})=100\text{mA}$
- High Precision Output  $V_o \pm 1.0\%$
- Internal Thermal Overload Protection
- Internal Over Current Protection
- Internal Reverse Current Protection
- Package Outline DFN6-G1(ESON6-G1), SOT-89-3

### ■ PRODUCT CLASSIFICATION


Device Name	Version	ON/OFF Function	Package	Status
NJW4181KG1-xxA	A	Yes	DFN6-G1(ESON6-G1)	PLAN
NJW4181U2-xxA	A	Yes	SOT-89-5	PLAN
NJW4181KG1-xxB	B	-	DFN6-G1(ESON6-G1)	
NJW4181U3-xxB	B	-	SOT-89-3	

xx=Output Voltage ex) 33=3.3V 05=5.0V

### ■ PIN CONFIGURATION



NJW4181KG1



NJW4181U3

### ■ INPUT VOLTAGE RANGE


$V_o \leq 3\text{V}$ :  $V_{IN} = +4.7\text{V}$  to  $+35\text{V}$

$3\text{V} < V_o \leq 5\text{V}$ :  $V_{IN} = V_o + 1.7\text{V}$  to  $+35\text{V}$

$V_o > 5\text{V}$ :  $V_{IN} = V_o + 2.0\text{V}$  to  $+35\text{V}$

# NJW4181

## ■BLOCK DIAGRAM



## ■OUTPUT VOLTAGE RANK LIST

DFN6-G1(ESON6-G1)

SOT-89-3

Device Name	V <sub>OUT</sub>	Device Name	V <sub>OUT</sub>
NJW4181KG1-25B	2.5V	NJW4181U3-25B	2.5V
NJW4181KG1-33B	3.3V	NJW4181U3-33B	3.3V
NJW4181KG1-05B	5.0V	NJW4181U3-05B	5.0V
NJW4181KG1-08B	8.0V	NJW4181U3-08B	8.0V
NJW4181KG1-15B	15.0V	NJW4181U3-12B	12.0V
		NJW4181U3-15B	15.0V

## ■ABSOLUTE MAXIMUM RATINGS

(Ta=25°C)

PARAMETER	SYMBOL	RATINGS	UNIT
Input Voltage	V <sub>IN</sub>	-0.3 to +40	V
Output Voltage	V <sub>OUT</sub>	-0.3 ~ V <sub>IN</sub> +7 ≤ 17 (Vo≤5.0V) -0.3 ~ +17 (Vo>5.0V)	V
Power Dissipation	P <sub>D</sub>	DFN6-G1	mW
		(ESON6-G1)	
		SOT-89-3	
Junction Temperature	T <sub>J</sub>	-40 to +150	°C
Operating Temperature	Topr	-40 to +85	°C
Storage Temperature	Tstg	-40 to +150	°C

(\*1): Mounted on glass epoxy board (101.5×114.5×1.6mm: based on EIA/JEDEC standard, 2Layers FR-4, with Exposed Pad)

(\*2): Mounted on glass epoxy board (101.5×114.5×1.6mm: based on EIA/JEDEC standard, 4Layers FR-4, with Exposed Pad)  
(4Layers: Applying 99.5×99.5mm inner Cu area and a thermal via hole to a board based on JEDEC standard JESD51-5)

(\*3): Mounted on glass epoxy board. (76.2×114.3×1.6mm:based on EIA/JDEC standard size, 2Layers, Cu area 100mm<sup>2</sup>)

(\*4): Mounted on glass epoxy board. (76.2×114.3×1.6mm:based on EIA/JDEC standard, 4Layers)

(4Layers: Applying 74.2×74.2mm inner Cu area and a thermal via hole to a board based on JEDEC standard JESD51-5)

## ■ ELECTRICAL CHARACTERISTICS



(Unless otherwise specified,  $V_{IN}=V_O+2.3V(3V<V_O\leq 5V: V_{IN} = V_O+2.0V, V_O\leq 3V: V_{IN} = 5.0V)$   
 $C_{IN} = 0.1 \mu F, C_O = 2.2\mu F, T_a = 25^\circ C$ )

PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Output Voltage	$V_O$	$I_O=30mA$	-1.0%	-	+1.0%	V
Quiescent Current	$I_Q$	$I_O=0mA$	-	9	20	$\mu A$
Output Current	$I_O$	$V_O \times 0.9$	100	-	-	mA
Line Regulation	$\Delta V_O/\Delta V_{IN}$	$V_O\leq 3V: V_{IN} = +5.0V$ to +35V $3V<V_O\leq 5V: V_{IN} = V_O+2.0V$ to +35V $V_O>5V: V_{IN} = V_O+2.3V$ to +35V, $I_O=30mA$	-	-	0.05	%/V
Load Regulation	$\Delta V_O/\Delta I_O$	$I_O=0mA$ to 100mA	-	-	0.005	%/mA
Average Temperature Coefficient of Output Voltage	$\Delta V_O/\Delta T_a$	$T_a=0$ to $85^\circ C, I_O=10mA$	-	$\pm 100$	-	ppm/ $^\circ C$
Sink Current under Reverse Current Protection operating	$I_{REVERSE}$	$V_{IN} = 0V, V_O=5V(V_O \leq 5.0V)$	-	0	1	$\mu A$
		$V_{IN} = 0V, V_O=15V(V_O > 5.0V)$		100	200	
Input Voltage	$V_{IN}$	$V_O\leq 3V$	4.7	-	35	V
		$3V<V_O\leq 5V$	$V_O+1.7$	-	35	
		$V_O>5V$	$V_O+2.0$	-	35	


The above specification is a common specification for all output voltages.

Therefore, it may be different from the individual specification for a specific output voltage.


## POWER DISSIPATION vs. AMBIENT TEMPERATURE



## ■ TEST CIRCUIT



## ■ TYPICAL APPLICATION



### \*Input Capacitor $C_{IN}$

Input Capacitor  $C_{IN}$  is required to prevent oscillation and reduce power supply ripple for applications when high power supply impedance or a long power supply line.

Therefore, use the recommended  $C_{IN}$  value (refer to conditions of ELECTRIC CHARACTERISTIC) or larger and should connect between GND and the  $V_{IN}$  pin as shortest path as possible to avoid the problem.

### \*Output Capacitor $C_O$

Output capacitor ( $C_O$ ) will be required for a phase compensation of the internal error amplifier.

The capacitance and the equivalent series resistance (ESR) influence to stable operation of the regulator.

Use of a smaller  $C_O$  may cause excess output noise or oscillation of the regulator due to lack of the phase compensation.

On the other hand, Use of a larger  $C_O$  reduces output noise and ripple output, and also improves output transient response when rapid load change.

Therefore, use the recommended  $C_O$  value (refer to conditions of ELECTRIC CHARACTERISTIC) or larger and should connect between GND and the  $V_{OUT}$  pin as shortest path as possible for stable operation

In addition, you should consider varied characteristics of capacitor (a frequency characteristic, a temperature characteristic, a DC bias characteristic and so on) and unevenness peculiar to a capacitor supplier enough.

When selecting  $C_O$ , recommend that have withstand voltage margin against output voltage and superior temperature characteristic.

### \*Reverse Current Protection







NJW4181 is built-in a Reverse Current Protection. This circuit restrains reverse current from the  $V_O$  pin to the  $V_{IN}$  pin when the input voltage is less than the output voltage.

In case of the voltage rank 5.0V or below, reverse voltage differential between output and input should keep  $V_{IN}+7V$  or less, to prevent IC breaking due to huge reverse current.







And also, the absolute maximum ratings of the  $V_O$  pin (17V) should not be exceeded.

# NJW4181

## NJW4181-05 TYPICAL CHARACTERISTICS









## NJW4181-05 TYPICAL CHARACTERISTICS









# NJW4181

## NJW4181-05 TYPICAL CHARACTERISTICS











## NJW4181-05 TYPICAL CHARACTERISTICS









# NJW4181







## ■ NJW4181-33 TYPICAL CHARACTERISTICS







## ■NJW4181-33 TYPICAL CHARACTERISTICS



## ■NJW4181-33 TYPICAL CHARACTERISTICS



## ■ NJW4181-33 TYPICAL CHARACTERISTICS



[CAUTION]  
 The specifications on this databook are only given for information, without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.