

# PM823

## Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO

Rev. 4 — 23 June 2022

Product data sheet  
PUBLIC

### 1 Product overview

---

The PM823 is an efficient low-cost power regulator. It consists of two 1.5 A buck regulators and one 525 mA LDO. The LDO can be powered by the buck converter output ( $\geq 1.6$  V) to minimize the power loss and simplify the system thermal de-sign.

The PM823 is optimized for module applications. It minimizes the PCB footprint and BOM cost. The PM823 12-bump WLCSP package provides the smallest footprint for the state-of-the-art module applications. For general purpose applications, the 24-pin QFN package can meet the low-cost PCB requirements. The QFN package also provides additional functions such as power good outputs.

The PM823 Dynamic Voltage Scaling (DVS) feature supports the latest SoC and processor power control scheme. The PM823 also supports Adaptive Voltage Scaling (AVS). The serial interface can be used to program the device to meet different application requirements.

#### Features

- Supports 2.7 V~5.5 V operating voltage
- Two 1.5 A synchronous buck converters
- Single LDO supports up to 525 mA
- Ultra low 15  $\mu$ A sleep current
- 3 MHz switching frequency
- High output voltage accuracy
- Supports both DVS and AVS
- Single wire proprietary serial interface

#### Package options

- WLCSP-12 lead (0.35 mm ball pitch)
- QFN-24 lead (0.5 mm pin pitch)

#### Applications

- IoT devices
- Wi-Fi modules
- Smart home devices
- Cameras, printers
- Smart appliances
- Wi-Fi hubs, Access Points (APs)
- Set top boxes






Figure 1. PM823 typical application-QFN package option




Figure 2. PM823 typical application-WLCSP package option

## 2 Ordering information




Figure 3. Part numbering scheme

The standard ordering part numbers for the respective solutions are the following:

Table 1. Part order options

Part order number	Buck1 output voltage	Buck2 output voltage	LDO output voltage	Package type
PM823UK/A0CZ (Tape and Reel)	1.1V	2.2V	1.8V	12-pad WLCSP
PM823HN/A0CHP (Tape and Reel)	1.1V	2.2V	1.8V	24-pin QFN


**Note:** Based on Marvell's 88PG823 RMA history, no RMA will be accepted except manufacturing defects. Device provided AS-IS and support limited to NXP Wi-Fi/Bluetooth system related questions.

### 3 Signal description

#### 3.1 Pin configuration

##### 3.1.1 12-lead WLCSP configuration

[Figure 4](#) shows PM823 12-lead WLCSP configuration diagram.



3.1.2 24-pin QFN configuration

Figure 5 shows PM823 24-pin QFN configuration diagram.




Figure 5. 4 mm x 4 mm QFN-24 in 0.5 mm pitch pin configuration, top (see through) view

3.2 Pin descriptions

Table 3 shows the pin description details for PM823.

Table 2. Pin types

Pin type	Description
I	Input
I/O	Input / Output
GND	Ground
NC	No Connection
S	Supply
O	Output

## Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO

Table 3. Pin description

Pin number		Pin name	Pin type	Function
WLCSP	QFN			
A1	18, 19, 20	PGND2	GND	Power ground for Buck2 regulator <ul style="list-style-type: none"> <li>It must be connected to the negative terminals of the input and output capacitors</li> <li>All PGND pins must be connected to SGND, EPAD, and make a star connection to system ground</li> <li><b>Do not float any PGND pin</b></li> </ul>
A2	21, 22	SW2	O	Switch node for Buck2 regulator <ul style="list-style-type: none"> <li>Internally connected to the drains of the high side and low side MOSFETs</li> <li>Connect to the external inductor</li> <li>When the switching regulator is disabled, the SW node is high impedance</li> <li>If step-down regulator 2 is not in use, float this pin</li> </ul>
A3	23, 24	PVIN	S	Switching regulator power input <ul style="list-style-type: none"> <li>Power input voltage. Internally connected to the source of the high side MOSFET</li> <li>Connect a ceramic input capacitor or an equivalent low ESR input capacitor between PVIN and PGND. Place it as close as possible to PVIN and PGND pins. See <a href="#">Section 8 "Application information"</a>.</li> <li>The voltage between SVIN and PVIN should be equal to 50mV or less</li> <li>All PVIN pins must be connected to the same voltage source</li> <li><b>Do not float any PVIN pin</b></li> </ul>
B1	N/A	EN	I	Enable Input for all regulators <ul style="list-style-type: none"> <li>Logic high enables regulators and logic low disables regulators</li> <li>See <a href="#">Section 4 "Electrical specifications"</a> for detailed logic high and logic low specifications</li> <li>When not in use, connect this pin to GND or connect a 0Ω resistor to GND</li> <li><b>Do not float this pin</b></li> </ul>
B2	12	DVS1	I	Dynamic voltage scaling control 1 <ul style="list-style-type: none"> <li>This digital input is used to select one of the three operating modes. See <a href="#">Section 5.6 "Operating modes"</a> output voltage settings for mode selection.</li> <li><b>Do not float this pin</b></li> </ul>
B3	1	SW1	O	Switch node for buck1 regulator <ul style="list-style-type: none"> <li>Internally connected to the drains of the high side and low side MOSFETs</li> <li>Connect to the external inductor</li> <li>When the switching regulator is disabled, the SW node is high impedance</li> <li>If Step-down Regulator 1 is not in use, float this pin</li> </ul>
C1	17	FB2	I	Buck2 regulator output voltage sense feedback <ul style="list-style-type: none"> <li>Connect this pin to the output capacitor</li> <li>This pin senses the output voltage of the switching regulator</li> <li><b>Do not float this pin</b></li> </ul>

Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO

Table 3. Pin description...continued

Pin number		Pin name	Pin type	Function
WLCSP	QFN			
C2	11	DVS0/SDI	I	Dynamic voltage scaling control 0 / serial data input <ul style="list-style-type: none"> <li>• This digital input pin has two functions</li> <li>• If DVS1=0, this pin is used as DVS0 input</li> <li>• If DVS1=1, this pin becomes the one wire serial interface input</li> <li>• Input data into this pin is used to program the output voltage (see <a href="#">Section 5.2 "Serial interface (1-wire)"</a>)</li> <li>• When not in use, connect this pin to GND or connect a 0Ω resistor to GND</li> <li>• See <a href="#">Section 5.7 "DVS output voltage settings"</a> for mode selection</li> <li>• <b>Do not share this pin with other serial interface pins</b></li> </ul> <b>Do not float this pin</b>
C3	2, 3	PGND1	GND	Power ground for Buck1 regulator <ul style="list-style-type: none"> <li>• This pin must be connected to the negative terminals of the input and output capacitors</li> <li>• All PGND pins must be connected to SGND, EPAD, and make a star connection to system ground</li> <li>• <b>Do not float this pin</b></li> </ul>
D1	14	FB1	I	Buck1 regulator output voltage sense feedback <ul style="list-style-type: none"> <li>• Connect this pin to the output capacitor</li> <li>• This pin senses the output voltage of the switching regulator</li> <li>• <b>Do not float this pin</b></li> </ul>
D2	6	VIN-LDO	S	LDO power supply <ul style="list-style-type: none"> <li>• This is the power supply input for the LDO Regulator</li> <li>• Connect a ceramic input capacitor or an equivalent low ESR input capacitor between this pin and the ground plane. Place it as close as possible to this pin and the ground plane. See <a href="#">Section 8 "Application information"</a>.</li> </ul>
D3	7	VLDO	O	LDO output <ul style="list-style-type: none"> <li>• This pin is the output of the LDO</li> <li>• Connect a ceramic output capacitor or an equivalent low ESR output capacitor between this pin and the ground plane. Place it as close as possible to this pin and the ground plane. See <a href="#">Section 8 "Application information"</a>.</li> </ul>
N/A	4	SGND	GND	Signal ground <ul style="list-style-type: none"> <li>• This pin must be connected to SGND, all PGNDx pins, and make a star connection to system ground</li> <li>• <b>Do not float this pin</b></li> </ul>
N/A	5	SVIN	S	Signal input voltage <ul style="list-style-type: none"> <li>• This is the input voltage pin to the internal circuitry. See <a href="#">Section 4.4 "Electrical characteristics "</a> for input voltage range.</li> <li>• Connect a decoupling ceramic capacitor or an equivalent low ESR decoupling capacitor between SVIN and SGND and position it as close as possible to the IC. See <a href="#">Section 8 "Application information"</a>.</li> <li>• The voltage between SVIN and PVIN should be equal to 50mV or less</li> <li>• <b>Do not float this pin</b></li> </ul>

## Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO

Table 3. Pin description...continued

Pin number		Pin name	Pin type	Function
WLCSP	QFN			
N/A	8	PG2	O	Buck2 regulator power good output <ul style="list-style-type: none"> <li>• This pin is an open-drain output</li> <li>• Connect a 100k<math>\Omega</math> pull-up resistor from this pin to VOUT or a logic rail that is equal to or less than SVIN</li> <li>• The PG is held low when the output voltage is outside its regulation band and goes high after the output voltage is within regulation</li> <li>• When not in use, float this pin</li> <li>• <b>In shutdown, the PG will be actively low</b></li> </ul>
N/A	9	PGLDO	O	LDO power good <ul style="list-style-type: none"> <li>• This pin is an open-drain output</li> <li>• Connect a 100k<math>\Omega</math> pull-up resistor from this pin to VOUT or a logic rail that is equal to or less than SVIN</li> <li>• The PG is held low when the output voltage is outside its regulation band and goes high after the output voltage is within regulation</li> <li>• When not in use, float this pin</li> <li>• <b>In shutdown, the PG will be actively low</b></li> </ul>
N/A	10	PG1	O	Buck1 regulator power good output <ul style="list-style-type: none"> <li>• This pin is an open-drain output</li> <li>• Connect a 100k<math>\Omega</math> pull-up resistor from this pin to VOUT or a logic rail that is equal to or less than SVIN</li> <li>• The PG is held low when the output voltage is outside its regulation band and goes high after the output voltage is within regulation</li> <li>• When not in use, float this pin</li> <li>• <b>In shutdown, the PG will be actively low</b></li> </ul>
N/A	13	EN2	I	Buck2 enable input <ul style="list-style-type: none"> <li>• See <a href="#">Section 5.4 "Power-up sequence"</a> to determine which part numbers have power sequences versus those that do not</li> <li>• For part numbers with a power sequence in the QFN-24 package, EN1, EN2, and ENLDO pins need to be connected together. Any logic high from EN1, EN2, and ENLDO pins enables all regulators. EN1, EN2, and ENLDO need to have logic low to disable all regulators. User can not individually enable or disable each step-down regulator for parts with a power sequence</li> <li>• For part numbers without a power sequence, logic high for this pin enables Step-down Regulator 2. Logic low for this pin disables Step-down Regulator 2</li> <li>• When not in use, connect this pin to GND or connect a 0<math>\Omega</math> resistor to ground</li> <li>• <b>Do not float this pin</b></li> </ul>

## Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO

Table 3. Pin description...continued

Pin number		Pin name	Pin type	Function
WLCSP	QFN			
N/A	15	EN1	I	Buck1 enable input <ul style="list-style-type: none"> <li>• See <a href="#">Section 5.4 "Power-up sequence"</a> to determine which part numbers have power sequences versus those that do not</li> <li>• For part numbers with a power sequence in the QFN-24 package, EN1, EN2, and ENLDO pins need to be connected together. Any logic high from EN1, EN2, and ENLDO pins enables all regulators. EN1, EN2, and ENLDO need to have logic low to disable all regulators. User can not individually enable or disable each step-down regulator for parts with a power sequence</li> <li>• For part numbers without a power sequence, logic high for this pin enables Step-down Regulator 1. Logic low for this pin disables Step-down Regulator 1</li> <li>• When not in use, connect this pin to GND or connect a 0Ω resistor to ground</li> <li>• <b>Do not float this pin</b></li> </ul>
N/A	16	ENLDO	I	LDO enable input <ul style="list-style-type: none"> <li>• See <a href="#">Section 5.4 "Power-up sequence"</a> to determine which part numbers have power sequences versus those that do not</li> <li>• For part numbers with a power sequence in the QFN-24 package, EN1, EN2, and ENLDO pins need to be connected together. Any logic high from EN1, EN2, and ENLDO pins enables all regulators. EN1, EN2, and ENLDO need to have logic low to disable all regulators. User can not individually enable or disable each step-down regulator for parts with a power sequence</li> <li>• For part numbers without a power sequence, logic high for this pin enables the LDO Regulator. Logic low for this pin disables the LDO Regulator</li> <li>• When not in use, connect this pin to GND or connect a 0Ω resistor to ground</li> <li>• The voltage on this pin must never be higher than the voltage on the SVIN pin + 0.3V for all conditions</li> <li>• <b>Do not float this pin</b></li> </ul>
N/A	25	EPAD	GND	Exposed thermal pad <ul style="list-style-type: none"> <li>• This pin must be connected to SGND, all PGND pins, and make a star connection to system ground. See <a href="#">Section 8 "Application information"</a>.</li> <li>• <b>Do not float this pin</b></li> </ul>

## 4 Electrical specifications

### 4.1 Absolute maximum ratings

Table 4. Absolute maximum ratings<sup>[1]</sup>

Parameter	Range	Unit
$V_{SVIN}$ to SGND	-0.3 to +6.0	V
$S_{VIN}$	$V_{PVINx} - 0.3$ to $V_{PVINx} + 0.3$	V
$V_{PVINx}$ to PGNDx	-0.3 to +6.0	V
$V_{SWx}$ to PGNDx <sup>[2]</sup>	-0.3 to ( $V_{PVINx} + 0.3$ )	V
SGND to PGNDx	-0.3 to +0.3	V
$V_{EN}$ , $V_{EN\_LDO}$ , $V_{EN1}$ , $V_{EN2}$	-0.3 to ( $V_{SVIN} + 0.3$ )	V
$V_{DVS0/SDI}$ , $V_{DVS1}$	-0.3 to +6.0	V
Maximum junction temperature	150	°C
Storage temperature range	-65 to 150	°C

[1] Exceeding the absolute maximum rating may damage the device.

[2] SWx is capable of sustaining -1.0V for less than 50 ns.

### 4.2 Recommended operating conditions

Table 5. Recommended operating conditions<sup>[1]</sup>

Symbol	Parameter	Min	Typ	Max	Unit
$V_{PVIN}$	Buck input power voltage	2.7		5.5	V
$V_{INLDO}$	LDO input power voltage	1.6		5.5	V
$T_{JMAX}$	Maximum operating junction temperature			125	°C
$\Theta_{JA}$	Package thermal resistance (WLCSP-22L)		40		°C/W
$\Theta_{JA}$	Package thermal resistance (QFN-24L)		50		°C/W
$T_A$	Operating ambient temperature range	-40		85	°C

[1] Specifications over the -40°C to 85°C operating temperature ranges are assured by design, characterization and correlation with statistical process controls.

### 4.3 External passive components

Table 6. External passive components

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
C <sub>IN1_BK</sub> (WLCSP), C <sub>IN1_BK1</sub> , C <sub>IN1_BK2</sub> ,	External components	The distance between this capacitor to PVINx and PGNDx must be less than 1 mm. The maximum case size is 0201 (0603 metric). Use capacitor with ±30% tolerance or better.	0.10	0.22		μF
C <sub>IN2_BK</sub>		WLCSP package: Use capacitor with ±30% tolerance or better.	2 x 10			μF
C <sub>IN2_BK1</sub> , C <sub>IN2_BK2</sub>		QFN package: Use capacitor with ±30% tolerance or better.	10			μF
C <sub>OUT_BK1</sub> , C <sub>OUT_BK2</sub>		Use capacitor with ±30% tolerance or better.	22			μF
L <sub>BK1</sub> , L <sub>BK2</sub>		Use capacitor with ±30% tolerance or better.		1.0		μH
LC <sub>BK1</sub> , LC <sub>BK2</sub>		The nominal L <sub>BUCKx</sub> x the TOTAL nominal C <sub>OUT_BUCKx</sub> must not exceed this maximum specification. Use inductor and capacitor with ±30% tolerance or better.			60	μH x μF
C <sub>IN_LDO</sub>		Use capacitor with ±30% tolerance or better.	10			μF
C <sub>OUT_LDO</sub>			4.7		20	

#### 4.4 Electrical characteristics

**Table 7. Electrical characteristics**

The following applies unless otherwise noted: Refer to the schematics shown in [Section 8.2 "PCB schematics"](#).  $V_{IN} = 3.6V$ ,  $T_A = -40^{\circ}C$  to  $+85^{\circ}C$ .

Symbol	Parameter	Conditions	Min	Typ	Max	Units
<b>Supply current</b>						
$I_{Q\_MODE1} / I_{Q\_MODE2}$	Active modes quiescent current	Active Mode 1 and Mode 2: Buck1 and Buck2 are in PFM mode and LDO is on. $V_{IN}=5V$ . No load.		170		$\mu A$
		Active mode 1 and mode 2: Buck1 and Buck2 are in PWM mode and LDO is on. $V_{IN}=5V$ . No load.		20		mA
$I_{Q\_MODE3}$		Active mode 3: Buck1 and Buck2 are in PFM mode and LDO is on. $V_{IN} = 5V$ . No load.		75		$\mu A$
		Active mode 3: Buck1 and Buck2 are in PWM mode and LDO is on. $V_{IN} = 5V$ . No load.		20		mA
$I_{Q\_SLP}$	Sleep mode quiescent current	$V_{DVS0} = V_{DVS1} = 0V$ . $V_{IN} = 5V$ . No load.		15		$\mu A$
$I_{SHDN}$	Shutdown current	$V_{ENx} = 0V$ . $V_{IN} = 5V$		1		$\mu A$
<b>Buck1 and Buck2</b>						
$V_{PVIN}$	Power supply input		2.7		5.5	V
$I_{OUT\_BK1} / I_{OUT\_BK2}$	Maximum output current in full power mode		1.5	--	--	A
$I_{OUT\_B^*K1\_SLP} / I_{OUT\_B^*K2\_SLP}$	Maximum output current in sleep mode	--	10	--	--	mA
$V_{OUT\_BK1} / V_{OUT\_BK2}$	Nominal output voltage	Programmable	0.6	--	3.3	V
$RDS_{PMOS}$	High-side (PMOS) on-resistance	$V_{IN} = 3.6V$	--	80	--	m $\Omega$
$RDS_{NMOS}$	Low-side (NMOS) on-resistance	$V_{IN} = 3.6V$	--	40	--	m $\Omega$
$F_{SW}$	Switching frequency	--	--	3	--	MHz
$DUTY_{MAX}$	Maximum duty cycle	--	--	--	100	%
$V_{DC\_ACCY}$	$V_{OUT}$ DC accuracy	--	--	$\pm 2$	--	%
$V_{LN\_REG}$	Line regulation	$V_{IN} = 2.7 V$ to $5.5 V$ at $I_{OUT} = 500 mA$	--	0.1	--	%/V

## Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO

Table 7. Electrical characteristics...continued

The following applies unless otherwise noted: Refer to the schematics shown in [Section 8.2 "PCB schematics"](#).  $V_{IN} = 3.6V$ ,  $T_A = -40^{\circ}C$  to  $+85^{\circ}C$ .

Symbol	Parameter	Conditions	Min	Typ	Max	Units
$V_{LD\_REG}$	Load regulation	$I_{OUT} = 100\text{ mA to }1500\text{ mA}$	--	0.2	--	%/A
$PG_{XVTH}$	BUCKx PG rising threshold	--	--	95	--	%/V <sub>OUT</sub>
$PG_{XHYS}$	BUCKx PG hysteresis	--	--	5	--	%/V <sub>OUT</sub>
$DV_{RAMP\_RATE}$	V <sub>OUT</sub> dynamic voltage ramp rate	--	--	7	--	mV/μs
<b>LDO</b>						
$V_{IN\_LDO}$	Power supply input	--	1.6	--	5.5	V
$I_{OUT\_LDO\_MAX}$	Maximum output current in full power mode	--	525	--	--	mA
$I_{OUT\_LDO\_MIN}$	Minimum LDO load current	--	5	--	--	μA
$I_{OUT\_LDO\_SLP}$	Maximum output current in sleep mode	--	10	--	--	mA
$V_{OUT\_LDO}$	Nominal output voltage	Programmable (device part number dependent)	1.2	--	3.3	V
$V_{LDO\_D-C\_ACCY}$	LDO output accuracy	--	--	±2	--	%
$V_{DROP}$	Dropout voltage	$V_{OUT} = 1.8\text{ V}; I_{OUT} = 100\text{ mA}$	--	100	--	mV
$V_{LDO\_L\_N\_REG}$	Line regulation	$V_{IN} = 2.7\text{ V to }5.5\text{ V at }I_{OUT} = 100\text{ mA}$	--	0.05	--	%/V
$V_{LDO\_LD\_REG}$	Load Regulation	$I_{OUT} = 100\text{ mA to }500\text{ mA}$	--	1	--	%
$PGLDO_{VTH}$	LDO PG rising threshold	--	--	95	--	%/V <sub>OUT</sub>
$PGLDO_{HYS}$	LDO PG hysteresis	--	--	5	--	
<b>Fault protection</b>						
$V_{UVLO}$	VIN under Vltage lock-out	VIN increasing	--	2.35	--	V
		Hysteresis	--	0.1	--	
$V_{OVP}$	VIN over voltage protection	VIN increasing	--	5.7	--	V
		Hysteresis	--	0.1	--	
$T_{OTS}$	Over-temperature thermal shutdown	Temperature rising	--	145	--	°C
		Hysteresis	--	20	--	
<b>Digital input thresholds</b>						
$V_{IH}$	High level input voltage threshold (EN, EN1, EN2, ENLDO, DVS0/SDI, DVS1)	$V_{SVIN} = 2.5V\text{ to }5.5V$	1.2	--	--	V

**Table 7. Electrical characteristics...continued**

The following applies unless otherwise noted: Refer to the schematics shown in [Section 8.2 "PCB schematics"](#).  $V_{IN} = 3.6V$ ,  $T_A = -40^{\circ}C$  to  $+85^{\circ}C$ .

Symbol	Parameter	Conditions	Min	Typ	Max	Units
$V_{IL}$	Low level input voltage threshold (EN, EN1, EN2, ENLDO, DVS0/SDI, DVS1)	$V_{SVIN} = 2.5V$ to $5.5V$	--	--	0.4	V

## 5 Functional description

---

### 5.1 Overview

The PM823 is a performant power management regulator as well as a general purpose power management regulator for portable applications. The PM823 includes two step-down switching (Buck) regulators and one Low Dropout (LDO) regulator. The switching step-down regulators utilize a proprietary internally compensated PWM control to regulate its respective output voltages that require no additional external compensation. The PM823 operates from an input voltage range of 2.7V to 5.5V. The LDO regulator can operate with an input voltage ranging from 100 mV above its regulation point to 5.5V. Each of the two switching regulators can deliver a maximum continuous load of 1.5A at 3 MHz switching frequency; while the LDO can deliver a continuous load current of up to 525 mA. [Figure 6](#) shows the PM823 block diagram.




Figure 6. Block diagram

### 5.2 Serial interface (1-wire)

The PM823 uses the 1-wire interface. The input for the serial interface is the DVS0 pin, but this functionality is only enabled when the DVS1 pin is set to a high state. Please note SDI capability is not available in sleep mode as this mode requires DVS0=DVS1=Low. The frequency of the SDI interface is 781.25kHz, and has a 20% tolerance. [Figure 7](#) illustrates the serial interface pulse setup.




Figure 7. Serial programmability

### 5.3 Soft start

The PM823 internally controls the inrush current when the regulator is enabled. This is accomplished by ramping up the desired output voltage based on steps for a predetermined amount of time. Allowing the output voltage to ramp up in this fashion minimizes the current required to charge the output capacitance, therefore limiting the inrush current.

The LDO typical soft start current limit is 50 mA. After the soft start timer has expired (~1 ms), the LDO outputs the full current.

### 5.4 Power-up sequence

For PM823 with WLCSP package, the EN pin controls the output sequence for all 3 regulators.

For PM823 with QFN package, it is recommended that EN1, EN2 and ENLDO are connected together. Once the part is enabled, Buck2 initializes. After Buck2 completes its start-up, the LDO initializes, followed by Buck1.




Figure 8. Power-up sequence timing diagram - WLCSP package option

5.5 Power good

The PM823 contains a power good comparator which pulls low when the output voltage falls below 90% of its regulated value, or when the output voltage is above 95% of its regulated value when the output voltage is rising. The PGOOD output is an open-drain transistor which is off and becomes high impedance when the output voltage is in regulation. This high impedance state allows an external resistor to pull the PGOOD pin high when this transistor is off, or when the buck regulator is disabled via the enable pin.

5.6 Operating modes

The PM823 supports four operating modes selected by the Dynamic Voltage Scaling (DVS) pins and the internal register as shown in Table 8. Each operating mode provides different power saving features to meet different application needs. For example, even if the serial interface is not used, the DVS pins are still able to provide the power saving feature.

Table 8. Operating mode selections

Operating mode	DVS1	DVS0	Reg 0x05 bit [2]	Functional description
Active Mode 1	High	SDI	X (don't care)	Full power mode and the serial interface (pin DVS0) is enabled
Active Mode 2	Low	High	1	Full power mode, but the serial interface is disabled
Active Mode 3	Low	High	0	Automatic power saving mode and the serial interface is disabled
Sleep Mode	Low	Low	1	Lowest power mode and the serial inter-face is disabled

The PM823 supports two full power modes, Active Mode 1 and Active Mode 2. Both full power modes have the same power consumption. The major differences are first that the serial interface is not enabled in Active Mode 2, and second that the buck1 regulator can be programmed to different output voltages in Active Modes 1 and 2 to support different applications.

When the PM823 is set to Active Mode 3, the internal clock automatically turns off during a light load (PFM) condition to reduce the system power consumption, but the output voltage remains the same as in Active Mode 1. Active Mode 3 improves the system power consumption if the serial interface is not used.

The PM823 also supports the Sleep Mode function which minimizes the system power during a low power mode event. The PM823 quiescent current is reduced to 15 µA during Sleep Mode. However, during Sleep Mode, the maximum output current for each regulator is limited to 10 mA. If the load current is increased beyond the limit, the over current protection mechanism kicks in and shuts down the output voltage. The buck1 output voltage can be set through Register 0x02.

### 5.7 DVS output voltage settings

The PM823 buck1 output voltage can be set to different output voltages in different operating modes through the internal registers. The buck2 and LDO output voltages can be changed as well during Active Mode 1 through programming. However, the buck2 and LDO remain the same across different operating modes.

Table 9. DVS output voltage settings

Operating mode	DVS1	DVS0	Reg 0x05 bit [2]	Buck1 output voltage settings
Active Mode 1	High	SDI	X (don't care)	See <a href="#">Section 10.3.1 "Buck1 active mode 1 and mode 3 output voltage control"</a> .
Active Mode 2	Low	High	1	See <a href="#">Section 10.3.2 "Buck1 active mode 2 output voltage control"</a> .
Active Mode 3	Low	High	0	See <a href="#">Section 10.3.1 "Buck1 active mode 1 and mode 3 output voltage control"</a> .
Sleep Mode	Low	Low	1	See <a href="#">Section 10.3.3 "Buck1 sleep mode output voltage control"</a> .

The time to change from one output voltage level to another can be calculated with the following equation:

$$t_{DV} = \frac{|V_{OUT\_CURRENT} - V_{OUT\_NEW}|}{DV_{RAMP\_RATE}}$$

**Example:**

$$V_{OUT\_CURRENT} = 1.2000V$$

$$V_{OUT\_NEW} = 1.2500V$$

$$DV_{RAMP\_RATE} = 7 \text{ mV}/\mu\text{s}$$

$$7.1429\mu\text{s} = \frac{|1.2000V - 1.2500V|}{(7\text{mV})/(\mu\text{s})}$$

### 5.8 Sleep mode

The PM823 supports the sleep mode function which saves power when the system is in low power mode. The maximum output current for each regulator is limited to 10 mA. If the load current is increased beyond the sleep mode current limit, the PM823 over-current protection kicks in and shuts down the corresponding output. The DVS0 and DVS1 pins are used to set the PM823 to different operating modes. Before entering sleep mode, the host needs to enable the DVS function by setting the REG5 bit[2] to 1. The sleep mode buck1 output voltage can be preprogrammed using REG0 bit[6:5] and REG2 bit[4:0]. The PM823 enters sleep mode when all the required registers are set and both DVS0 and DVS1 pins are asserted to low.

**5.9 Under voltage lock-out (UVLO)**

This feature ensures that both internal MOSFETs for the step-down regulators and for the LDO regulator have adequate voltage levels to operate. When the input voltage is below UVLO low threshold, both MOSFETs for the step-down regulators and for the LDO regulator are off until the input rises above the UVLO high threshold. The switching nodes (SW) for both step-down regulators are in high Z state when the input voltage is less than UVLO high threshold.

**5.10 Over voltage protection (OVP)**

An over-voltage comparator guards against line transient overshoots, as well as other serious conditions that may damage the IC. When the input voltage is above OVP high threshold the output turns off and the switching node (SW) for both step-down regulators are high Z. The device will remain at this state until the input voltage comes back below OVP low threshold.




Figure 9. UVLO and OVP waveforms

### 5.11 Over-temperature thermal shutdown (OTS)

When the junction temperature exceeds OTS high threshold, the thermal shutdown circuitry disables the PM823. The device is enabled again once the junction temperature is below OTS low threshold.

## 6 Functional characteristics

See [Section 8.2 "PCB schematics"](#). The following applies unless otherwise noted:  $T_A = 25^\circ\text{C}$ ,

$V_{IN} = 5\text{V}$ ,  $V_{OUT\_BK1} = 1.1\text{V}$ ,  $V_{OUT\_BK2} = 2.2\text{V}$ , and  $V_{OUT\_LDO} = 1.8\text{V}$ .

### 6.1 Start-up waveforms




Figure 10. Startup




Figure 11. UVLO / OVP Thresholds




Figure 12. Buck1 short circuit




Figure 13. Buck2 short circuit

6.2 Load transient waveforms




Figure 14. Buck1 (1.1V) load transient response 100 mA to 750 mA




Figure 15. Buck1 (1.1V) load transient response 750 mA to 1.5A




Figure 16. Buck2 (2.2V) load transient response 100 mA to 750 mA




Figure 17. Buck2 (2.2V) load transient response 750 mA to 1.5A

6.3 Switching waveforms




Figure 18. Buck1 (1.1V) PFM Output Ripples at 25 mA




Figure 19. Buck1 (1.1V) PWM Output Ripples at 1.5A




Figure 20. Buck2 (2.2V) PFM Output Ripples at 45 mA




Figure 21. Buck2 (2.2V) PWM Output Ripples at 1.5A

7 Typical characteristics

Unless otherwise noted, the following typical scope photographs were taken using the test circuits shown in [Section 8.2 "PCB schematics"](#) at  $T_A = 25^\circ\text{C}$ .




Figure 22. Buck1 (1.1V) efficiency vs output current WLCSP-12




Figure 23. Buck2 (2.2V) efficiency vs output current WLCSP-12




Figure 24. Buck1 (3.3V) efficiency vs output current QFN-24




Figure 25. Buck2 (1.8V) efficiency vs output current QFN-24




Figure 26. Buck1 (1.1V) output voltage vs output current WLCSP-12




Figure 27. Buck2 (2.2V) output voltage vs output current WLCSP-12




Figure 28. Buck1 (3.3V) output voltage vs output current QFN-24




Figure 29. Buck2 (1.8V) output voltage vs output current QFN-24

Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO




Figure 30. Buck1 output voltage vs input voltage WLCSP-12





Figure 31. Buck2 Output Voltage vs Input Voltage WLCSP-12



(BK1=1.1V, BK2=2.2V, LDO=1.8V,  $V_{INLDO}$  connect to  $V_{INBUCK}$ )

Figure 32. Quiescent Current vs Input Voltage For Active Mode 3




Figure 33. Buck1 high side  $R_{DS(ON)}$  vs. input voltage WLCSP-12




Figure 34. Buck2 high side  $R_{DS(ON)}$  vs. input voltage WLCSP-12




Figure 35. Buck1 low side  $R_{DS(ON)}$  vs. input voltage WLCSP-12




Figure 36. Buck2 low side  $R_{DS(ON)}$  vs. input voltage WLCSP-12

Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO




Figure 37. Buck1 high side  $R_{DS(ON)}$  vs. input voltage QFN-24




Figure 38. Buck2 high side  $R_{DS(ON)}$  vs. input voltage QFN-24




Figure 39. Buck1 low side  $R_{DS(ON)}$  vs. input voltage QFN-24




Figure 40. Buck2 low side  $R_{DS(ON)}$  vs. input voltage QFN-24




Figure 41. Buck1 Output Voltage Error vs Temperature





Figure 42. Buck2 Output Voltage Error vs Temperature



(BK1=1.1V, BK2=2.2V, LDO=1.8V,  $V_{INLDO}$  connect to  $V_{INBUCK}$ )

Figure 43. Quiescent current vs temperature for active mode 3

Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO




Figure 44. Buck1 high side  $R_{DS(ON)}$  vs. temperature WLCSP-12




Figure 45. Buck2 high side  $R_{DS(ON)}$  vs. temperature WLCSP-12




Figure 46. Buck1 low side  $R_{DS(ON)}$  vs. temperature WLCSP-12




Figure 47. Buck2 low side  $R_{DS(ON)}$  vs. temperature WLCSP-12




Figure 48. Buck1 high side  $R_{DS(ON)}$  vs. temperature QFN-24




Figure 49. Buck2 high side  $R_{DS(ON)}$  vs. temperature QFN-24




Figure 50. Buck1 low side  $R_{DS(ON)}$  vs. temperature QFN-24




Figure 51. Buck2 low side  $R_{DS(ON)}$  vs. temperature QFN-24

## 8 Application information

### 8.1 PC board layout considerations and guidelines

**Caution:** To avoid abnormal noise and operating behavior follow these layout recommendations.

The PC board layout is very critical in any switching converter application. An improper layout can contribute to system instability, excessive EMI (electromagnetic interference), and high switching loss. Follow these basic guidelines to assure a good PCB layout:

1. Copy these layout guidelines within this section as much as possible including the use of the recommended BOM
2. Before importing the net list into the layout tool, it is highly recommended to go through the board floor planning phase (the process defining the general location of components on the blank PCB before drawing in any traces).
  - a. It is highly recommended to allocate 40% or more of the layout schedule to dedicate for floor planning of the board.
  - b. Here are some of the questions that are commonly derived from the floor planning phase.  
Where to place the SOC on the board?  
On the top or bottom layer?  
In the center?
  - c. After deciding where to place the SOC, the next step is to place the power management IC for the core voltage of the SOC.
  - d. The optimum position to place the power management IC is on the same layer as the SOC. The output voltage of the power management IC should be close to the input voltage of the SOC.
  - e. Continue this floor planning phase for the rest of the voltage rails before starting to layout the board.
3. ATTENTION: Before starting to route any traces and after choosing where to place the power management IC on the board, the next step is to place the input capacitors.
  - a. Place input capacitor for the SVIN and SGND pins on the same layer as the IC.
  - b. Then, place input capacitor for the PVIN and PGND pins on the same layer as the IC.
  - c. Next, place the negative terminal for the output capacitors next to the negative terminal of the input capacitors.
  - d. See [Section 4.4 "Electrical characteristics "](#) for the recommended input and output capacitor values.
  - e. See [Section 4.4 "Electrical characteristics "](#) for the recommended distance between the IC and the input and output capacitors.
  - f. **Do not place the inductor before placing the capacitors.** The input capacitors placement is the most crucial for proper operation. The AC current circulating through the input capacitors, loop (LP1), is a square wave with rise and fall times as fast as 8ns (typical) with slew rates being as high as 300µA/µs (typical). At these fast slew rates, stray and parasitic PCB inductance can generate voltage spikes as high as 3V per inch of the PCB trace;  
 $V_{IND} = L * di/dt.$



8.2 PCB schematics




Figure 52. PCB schematic - WLCSP package

Notes:

- For C3 and C4, can use 0.1 µF but it is best to use maximum capacitance for the 0603(mm)/0201(in) case size. For example, 0.22 µF is available 0603(mm)/0201(in) size.
- For all capacitors, use the highest voltage rating available for the case size. For example, 22 µF is available in 1608(mm)/0603(in) case size with 6.3V and 10V rating. Use 22 µF/10V rating instead of 22 µF/6.3V rating
- See [Section 5.4 "Power-up sequence"](#) for the power sequence function
- See [Section 5.7 "DVS output voltage settings"](#) for DVS0 and DVS1 function and configuration. Do not float DVS/SDI and DVS1 pin.

Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO




Figure 53. PCB schematic - QFN package

Notes:


- For C3 and C4, can use 0.1µF but it is best to use maximum capacitance for the 0603(mm)/0201(in) case size. For example, 0.22µF is available 0603(mm)/0201(in) size
- For all capacitors, use the highest voltage rating available for the case size. For example, 22µF is available in 1608 (mm) / 0603 (in) case size with 6.3V and 10V rating. Use 22µF/10V rating instead of 22µF/6.3V rating
- For EN1, EN2, and ENLDO pins, can connect directly to VIN or through a 100K pull-up resistor if all outputs are turned on at the same time
- If the LDO output voltage comes after the Buck2 output, then connect VIN\_LDO to VOUT2\_BK2. Either have the ENLDO pin connect to VOUT\_BK2 or connect through a 100K pull-up resistor.
- See [Section 5.2 "Serial interface \(1-wire\)"](#) for the SDI function and configuration
- See [Section 5.4 "Power-up sequence"](#) for the power sequence function
- See [Section 5.7 "DVS output voltage settings"](#) for DVS0 and DVS1 function and configuration. Do not float DVS0/SDI and DVS1 pin.

8.3 PCB layout examples

- WLCSP actual board size = 286 mil x 258 mil
- QFN actual board size = 409 mil x 510 mil

- WLCSP total copper layers = 4
- QFN total copper layers = 2

8.3.1 PCB layout for WLCSP package










Figure 55. Layer 2 vias and copper (not to scale)





8.3.2 PCB layout for QFN package





## 8.4 Bill of materials (BOM)

### Note:

Check component datasheets for the latest updates before designing these components in the schematic.

Check the maximum temperature of the applications and maximum heat source that these components will be placed next to. For example, these components might be placed near the SOC and the SOC might act as the heat source. This heat source can have a higher temperature than the ambient temperature. These recommended components are suitable for hand-held and portable applications. Components with high temperature ratings might be needed based on the maximum temperature of the application or the maximum heat source that these components will be subject to.

Table 10. BOM for WLCSP package

Item	Qty	Ref	Manufacturer part number	Manufacturer	Description
1	3	C1,C2, C8	GRM188R61A106KE69D	Murata	CAP CER 10 $\mu$ F 10V $\pm$ 10% X5R 1608(mm) / 0603(in)
2	2	C3,C4	GRM033R61A224ME90D	Murata	CAP CER 0.22 $\mu$ F 10V $\pm$ 20% X5R 0603(mm) / 0201(in)
3	2	C5,C7	GRM188R61A226ME15	Murata	CAP CER 22 $\mu$ F 10V $\pm$ 20% X5R 1608(mm) / 0603(in)
4	1	C6	GRM155R61A475MEAA	Murata	CAP CER 4.7 $\mu$ F 10V $\pm$ 20% X5R 1005(mm) / 0402(in)
5	2	L1,L2	HEI201612A-1R0M-Q8D2	Chilisin	HEI201612A Series 1.0 $\mu$ H, L = 2.0mm, W = 1.6mm, H = 1.2mm
			MHCD201612A-1R0M-A8SDZ	Chilisin	MHCD201612A Series 1.0 $\mu$ H, L = 2.0mm, W = 1.6mm, H = 1.2mm
6	1	U1	PM823	NXP	PM823 in WLCSP-12 package with dual synchronous bucks and LDO

## Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO

Table 11. BOM for QFN Package

Item	Qty	Ref	Manufacturer part number	Manufacturer	Description
1	3	C1,C2, C10	GRM188R61A106KE69	Murata	CAP CER 10 $\mu$ F 10V $\pm$ 10% X5R 1608(mm) / 0603(in)
2	3	C3,C4, C12	GRM033R61A224ME90D	Murata	CAP CER 0.22 $\mu$ F 10V $\pm$ 20% X5R 0603(mm) / 0201(in)
3	2	C5,C7	GRM188R61A226ME15	Murata	CAP CER 22 $\mu$ F 10V $\pm$ 20% X5R 1608(mm) / 0603(in)
4	1	C9	GRM155R61A475MEAA	Murata	CAP CER 4.7 $\mu$ F 10V $\pm$ 20% X5R 1005(mm) / 0402(in)
5	2	L1,L2	HEI201612A-1R0M-Q8D2	Chilisin	HEI201612A Series 1.0 $\mu$ H, L = 2.0mm, W = 1.6mm, H = 1.2mm
			MHCD201612A-1R0M-A8SDZ	Chilisin	MHCD201612A Series 1.0 $\mu$ H, L = 2.0mm, W = 1.6mm, H = 1.2mm
6	1	R1	RC0402FR-0710RL	Yageo	RES 10 $\Omega$ 1/16W $\pm$ 1% 0402 SMD
7	3	R2,R3, R4	RC0402JR-07100KL	Yageo	RES 100k $\Omega$ 1/16W $\pm$ 5% 0402 SMD
8	1	U1	PM823	NXP	PM823 in QFN-24 package with dual synchronous bucks and LDO

9 Package information

9.1 Package mechanical drawings





Figure 60. 1.260mm x 1.545mm WLCSP-12 mechanical drawing

**Note:** All dimensions in mm. See [Section 9.2 "Package markings"](#) for package marking and pin 1 location.



**Note:** All dimensions in mm. See [Section 9.2 "Package markings"](#) for package marking and pin 1 location.






Figure 62. 4mm x 4mm QFN-24 mechanical drawing - Details E

9.2 Package markings



## 10 PM823 register sets

### 10.1 Register conventions

The register tables include the following information:

- **Register address:** included in the table caption
- **Bits:** Bits and/or bit fields
- **Type:** Read (R), write (W), read/write (RW)
- **Default:** Power-on hardware reset default value
- **Description:** Description of the bit or bit field and definition of the values

### 10.2 Register map

Table 12. Register map

Register name	Register address	Read / Write
Buck1 Active Mode 0 and Mode 3 Output Voltage Control	0x00	W
Buck1 Active Mode 1 Output Voltage Control	0x01	W
Buck1 Sleep Mode Output Voltage Control	0x02	W
Buck2 Output Voltage Control	0x03	W
LDO Output Voltage Control	0x04	W
MISC Control	0x05	W

### 10.3 Register descriptions

#### 10.3.1 Buck1 active mode 1 and mode 3 output voltage control

Table 13. Register 0x00

Bit	Field	Type	Default	Description
D[7]	EN_BK1_ENABLE	W	1	<b>Buck1 Software Enable</b> 1: Buck1 is enabled 0: Buck1 is disabled
D[6:5]	BK1_VOUT_RANGE	W	00	<b>Buck1 V<sub>OUT</sub> Range</b> Used to set the Buck1 output voltage range 00: 0.6V ~ 1.375V 01: 1.4V ~ 2.85V 10: 2.9V ~ 3.3V 11: Reserved

Table 13. Register 0x00...continued

Bit	Field	Type	Default	Description																																																																																																			
D[4:0]	BK1_M0_VOUT	W	1_0100	<p><b>Buck1 Active Mode 0 Output Voltage</b></p> <p>When the DVS1 input pin is high, Buck1 is set to Active Mode 0 and these register bits with the BK1_VOUT_RANGE register are used to set the Buck1 output voltage</p> <table border="1"> <thead> <tr> <th>BK1_VOUT_RANGE = 00</th> <th>BK1_VOUT_RANGE = 01</th> <th>BK1_VOUT_RANGE = 10</th> </tr> </thead> <tbody> <tr><td>0_0000 = 0.6V</td><td>0_0000 = 1.4V</td><td>0_0000 = 2.9V</td></tr> <tr><td>0_0001 = 0.625V</td><td>0_0001 = 1.425V</td><td>0_0001 = 2.95V</td></tr> <tr><td>0_0010 = 0.65V</td><td>0_0010 = 1.45V</td><td>0_0010 = 3.0V</td></tr> <tr><td>0_0011 = 0.675V</td><td>0_0011 = 1.475V</td><td>0_0011 = 3.05V</td></tr> <tr><td>0_0100 = 0.7V</td><td>0_0100 = 1.5V</td><td>0_0100 = 3.1V</td></tr> <tr><td>0_0101 = 0.725V</td><td>0_0101 = 1.55V</td><td>0_0101 = 3.15V</td></tr> <tr><td>0_0110 = 0.75V</td><td>0_0110 = 1.6V</td><td>0_0110 = 3.2V</td></tr> <tr><td>0_0111 = 0.775V</td><td>0_0111 = 1.65V</td><td>0_0111 = 3.25V</td></tr> <tr><td>0_1000 = 0.8V</td><td>0_1000 = 1.7V</td><td>0_1000 = 3.3V</td></tr> <tr><td>0_1001 = 0.825V</td><td>0_1001 = 1.75V</td><td>Others Reserved</td></tr> <tr><td>0_1010 = 0.85V</td><td>0_1010 = 1.8V</td><td></td></tr> <tr><td>0_1011 = 0.875V</td><td>0_1011 = 1.85V</td><td></td></tr> <tr><td>0_1100 = 0.9V</td><td>0_1100 = 1.9V</td><td></td></tr> <tr><td>0_1101 = 0.925V</td><td>0_1101 = 1.95V</td><td></td></tr> <tr><td>0_1110 = 0.95V</td><td>0_1110 = 2.0V</td><td></td></tr> <tr><td>0_1111 = 0.975V</td><td>0_1111 = 2.05V</td><td></td></tr> <tr><td>1_0000 = 1.0V</td><td>1_0000 = 2.1V</td><td></td></tr> <tr><td>1_0001 = 1.025V</td><td>1_0001 = 2.15V</td><td></td></tr> <tr><td>1_0010 = 1.05V</td><td>1_0010 = 2.2V</td><td></td></tr> <tr><td>1_0011 = 1.075V</td><td>1_0011 = 2.25V</td><td></td></tr> <tr><td>1_0100 = 1.1V</td><td>1_0100 = 2.3V</td><td></td></tr> <tr><td>1_0101 = 1.125V</td><td>1_0101 = 2.35V</td><td></td></tr> <tr><td>1_0110 = 1.15V</td><td>1_0110 = 2.4V</td><td></td></tr> <tr><td>1_0111 = 1.175V</td><td>1_0111 = 2.45V</td><td></td></tr> <tr><td>1_1000 = 1.2V</td><td>1_1000 = 2.5V</td><td></td></tr> <tr><td>1_1001 = 1.225V</td><td>1_1001 = 2.55V</td><td></td></tr> <tr><td>1_1010 = 1.25V</td><td>1_1010 = 2.6V</td><td></td></tr> <tr><td>1_1011 = 1.275V</td><td>1_1011 = 2.65V</td><td></td></tr> <tr><td>1_1100 = 1.3V</td><td>1_1100 = 2.7V</td><td></td></tr> <tr><td>1_1101 = 1.325V</td><td>1_1101 = 2.75V</td><td></td></tr> <tr><td>1_1110 = 1.35V</td><td>1_1110 = 2.8V</td><td></td></tr> <tr><td>1_1111 = 1.375V</td><td>1_1111 = 2.85V</td><td></td></tr> </tbody> </table>	BK1_VOUT_RANGE = 00	BK1_VOUT_RANGE = 01	BK1_VOUT_RANGE = 10	0_0000 = 0.6V	0_0000 = 1.4V	0_0000 = 2.9V	0_0001 = 0.625V	0_0001 = 1.425V	0_0001 = 2.95V	0_0010 = 0.65V	0_0010 = 1.45V	0_0010 = 3.0V	0_0011 = 0.675V	0_0011 = 1.475V	0_0011 = 3.05V	0_0100 = 0.7V	0_0100 = 1.5V	0_0100 = 3.1V	0_0101 = 0.725V	0_0101 = 1.55V	0_0101 = 3.15V	0_0110 = 0.75V	0_0110 = 1.6V	0_0110 = 3.2V	0_0111 = 0.775V	0_0111 = 1.65V	0_0111 = 3.25V	0_1000 = 0.8V	0_1000 = 1.7V	0_1000 = 3.3V	0_1001 = 0.825V	0_1001 = 1.75V	Others Reserved	0_1010 = 0.85V	0_1010 = 1.8V		0_1011 = 0.875V	0_1011 = 1.85V		0_1100 = 0.9V	0_1100 = 1.9V		0_1101 = 0.925V	0_1101 = 1.95V		0_1110 = 0.95V	0_1110 = 2.0V		0_1111 = 0.975V	0_1111 = 2.05V		1_0000 = 1.0V	1_0000 = 2.1V		1_0001 = 1.025V	1_0001 = 2.15V		1_0010 = 1.05V	1_0010 = 2.2V		1_0011 = 1.075V	1_0011 = 2.25V		1_0100 = 1.1V	1_0100 = 2.3V		1_0101 = 1.125V	1_0101 = 2.35V		1_0110 = 1.15V	1_0110 = 2.4V		1_0111 = 1.175V	1_0111 = 2.45V		1_1000 = 1.2V	1_1000 = 2.5V		1_1001 = 1.225V	1_1001 = 2.55V		1_1010 = 1.25V	1_1010 = 2.6V		1_1011 = 1.275V	1_1011 = 2.65V		1_1100 = 1.3V	1_1100 = 2.7V		1_1101 = 1.325V	1_1101 = 2.75V		1_1110 = 1.35V	1_1110 = 2.8V		1_1111 = 1.375V	1_1111 = 2.85V	
BK1_VOUT_RANGE = 00	BK1_VOUT_RANGE = 01	BK1_VOUT_RANGE = 10																																																																																																					
0_0000 = 0.6V	0_0000 = 1.4V	0_0000 = 2.9V																																																																																																					
0_0001 = 0.625V	0_0001 = 1.425V	0_0001 = 2.95V																																																																																																					
0_0010 = 0.65V	0_0010 = 1.45V	0_0010 = 3.0V																																																																																																					
0_0011 = 0.675V	0_0011 = 1.475V	0_0011 = 3.05V																																																																																																					
0_0100 = 0.7V	0_0100 = 1.5V	0_0100 = 3.1V																																																																																																					
0_0101 = 0.725V	0_0101 = 1.55V	0_0101 = 3.15V																																																																																																					
0_0110 = 0.75V	0_0110 = 1.6V	0_0110 = 3.2V																																																																																																					
0_0111 = 0.775V	0_0111 = 1.65V	0_0111 = 3.25V																																																																																																					
0_1000 = 0.8V	0_1000 = 1.7V	0_1000 = 3.3V																																																																																																					
0_1001 = 0.825V	0_1001 = 1.75V	Others Reserved																																																																																																					
0_1010 = 0.85V	0_1010 = 1.8V																																																																																																						
0_1011 = 0.875V	0_1011 = 1.85V																																																																																																						
0_1100 = 0.9V	0_1100 = 1.9V																																																																																																						
0_1101 = 0.925V	0_1101 = 1.95V																																																																																																						
0_1110 = 0.95V	0_1110 = 2.0V																																																																																																						
0_1111 = 0.975V	0_1111 = 2.05V																																																																																																						
1_0000 = 1.0V	1_0000 = 2.1V																																																																																																						
1_0001 = 1.025V	1_0001 = 2.15V																																																																																																						
1_0010 = 1.05V	1_0010 = 2.2V																																																																																																						
1_0011 = 1.075V	1_0011 = 2.25V																																																																																																						
1_0100 = 1.1V	1_0100 = 2.3V																																																																																																						
1_0101 = 1.125V	1_0101 = 2.35V																																																																																																						
1_0110 = 1.15V	1_0110 = 2.4V																																																																																																						
1_0111 = 1.175V	1_0111 = 2.45V																																																																																																						
1_1000 = 1.2V	1_1000 = 2.5V																																																																																																						
1_1001 = 1.225V	1_1001 = 2.55V																																																																																																						
1_1010 = 1.25V	1_1010 = 2.6V																																																																																																						
1_1011 = 1.275V	1_1011 = 2.65V																																																																																																						
1_1100 = 1.3V	1_1100 = 2.7V																																																																																																						
1_1101 = 1.325V	1_1101 = 2.75V																																																																																																						
1_1110 = 1.35V	1_1110 = 2.8V																																																																																																						
1_1111 = 1.375V	1_1111 = 2.85V																																																																																																						

10.3.2 Buck1 active mode 2 output voltage control

Table 14. Register 0x01

Bit	Field	Type	Default	Description																																																																																																			
D[7:5]	Reserved	W	000	<b>Reserved</b> Set bits to 0 when written																																																																																																			
D[4:0]	BK1_M1_VOUT	W	1_0100	<p><b>Buck1 Active Mode 1 Output Voltage</b> When the DVS1=0 and DVS0=1 register bit is set to 1, Buck1 is set to Active Mode 0 and these register bits with the BK1_VOUT_RANGE register are used to set the Buck1 output voltage</p> <table border="1"> <thead> <tr> <th>BK1_VOUT_RANGE = 00</th> <th>BK1_VOUT_RANGE = 01</th> <th>BK1_VOUT_RANGE = 10</th> </tr> </thead> <tbody> <tr> <td>0_0000 = 0.6V</td> <td>0_0000 = 1.4V</td> <td>0_0000 = 2.9V</td> </tr> <tr> <td>0_0001 = 0.625V</td> <td>0_0001 = 1.425V</td> <td>0_0001 = 2.95V</td> </tr> <tr> <td>0_0010 = 0.65V</td> <td>0_0010 = 1.45V</td> <td>0_0010 = 3.0V</td> </tr> <tr> <td>0_0011 = 0.675V</td> <td>0_0011 = 1.475V</td> <td>0_0011 = 3.05V</td> </tr> <tr> <td>0_0100 = 0.7V</td> <td>0_0100 = 1.5V</td> <td>0_0100 = 3.1V</td> </tr> <tr> <td>0_0101 = 0.725V</td> <td>0_0101 = 1.55V</td> <td>0_0101 = 3.15V</td> </tr> <tr> <td>0_0110 = 0.75V</td> <td>0_0110 = 1.6V</td> <td>0_0110 = 3.2V</td> </tr> <tr> <td>0_0111 = 0.775V</td> <td>0_0111 = 1.65V</td> <td>0_0111 = 3.25V</td> </tr> <tr> <td>0_1000 = 0.8V</td> <td>0_1000 = 1.7V</td> <td>0_1000 = 3.3V</td> </tr> <tr> <td>0_1001 = 0.825V</td> <td>0_1001 = 1.75V</td> <td>Others Reserved</td> </tr> <tr> <td>0_1010 = 0.85V</td> <td>0_1010 = 1.8V</td> <td></td> </tr> <tr> <td>0_1011 = 0.875V</td> <td>0_1011 = 1.85V</td> <td></td> </tr> <tr> <td>0_1100 = 0.9V</td> <td>0_1100 = 1.9V</td> <td></td> </tr> <tr> <td>0_1101 = 0.925V</td> <td>0_1101 = 1.95V</td> <td></td> </tr> <tr> <td>0_1110 = 0.95V</td> <td>0_1110 = 2.0V</td> <td></td> </tr> <tr> <td>0_1111 = 0.975V</td> <td>0_1111 = 2.05V</td> <td></td> </tr> <tr> <td>1_0000 = 1.0V</td> <td>1_0000 = 2.1V</td> <td></td> </tr> <tr> <td>1_0001 = 1.025V</td> <td>1_0001 = 2.15V</td> <td></td> </tr> <tr> <td>1_0010 = 1.05V</td> <td>1_0010 = 2.2V</td> <td></td> </tr> <tr> <td>1_0011 = 1.075V</td> <td>1_0011 = 2.25V</td> <td></td> </tr> <tr> <td>1_0100 = 1.1V</td> <td>1_0100 = 2.3V</td> <td></td> </tr> <tr> <td>1_0101 = 1.125V</td> <td>1_0101 = 2.35V</td> <td></td> </tr> <tr> <td>1_0110 = 1.15V</td> <td>1_0110 = 2.4V</td> <td></td> </tr> <tr> <td>1_0111 = 1.175V</td> <td>1_0111 = 2.45V</td> <td></td> </tr> <tr> <td>1_1000 = 1.2V</td> <td>1_1000 = 2.5V</td> <td></td> </tr> <tr> <td>1_1001 = 1.225V</td> <td>1_1001 = 2.55V</td> <td></td> </tr> <tr> <td>1_1010 = 1.25V</td> <td>1_1010 = 2.6V</td> <td></td> </tr> <tr> <td>1_1011 = 1.275V</td> <td>1_1011 = 2.65V</td> <td></td> </tr> <tr> <td>1_1100 = 1.3V</td> <td>1_1100 = 2.7V</td> <td></td> </tr> <tr> <td>1_1101 = 1.325V</td> <td>1_1101 = 2.75V</td> <td></td> </tr> <tr> <td>1_1110 = 1.35V</td> <td>1_1110 = 2.8V</td> <td></td> </tr> <tr> <td>1_1111 = 1.375V</td> <td>1_1111 = 2.85V</td> <td></td> </tr> </tbody> </table>	BK1_VOUT_RANGE = 00	BK1_VOUT_RANGE = 01	BK1_VOUT_RANGE = 10	0_0000 = 0.6V	0_0000 = 1.4V	0_0000 = 2.9V	0_0001 = 0.625V	0_0001 = 1.425V	0_0001 = 2.95V	0_0010 = 0.65V	0_0010 = 1.45V	0_0010 = 3.0V	0_0011 = 0.675V	0_0011 = 1.475V	0_0011 = 3.05V	0_0100 = 0.7V	0_0100 = 1.5V	0_0100 = 3.1V	0_0101 = 0.725V	0_0101 = 1.55V	0_0101 = 3.15V	0_0110 = 0.75V	0_0110 = 1.6V	0_0110 = 3.2V	0_0111 = 0.775V	0_0111 = 1.65V	0_0111 = 3.25V	0_1000 = 0.8V	0_1000 = 1.7V	0_1000 = 3.3V	0_1001 = 0.825V	0_1001 = 1.75V	Others Reserved	0_1010 = 0.85V	0_1010 = 1.8V		0_1011 = 0.875V	0_1011 = 1.85V		0_1100 = 0.9V	0_1100 = 1.9V		0_1101 = 0.925V	0_1101 = 1.95V		0_1110 = 0.95V	0_1110 = 2.0V		0_1111 = 0.975V	0_1111 = 2.05V		1_0000 = 1.0V	1_0000 = 2.1V		1_0001 = 1.025V	1_0001 = 2.15V		1_0010 = 1.05V	1_0010 = 2.2V		1_0011 = 1.075V	1_0011 = 2.25V		1_0100 = 1.1V	1_0100 = 2.3V		1_0101 = 1.125V	1_0101 = 2.35V		1_0110 = 1.15V	1_0110 = 2.4V		1_0111 = 1.175V	1_0111 = 2.45V		1_1000 = 1.2V	1_1000 = 2.5V		1_1001 = 1.225V	1_1001 = 2.55V		1_1010 = 1.25V	1_1010 = 2.6V		1_1011 = 1.275V	1_1011 = 2.65V		1_1100 = 1.3V	1_1100 = 2.7V		1_1101 = 1.325V	1_1101 = 2.75V		1_1110 = 1.35V	1_1110 = 2.8V		1_1111 = 1.375V	1_1111 = 2.85V	
BK1_VOUT_RANGE = 00	BK1_VOUT_RANGE = 01	BK1_VOUT_RANGE = 10																																																																																																					
0_0000 = 0.6V	0_0000 = 1.4V	0_0000 = 2.9V																																																																																																					
0_0001 = 0.625V	0_0001 = 1.425V	0_0001 = 2.95V																																																																																																					
0_0010 = 0.65V	0_0010 = 1.45V	0_0010 = 3.0V																																																																																																					
0_0011 = 0.675V	0_0011 = 1.475V	0_0011 = 3.05V																																																																																																					
0_0100 = 0.7V	0_0100 = 1.5V	0_0100 = 3.1V																																																																																																					
0_0101 = 0.725V	0_0101 = 1.55V	0_0101 = 3.15V																																																																																																					
0_0110 = 0.75V	0_0110 = 1.6V	0_0110 = 3.2V																																																																																																					
0_0111 = 0.775V	0_0111 = 1.65V	0_0111 = 3.25V																																																																																																					
0_1000 = 0.8V	0_1000 = 1.7V	0_1000 = 3.3V																																																																																																					
0_1001 = 0.825V	0_1001 = 1.75V	Others Reserved																																																																																																					
0_1010 = 0.85V	0_1010 = 1.8V																																																																																																						
0_1011 = 0.875V	0_1011 = 1.85V																																																																																																						
0_1100 = 0.9V	0_1100 = 1.9V																																																																																																						
0_1101 = 0.925V	0_1101 = 1.95V																																																																																																						
0_1110 = 0.95V	0_1110 = 2.0V																																																																																																						
0_1111 = 0.975V	0_1111 = 2.05V																																																																																																						
1_0000 = 1.0V	1_0000 = 2.1V																																																																																																						
1_0001 = 1.025V	1_0001 = 2.15V																																																																																																						
1_0010 = 1.05V	1_0010 = 2.2V																																																																																																						
1_0011 = 1.075V	1_0011 = 2.25V																																																																																																						
1_0100 = 1.1V	1_0100 = 2.3V																																																																																																						
1_0101 = 1.125V	1_0101 = 2.35V																																																																																																						
1_0110 = 1.15V	1_0110 = 2.4V																																																																																																						
1_0111 = 1.175V	1_0111 = 2.45V																																																																																																						
1_1000 = 1.2V	1_1000 = 2.5V																																																																																																						
1_1001 = 1.225V	1_1001 = 2.55V																																																																																																						
1_1010 = 1.25V	1_1010 = 2.6V																																																																																																						
1_1011 = 1.275V	1_1011 = 2.65V																																																																																																						
1_1100 = 1.3V	1_1100 = 2.7V																																																																																																						
1_1101 = 1.325V	1_1101 = 2.75V																																																																																																						
1_1110 = 1.35V	1_1110 = 2.8V																																																																																																						
1_1111 = 1.375V	1_1111 = 2.85V																																																																																																						

10.3.3 Buck1 sleep mode output voltage control

Table 15. Register 0x02

Bit	Field	Type	Default	Description																																																																																																			
D[7:5]	Reserved	W	000	<b>Reserved</b> Set bits to 0 when written																																																																																																			
D[4:0]	BK1_SLP_VOUT	W	1_0100	<p><b>Buck1 Sleep Mode Output Voltage</b> When the DVS1=0 and DVS0=0 and DVS_EN register bit is set to 1, Buck1 is set to Active Mode 0 and these register bits with the BK1_VOUT_RANGE register are used to set the Buck1 output voltage</p> <table border="1"> <thead> <tr> <th>BK1_VOUT_RANGE = 00</th> <th>BK1_VOUT_RANGE = 01</th> <th>BK1-VOUT_RANGE = 10</th> </tr> </thead> <tbody> <tr><td>0_0000 = 0.6V</td><td>0_0000 = 1.4V</td><td>0_0000 = 2.9V</td></tr> <tr><td>0_0001 = 0.625V</td><td>0_0001 = 1.425V</td><td>0_0001 = 2.95V</td></tr> <tr><td>0_0010 = 0.65V</td><td>0_0010 = 1.45V</td><td>0_0010 = 3.0V</td></tr> <tr><td>0_0011 = 0.675V</td><td>0_0011 = 1.475V</td><td>0_0011 = 3.05V</td></tr> <tr><td>0_0100 = 0.7V</td><td>0_0100 = 1.5V</td><td>0_0100 = 3.1V</td></tr> <tr><td>0_0101 = 0.725V</td><td>0_0101 = 1.55V</td><td>0_0101 = 3.15V</td></tr> <tr><td>0_0110 = 0.75V</td><td>0_0110 = 1.6V</td><td>0_0110 = 3.2V</td></tr> <tr><td>0_0111 = 0.775V</td><td>0_0111 = 1.65V</td><td>0_0111 = 3.25V</td></tr> <tr><td>0_1000 = 0.8V</td><td>0_1000 = 1.7V</td><td>0_1000 = 3.3V</td></tr> <tr><td>0_1001 = 0.825V</td><td>0_1001 = 1.75V</td><td>Others Reserved</td></tr> <tr><td>0_1010 = 0.85V</td><td>0_1010 = 1.8V</td><td></td></tr> <tr><td>0_1011 = 0.875V</td><td>0_1011 = 1.85V</td><td></td></tr> <tr><td>0_1100 = 0.9V</td><td>0_1100 = 1.9V</td><td></td></tr> <tr><td>0_1101 = 0.925V</td><td>0_1101 = 1.95V</td><td></td></tr> <tr><td>0_1110 = 0.95V</td><td>0_1110 = 2.0V</td><td></td></tr> <tr><td>0_1111 = 0.975V</td><td>0_1111 = 2.05V</td><td></td></tr> <tr><td>1_0000 = 1.0V</td><td>1_0000 = 2.1V</td><td></td></tr> <tr><td>1_0001 = 1.025V</td><td>1_0001 = 2.15V</td><td></td></tr> <tr><td>1_0010 = 1.05V</td><td>1_0010 = 2.2V</td><td></td></tr> <tr><td>1_0011 = 1.075V</td><td>1_0011 = 2.25V</td><td></td></tr> <tr><td>1_0100 = 1.1V</td><td>1_0100 = 2.3V</td><td></td></tr> <tr><td>1_0101 = 1.125V</td><td>1_0101 = 2.35V</td><td></td></tr> <tr><td>1_0110 = 1.15V</td><td>1_0110 = 2.4V</td><td></td></tr> <tr><td>1_0111 = 1.175V</td><td>1_0111 = 2.45V</td><td></td></tr> <tr><td>1_1000 = 1.2V</td><td>1_1000 = 2.5V</td><td></td></tr> <tr><td>1_1001 = 1.225V</td><td>1_1001 = 2.55V</td><td></td></tr> <tr><td>1_1010 = 1.25V</td><td>1_1010 = 2.6V</td><td></td></tr> <tr><td>1_1011 = 1.275V</td><td>1_1011 = 2.65V</td><td></td></tr> <tr><td>1_1100 = 1.3V</td><td>1_1100 = 2.7V</td><td></td></tr> <tr><td>1_1101 = 1.325V</td><td>1_1101 = 2.75V</td><td></td></tr> <tr><td>1_1110 = 1.35V</td><td>1_1110 = 2.8V</td><td></td></tr> <tr><td>1_1111 = 1.375V</td><td>1_1111 = 2.85V</td><td></td></tr> </tbody> </table>	BK1_VOUT_RANGE = 00	BK1_VOUT_RANGE = 01	BK1-VOUT_RANGE = 10	0_0000 = 0.6V	0_0000 = 1.4V	0_0000 = 2.9V	0_0001 = 0.625V	0_0001 = 1.425V	0_0001 = 2.95V	0_0010 = 0.65V	0_0010 = 1.45V	0_0010 = 3.0V	0_0011 = 0.675V	0_0011 = 1.475V	0_0011 = 3.05V	0_0100 = 0.7V	0_0100 = 1.5V	0_0100 = 3.1V	0_0101 = 0.725V	0_0101 = 1.55V	0_0101 = 3.15V	0_0110 = 0.75V	0_0110 = 1.6V	0_0110 = 3.2V	0_0111 = 0.775V	0_0111 = 1.65V	0_0111 = 3.25V	0_1000 = 0.8V	0_1000 = 1.7V	0_1000 = 3.3V	0_1001 = 0.825V	0_1001 = 1.75V	Others Reserved	0_1010 = 0.85V	0_1010 = 1.8V		0_1011 = 0.875V	0_1011 = 1.85V		0_1100 = 0.9V	0_1100 = 1.9V		0_1101 = 0.925V	0_1101 = 1.95V		0_1110 = 0.95V	0_1110 = 2.0V		0_1111 = 0.975V	0_1111 = 2.05V		1_0000 = 1.0V	1_0000 = 2.1V		1_0001 = 1.025V	1_0001 = 2.15V		1_0010 = 1.05V	1_0010 = 2.2V		1_0011 = 1.075V	1_0011 = 2.25V		1_0100 = 1.1V	1_0100 = 2.3V		1_0101 = 1.125V	1_0101 = 2.35V		1_0110 = 1.15V	1_0110 = 2.4V		1_0111 = 1.175V	1_0111 = 2.45V		1_1000 = 1.2V	1_1000 = 2.5V		1_1001 = 1.225V	1_1001 = 2.55V		1_1010 = 1.25V	1_1010 = 2.6V		1_1011 = 1.275V	1_1011 = 2.65V		1_1100 = 1.3V	1_1100 = 2.7V		1_1101 = 1.325V	1_1101 = 2.75V		1_1110 = 1.35V	1_1110 = 2.8V		1_1111 = 1.375V	1_1111 = 2.85V	
BK1_VOUT_RANGE = 00	BK1_VOUT_RANGE = 01	BK1-VOUT_RANGE = 10																																																																																																					
0_0000 = 0.6V	0_0000 = 1.4V	0_0000 = 2.9V																																																																																																					
0_0001 = 0.625V	0_0001 = 1.425V	0_0001 = 2.95V																																																																																																					
0_0010 = 0.65V	0_0010 = 1.45V	0_0010 = 3.0V																																																																																																					
0_0011 = 0.675V	0_0011 = 1.475V	0_0011 = 3.05V																																																																																																					
0_0100 = 0.7V	0_0100 = 1.5V	0_0100 = 3.1V																																																																																																					
0_0101 = 0.725V	0_0101 = 1.55V	0_0101 = 3.15V																																																																																																					
0_0110 = 0.75V	0_0110 = 1.6V	0_0110 = 3.2V																																																																																																					
0_0111 = 0.775V	0_0111 = 1.65V	0_0111 = 3.25V																																																																																																					
0_1000 = 0.8V	0_1000 = 1.7V	0_1000 = 3.3V																																																																																																					
0_1001 = 0.825V	0_1001 = 1.75V	Others Reserved																																																																																																					
0_1010 = 0.85V	0_1010 = 1.8V																																																																																																						
0_1011 = 0.875V	0_1011 = 1.85V																																																																																																						
0_1100 = 0.9V	0_1100 = 1.9V																																																																																																						
0_1101 = 0.925V	0_1101 = 1.95V																																																																																																						
0_1110 = 0.95V	0_1110 = 2.0V																																																																																																						
0_1111 = 0.975V	0_1111 = 2.05V																																																																																																						
1_0000 = 1.0V	1_0000 = 2.1V																																																																																																						
1_0001 = 1.025V	1_0001 = 2.15V																																																																																																						
1_0010 = 1.05V	1_0010 = 2.2V																																																																																																						
1_0011 = 1.075V	1_0011 = 2.25V																																																																																																						
1_0100 = 1.1V	1_0100 = 2.3V																																																																																																						
1_0101 = 1.125V	1_0101 = 2.35V																																																																																																						
1_0110 = 1.15V	1_0110 = 2.4V																																																																																																						
1_0111 = 1.175V	1_0111 = 2.45V																																																																																																						
1_1000 = 1.2V	1_1000 = 2.5V																																																																																																						
1_1001 = 1.225V	1_1001 = 2.55V																																																																																																						
1_1010 = 1.25V	1_1010 = 2.6V																																																																																																						
1_1011 = 1.275V	1_1011 = 2.65V																																																																																																						
1_1100 = 1.3V	1_1100 = 2.7V																																																																																																						
1_1101 = 1.325V	1_1101 = 2.75V																																																																																																						
1_1110 = 1.35V	1_1110 = 2.8V																																																																																																						
1_1111 = 1.375V	1_1111 = 2.85V																																																																																																						

10.3.4 Buck2 output voltage control

Table 16. Register 0x03

Bit	Field	Type	Default	Description
D[7]	EN_BK2_ENABLE	W	1	<b>Buck2 Software Enable</b> 1: Buck2 is enabled 0: Buck2 is disabled
D[6:0]	BK2_VOUT	W	1_0100	<b>Buck2 Output Voltage</b> Used to control the Buck2 output voltage 0_0000 = 0.6V 0_0001 = 0.625V 0_0010 = 0.65V 0_0011 = 0.675V 0_0100 = 0.7V 0_0101 = 0.725V 0_0110 = 0.75V 0_0111 = 0.775V 0_1000 = 0.8V 0_1001 = 0.825V 0_1010 = 0.85V 0_1011 = 0.875V 0_1100 = 0.9V 0_1101 = 0.925V 0_1110 = 0.95V 0_1111 = 0.975V 1_0000 = 1.0V 1_0001 = 1.025V 1_0010 = 1.05V 1_0011 = 1.075V 1_0100 = 1.1V 1_0101 = 1.125V 1_0110 = 1.15V 1_0111 = 1.175V 1_1000 = 1.2V 1_1001 = 1.225V 1_1010 = 1.25V 1_1011 = 1.275V 1_1100 = 1.3V 1_1101 = 1.325V 1_1110 = 1.35V 1_1111 = 1.375V 0_0000 = 1.4V 0_0001 = 1.425V 0_0010 = 1.45V 0_0011 = 1.475V 0_0100 = 1.5V 0_0101 = 1.55V 0_0110 = 1.6V 0_0111 = 1.65V 0_1000 = 1.7V 0_1001 = 1.75V 0_1010 = 1.8V 0_1011 = 1.85V 0_1100 = 1.9V 0_1101 = 1.95V 0_1110 = 2.0V 0_1111 = 2.05V 1_0000 = 2.1V 1_0001 = 2.15V 1_0010 = 2.2V 1_0011 = 2.25V 1_0100 = 2.3V 1_0101 = 2.35V 1_0110 = 2.4V 1_0111 = 2.45V 1_1000 = 2.5V 1_1001 = 2.55V 1_1010 = 2.6V 1_1011 = 2.65V 1_1100 = 2.7V 1_1101 = 2.75V 1_1110 = 2.8V 1_1111 = 2.85V 0_0000 = 2.9V 0_0001 = 2.95V 0_0010 = 3.0V 0_0011 = 3.05V 0_0100 = 3.1V 0_0101 = 3.15V 0_0110 = 3.2V 0_0111 = 3.25V 0_1000 = 3.3V Others Reserved

### 10.3.5 LDO output voltage control

Table 17. Register 0x04

Bit	Field	Type	Default	Description
D[7:5]	Reserved	W	000	<b>Reserved</b> Set bits to 0 when written
D[4]	EN_LDO	W	1	<b>LDO Software Enable</b> 1: LDO is enabled 0: LDO is disabled
D[3:0]	LDO_VOUT	W	1000	<b>LDO Output Voltage Setting</b> Used to set the LDO output voltage as follows...  0000 = 1.6V 0001 = 1.625V 0010 = 1.65V 0011 = 1.675V 0100 = 1.7V 0101 = 1.725V 0110 = 1.75V 0111 = 1.775V 1000 = 1.8V 1001 = 1.825V 1010 = 1.85V 1011 = 1.875V 1100 = 1.9V 1101 = 1.925V 1110 = 1.95V 1111 = 1.975V

### 10.3.6 Miscellaneous control

Table 18. Register 0x05

Bit	Field	Type	Default	Description
D[7:3]	Reserved	W	0000_0	<b>Reserved</b> Set bits to 0 when written
D[2]	DVS_EN	W	0	<b>DVS Enable</b> 1: DVS is enabled 0: DVS is disabled
D[1]	FPWM_BK1	W	0	<b>Buck1 FPWM</b> 1: When set, forces PWM mode 0: Auto switch between PWM and PFM modes
D[0]	FPWM_BK2	W	0	<b>Buck2 FPWM</b> 1: When set, forces PWM mode 0: Auto switch between PWM and PFM modes

## 11 Revision history

Table 19. Revision history

Document ID	Release date	Data sheet status	Change notice	Supersedes
PM823 v4.0	20220623	Product data sheet	-	PM823 v3.0
Modifications	Changed the document confidentiality level from "Company Confidential" to "Public". No changes in the content.			
PM823 v3.0	20210524	Product data sheet	-	PM823 v2.0
Modifications	<b>Signal description</b> <ul style="list-style-type: none"> <li><a href="#">Figure 4 "1.26 mm x 1.545 mm WLCSP-12 lead, pop (see through) view"</a>: corrected</li> </ul> <b>Application information</b> <ul style="list-style-type: none"> <li><a href="#">Figure 53 "PCB schematic - QFN package"</a>: corrected</li> </ul> <b>Package information</b> <ul style="list-style-type: none"> <li><a href="#">Section 9.2 "Package markings"</a>: updated with the marking of QFN ( <a href="#">Figure 63</a> ) and WLCSP ( <a href="#">Figure 64</a> ) packages</li> </ul>			
PM823 v2.0	20210512	Product data sheet	-	PM823 v1.0
Modifications	<b>Signal description</b> <ul style="list-style-type: none"> <li><a href="#">Figure 5 "4 mm x 4 mm QFN-24 in 0.5 mm pitch pin configuration, top (see through) view"</a>: corrected</li> </ul>			
PM823 v1.0	20201118	Objective data sheet	-	-

## 12 Legal information

### 12.1 Data sheet status

Document status <sup>[1][2]</sup>	Product status <sup>[3]</sup>	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions".

[3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL <http://www.nxp.com>.

### 12.2 Definitions

**Draft** — A draft status on a document indicates that the content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included in a draft version of a document and shall have no liability for the consequences of use of such information.

**Short data sheet** — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

**Product specification** — The information and data provided in a Product data sheet shall define the specification of the product as agreed between NXP Semiconductors and its customer, unless NXP Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the NXP Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

### 12.3 Disclaimers

**Limited warranty and liability** — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of NXP Semiconductors.

**Right to make changes** — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

**Suitability for use** — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors and its suppliers accept no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

**Applications** — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

**Limiting values** — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

**Terms and conditions of commercial sale** — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at <http://www.nxp.com/profile/terms>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

**No offer to sell or license** — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

## Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO

**Quick reference data** — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

**Export control** — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

**Suitability for use in non-automotive qualified products** — Unless this data sheet expressly states that this specific NXP Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. NXP Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without NXP Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond NXP Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies NXP Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond NXP Semiconductors' standard warranty and NXP Semiconductors' product specifications.

**Translations** — A non-English (translated) version of a document, including the legal information in that document, is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

**Security** — Customer understands that all NXP products may be subject to unidentified vulnerabilities or may support established security standards or specifications with known limitations. Customer is responsible for the design and operation of its applications and products throughout their lifecycles to reduce the effect of these vulnerabilities on customer's applications and products. Customer's responsibility also extends to other open and/or proprietary technologies supported by NXP products for use in customer's applications. NXP accepts no liability for any vulnerability. Customer should regularly check security updates from NXP and follow up appropriately.

Customer shall select products with security features that best meet rules, regulations, and standards of the intended application and make the ultimate design decisions regarding its products and is solely responsible for compliance with all legal, regulatory, and security related requirements concerning its products, regardless of any information or support that may be provided by NXP.

NXP has a Product Security Incident Response Team (PSIRT) (reachable at [PSIRT@nxp.com](mailto:PSIRT@nxp.com)) that manages the investigation, reporting, and solution release to security vulnerabilities of NXP products.

## 12.4 Trademarks

Notice: All referenced brands, product names, service names, and trademarks are the property of their respective owners.

**NXP** — wordmark and logo are trademarks of NXP B.V.

Tables

Tab. 1.	Part order options	4	Tab. 11.	BOM for QFN Package	42
Tab. 2.	Pin types	6	Tab. 12.	Register map	47
Tab. 3.	Pin description	7	Tab. 13.	Register 0x00	47
Tab. 4.	Absolute maximum ratings	11	Tab. 14.	Register 0x01	49
Tab. 5.	Recommended operating conditions	11	Tab. 15.	Register 0x02	50
Tab. 6.	External passive components	12	Tab. 16.	Register 0x03	51
Tab. 7.	Electrical characteristics	13	Tab. 17.	Register 0x04	52
Tab. 8.	Operating mode selections	20	Tab. 18.	Register 0x05	52
Tab. 9.	DVS output voltage settings	21	Tab. 19.	Revision history	53
Tab. 10.	BOM for WLCSP package	41			

Figures

Fig. 1.	PM823 typical application-QFN package option	2	Fig. 27.	Buck2 (2.2V) output voltage vs output current WLCSP-12	27
Fig. 2.	PM823 typical application-WLCSP package option	3	Fig. 28.	Buck1 (3.3V) output voltage vs output current QFN-24	27
Fig. 3.	Part numbering scheme	4	Fig. 29.	Buck2 (1.8V) output voltage vs output current QFN-24	27
Fig. 4.	1.26 mm x 1.545 mm WLCSP-12 lead, pop (see through) view	5	Fig. 30.	Buck1 output voltage vs input voltage WLCSP-12	28
Fig. 5.	4 mm x 4 mm QFN-24 in 0.5 mm pitch pin configuration, top (see through) view	6	Fig. 31.	Buck2 Output Voltage vs Input Voltage WLCSP-12	28
Fig. 6.	Block diagram	17	Fig. 32.	Quiescent Current vs Input Voltage For Active Mode 3	28
Fig. 7.	Serial programmability	18	Fig. 33.	Buck1 high side RDS(ON) vs. input voltage WLCSP-12	28
Fig. 8.	Power-up sequence timing diagram - WLCSP package option	19	Fig. 34.	Buck2 high side RDS(ON) vs. input voltage WLCSP-12	28
Fig. 9.	UVLO and OVP waveforms	22	Fig. 35.	Buck1 low side RDS(ON) vs. input voltage WLCSP-12	28
Fig. 10.	Startup	24	Fig. 36.	Buck2 low side RDS(ON) vs. input voltage WLCSP-12	28
Fig. 11.	UVLO / OVP Thresholds	24	Fig. 37.	Buck1 high side RDS(ON) vs. input voltage QFN-24	29
Fig. 12.	Buck1 short circuit	24	Fig. 38.	Buck2 high side RDS(ON) vs. input voltage QFN-24	29
Fig. 13.	Buck2 short circuit	24	Fig. 39.	Buck1 low side RDS(ON) vs. input voltage QFN-24	29
Fig. 14.	Buck1 (1.1V) load transient response 100 mA to 750 mA	25	Fig. 40.	Buck2 low side RDS(ON) vs. input voltage QFN-24	29
Fig. 15.	Buck1 (1.1V) load transient response 750 mA to 1.5A	25	Fig. 41.	Buck1 Output Voltage Error vs Temperature	29
Fig. 16.	Buck2 (2.2V) load transient response 100 mA to 750 mA	25	Fig. 42.	Buck2 Output Voltage Error vs Temperature	29
Fig. 17.	Buck2 (2.2V) load transient response 750 mA to 1.5A	25	Fig. 43.	Quiescent current vs temperature for active mode 3	29
Fig. 18.	Buck1 (1.1V) PFM Output Ripples at 25 mA	26	Fig. 44.	Buck1 high side RDS(ON) vs. temperature WLCSP-12	30
Fig. 19.	Buck1 (1.1V) PWM Output Ripples at 1.5A	26	Fig. 45.	Buck2 high side RDS(ON) vs. temperature WLCSP-12	30
Fig. 20.	Buck2 (2.2V) PFM Output Ripples at 45 mA	26	Fig. 46.	Buck1 low side RDS(ON) vs. temperature WLCSP-12	30
Fig. 21.	Buck2 (2.2V) PWM Output Ripples at 1.5A	26	Fig. 47.	Buck2 low side RDS(ON) vs. temperature WLCSP-12	30
Fig. 22.	Buck1 (1.1V) efficiency vs output current WLCSP-12	27			
Fig. 23.	Buck2 (2.2V) efficiency vs output current WLCSP-12	27			
Fig. 24.	Buck1 (3.3V) efficiency vs output current QFN-24	27			
Fig. 25.	Buck2 (1.8V) efficiency vs output current QFN-24	27			
Fig. 26.	Buck1 (1.1V) output voltage vs output current WLCSP-12	27			

Dual Synchronous 1.5A/1.5A Step-down Buck Regulators with 525 mA LDO

Fig. 48.	Buck1 high side RDS(ON) vs. temperature QFN-24 .....	30	Fig. 57.	Bottom traces, vias, and copper (not to scale) .....	38
Fig. 49.	Buck2 high side RDS(ON) vs. temperature QFN-24 .....	30	Fig. 58.	Top traces, vias, and copper (not to scale) .....	39
Fig. 50.	Buck1 low side RDS(ON) vs. temperature QFN-24 .....	30	Fig. 59.	Bottom traces, vias, and copper (not to scale) .....	40
Fig. 51.	Buck2 low side RDS(ON) vs. temperature QFN-24 .....	30	Fig. 60.	1.260mm x 1.545mm WLCSP-12 mechanical drawing .....	43
Fig. 52.	PCB schematic - WLCSP package .....	33	Fig. 61.	4mm x 4mm QFN-24 mechanical drawing .....	44
Fig. 53.	PCB schematic - QFN package .....	34	Fig. 62.	4mm x 4mm QFN-24 mechanical drawing - Details E .....	45
Fig. 54.	Top traces, vias, and copper (not to scale) .....	35	Fig. 63.	Package marking and pin 1 location - QFN package .....	46
Fig. 55.	Layer 2 vias and copper (not to scale) .....	36	Fig. 64.	Package marking and pin 1 location - WLCSP package .....	46
Fig. 56.	Layer 3 vias and copper (not to scale) .....	37			

## Contents

<b>1</b>	<b>Product overview</b>	<b>1</b>
<b>2</b>	<b>Ordering information</b>	<b>4</b>
<b>3</b>	<b>Signal description</b>	<b>5</b>
3.1	Pin configuration	5
3.1.1	12-lead WLCSP configuration	5
3.1.2	24-pin QFN configuration	6
3.2	Pin descriptions	6
<b>4</b>	<b>Electrical specifications</b>	<b>11</b>
4.1	Absolute maximum ratings	11
4.2	Recommended operating conditions	11
4.3	External passive components	12
4.4	Electrical characteristics	13
<b>5</b>	<b>Functional description</b>	<b>16</b>
5.1	Overview	16
5.2	Serial interface (1-wire)	18
5.3	Soft start	19
5.4	Power-up sequence	19
5.5	Power good	20
5.6	Operating modes	20
5.7	DVS output voltage settings	21
5.8	Sleep mode	21
5.9	Under voltage lock-out (UVLO)	22
5.10	Over voltage protection (OVP)	22
5.11	Over-temperature thermal shutdown (OTS)	23
<b>6</b>	<b>Functional characteristics</b>	<b>24</b>
6.1	Start-up waveforms	24
6.2	Load transient waveforms	25
6.3	Switching waveforms	26
<b>7</b>	<b>Typical characteristics</b>	<b>27</b>
<b>8</b>	<b>Application information</b>	<b>31</b>
8.1	PC board layout considerations and guidelines	31
8.2	PCB schematics	33
8.3	PCB layout examples	34
8.3.1	PCB layout for WLCSP package	35
8.3.2	PCB layout for QFN package	39
8.4	Bill of materials (BOM)	41
<b>9</b>	<b>Package information</b>	<b>43</b>
9.1	Package mechanical drawings	43
9.2	Package markings	46
<b>10</b>	<b>PM823 register sets</b>	<b>47</b>
10.1	Register conventions	47
10.2	Register map	47
10.3	Register descriptions	47
10.3.1	Buck1 active mode 1 and mode 3 output voltage control	47
10.3.2	Buck1 active mode 2 output voltage control	49
10.3.3	Buck1 sleep mode output voltage control	50
10.3.4	Buck2 output voltage control	51
10.3.5	LDO output voltage control	52
10.3.6	Miscellaneous control	52
<b>11</b>	<b>Revision history</b>	<b>53</b>
<b>12</b>	<b>Legal information</b>	<b>54</b>

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.