

8 Bit Microcontroller TLCS-870/X Series

TMP88FW45AFG

The information contained herein is subject to change without notice. 021023_D

TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSH-IBA products specifications.

Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc. 021023_A

The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk. 021023_B

The products described in this document shall not be used or embedded to any downstream products of which manufacture, use and/or sale are prohibited under any applicable laws and regulations. 060106_Q

The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patents or other rights of TOSHIBA or the third parties. 070122_C

For a discussion of how the reliability of microcontrollers can be predicted, please refer to Section 1.3 of the chapter entitled Quality and Reliability Assurance/Handling Precautions. 030619_S

© 2008 TOSHIBA CORPORATION All Rights Reserved

 \wedge

Difference between TMP88FW45FG and TMP88FW45AFG

In TMP88FW45AFG, all SFR/DBR/EBR registers except the oscillation frequency detector are mapped to the same address as TMP88FW45FG. Therefore, the software for TMP88FW45FG can be used in TMP88FW45AFG. As the oscillation frequency detector is not available in Emulator (BM88FW44F0A-M15), please use the flash product (TMP88FW45AFG) to check the oscillation frequency detection.

Products name	TMP88FW45	TMP88FW45A
ROM	122880 by	rtes (Flash)
RAM	4224	bytes
DBR/EBR	144 bytes	144 bytes Registers of oscillation frequency detector are included
I/O port	71	pihs
High-current port	24 pins (sin	< open drain)
Interrupt	External: 5 interrupts,	Internal: 31 interrupts
Timer/counter	16-bit: 2. 8-bit: 4 0	channels channels
PMD	2 chi	annel
UART	2 cha	annels
SIO	1 cha	annels
8-bit High-speed PWM	2 cha	annels
10-bit AD converter	16 ch	annels
Oscillation Frequency Detectior	Non Available	Available
Flash Security	Read protect	"Write protect" has been added in "Read protect". And the name of Read protect has been changed to "Security Program".
Flash size code in Product ID	0EH	1DH
The number of Flash Cell	2	1 (Note 1)
Flash Programming Adapter	PN41	10104
Structuer of TEST pin	VDD O R M T	without protect diode on the VDD side
Absolute Maximum Ratin of Power supply (VDD)	6.5V	6.0V
Operating condition Read/Fetch	4.5V to 5.5V at 20	MHz (-40 to 85 °C)
(MCU mode) Program/Erase	4.5V to 5.5V at 20	MHz (-10 to 40 °C)
Operating condition (Serial PROM mode)	4.5V to 5.5V at 20	MHz (-10 to 40 °C)

Note 1: The same command sequence of TMP88FW45FG can be used in TMP88FW45AFG.

 \Diamond

Revision History

Date	Revision	Comment
2008/5/29	Tentative 1	First Release
2008/10/24	2	Contents Revised

Table of Contents

Difference between TMP88FW45FG and TMP88FW45AFG

TMP88FW45AFG

- 1.1 Features..... 1 <u>____</u>
- 1.2
- 1.3 <u>_____</u> 1.4 Pin Names and Functions

Functional Description 2.

2.1 Functions of the CPU Core

- 2.1.1 Memory Address Map..... 2.1.2 Program Memory (ROM).....
- Data Memory (RAM)..... 2.1.3
- 2.1.4 System Clock Control Circuit.....
 - 2.1.4.1 2.1.4.2 Clock Generator
 - Timing Generator
 - 2.1.4.3 Standby Control Circuit
 - 2.1.4.4 Controlling Operation Modes

2.1.5 Reset Circuit.....

- 2.1.5.1 External Reset Input 2.1.5.2 Address Trap Reset
- 2.1.5.3 Watchdog Timer Reset
- 2.1.5.4 System Clock Reset
- 2.1.5.5 Oscillation Frequency Detection Reset

3. Interrupt Control Circuit

3.1 Interrupt latches (IL39 to IL2)	
3.2 Interrupt enable register (EIR)	27
3.2.1 Interrupt master enable flag (IMF)	
3.2.2 Individual interrupt enable flags (EF39 to EF3)	27
3.3 Interrupt Sequence	
3.3.1 Interrupt acceptance processing is packaged as follows.	
3.3.2 Saving/restoring general-purpose registers	
3.3.2.1 Using Automatic register bank switching	
3.3.2.2 Using register bank switching	
3.3.2.3 Using PUSH and POP instructions	
3.3.2.4 Using data transfer instructions	
3.3.3 Interrupt return	
3.4 Software Interrupt (INTSW)	
3.4.1 Address error detection	
3.4.2 Debugging	
3.5 External Interrupts	35

3

4

.....9

11

10

. 9

ار ب ا

.....

 \smile

4.	Spe	cial Function Register	
	41	SFR	37
	42	FBR	39
	43	DBR	40
	ч.5		
5.	Inp	ut/Output Ports	
	5.1	Port P0 (P03 to P00)	45
	5.2	Port P1 (P17 to P10)	
	5.3	Port P2 (P22 to P20)	
	5.4	Port P3 (P37 to P30)	50
	5.5	Port P4 (P47 to P40)	
	5.6	Port P5 (P57 to P50)	54
	5.7	Port P6 (P67 to P60)	56
	5.8	Port P7 (P77 to P70)	58
	5.9	Port P8 (P87 to P80)	
	5.10) Port P9 (P97 to P90)	
6.	Tim	e Base Timer (TBT) and Divider Output (DVO)	
	61	Time Base Timer	65
	6 2	Divider Output (DVO)	
	0.2		
7.	Wat	tchdog Timer (WDT)	
	7.1	Watchdog Timer Configuration	69
	7.2	Watchdog Timer Control	70
	7.2	2.1 Malfunction Detection Methods Using the Watchdog Timer	70
	7.2	2.2 Watchdog Timer Enable	
	7.2	2.4 Watchdog Timer Interrupt (INTWDT)	72
	7.2	2.5 Watchdog Timer Reset	73
	\bigtriangleup		
8.	Ose	illation Frequency Detector	
	81	Configuration	75
	82	Control	
	83	Function	ייייייייייייייייייייייייייייייייייייי
	8.3	3.1 Enabling and Disabling the Oscillation Frequency Detection	
	8.3	3.2 Setting the Lower and Higher Frequency for Detection	78
	8.3	3.3 Oscillation Frequency Detection Reset	78

9. 16-Bit TimerCounter 1 (TC1)

9.1	Configuration	8	31
-----	---------------	---	----



10. 16-Bit Timer (CTC)

10.1	Configuration		
10.2	Control	21	96
10.3	Function		90
10.3.1	Timer mode with software start	$(\Omega \land \Delta)$	
10.3.2	Timer mode with external trigger start	$(\mathbb{V}_{\mathbb{Z}})$	
10.3.3	Event counter mode		101
10.3.4	Programmable Pulse Generate (PPG) output mode		

11. 8-Bit TimerCounter 3 (TC3)

11.1 Configuration	
--------------------	--

...... 11.2

11.3 11.3.1

- 11.3.2
- Capture Mode..... 11.3.3

12. 8-Bit TimerCounter 4 (TC4)

12.1 (Configuration	
12.2 T	SimerCounter Control	
12.3 F	Function	
12.3.1	Timer Mode	
12.3.2	Event Counter Mode	
12.3.3	Programmable Divider Output (PDO) Mode	
12.3.4	Pulse Width Modulation (PWM) Output Mode	

8-Bit TimerCounter 5,6(TC5, 6) 13.

13.1 (Configuration	
13.2	FimerCounter Control	
13.3 I	Function	
13.3.1	8-Bit Timer Mode (TC5 and 6)	
13.3.2	8-Bit Event Counter Mode (TC5, 6)	
13.3.3	8-Bit Programmable Divider Output (PDO) Mode (TC5, 6)	
13.3.4	8-Bit Pulse Width Modulation (PWM) Output Mode (TC5, 6)	
13.3.5	16-Bit Timer Mode (TC5 and 6)	
13.3.6	16-Bit Event Counter Mode (TC5 and 6)	
13.3.7	16-Bit Pulse Width Modulation (PWM) Output Mode (TC5 and 6)	
13.3.8	16-Bit Programmable Pulse Generate (PPG) Output Mode (TC5 and 6)	

14. Motor Control Circuit (PMD: Programmable motor driver) 14.1 14.2 Position Detection Unit. 139 Configuration of the position detection unit. 140 Position Detection Circuit Register Functions. 141 14.3 14.3.1 14.3.2 14.3.3 14.4 14.4.1 Configuration of the Timer Unit..... 147 14.4.1.1 Timer Circuit Register Functions Outline Processing in the Timer Unit 14.4.1.2 14.5 14.5.1 Configuration of the three-phase PWM output unit. 152 14.5.1.1 Pulse width modulation circuit (PWM waveform generating unit) 152 \bigcirc 14.5.1.2 Commutation control circuit \neg Register Functions of the Waveform Synthesis Circuit. 14.5.2 156 Port output as set with UOC/VOC/WOC bits and UPWM/VPWM/WPWM bits..... 14.5.3 14.5.4 Protective Circuit 14.5.5 Functions of Protective Circuit Registers 14.6 Electrical Angle Timer and Waveform Arithmetic Circuit Functions of the Electrical Angle Timer and Waveform Arithmetic Circuit Registers 14.6.1.1 14.6.1.2 List of PMD Related Control Registers

15. Asynchronous Serial interface (UART1)

15.1	Configuration	
15.2	Control	
15.3	Transfer Data Format	
15.4	Transfer Rate	
15.5	Data Sampling Method	
15.6	STOP Bit Length	
15.7	Parity	
15.8	Transmit/Receive Operation	
15.8.	1 Data Transmit Operation.	
15.8.2	2 Data Receive Operation	
15.9	Status Flag	
15.9.	1 Parity Error	
15.9.2	2 Framing Error	
15.9.1	3 Overrun Error	
15.9.4	4 Receive Data Buffer Full.	
15.9.	5 Transmit Data Buffer Empty	
15.9.0	6 Transmit End Flag	

16. Asynchronous Serial interface (UART2)

.189
.190
.192
.193
.193
.194

16.7 Parity		
16.8 Transmit/Receive Operation		
16.8.1 Data Transmit Operation		
16.8.2 Data Receive Operation		19
16.9 Status Flag		
16.9.1 Parity Error		19
16.9.2 Framing Error		19
16.9.4 Receive Data Buffer Full		
16.9.5 Transmit Data Buffer Empty		19
16.9.6 Transmit End Flag	$\langle () \rangle$	19
Synchronous Serial Interface (SIO)		\searrow
17.1 Configuration	\square	Ş
17.2 Control		,.)
17.3 Serial clock		/
17.3.1 Clock source	\rightarrow	20
17.3.1.2 External clock		
17.3.2 Shift edge	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	
17.3.2.1 Leading edge	$(7/s)^{-}$	
17.4 Number of bits to transfer	\sim	
17.5 Number of words to transfer		
17.6 Transfer Mode	$\langle \langle \rangle \rangle$	
17.6.1 4-bit and 8-bit transfer modes.		
17.6.2 4-bit and 8-bit receive modes.		20
17.6.3 8-bit transfer / receive mode	<u> </u>	20
10-bit AD Converter (ADC)		
18.1 Configuration	~	
18.2 Register configuration		
18.3 Function		
18.3.1 Software Start Mode		
18.3.2 Repeat Mode		
18.3.2.1 Register Setting		
18.4 STOP mode during AD Conversion	•	
18.5 Analog Input Voltage and AD Conversion Res	ult	
18.6 Precautions about AD Converter		
18.6.1 Analog input pin voltage range		
IX 6 X Analog input shared pins		

19. 8-Bit High-speed PWM (HPWM0 and HPWM1)

19.1 Configuration	
19.2 Control	
19.3 Functional Description	
19.3.1 Operation modes	
19.3.1.1 8-bit mode	
19.3.1.2 7-bit mode	
19.3.1.3 6-bit mode	
19.3.2 Setting output data	

20. Flash Memory

20.1 F	lash Memory Control		228
20.1.1	Flash Memory Command Sequence Execution Control (FLSCR <flsmd>)</flsmd>)*	.228
20.2 C	Command Sequence		229
20.2.1	Byte Program.		.229
20.2.2	Sector Erase (4-kbyte Erase)		.229
20.2.3	Chip Erase (All Erase)	<u></u>	.230
20.2.4	Product ID Entry	·····	.230
20.2.5	Product ID Exit	\bigcirc	.230
20.2.6	Security Program.		.230
20.3 T	oggle Bit (D6)		231
20.4 A	ccess to the Flash Memory Area		231
20.4.1	Flash Memory Control in the Serial PROM Mode		.231
20.4.1	.1 How to write to the flash memory by executing the control program in the RAM area (in the RAM loader mode within the seria	1
	PROM mode)		
20.4.2	Flash Memory Control in the MCU mode		.233
20.4.2	2.1 How to write to the flash memory by executing a user write control program in the R.	AM area (in the MCU mode)	

Ć

21. Serial PROM Mode

21.1	Outline	235
21.2	Memory Mapping.	
21.3	Serial PROM Mode Setting	236
21.3	1 Serial PROM Mode Control Pins	236
21.3.	2 Pin Function	
21.3.	3 Example Connection for On-Board Writing	
21.3.4	4 Activating the Serial PROM Mode	
21.4	Interface Specifications for UART	239
21.5	Operation Command	
21.6	Oneration Mode	240
21.6	1 Flash Memory Erasing Mode (Operating command: F0H)	242
21.6.	2 Flash Memory Writing Mode (Operation command: 30H).	
21.6.	3 RAM Loader Mode (Operation Command: 60H)	
21.6.4	4 Flash Memory SUM Output Mode (Operation Command: 90H)	
21.6.	5 Product ID Code Output Mode (Operation Command: C0H)	
21.6.	5 Flash Memory Status Output Mode (Operation Command: C3H)	
21.6.	7 Flash Memory Security Program Setting Mode (Operation Command: FAH)	
21.7	Error Code	255
21.8	Checksum (SUM)	255
21.8.	1 Calculation Method	
21.8.	2 Calculation data	
21.9	Intel Hex Format (Binary)	257
21.10	Passwords	
21.10	0.1 Password String	
21.10	2 Handling of Password Error	
21.10	.3 Password Management during Program Development	
21.11	Product ID Code	259
21.12	Flash Memory Status Code	
21.13	Specifying the Erasure Area	
21.14	Port Input Control Register	
21.15	Flowchart	
21.16	UART Timing	
. = +	0	

22.	Inp	ıt/Output Circuitry		
	22.1 22.2	Control pins Input/output ports		67 67
		input output por so		07
23.	Elec	trical Characteristics		
	23.1	Absolute Maximum Ratings	2	69
	23.2	Operating Conditions		70
	23.2 23.2 23.2	MCU mode (Flash Programming or erasing) MCU mode (Except Flash Programming or erasing) Serial PROM mode	270 271 271	
	23.3	DC Characteristics	2	72
	23.4	AD Characteristics		73
	23.5	AC Characteristics	2	73
	23.6	Oscillation Frequency Detection AC Char	racteristics	74
	23.7	Flash Characteristics		74
	23.8	Recommended Oscillating Conditions	2'	75
	23.9	Handling Precaution		75
		-		

24. Package Dimensions

CMOS 8-Bit Microcontroller

TMP88FW45AFG

Product No.	ROM (FLASH)	RAM	Package
TMP88FW45AFG	122880 bytes	4224 bytes	QFP80-P-1420-0.80B

1.1 Features

- 1. 8-bit single chip microcomputer TLCS-870/X series
 - Instruction execution time :
 - 0.20 µs (at 20 MHz)
 - 181 types & 842 basic instructions
- 2. 36 interrupt sources (External : 5 Internal : 31)
- 3. Input / Output ports (71 pins)

Large current output: 24pins (Typ. 20mA), LED direct drive

- 4. Prescaler
 - Time base timer
 - Divider output function (DVO)
- 5. Watchdog Timer

Select of "internal reset request" or "interrupt request".

- 6. Oscillation Frequency Detector : 1ch
- 7. 16-bit timer counter: 1 ch
 - Timer, External trigger, Window, Pulse width measurement,
 - Event counter, Programmable pulse generate (PPG) modes
- 8. 16-bit timer/counter(CTC): 1ch
 - CTC:Timer, event counter or PPG (Programmable Pulse) output
- 9. 8-bit timer counter : 1 ch

 \rightarrow

This product uses the Super Flash® technology under the licence of Silicon Storage Technology, Inc. Super Flash® is registered trademark of Silicon Storage Technology, Inc.

The information contained herein is subject to change without notice. 021023_D

TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc. 021023_A

The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk. 021023_B

The products described in this document shall not be used or embedded to any downstream products of which manufacture, use and/
 or sale are prohibited under any applicable laws and regulations. 060106_Q

The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patents or other rights of TOSHIBA or the third parties. 070122_C

[•] For a discussion of how the reliability of microcontrollers can be predicted, please refer to Section 1.3 of the chapter entitled Quality and Reliability Assurance/Handling Precautions. 030619_S

- Timer, Event counter, Capture modes
- 10. 8-bit timer counter : 1 ch
 - Timer, Event counter, Pulse width modulation (PWM) output,
 - Programmable divider output (PDO) modes
- 11. 8-bit timer counter : 2 ch
 - Timer, Event counter, Programmable divider output (PDO),
 - Pulse width modulation (PWM) output,
 - Programmable pulse generation (PPG) modes
- 12. Programmable motor driver (PMD) : 2 ch
 - Sine wave drive circuit (built-in sine wave data-table RAM)
 - Rotor position detect function
 - Motor control timer and capture function
 - Overload protective function
 - Auto commutation and auto position detection start function
- 13. 8-bit UART : 2 ch
- 14. 8-bit SIO: 1 ch
- 15. 10-bit successive approximation type AD converter
 - Analog input: 16 ch
- 16. 8-bit High-speed PWM (HPWM0 and HPWM1)
- 17. Clock oscillation circuit : 1 set
- 18. Low power consumption operation (2 modes)
 - STOP mode: Oscillation stops. (Battery/Capacitor back-up.)
 - IDLE mode: CPU stops.

4.5 V to 5.5 V at 20MHz

Only peripherals operate using high frequency clock. Release by interrupts (CPU restarts).

19. Operation voltage:

1.2 Pin Assignment



1.3 Block Diagram



Figure 1-2 Block Diagram

1.4 Pin Names and Functions

The TMP88FW45AFG has MCU mode, parallel PROM mode, and serial PROM mode. Table 1-1 shows the pin functions in MCU mode. The serial PROM mode is explained later in a separate chapter.

	Table 1-1	Pin Names	and Functions	(1/4)
--	-----------	-----------	---------------	-------

		1	
Pin Name	Pin Number	Input/Output	Functions
P03 HPWM1	64	10 0	PORT03 High-spped PWM1 output
P02 HPWM0	63	10 0	PORT02 High-spped RWM0 output
P01 TXD2 PD06/PWM6/PPG6	62	10 0 0	PORT01 UART data output 2 PDO6/PWM6/PPG6 output
P00 RXD2 TC6	61	IO	PORT00 UART data input 2 TC6 input
P17 PDW2	72		PORT17 PMD control input W2
P16 PDV2	71		PORT16 PMD control input V2
P15 PDU2	70		PORT15 PMD control input U2
P14 PPG1 PWM5/PDO5	69		PORT14 PPG1 output PWM5/PDO5 output
P13 DVO TC5	68		PORT13 Divider Output TC5 input
P12 INT2 TC1	67		PORT12 External interrupt 2 input TC1 input
P11 INT1	66		PORT11 External interrupt 1 input
P10 INTO	65	IO I	PORT10 External interrupt 0 input
P22 INT4 TC4 PWM4/PD04			PORT22 External interrupt 4 input TC4 input PWM4/PDO4 output
P21 TC3	6	IO I	PORT21 TC3 pin input
P20 INT5 STOP	9	IO I I	PORT20 External interrupt 5 input STOP mode release signal input
P37 CL1	17	IO I	PORT37 PMD over load protection input1

Table 1-1 Pin Names and Functions (2/4)

Pin Name	Pin Number	Input/Output	Functions
P36 EMG1	16	IO I	PORT36 PMD emergency stop input1
P35 U1	15	10 0	PORT35 PMD control output U1
P34 V1	14	10 0	PORT34 PMD control output V1
P33 W1	13	10 0	PORT33 PMD control output W1
P32 X1	12	10 0	PORT32 PMD control output X1
P31 Y1	11		PORT31 PMD control output Y1
P30 Z1	10	0	PORT30 PMD control output Z1
P47 CTC	25		PORT47 CTC input
P46 PPG2	24	0	PORT46 PPG2 出力
P45 TXD1 SO	23		PORT45 UART data output 1 Serial Data Output
P44 RXD1 SI BOOT	22		PORT44 UART data input 1 Serial Data Input Serial PROM mode control input
P43 SCK	21		PORT43 Serial Clock I/O
P42 PDU1	20	Ю	PORT42 PMD control input U1
P41 PDV1	19		PORT41 PMD control input V1
P40 PDW1	18		PORT40 PMD control input W1
P57 Z2	80	10 0	PORT57 PMD control output Z2
P56 Y2	79	10 0	PORT56 PMD control output Y2
P55 X2	78	IO 0	PORT55 PMD control output X2
P54 W2	77	10 0	PORT54 PMD control output W2

Table 1-1 Pin Names and Functions (3/4)

Pin Name	Pin Number	Input/Output	Functions
P53 V2	76	10 0	PORT53 PMD control output V2
P52 U2	75	10 0	PORT52 PMD control output U2
P51 EMG2	74	IO I	PORT51 PMD emergency stop input2
P50 CL2	73	IO I	PORT50 PMD over load protection input2
P67 AIN7 DBOUT1	33	IO I O	PORT67 Analog Input7 PMD debug output1
P66 AIN6	32		PORT66 Analog Input6
P65 AIN5	31		PORT65 Analog Input5
P64 AIN4	30		PORT64 Analog-Input4
P63 AIN3	29		PORT63 Analog Input3
P62 AIN2	28		PORT62 Analog Input2
P61 AIN1	27		PORT61 Analog Input1
P60 AIN0	26		PORT60 Analog Input0
P77 AIN15 DBOUT2	41		PORT77 Analog Input15 PMD debug output2
P76 AIN14	40		PORT76 Analog Input14
P75 AIN13	39		PORT75 Analog Input13
P74 AIN12	38		PORT74 Analog Input12
P73 AIN11	37	IO I	PORT73 Analog Input11
P72 AIN10	36	IO I	PORT72 Analog Input10
P71 AIN9	35	IO I	PORT71 Analog Input9
P70 AIN8	34	IO I	PORT70 Analog Input8

Pin Name	Pin Number	Input/Output	Functions
P87	52	IO	PORT87
P86	51	IO	PORT86
P85	50	IO	PORT85
P84	49	IO	PORT84
P83	48	Ю	PORT83
P82	47	Ю	PORT82
P81 TXD3	46	IO I	PORT81 UART data output 3
P80 RXD3	45	IO I	PORT80 UART data input 3
P97	60	10	PORT97
P96	59		PORT96
P95	58	10	PORT95
P94	57	Ю	PORT94
P93	56	ю	PORT93
P92	55	ю	PORT92
P91	54	ю	PORT91
P90	53	Ol IO	PORT90
XIN	2		Resonator connecting pins for high-frequency clock
XOUT	3		Resonator connecting pins for high-frequency clock
RESET	8		Reset signal
TEST	4		Test pin for out-going test and the Serial PROM mode control pin. Usually fix to low level. Fix to high level when the Serial PROM mode starts.
VAREF	42		Analog Base Voltage Input Pin for A/D Conversion
AVDD	43		Analog Power Supply
AVSS	44		Analog Power Supply
VDD	5))	+5V
vss			0(GND)

2. Functional Description

2.1 Functions of the CPU Core

The CPU core consists mainly of the CPU, system clock control circuit, and interrupt control circuit.

This chapter describes the CPU core, program memory, data memory, and reset circuit of the TMP88FW45AFG.

2.1.1 Memory Address Map

The memory of the TMP88FW45AFG consists of four blocks: ROM, RAM, SFR (Special Function Registers), and DBR/EBR (Data Buffer Registers), which are mapped into one 1-Mbyte address space. The general-purpose registers consist of 16 banks, which are mapped into the RAM address space. Figure 2-1 shows a memory address map of the TMP88FW45AFG.



2.1.2 Program Memory (ROM)

The TMP88FW45AFG contains 120Kbytes program memory (Flash) located at addresses 04000H to 21EFFH and addresses FFF00H to FFFFFH.

2.1.3 Data Memory (RAM)

The TMP88FW45AFG contains 4Kbytes +128bytes RAM. The first 128bytes location (00040H to 000BFH) of the internal RAM is shared with a general-purpose register bank.

The content of the data memory is indeterminate at power-on, so be sure to initialize it in the initialize routine.

Example :Clearing the internal RAM of the TMP88FW45AFG (clear all RAM addresses to 0, except bank 0)

	LD	HL, 0048H	; Set the start address
	LD	A, 00H	; Set the initialization data (00H)
	LD	BC, 1077H	; Set byte counts (-1)
SRAMCLR:	LD	(HL+), A	
	DEC	BC	
	JRS	F, SRAMCLR	

Note: Because general-purpose registers exist in the RAM, never clear the current bank address of RAM. In the above example, the RAM is cleared except bank 0.

2.1.4 System Clock Control Circuit

The System Clock Control Circuit consists of a clock generator, timing generator, and standby control circuit.



2.1.4.1 Clock Generator

The Clock Generator generates the fundamental clock which serves as the reference for the system clocks supplied to the CPU core and peripheral hardware units.

The high-frequency clock (frequency fc) can be obtained easily by connecting a resonator to the XIN and XOUT pins. Or a clock generated by an external oscillator can also be used. In this case, enter the external clock from the XIN pin and leave the XOUT pin open. The TMP88FW45AFG does not support the CR network that produces a time constant.



Note: Although no hardware functions are provided that allow the fundamental clock to be monitored directly from the outside, the oscillation frequency can be adjusted by forwarding the pulse of a fixed frequency (e.g., clock output) to a port and monitoring it in a program while interrupts and the watchdog timer are disabled. For systems that require adjusting the oscillation frequency, an adjustment program must be created beforehand.

2.1.4.2 Timing Generator

The Timing Generator generates various system clocks from the fundamental clock that are supplied to the CPU core and peripheral hardware units. The Timing Generator has the following functions:

1. Generate a divider output $(\overline{\text{DVO}})$ pulse

- 2. Generate the source clock for the time base timer
- 3. Generate the source clock for the watchdog timer
- 4. Generate the internal source clock for the timer counter
- 5. Generate a warm-up clock when exiting STOP mode

(1) Configuration of the Timing Generator

The Timing Generator a 3-stage prescaler, 21-stage dividers, and a machine cycle counter.

When reset and when entering/exiting STOP mode, the prescaler and dividers are cleared to 0.



<u>TOSHIBA</u>

Divider Control Register



2.1.4.3 Standby Control Circuit

The Standby Control Circuit starts/stops the high-frequency clock oscillator circuit and selects the main system clock. The System Control Registers (SYSCR1, SYSCR2) are used to control operation modes of this circuit. Figure 2-6 shows an operation mode transition diagram, followed by description of the System Control Registers.

(1) Single clock mode

Only the high-frequency clock oscillator circuit is used. Because the main system clock is generated from the high-frequency clock, the machine cycle time in single clock mode is 4/fc [s].

1. NORMAL mode

In this mode, the CPU core and peripheral hardware units are operated with the high-frequency clock. The TMP88FW45AFG enters this NORMAL mode after reset.

2. IDLE mode

In this mode, the CPU and watchdog timer are turned off while the peripheral hardware units are operated with the high-frequency clock. IDLE mode is entered into by using System Control Register 2. The device is placed out of this mode and back into NORMAL mode by an interrupt from the peripheral hardware or an external interrupt. When IMF (interrupt master enable flag) = 1 (interrupt enabled), the device returns to normal operation after the interrupt has been serviced. When IMF = 0 (interrupt disabled), the device restarts execution beginning with the instruction next to one that placed it in IDLE mode.

3. STOP mode

The entire system operation including the oscillator circuit is halted, retaining the internal state immediately before being stopped, with a minimal amount of power consumed.

STOP mode is entered into by using System Control Register 1, and is exited by $\overline{\text{STOP}}$ pin input (level or edge selectable). After an elapse of the warm-up time, the device restarts execution beginning with the instruction next to one that placed it in STOP mode.



Table 2-1 Single Clock Mode

Figure 2-6 Operation Mode Transition Diagram

TOSHIBA

System Control Register 1

SYSCR1	7	6	5	4	3	2	1	0		
(0038H)	STOP	RELM	RETM	OUTEN	WL	JT			(Initial value: 0000 00**)	
	STOP	Place	the device i	n STOP mod	e 0: Keep 1: Stop	the CPU the CPU c	core and pe ore and per	ripheral ha ipheral har	rdware operating rdware (placed in STOP mode)	
	RELM	Select vice is mode	t method by released fr	which the de om STOP	0: Relea	ased by a lased by a l	rising edge o nigh level or	on <u>STOP</u> p n <u>STOP</u> pir	bin input n input	
	RETM	Select iting S	t operation r STOP mode	mode after ex	- 0: Retu 1: Rese	rns to NOF erved	RMAL mode	È		
	OUTEN	Select STOP	t port output ' mode	t state during	0: High 1: Hold	-impedanc output	e state			R/W
							Whe	en Returnir	ng to NORMAL Mode	
							DV1CK =	= 0	DV1CK = 1	
		Unit o	f warm-up t	ime when ex	00		3 × 2 ¹⁶ /f	ic)	3 × 2 ¹⁷ /fc	
	0001	iting S	TOP mode		01	G	2 ¹⁶ /fc		247/fc	
					10	20	214/fc		215/fc	
					11	\mathcal{U}	Reserve	ed	Reserved	

Note 1: When entering from NORMAL mode into STOP mode, always be sure to set SYSCR1<RETM> to 0.

- Note 2: When the device is released from STOP mode by RESET pin input, it always returns to NORMAL mode regardless of how SYSCR1<RETM> is set.
- Note 3: fc: High-frequency clock [Hz], *: Don't care
- Note 4: The values of the SYSCR1 Register bits 1 and 0 are indeterminate when read.
- Note 5: When placed the device in STOP mode, make sure to set "1" to SYSCR1<OUTEN>.
- Note 6: Releasing the device from the STOP mode causes the STOP bit to be automatically cleared to "0".
- Note 7: Select an appropriate value for the warm-up time according to the characteristic of the resonator used.

System Control Register 2

SYSCF
(0039H

R2	7	6	-5	7 4	3 2	1	0	
9H)	XEN	0	SYSCK	IDLE				(Initial value: 1000 ****)

XEN	Control high-frequency oscilla- tor	0: Stop oscillation 1: Continue or start oscillating	R/W
SYSCK	Select (write)/monitor (read) system clock	0: High-frequency clock (NORMAL/IDLE) 1: Reserved	R/W
IDLE	Place the device in IDLE mode	0: Keep the CPU and WDT operating 1: Stop the CPU and WDT (IDLE mode entered)	R/W

RETM	Operation Mode after Releasing STOP Mode	XEN	SYSCK
0	NORMAL mode	1	0
1	No operation	0	1

Note 1: When exiting STOP mode, SYSCR2<XEN and SYSCK> are automatically rewritten according to SYSCR1<RETM>.

- Note 2: When SYSCR2<XEN> is cleared to 0, the device is reset.
- Note 3: WDT: Watchdog Timer, *: Don't care
- Note 4: Be sure to write "0" to SYSCR2 Register bit6.
- Note 5: The values of the SYSCR2 Register bits 3 to 0 are indeterminate when read.
- Note 6: Change the operation mode after disabling external interrupts. If interrupts are enabled after changing operation mode, clear interrupt latches as appropriate in advance.

2.1.4.4 Controlling Operation Modes

(1) STOP mode

STOP mode is controlled by System Control Register 1 (SYSCR1) and the $\overline{\text{STOP}}$ pin input. The $\overline{\text{STOP}}$ pin is shared with P20 port and $\overline{\text{INT5}}$ (external interrupt input 5). STOP mode is entered into by setting STOP (SYSCR1 Register bit 7) to 1. During STOP mode, the device retains the following state.

- 1. Stop oscillation, thereby stopping operation of all internal circuits.
- 2. The data memory, register, program status word, and port output latch hold the state in which they were immediately before entering STOP mode.
- 3. Clear the prescaler and divider for the timing generator to 0.
- 4. The program counter holds the instruction address two instructions ahead the one that placed the device in STOP mode (e.g., "SET (SYSCR1).7").

The device is released from STOP mode by the active level or edge on STOP pin input as selected by SYSCR1<RELM>.

Note: Before entering STOP mode, be sure to disable interrupts. This is because if the signal on an external interrupt pin changes state during STOP (from entering STOP mode till completion of warm-up) the interrupt latch is set to 1, so that the device may accept the interrupt immediately after exiting STOP mode. Also, when enabling interrupts after exiting STOP mode, be sure to clear the unnecessary interrupt latches beforehand.

a. <u>Released by level</u> (when RELM = 1)

The device is released from STOP mode by a high level on STOP pin input.

Any instruction to place the device in STOP mode is ignored when executed while $\overline{\text{STOP}}$ pin input level is high, and the device immediately goes to a release sequence (warm-up) without entering STOP mode. Therefore, before STOP mode can be entered while RELM = 1, the $\overline{\text{STOP}}$ pin input must be verified to be low in a program. There are following methods to do this verification.

- 1. Testing the port status
- 2. INT5 interrupt (interrupt generated at a falling edge on INT5 pin input)

Example 1 :Entering STOP mode from NORMAL mode by testing P20 port

	*		
\sim	LD	(SYSCR1), 01010000B	; Select to be released from STOP mode by level
SSTOPH :	TEST	(P2DR) 0	; Wait until $\overline{\text{STOP}}$ pin input goes low
	JRS	F, SSTOPH	
$\langle (()) \rangle$	DI		; IMF ← 0
	SET	(SYSCR1).7	; Place the device in STOP mode

Example 2 :Entering STOP mode from NORMAL mode by INT5 interrupt

PINT5 :	TEST	(P2DR) . 0	; Do not enter STOP mode if P20 port input level is high, to eliminate noise
	JRS	F, SINT5	; Do not enter STOP mode if P20 port input level is high, to eliminate noise
	LD	(SYSCR1), 01010000B	; Select to be released from STOP mode by level
	DI		; IMF ← 0
	SET	(SYSCR1).7	; Place the device in STOP mode
SINT5 :	RETI		



Figure 2-7 Released from STOP Mode by Level

- Note 1: Once warm-up starts, the device does not return to STOP mode even when the STOP pin input is pulled low again.
- Note 2: If RELM is changed to 1 (level mode) after being set to 0 (edge mode), STOP mode remains unchanged unless a rising edge on STOP pin input is detected.
 - a. <u>Released by edge</u> (when RELM = 0)

The device is released from STOP mode by a rising edge on $\overline{\text{STOP}}$ pin input. This method is used in applications where a relatively short time of program processing is repeated at certain fixed intervals. Apply a fixed-period signal (e.g., clock from the low-power oscillating source) to the $\overline{\text{STOP}}$ pin. When RELM = 0 (edge mode), the device is placed in STOP mode even when the $\overline{\text{STOP}}$ pin input level is high.

Example : Entering STOP mode from NORMAL mode



The device is released from STOP mode following the sequence described below.

- 1. Only the high-frequency oscillator is oscillating.
- 2. A warm-up time is inserted in order to allow for the clock oscillation to stabilize. During warmup, the internal circuits remain idle. The warm-up time can be selected from three choices according to the oscillator characteristics by using SYSCR1<WUT>.
- 3. After an elapse of the warm-up time, the device restarts normal operation beginning with the instruction next to one that placed it in STOP mode. At this time, the prescaler and divider for the timing generator start from the zero-cleared state.

	Warm-up	Time [ms]	\mathcal{I}
WUT	When Returning t		
	DV1CK = 0	DV1CK = 1	
00	9.831	19.662	
01	3.277	6.554	
10	0.819	1.638	90
11	Reserved	Reserved	

Table 2-2 Warm-up Time (Example: fc = 20 MHz)

Note: Because the warm-up time is obtained from the fundamental clock by dividing it, if the oscillation frequency fluctuates while exiting STOP mode, the warm-up time becomes to have some error. Therefore, the warm-up time must be handled as an approximate value.

The device can also be released from STOP mode by pulling the RESET pin input low, in which case the device is immediately reset as is normally reset by RESET. After reset, the device starts operating from NORMAL mode.

Note: When exiting STOP mode while the device is retained at low voltage, the following caution is required.

Before exiting STOP mode, the power supply voltage must be raised to the operating voltage. At this time, the RESET pin level also is high and rises along with the power supply voltage. If the device has a time-constant circuit added external to the chip, the voltage on RESET pin input does not rise as fast as the power supply voltage. Therefore, if the voltage level on RESET pin input is below the RESET pin's noninverted, high-level input voltage (hysteresis input), the device may be reset.



TOSHIBA

(2) IDLE mode

IDLE mode is controlled by System Control Register 2 (SYSCR2) and a maskable interrupt. During IDLE mode, the device retains the following state.

1. The CPU and watchdog timer stop operating.

The peripheral hardware continues operating.

- 2. The data memory, register, program status word, and port output latch hold the state in which they were immediately before entering IDLE mode.
- 3. The program counter holds the instruction address two instructions ahead the one that placed the device in IDLE mode.

Example :Placing the device in IDLE mode



The device can be released from IDLE mode normally or by an interrupt as selected with the interrupt master enable flag (IMF).

a. <u>Released normally</u> (when IMF = 0)

The device can be released from IDLE mode by the interrupt source enabled by the interrupt individual enable flag (EF), and restarts execution beginning with the instruction next to one that placed it in IDLE mode. The interrupt latch (IL) for the interrupt source used to exit IDLE mode normally needs to be cleared to 0 using a load instruction.

b. <u>Released by interrupt</u> (when IMF = 1)

The device can be released from IDLE mode by the interrupt source enabled by the interrupt individual enable flag (EF), and enters interrupt handling. After interrupt handling, the device returns to the instruction next to one that placed it in IDLE mode.

The device can also be released from IDLE mode by pulling the RESET pin input low, in which case the device is immediately reset as is normally reset by RESET. After reset, the device starts operating from NORMAL mode.

Note: If a watchdog timer interrupt occurs immediately before entering IDLE mode, the device processes the watchdog timer interrupt without entering IDLE mode. Functions of the CPU Core

2.1

TMP88FW45AFG



Figure 2-11 Entering and Exiting IDLE Mode
2.1.5 Reset Circuit

The TMP88FW45AFG has five ways to generate a reset: external reset input, address trap reset, watchdog timer reset, system clock reset and oscillation frequency detection reset.

Table 2-3 shows how the internal hardware is initialized by reset operation.

At power-on time, the internal cause reset circuits (watchdog timer reset, address trap reset, and system clock reset) are not initialized.

Internal Hardware	Initial Value	Internal Hardware	Initial Value
Program Counter (PC)	(FFFFEH to FFFFCH)	$\langle () \rangle$	
Stack Pointer (SP)	Not initialized	Prescaler and divider for the	0
General-purpose Registers (W, A, B, C, D, E, H, L)	Not initialized	timing generator	
Register Bank Selector (RBS)	0		Cachlas
Jump Status Flag (JF)	1		Enable
Zero Flag (ZF)	Not initialized		
Carry Flag (CF)	Not initialized		
Half Carry Flag (HF)	Not initialized		See description of
Sign Flag (SF)	Not initialized		port.
Overflow Flag (VF)	Not initialized		
Interrupt Master Enable Flag (IMF)			
Interrupt Individual Enable Flag (EF)	0		See description of
Interrupt Latch (IL)		Control register	each control register.
Interrupt Nesting Flag (INF)		RAM	Not initialized

Table 2-3 In	ternal Hardware	Initialization	by	Reset (Operation

2.1.5.1 External Reset Input

The $\overline{\text{RESET}}$ pin is a hysteresis input with a pull-up resistor included. By holding the $\overline{\text{RESET}}$ pin low for at least three machine cycles (12/fc [s]) or more while the power supply voltage is within the rated operating voltage range and the oscillator is oscillating stably, the device is reset and its internal state is initialized.

When the $\overline{\text{RESET}}$ pin input is released back high, the device is freed from reset and starts executing the program beginning with the vector address stored at addresses FFFFCH to FFFFEH.





2.1.5.2 Address Trap Reset

If the CPU should start looping for reasons of noise, etc. and attempts to fetch instructions from the internal RAM,SFR or DBR/EBR area, the device generates an internal reset.

The address trap permission/prohibition is set by the address trap reset control register (ATAS,ATKEY). The address trap is permitted initially and the internal reset is generated by fetching from internal RAM,SFR or DBR/EBR area. If the address trap is prohibited, instructions in the internal RAM area can be executed.

Address Trap Control Register



The oscillation frequency detector generates a reset for I/O if the oscillation of high frequency is lower than a lower detection frequency, or higher than an upper detection frequency. Refer to Section "Oscillation Frequency Detector".

3. Interrupt Control Circuit

The TMP88FW45AFG has a total of 36 interrupt sources excluding reset. Interrupts can be nested with priorities. Two of the internal interrupt sources are pseudo non-maskable while the rest are maskable.

Interrupt sources are provided with interrupt latches (IL), which hold interrupt requests, and independent vectors. The interrupt latch is set to "1" by the generation of its interrupt request which requests the CPU to accept its interrupts. Interrupts are enabled or disabled by software using the interrupt master enable flag (IMF) and interrupt enable flag (EF). If more than one interrupts are generated simultaneously, interrupts are accepted in order which is dominated by hardware. However, there are no prioritized interrupt factors among non-maskable interrupts.

					·
	Interrupt Factors	Enable Condition	Interrupt Latch	Vector Ad- dress	Priority
Internal/External	(Reset)	Non-maskable	- /	FFFFC	High 0
Internal	INTSWI (Software interrupt)	Pseudo non-maskable	- (FEFF8	1
Internal	INTWDT (Watchdog timer interrupt)	Pseudo non-maskable	IL2	FFFF4	2
External	INT0 (External interrupt 0)	IMF • EF3 = 1, INT0EN = 1	IL3	FFFF0	3
	Reserved	IMF · EF4=1	14	FFFEC	4
External	INT1 (External interrupt 1)	IMF • EF5 = 1	115	FFFE8	5
Internal	INTTBT (TBT interrupt)	IMF · EF6 = 1	IL6	FFFE4	6
	Reserved	IMF EF7 = 1		FFFE0	7
Internal	INTEMG1 (ch1 Error detect interrupt)	IMF · EF8 = 1	IL8	FFFDC	8
Internal	INTEMG2 (ch2 Error detect interrupt)	IMF • EF9 = 1	IL9	FFFD8	9
Internal	INTCLM1 (ch1 Overload protection interrupt)	IMF · EF10=1	IL10	FFFD4	10
Internal	INTCLM2 (ch2 Overload protection interrupt)	IMF • EF11 = 1	IL11	FFFD0	11
Internal	INTTMR31 (ch1 Timer 3 interrupt)	IMF · EF12=1	IL12	FFFCC	12
Internal	INTTMR32 (ch2 Timer 3 interrupt)	IMF • EF13 = 1	IL13	FFFC8	13
	Reserved	IMF · EF14 = 1	IL14	FFFC4	14
External	INT5 (External interrupt 5)	JMF · EF15 = 1	IL15	FFFC0	15
Internal	INTPDC1 (ch1 Position detect interrupt)	IMF · EF16 = 1	IL16	FFFBC	16
Internal	INTPDC2 (ch2 Position detect interrupt)	IMF · EF17 = 1	IL17	FFFB8	17
Internal	INTPWM1 (ch1 Waveform generates interrupt)	IMF • EF18 = 1	IL18	FFFB4	18
Internal	INTPWM2 (ch2 Waveform generates interrupt)	IMF • EF19 = 1	IL19	FFFB0	19
Internal	INTEDT1 (ch1 Electric angle Timer interrupt)	IMF · EF20 = 1	IL20	FFFAC	20
Internal	INTEDT2 (ch2 Electric angle Timer interrupt)	IMF • EF21 = 1	IL21	FFFA8	21
Internal	INTTMR11 (ch1 Timer1 interrupt)	IMF • EF22 = 1	IL22	FFFA4	22
Internal	INTTMR12 (ch2 Timer1 interrupt)	IMF • EF23 = 1	IL23	FFFA0	23
Internal	INTTMR21 (ch1 Timer2 interrupt)	IMF • EF24 = 1	IL24	FFF9C	24
Internal	INTTMR22 (ch2 Timer2 interrupt)	IMF • EF25 = 1	IL25	FFF98	25
Internal	INTTC1 (TC1 interrupt)	IMF • EF26 = 1	IL26	FFF94	26
Internal	INTCTC (CTC interrupt)	IMF • EF27 = 1	IL27	FFF90	27
Internal	INTTC6 (TC6 8bit/16bit interrupt)	IMF • EF28 = 1	IL28	FFF8C	28
External	INT2 (External interrupt 2)	IMF • EF29 = 1	IL29	FFF88	29
Internal	INTRXD2 (ch2 UART receive interrupt)	IMF • EF30 = 1	IL30	FFF84	30
External	INT4 (External interrupt 4)	IMF • EF31 = 1	IL31	FFF80	31
Internal	INTRXD (ch1 UART receive interrupt)	IMF • EF32 = 1	IL32	FFF3C	32
Internal	INTTXD (ch1 UART transmit interrupt)	IMF • EF33 = 1	IL33	FFF38	33
Internal	INTSIO (SIO interrupt)	IMF • EF34 = 1	IL34	FFF34	34
Internal	INTTC3 (TC3 interrupt)	IMF • EF35= 1	IL35	FFF30	35
Internal	INTTC4 (TC4 interrupt)	IMF • EF36 = 1	IL36	FFF2C	36
Internal	INTTC5 (TC5 interrupt)	IMF • EF37 = 1	IL37	FFF28	37
Internal	INTADC (A/D converter interrupt)	IMF • EF38 = 1	IL38	FFF24	38
Internal	INTTXD2 (ch2 UART transmit interrupt)	IMF • EF39 = 1	IL39	FFF20	Low 39

Note 1: To use the watchdog timer interrupt (INTWDT), clear WDTCR1<WDTOUT> to "0" (It is set for the "Reset request" after reset is released). It is described in the section "Watchdog Timer" for details.

3.1 Interrupt latches (IL39 to IL2)

An interrupt latch is provided for each interrupt source, except for a software interrupt and an executed the undefined instruction interrupt. When interrupt request is generated, the latch is set to "1", and the CPU is requested to accept the interrupt if its interrupt is enabled. The interrupt latch is cleared to "0" immediately after accepting interrupt. All interrupt latches are initialized to "0" during reset.

The interrupt latches are located on address 003CH, 003DH, 002EH, 002FH and 002BH in SFR area. Each latch can be cleared to "0" individually by instruction. However, IL2 and IL3 should not be cleared to "0" by software. For clearing the interrupt latch, load instruction should be used and then IL2 should be set to "1". If the read-modify-write instructions such as bit manipulation or operation instructions are used, interrupt request would be cleared inadequately if interrupt is requested while such instructions are executed.

Since interrupt latches can be read, the status for interrupt requests can be monitored by software. But interrupt latches are not set to "1" by an instruction.

Note: In main program, before manipulating the interrupt enable flag (EF) or the interrupt latch (IL), be sure to clear IMF to "0" (Disable interrupt by DI instruction). Then set IMF newly again as required after operating on the EF or IL (Enable interrupt by EI instruction)

In interrupt service routine, because the IMF becomes "0" automatically, clearing-IMF need not execute normally on interrupt service routine. However, if using multiple interrupt on interrupt service routine, manipulating EF or IL should be executed before setting IMF="1".

Example 1 :Clears interrupt latches



3.2 Interrupt enable register (EIR)

The interrupt enable register (EIR) enables and disables the acceptance of interrupts, except for the pseudo nonmaskable interrupts (Software interrupt, undefined instruction interrupt, address trap interrupt and watchdog interrupt). Pseudo non-maskable interrupt is accepted regardless of the contents of the EIR.

The EIR consists of an interrupt master enable flag (IMF) and the individual interrupt enable flags (EF). These registers are located on address 003AH, 003BH, 002CH, 002DH and 002AH in SFR area, and they can be read and written by an instructions (Including read-modify-write instructions such as bit manipulation or operation instructions).

3.2.1 Interrupt master enable flag (IMF)

The interrupt enable register (IMF) enables and disables the acceptance of the whole maskable interrupt. While IMF = "0", all maskable interrupts are not accepted regardless of the status on each individual interrupt enable flag (EF). By setting IMF to "1", the interrupt becomes acceptable if the individuals are enabled.

When an interrupt is accepted, IMF is cleared to "0" after the latest status on IMF is stacked. Thus the maskable interrupts which follow are disabled temporarily. IMF flag is set to "1" by the maskable interrupt return instruction [RETI] after executing the interrupt service program routine, and MCU can accept the interrupt again. The latest interrupt request is generated already, it is available immediately after the [RETI] instruction is executed.

On the pseudo non-maskable interrupt, the non-maskable return instruction [RETN] is adopted. In this case, IMF flag is set to "1" only when it performs the pseudo non-maskable interrupt service routine on the interrupt acceptable status (IMF=1). However, IMF is set to "0" in the pseudo non-maskable interrupt service routine, it maintains its status (IMF="0").

The IMF is located on bit0 in EIRL (Address: 003AH in SFR), and can be read and written by an instruction. The IMF is normally set and cleared by [EI] and [DI] instruction respectively. During reset, the IMF is initialized to "0".

3.2.2 Individual interrupt enable flags (EF39 to EF3)

Each of these flags enables and disables the acceptance of its maskable interrupt. Setting the corresponding bit of an individual interrupt enable flag to "1" enables acceptance of its interrupt, and setting the bit to "0" disables acceptance. During reset, all the individual interrupt enable flags (EF39 to EF3) are initialized to "0" and all maskable interrupts are not accepted until they are set to "1".

Note: In main program, before manipulating the interrupt enable flag (EF) or the interrupt latch (IL), be sure to clear IMF to "0" (Disable interrupt by DI instruction). Then set IMF newly again as required after operating on the EF or IL (Enable interrupt by El instruction)

In interrupt service routine, because the IMF becomes "0" automatically, clearing IMF need not execute normally on interrupt service routine. However, if using multiple interrupt on interrupt service routine, manipulating EF or IL should be executed before setting IMF="1".

Example : Enables interrupts individually and sets IMF

DI		; IMF ← 0
SET	(EIRL), .5	; EF5 ← 1
CLR	(EIRL), .6	; EF6 ← 0
CLR	(EIRH), .4	; EF12 ← 0
CLR	(EIRD), .0	; EF24 ← 0
:		
EI		; IMF ← 1

(Initial value: 0*000000 *00*0000) 13 12 10 9 7 6 4 3 2 ILH,ILL 15 14 11 8 5 1 0 (003DH, 003CH) IL15 IL13 IL12 IL11 IL10 IL8 IL6 IL5 IL3 INF IL9 IL2 -ILH (003DH) ILL (003CH) (Initial value: 00000000 0000000) 9 7 6 4 3 2 0 15 14 13 12 11 10 8 1 ILD,ILE 5 (002FH, 002EH) IL23 IL31 IL29 IL27 IL26 IL25 IL24 IL22 IL20 IL17 IL30 IL28 IL21 IL19 IL18 IL16 ILD (002FH) ILE (002EH) (Initial value: 00000000) 6 5 4 2 1 0 7 З II C (002BH) IL39 1L38 IL37 IL36 IL35 IL34 IL33 IL32 ILE (002BH) Read Write IL39 to IL2 Interrupt latches 0: No interrupt request 0: Clears the interrupt request (Note1) 1: Interrupt request 1: (Unable to set interrupt latch) 00: Reserved 00: Out of interrupt service R/W 01: On interrupt service of level 1 01: Clear the nesting counter 10: On interrupt service of more than 10: Count-down 1 step for the nesting INF Interrupt Nesting Flag counter (Note2) level 2 11: Reserved 11: On interrupt service of more than

Interrupt Latches

Note 1: IL2 cannot alone be cleared.

- Note 2: Unable to detect the under-flow of counter.
- Note 3: The nesting counter is set "0" initially, it performs count-up by the interrupt acceptance and count-down by executing the interrupt return instruction.
- Note 4: In main program, before manipulating the interrupt enable flag (EF) or the interrupt latch (IL), be sure to clear IMF to "0" (Disable interrupt by DI instruction). Then set IMF newly again as required after operating on the EF or IL (Enable interrupt by EI instruction)

In interrupt service routine, because the IMF becomes "0" automatically, clearing IMF need not execute normally on interrupt service routine. However, if using multiple interrupt on interrupt service routine, manipulating EF or IL should be executed before setting IMF="1".

Note 5: Do not clear IL with read-modify-write instructions such as bit operations.

level 3



Interrupt Enable Registers



- Note 1: Do not set IMF and the interrupt enable flag (EF39 to EF3) to "1" at the same time.
- Note 2: In main program, before manipulating the interrupt enable flag (EF) or the interrupt latch (IL), be sure to clear IMF to "0" (Disable interrupt by DI instruction). Then set IMF newly again as required after operating on the EF or IL (Enable interrupt by EI instruction)

In interrupt service routine, because the IMF becomes "0" automatically, clearing IMF need not execute normally on interrupt service routine. However, if using multiple interrupt on interrupt service routine, manipulating EF or IL should be executed before setting IMF="1":

3.3 Interrupt Sequence

An interrupt request, which raised interrupt latch, is held, until interrupt is accepted or interrupt latch is cleared to "0" by resetting or an instruction. Interrupt acceptance sequence requires 12 machine cycles ($2.4 \ \mu s \ @20 \ MHz$) after the completion of the current instruction. The interrupt service task terminates upon execution of an interrupt return instruction [RETI] (for maskable interrupts) or [RETN] (for non-maskable interrupts). Figure 3-1 shows the timing chart of interrupt acceptance processing.

3.3.1 Interrupt acceptance processing is packaged as follows;

- a. The interrupt master enable flag (IMF) is cleared to "0" in order to disable the acceptance of any following interrupt.
- b. The interrupt latch (IL) for the interrupt source accepted is cleared to "0".
- c. The contents of the program counter (PC) and the program status word, including the interrupt master enable flag (IMF), are saved (Pushed) on the stack in sequence of PSWH, PSWL, PCE, PCH, PCL. Meanwhile, the stack pointer (SP) is decremented by 5.
- d. The entry address (Interrupt vector) of the corresponding interrupt service program, loaded on the vector table, is transferred to the program counter.
- e. Read the RBS control code from the vector table, add its MSB(4bit) to the register bank selector (RBS).
- f. Count up the interrupt nesting counter.
- g. The instruction stored at the entry address of the interrupt service program is executed.

Note: When the contents of PSW are saved on the stack, the contents of IMF are also saved.



Note 1: a: Return address, b: Entry address, c: Address which RETI instruction is stored

Note 2: On condition that interrupt is enabled, it takes 62/fc [s] at maximum (If the interrupt latch is set at the first machine cycle on 15 cycle instruction) to start interrupt acceptance processing since its interrupt latch is set.

Figure 3-1 Timing Chart of Interrupt Acceptance/Return Interrupt Instruction

Example: Correspondence between vector table address for INTTBT and the entry address of the interrupt service program



Figure 3-2 Vector table address, Entry address

A maskable interrupt is not accepted until the IMF is set to "1" even if the maskable interrupt higher than the level of current servicing interrupt is requested.

In order to utilize nested interrupt service, the IMF is set to "1" in the interrupt service program. In this case, acceptable interrupt sources are selectively enabled by the individual interrupt enable flags. But don't use the read-modify-write instruction for EIRL(0003AH) on the pseudo non-maskable interrupt service task.

To avoid overloaded nesting, clear the individual interrupt enable flag whose interrupt is currently serviced, before setting IMF to "1". As for non-maskable interrupt, keep interrupt service shorten compared with length between interrupt requests; otherwise the status cannot be recovered as non-maskable interrupt would simply nested.

3.3.2 Saving/restoring general-purpose registers

During interrupt acceptance processing, the program counter (PC) and the program status word (PSW, includes IMF) are automatically saved on the stack, but the accumulator and others are not. These registers are saved by software if necessary. When multiple interrupt services are nested, it is also necessary to avoid using the same data memory area for saving registers. The following four methods are used to save/restore the general-purpose registers.

3.3.2.1 Using Automatic register bank switching

By switching to non-use register bank, it can restore the general-purpose register at high speed.

Usually the bank register "0" is assigned for main task and the bank register "1 to 15" are for the each interrupt service task. To make up its data memory efficiency, the common bank is assigned for non-multiple interrupt factor.

It can return back to main-flow by executing the interrupt return instructions ([RETI]/[RETN]) from the current interrupt register bank automatically. Thus, no need to restore the RBS by a program.

Example : Register bank switching

PINTxx:	(interrupt proce	ssing)	; Begin of interrupt routine
	RETI		; End of interrupt
	:		
VINTxx:	DP	PINTxx	; PINTxx vector address setting
	DB	1	; RBS <- RBS + 1 RBS setting on PINTx

3.3.2.2 Using register bank switching

By switching to non-use register bank, it can restore the general-purpose register at high speed. Usually the bank register "0" is assigned for main task and the bank register "1 to 15" are for the each interrupt service task.

3.3 Interrupt Sequence

PINTxx:	LD	RBS, n	; RBS <- n Begin of interrupt routine
	(interrupt p	processing)	
	RETI		; End of interrupt, restore RBS and interrupt return
	:		
VINTxx:	DP	PINTxx	; PINTxx vector address setting
	DB	0	; RBS <- RBS + 0 RBS setting on PINTxx

Example :Register bank switching

3.3.2.3 Using PUSH and POP instructions

If only a specific register is saved or interrupts of the same source are nested, general-purpose registers can be saved/restored using the PUSH/POP instructions.

Example :Save/store register using PUSH and POP instructions



Figure 3-3 Save/store register using PUSH and POP instructions

3.3.2.4 Using data transfer instructions

To save only a specific register without nested interrupts, data transfer instructions are available.

Example :Save/store register using data transfer instructions

PINTxx:	LD (interrupt	(GSAVA), A processing)	; Save A register
	LD	A, (GSAVA)	; Restore A register
	RETI		; Return

TOSHIBA



Figure 3-4 Saving/Restoring General-purpose Registers under Interrupt Processing

3.3.3 Interrupt return

Interrupt return instructions [RETI]/[RETN] perform as follows.

[RETI] Maskable Interrupt Return	[RETN] Non-maskable Interrupt Return
1. The contents of the program counter and the	1. The contents of the program counter and the
program status word are restored from the stack.	program status word are restored from the stack.
2. The stack pointer is incremented 5 times.	2. The stack pointer is incremented 5 times.
3. The interrupt master enable flag is set to "1".	3. The interrupt master enable flag is set to "1" only
4. The interrupt nesting counter is decremented,	when a non-maskable interrupt is accepted in
and the interrupt nesting flag is changed.	interrupt enable status. However, the interrupt
	master enable flag remains at "0" when so clear
$(\overline{\Omega})$	by an interrupt service program.
$(\vee))$	4. The interrupt nesting counter is decremented,
	and the interrupt nesting flag is changed.

Interrupt requests are sampled during the final cycle of the instruction being executed. Thus, the next interrupt can be accepted immediately after the interrupt return instruction is executed.

Note: When the interrupt processing time is longer than the interrupt request generation time, the interrupt service task is performed but not the main task.

3.4 Software Interrupt (INTSW)

Executing the SWI instruction generates a software interrupt and immediately starts interrupt processing (INTSW is highest prioritized interrupt). However, if processing of a non-maskable interrupt is already underway, executing the SWI instruction will not generate a software interrupt but will result in the same operation as the NOP instruction.

Use the SWI instruction only for detection of the address error or for debugging.

3.4.1 Address error detection

FFH is read if for some cause such as noise the CPU attempts to fetch an instruction from a non-existent memory address during single chip mode. Code FFH is the SWI instruction, so a software interrupt is generated and an address error is detected. The address error detection range can be further expanded by writing FFH to unused areas of the program memory. Address trap reset is generated in ease that an instruction is fetched from RAM, DBR or SFR areas.

3.4.2 Debugging

Debugging efficiency can be increased by placing the SWI instruction at the software break point setting address.

3.5 External Interrupts

The TMP88FW45AFG has 5 external interrupt inputs. These inputs are equipped with digital noise reject circuits (Pulse inputs of less than a certain time are eliminated as noise).

Edge selection is also possible with INT1,INT2 and INT4. The INT0/P10 pin can be configured as either an external interrupt input pin or an input/output port, and is configured as an input port during reset.

Edge selection, and noise reject control and INT0/P10 pin function selection are performed by the external interrupt control register (EINTCR).

Source	Pin	Sub-Pin	Enable Conditions	Release Edge (level)	Digital Noise Reject
INT0	ĪNT0	P10	IMF + EF3 + INT0EN=1	Falling edge	Pulses of less than 2/fc [s] are eliminated as noise. Pulses of 6/fc [s] or more are considered to be signals. (at CGCR <dv1ck>=0).</dv1ck>
INT1	INT1	P11	IMF + EF5 = 1	Falling edge	Pulses of less than 15/fc or 63/fc [s] are elimina- ted as noise. Pulses of 48/fc or 192/fc [s] or more are considered to be signals. (at CGCR <dv1ck>=0).</dv1ck>
INT2	INT2	P12/TC1	IMF + EF29 = 1	Rising edge	Pulses of less than 7/fc [s] are eliminated as
INT4	INT4	P22/TC4	IMF + EF31 = 1		to be signals (at CGCR <dv1ck>=0).</dv1ck>
INT5	INT5	P20/STOP	IMF + EF15 = 1	Falling edge	Pulses of less than 2/fc [s] are eliminated as noise. Pulses of 6/fc [s] or more are considered to be signals.

Note 1: In NORMAL or IDLE mode, if a signal with no noise is input on an external interrupt pin, it takes a maximum of "signal establishment time" from the input signal's edge to set the interrupt latch.

(1) INT1 pin 49/fc [s] (at EINTCR<INT1NC> = "1"), 193/fc [s] (at EINTCR<INT1NC> = "0")

(2) INT2 , 4 pins 25/fc [s]

Note 2: When EINTCR<INT0EN> = "0", IL3 is not set even if a falling edge is detected on the INT0 pin input.

Note 3: When a pin with more than one function is used as an output and a change occurs in data or input/output status, an interrupt request signal is generated in a pseudo manner. In this case, it is necessary to perform appropriate processing such as disabling the interrupt enable flag.

External Interrupt Control Register

EINTCR	7	6	5	4	3	2	1	0	
(0037H)	INT1NC	INTOEN	INT4ES			INT2ES	INT1ES		(Initial value: 0000 *00*)
				1 4		7			

		Noise reject time select	0: Pulses of less than 63/fc [s] are eliminated as noise 1: Pulses of less than 15/fc [s] are eliminated as noise	R/W			
	INTOEN	P10/INT0 pin configuration	0: P10 input/output port 1: INT0 pin (Port P10 should be set to an input mode)	R/W			
	INT4 ES	INT4 edge select	00: Rising edge 01: Falling edge 10: Rising edge and Falling edge 11: H level	R/W			
\checkmark	INT2 ES	INT2 edge select	0: Rising edge	DAA			
	INT1 ES	INT1 edge select	1: Falling edge	rv/VV			

Note 1: fc: High-frequency clock [Hz], *: Don't care

Note 2: When the external interrupt control register (EINTCR) is overwritten, the noise canceller may not operate normally. It is recommended that external interrupts are disabled using the interrupt enable register (EIR).

Note 3: The maximum time from modifying EINTCR<INT1NC> until a noise reject time is changed is 2⁶/fc.

Note 4: In case RESET pin is released while the state of INT4 pin keeps "H" level, the external interrupt 4 request is not generated even if the INT4 edge select(EINTCR<INT4ES>) is specified as "H" level. The rising edge is needed after RESET pin is released.

- 3. Interrupt Control Circuit
- 3.5 External Interrupts



4. Special Function Register

The TMP88FW45AFG adopts the memory mapped I/O system, and all peripheral control and transfers are performed through the special function register (SFR) or the data buffer register (DBR,EBR). The SFR is mapped on address 0000H to 003FH, DBR is mapped on address 1F80H to 1FFFH and EBR is mapped on address 1F70H to 1F7FH.

This chapter shows the arrangement of the special function register (SFR) and data buffer register (DBR,EBR) for TMP88FW45AFG.

4.1 SFR

Address	Read	Wr	ite			
0000H	PODR					
0001H	PI	R	65			
0002H	P2I	R 🛇	9			
0003H	P3DR					
0004H	P4I	R				
0005H	P5I	IR)			
0006H	P6I		\mathcal{I}			
0007H	P7I	R				
0008H	P8I	R				
0009H	P9I	R				
000AH	Poo	R				
000BH	P1	R				
000CH	HPWMCR					
000DH	HPWMDR0					
000EH	HPWMDR1					
000FH	TC1CR					
0010H	TC1DRAL					
0011H	TC1DRAH					
0012H	TC1DRBL					
0013H	TC1D	RBH				
0014H	стс1	CR1				
0015H	Стст	CR2				
0016H	<u>- </u>	CTC1	DRL			
0017Н		CTC1	DRH			
0018H	Rese	ved				
0019H	Rese	ved				
001AH	TC4	CR				
001BH	TC4	DR				
001CH	TC3	RA				
001DH	TC3DRB	-				
001EH	TC3	CR				
001FH	Reserved					
0020H	TC5	CR				
0021H	TC6	CR				
0022H	TTR	G5				
0023H	TTR	G6				
0024H	PWREG5					

Address	Read	Write				
0025H	PWREG6					
0026H	ADC	CRA				
0027H	ADC	CRB				
0028H	ADCDRL ->					
0029H	ADCDRH					
002AH	EIF	25				
002BH	IL	c (7/5)				
002CH	EI	RE				
002DH	EIF	RD OF				
002EH	IL	E				
002FH	цр					
0030H	CGCR					
0031H	Reserved					
0032H	Rese	erved				
0033H	Rese	rved				
0034H	- 20	WDTCR1				
0035H	- 20	WDTCR2				
0036H	ТВТ	CR				
0037H	EIN					
0038H	SYS	CR1				
0039H	ŚYŚ	CR2				
003AH	EI	શ)				
003BH	EIRH					
003CH		L				
003DH		Н				
003EH	PS	WL				
003FH	()) PS'	МН				

Note 1: Do not access reserved areas by the program.

Note 2: -; Cannot be accessed.

Note 3: Write-only registers and interrupt latches cannot use the read-modify-write instructions (Bit manipulation instructions such as SET, CLR, etc. and logical operation instructions such as AND, OR, etc.).



TOSHIBA

4.2 EBR

Address	Read	Write			
1F70H	UARTSR2	UARTCR21			
1F71H	-	UARTCR22			
1F72H	RDBUF2	TDBUF2			
1F73H	Rese	erved			
1F74H	Rese	erved			
1F75H	Rese	erved			
1F76H	Reserved				
1F77H	Reserved				
1F78H	Rese	erved			
1F79H	Rese	erved			
1F7AH	Rese	erved			
1F7BH	Rese	arved			
1F7CH	CLKSCR2				
1F7DH	CLKSMN				
1F7EH	ССК	SMX			
1F7FH		SCR1			

Note 1: Do not access reserved areas by the program.

Note 2: -; Cannot be accessed.

Note 3: Write-only registers and interrupt latches cannot use the read-modify-write instructions (Bit manipulation instructions such as SET, CLR, etc. and logical operation instructions such as AND, OR, etc.).

Page 39

4.3 DBR

.

	Address	PMD ch	Read	Write
ĺ	1F80H		POC	DE
Î	1F81H		-	- ~
Î	1F82H		-	
Î	1F83H		P3C	DE
Î	1F84H		P4C	DE
Î	1F85H		P5C	
Î	1F86H		P8C	DE
Î	1F87H		P9C	DE
Î	1F88H		-	
İ	1F89H		(P3	CR
Î	1F8AH		P4	
Î	1F8BH		P5	CR
ľ	1F8CH		P6	
ľ	1F8DH		P7	
İ	1F8EH		P8	CR
ľ	1F8FH		P9	
Ì	1F90H		UAR	rsel
ľ	1F91H		UARTSR	UARTCR1
ľ	1F92H			UARTCR2
ľ	1F93H		RDBUF	TDBUF
ľ	1F94H			ATAS
ł	1F95H		(\bigcirc) - (\bigcirc)	ATKEY
ľ	1F96H	C		SIOCR1
ľ	1F97H		SIOSR	SIOCR2
ľ	1F98H		SIO	BR0
ľ	1F99H	$\sim ((// j))$	SIO	3R1
ľ	1F9AH	$\bigcirc \bigcirc$	sion	3R2
ľ	1F9BH		SIO	3R3
ľ	1F9CH	\sim	SIO	3R4
ľ	1F9DH	\sim	SIO	3R5
ľ	1F9EH		SIO	3R6
ľ	1F9FH	л <u>г</u>	SIO	3R7
ľ	1FA0H	for PMD ch.1	PDC	CRA
$\langle \rangle$	(FA1H)	for PMD ch.1	PDC	CRB
ľ	1FA2H	for PMD ch.1	PDCRC	-
	1FA3H	for PMD ch.1	SDF	REG
	1FA4H	for PMD ch.1	MTC	CRA
Ì	1FA5H	for PMD ch.1	MTC	CRB
ľ	1FA6H	for PMD ch.1	MCAPL	_
ľ	1FA7H	for PMD ch.1	МСАРН	_
İ	1FA8H	for PMD ch.1	CMI	P1L
İ	1FA9H	for PMD ch.1	CMI	Р1Н
İ	1FAAH	for PMD ch.1	CM	P2L
ľ	1FABH	for PMD ch.1	CMI	P2H
Ì	1FACH	for PMD ch.1	CM	P3L
ľ	1FADH	for PMD ch.1	CMI	РЗН
Ì	1FAEH	for PMD ch.1	MDC	CRA
ľ	1FAFH	for PMD ch.1	MDO	CRB

	Address	PMD ch	Read	Write
	1FB0H	for PMD ch.1	EMG	CRA
	1FB1H	for PMD ch.1	EMG	CRB
	1FB2H	for PMD ch.1	MDC	DUTL
	1FB3H	for PMD ch.1	MDC	ОТН
	1FB4H	for PMD ch.1	MDCNTL	$\left(\begin{array}{c} - \end{array} \right)$
	1FB5H	for PMD ch.1	MDCNTH	
	1FB6H	for PMD ch.1	MDP	RDL
	1FB7H	for PMD ch.1	MDP	RDH
	1FB8H	for PMD ch.1	CMI	
	1FB9H	for PMD ch.1	CME	рин
	1FBAH	for PMD ch 1	CM	RVI
	1FBBH	for PMD ch.1	CM	PVH A
	1EBCH	for PMD ch 1	CM	2W/t
	1FBDH	for PMD ch 1		
	1FBEH	for PMD ch 1		IR A A A A A A A A A A A A A A A A A A A
	1FBEH	for PMD ch 1		FMGREL
	1FC0H	for PMD ch 1		
	1FC1H	for PMD ch 1		
	1FC2H	for PMD ch 1		ETI (7/A
	1FC3H	for PMD ch 1	FDS	БТН
	1FC4H	for PMD ch 1	FLD	EGL
	1EC5H	for PMD ch 1	ELD ELD	EGH
	1FC6H	for PMD ch 1		
	1FC7H	for PMD ch 1		PH
	1FC8H	for PMD ch 1	EDCAPIO	_
	1FC9H	for PMD ch 1	EDCAPH	
	1ECAH	for PMD ch 1	-	WEMDR
	1FCBH			-
	1ECCH		Rese	prved
	1ECDH		Rese	arved
	1ECEH		Rese	arved
	1FCFH	*	Rese	erved
	1ED0H	for PMD ch 2	PDC	CRA
	1ED1H	for PMD ch 2	ר דע דע דע דע דע דע דע דע דע דע דע דע דע	CRB
2	1ED2H	for PMD ch-2	PDCRC	_
	1FD3H	for PMD ch.2	SDF	REG
11	1FD4H	for PMD ch.2	Мтс	CRA
1	1FD5H	for PMD ch.2	MTC	CRB
	1FD6H	for PMD ch.2	MCAPL	_
	1FD7H	for PMD ch.2	MCAPH	_
	1FD8H	for PMD ch 2	CM	P1I
	1FD9H	for PMD ch.2	CMI	P1H
	1FDAH	for PMD ch.2	CM	P2L
	1FDBH	for PMD ch 2	CMI	P2H
	1FDCH	for PMD ch 2	CMI	 P3I
		for PMD ch 2		р _{3Н}
	1EDEH	for PMD ch 2		CRA
		for PMD ch 2		CRB
		for PMD ch 2		CRA
			EMG	

Address	PMD ch	Read	Write			
1FE1H	for PMD ch.2	EMG	CRB			
1FE2H	for PMD ch.2	MDC	DUTL			
1FE3H	for PMD ch.2	MDC	ИТН			
1FE4H	for PMD ch.2	MDCNTL	>-			
1FE5H	for PMD ch.2	MDCNTH				
1FE6H	for PMD ch.2	MDP	RDL			
1FE7H	for PMD ch.2	MDP	RDH			
1FE8H	for PMD ch.2	CM	PUL			
1FE9H	for PMD ch.2	CMF	рин			
1FEAH	for PMD ch.2	CM	PVL			
1FEBH	for PMD ch.2	CMI	2VH			
1FECH	for PMD ch.2	CMF	PWL A			
1FEDH	for PMD ch.2	CMF	AMH AMA			
1FEEH	for PMD ch.2					
1FEFH	for PMD ch.2	-	ÉMGREL			
1FF0H	for PMD ch.2	EDC				
1FF1H	for PMD ch.2	EDC				
1FF2H	for PMD ch.2	EDS	ETL			
1FF3H	for PMD ch.2	EDS	ЕТН			
1FF4H	for PMD ch.2	ELD	EGL			
1FF5H	for PMD ch.2	ELD	EGH			
1FF6H	for PMD ch.2	AM	IPL))			
1FF7H	for PMD ch.2	AM	РН			
1FF8H	for PMD ch.2	EDCAPL	-			
1FF9H	for PMD ch.2	EDCAPH	-			
1FFAH	for PMD ch.2		WFMDR			
1FFBH	$(\sqrt{3})$		-			
1FFCH		Rese	erved			
1FFDH		Reserved				
1FFEH		SP	CR			
1FFFH	\searrow	FLS	SCR			

Note 1: Do not access reserved areas by the program.

Note 2: -; Cannot be accessed.

Note 3: Write-only registers and interrupt latches cannot use the read-modify-write instructions (Bit manipulation instructions such as SET, CLR, etc. and logical operation instructions such as AND, OR, etc.).

5. Input/Output Ports

	Primary Function	Secondary Functions
Port P0	4-bit I/O port	Timer/counter input, serial interface input/output, and high-speed PWM out- put
Port P1	8-bit I/O port	External interrupt input, timer/counter input/output, divider output, and motor control circuit input
Port P2	3-bit I/O port	External interrupt input, timer/counter input/output, and STOP mode release signal input
Port P3	8-bit I/O port	Motor control input/output
Port P4	8-bit I/O port	Timer/counter output, serial interface input/output, motor control circuit input and serial PROM mode control input
Port P5	8-bit I/O port	Motor control circuit input/output
Port P6	8-bit I/O port	Analog input and motor control circuit output
Port P7	8-bit I/O port	Analog input and motor control circuit output
Port P8	8-bit I/O port	Serial interface input/output
Port P9	8-bit I/O port	

The TMP88FW45AFG contains 10 input/output ports comprised of 71 pins.

All output ports contain a latch, and the output data therefore are retained by the latch. But none of the input ports have a latch, so it is desirable that the input data be retained externally until it is read out, or read several times before being processed. Figure 5-1 shows input/output timing.

The timing at which external data is read in from input/output ports is \$1 state in the read cycle of instruction execution. Because this timing cannot be recognized from the outside, transient input data such as chattering needs to be dealt with in a program. The timing at which data is forwarded to input/output ports is \$2 state in the write cycle of instruction execution.

If high frequency oscillation stops or becomes abnormal in NORMAL/IDLE mode, the TMP88FW45AFG generates the oscillation frequency detection reset and all I/O pins become high impedance.



Note: The read/write cycle positions vary depending on instructions.

Figure 5-1 Example of Input/Output Timing

When an operation is performed for read from any input/output port except programmable input/output ports, whether the input value of the pin or the content of the output latch is read depends on the instruction executed, as shown below.

- 1. Instructions which read the content of the output latch
 - XCH r, (src)
 - SET/CLR/CPL (src).b
 - SET/CLR/CPL (pp).g
 - LD (src).b, CF
 - LD (pp).b, CF
 - XCH CF, (src). b
 - ADD/ADDC/SUB/SUBB/AND/OR/XOR (src), n
 - ADD/ADDC/SUB/SUBB/AND/OR/XOR (src), (HL) instructions, the (src) side thereof
 - MXOR (src), m
- 2. Instructions which read the input value of the pin

Any instructions other than those listed above and ADD/ADDC/SUB/SUBB/AND/OR/XOR (src),(HL) instructions, the (HL) side thereof

5.1 Port P0 (P03 to P00)

Port P0 is a 4-bit input/output port shared with serial interface input/output. This port is switched between input and output modes using the P0 port input/output control register (P0CR). When reset, the P0CR register is initialized to 0, with the P0 port set for input mode. Also, the output latch (P0DR) is initialized to 0 when reset.

The P0 port contains bit wise programmable open-drain control. The P0 port open-drain control register (P0ODE) is used to select open-drain or tri-state mode for the port. When reset, the P0ODE register is initialized to 0, with tri-state mode selected for the port.

If high frequency oscillation stops or becomes abnormal in NORMAL/IDLE mode, the TMP88FW45AFG generates the oscillation frequency detection reset and Port P0 becomes high impedance.

P0ODE	P0CR	P0DR	Data input (by reading instruction)	Control input	Output data
0	0	0	Input Data from port	Input Data from port	Hi-Z
0	0	1	Input Data from port	Input Data from port	HIFZ
0	1	0	"0" (output latch data)	"0" (output latch data)	"0"
0	1	1	"1" (output latch data)	"1" (output latch data)	"1"
1	0	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	0	1	Input Data from port	Input Data from port) Hi-Z
1	1	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	1	1	Input Data from port	Input Data from port	Hi-Z

Та	ble	5-1	



Note 1: i = 3 to 0

Note 2: OFDRST shows a reset signal of oscillation frequency detection.

Figure 5-2 Port P0



5.2 Port P1 (P17 to P10)

Port P1 is an 8-bit input/output port shared with external interrupt input, timer/counter input/output, and divider output. This port is switched between input and output modes using the P1 port input/output control register (P1CR). When reset, the P1CR register is initialized to 0, with the P1 port set for input mode. Also, the output latch (P1DR) is initialized to 0 when reset.

If high frequency oscillation stops or becomes abnormal in NORMAL/IDLE mode, the TMP88FW45AFG generates the oscillation frequency detection reset and Port P1 becomes high impedance.

 $(\square) \land$

Table 5-2					
P10DE	P1CR	P1DR	Data input (by reading instruction)	Control input	Output data
0	0	0	Input Data from port	Input Data from port	Hi-Z
0	0	1	Input Data from port	Input Data from port	Hi-Z
0	1	0	"0" (output latch data)	"0" (output latch data)	"0"
0	1	1	"1" (output latch data)	"1" (output latch data)	"4"
1	0	0	Input Data from port (Low)	Input Data from port (Low)	() ("0"
1	0	1	Input Data from port	Input Data from port	Hi-z
1	1	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	1	1	Input Data from port	Input Data from port	Hi-Z







P1 Port Input/Output Registers



Note 1: TC5O: PDO5, PWM5

5.3 Port P2 (P22 to P20)

Port P2 is a 3-bit input/output port shared with external interrupt input and STOP mode release signal. When using this port as these functional pins or an input port, set the output latch to 1. When reset, the output latch is initialized to 1.

We recommend using the P20 pin as external interrupt input, STOP mode release signal input, or input port. When using this port as an output port, note that the interrupt latch is set by a falling edge of output pulse. And note that outputs on this port during STOP mode go to a high-impedance state even if SYSCR1<OUTEN> is set "1", because P20 port is also used as STOP port.

When a read instruction is executed on P2 port, indeterminate values are read in from bits 7 to 3.

When any read-modify-write instruction is executed on P2 port, the content of the output latch is read out. When any other instruction is executed, the external pin state is read out.

If high frequency oscillation stops or becomes abnormal in NORMAL/IDLE mode, the TMP88FW45AFG generates the oscillation frequency detection reset and Port P2 becomes high impedance.





Note 1: When a read instruction is executed on P2 port, indeterminate values are read in from bits 7 to 3.

TOSHIBA

Note 2: Port P20 is used as STOP pin. Therefore, when stop mode is started, SYSCR1<OUTEN> does not affect to P20, and P20 becomes High-Z mode.

Note 3: *: Don't care



5.4 Port P3 (P37 to P30)

Port P3 is an 8-bit input/output port. This port is switched between input and output modes using the P3 port Input/ output Control Register (P3CR). When reset, the P3CR Register is initialized to 0, with the P3 port set for input mode. Also, the Output Latch (P3DR) is initialized to 0 when reset.

The P3 port contains bit wise programmable open-drain control. The P3 Port Open-drain Control Register (P3ODE) is used to select open-drain or tri-state mode for the port. When reset, the P3ODE Register is initialized to 0, with tri-state mode selected for the port.

If high frequency oscillation stops or becomes abnormal in NORMAL/IDLE mode, the TMP88FW45AFG generates the oscillation frequency detection reset and Port P3 becomes high impedance.

P3ODE	P3CR	P3DR	Data input (by reading instruction)	Control input	Output data
0	0	0	Input Data from port	Input Data from port	Hi-Z
0	0	1	Input Data from port	Input Data from port	Hi-Z
0	1	0	"0" (output latch data)	"0" (output latch data)	"O"
0	1	1	"1" (output latch data)	"1" (output latch data)	"1"
1	0	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	0	1	Input Data from port	Input Data from port	Hi-Z
1	1	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	1	1	Input Data from port	Input Data from port	Hi-Z

Table 5-3



Note 1: i = 7 to 0

Note 2: OFDRST shows a reset signal of oscillation frequency detection.

Figure 5-5 Port P3

TOSHIBA

P3DR	7	6	5	4	3	2	1	0	1
(00003H)	P37	P36	P35	P34	P33	P32	P31	P30	Read/Write
,	CL1	EMG1	01	V1	VV1	X1	¥1	Ζ1	
P3CR	7	6	5	4	3	2	1	0	
(01F89H)									(Initial value: 0000 0000)
		P3 po	rt input/out	out control	0: Inpu	ut mode		\sim	
	P3CR	(Spec	ify bit wise)		1: Out	put mode			R/W
P3ODE	7	6	5	4	3	2	1		
(01F83H)							. ((Initial value: 0000 0000)
						l	4		
	B30D	P3 po	rt open-dra	n control	0: Tri-:	state	$\left(\right)$		PM/
	FJODI	(Spec	ify bit wise)		1: Ope	en-drain))	
Note 1	1: Even w	/hen open	-drain moo	le is selec	ed, the pr	otective d	iode remai	ins conne	cted. Therefore, do not apply voltages ex-
Noto (9 VDD-		oporation	ovocutos	at apon dr		is soloctor	d road out the output latch states
NOLE 2	2. Neau-r	noully-vvii			d ovtorp	al open-ui			d, lead out the output laten states.
Note (ar pin state		Jui.	
Note 3			oulpul, sei		output lat			((// 5)
Note 4	Note 4. When using P3 port as an input/output port, disable the ENGT circuit.								

P3 Port Input/Output Registers

5.5 Port P4 (P47 to P40)

Port P4 is an 8-bit input/output port shared with serial interface input/output and serial PROM mode control input. This port is switched between input and output modes using the P4 port input/output control register (P4CR). When reset, the P4CR register is initialized to 0, with the P4 port set for input mode. Also, the output latch (P4DR) is initialized to 0 when reset.

The P4 port contains bit wise programmable open-drain control. The P4 port open-drain control register (P4ODE) is used to select open-drain or tri-state mode for the port. When reset, the P4ODE register is initialized to 0, with tri-state mode selected for the port.

If high frequency oscillation stops or becomes abnormal in NORMAL/IDLE mode, the TMP88FW45AFG generates the oscillation frequency detection reset and Port P4 becomes high impedance.

P4ODE	P4CR	P4DR	Data input (by reading instruction)	Control input	Output data
0	0	0	Input Data from port	Input Data from port	Hi-Z
0	0	1	Input Data from port	Input Data from port	Hi _t z
0	1	0	"0" (output latch data)	"0" (output latch data)	"0"
0	1	1	"1" (output latch data)	"1" (output latch data)	"1"
1	0	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	0	1	Input Data from port	Input Data from port	Hi-Z
1	1	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	1	1	Input Data from port	Input Data from port	Hi-Z

Table 5-4



Note 1: i = 7 to 0

Note 2: OFDRST shows a reset signal of oscillation frequency detection.

Figure 5-6 Port P4

TOSHIBA



P4 Port Input/Output Registers

Note 1: Even when open-drain mode is selected, the protective diode remains connected. Therefore, do not apply voltages exceeding V_{DD} .

Note 2: Read-Modify-Write (RMW) operation executes at open-drain mode is selected, read out the output latch states. When any other instruction is executed, external pin states is read out.

Note 3: When using the 16-bit timer (CTC) as an ordinary timer, set P47 (CTC) for output mode.

5.6 Port P5 (P57 to P50)

Port P5 is an 8-bit input/output port. This port is switched between input and output modes using the P5 port input/ output control register (P5CR). When reset, the P5CR register is initialized to 0, with the P5 port set for input mode. Also, the output latch (P5DR) is initialized to 0 when reset.

The P5 port contains bit wise programmable open-drain control. The P5 port open-drain control register (P5ODE) is used to select open-drain or tri-state mode for the port. When reset, the P5ODE register is initialized to 0, with tri-state mode selected for the port.

If high frequency oscillation stops or becomes abnormal in NORMAL/IDLE mode, the TMP88FW45AFG generates the oscillation frequency detection reset and Port P5 becomes high impedance.

	î		1		
P5ODE	P5CR	P5DR	Data input (by reading instruction)	Control input	Output data
0	0	0	Input Data from port	Input Data from port	Hi-Z
0	0	1	Input Data from port	Input Data from port	HIFZ
0	1	0	"0" (output latch data)	"0" (output latch data)	"0"
0	1	1	"1" (output latch data)	"1" (output latch data)	"1"
1	0	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	0	1	Input Data from port	Input Data from port) Hi-Z
1	1	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	1	1	Input Data from port	Input Data from port	Hi-Z





Note 1: i = 7 to 0 Note 2: OFDRST shows a reset signal of oscillation frequency detection.

Figure 5-7 Port P5

P5 Port Input/Output Registers



TOSHIBA

P5ODE		7	6	5	4	3	2	1	0	1	
(01F85H)										(Initial value: 0000 0000)	
_											
	P5 port open-drain control					0: Tri-s	state			$\langle \rangle$	R/W
L		(Specify bit wise)					en-drain				1000
Note 1	: E'	Even when open-drain mode is selected, the protective diode remains connected. Therefore, do not apply voltages e									
	CE	ceeding V _{DD} .									
Note 2	:: Read-Modify-Write (RMW) operation executes at open-drain mode is selected, read out the output latch states.										
	W	When any other instruction is executed, external pin states is read out.									
Note 3	: Fo	For PMD circuit output, set the P5DR output latch to 1.									
Note 4	·. vv	when using P5 port as an input/output port, disable the EMG2 circuit.									
								(
								Z	$(\)$		
									$\langle \rangle$		
								(7)	\wedge		
									<i>)</i>		
							((\swarrow			
								\sim			
							$\langle \langle \rangle$	\searrow			
						G		>	6	770	
						G	\sim		~ 0	$\langle O \rangle$	
						40	\searrow	1	\sim		
					/		>	$\langle \langle \rangle$			
					()	()	~		> //		
					\frown	\bigcirc			\sim		
						\wedge		$\langle \rangle$			
))	\langle	\geq			
				(0	77~	-		\mathbb{N}_{\sim}			
			6	$> \lor$	$\bigcirc)$		$\overline{\Box}$	\rightarrow			
						\sim	$(// \leq$				
			\sim		7		X				
				$\langle \rangle$	\langle						
			~	\sim		\backslash					
		$\langle \rangle$	Ζ.				>				
		\sim	\searrow	7	$\left(\right)$						
	(\frown	\mathcal{A}		41						
\sim		\mathcal{L}))			\geq					
	$\langle \rangle$	\sim		\bigcirc (()	Ť					
$\langle \subset$		\geq		$\langle \bigtriangledown \rangle$	\bigcirc						
				4							
	\searrow				\searrow						

5.7 Port P6 (P67 to P60)

Port P6 is an 8-bit input/output port shared with AD converter analog input. This port is switched between input and output modes using the P6 port input/output control register (P6CR), P6 port output latch (P6DR), and ADC-CRA<AINDS>. When reset, the P6CR Register and the P6DR output latch are initialized to 0 while ADC-CRA<AINDS> is set to 1, so that P67 to P60 have their inputs fixed low (= 0). When using the P6 port as an input port, set the corresponding bits for input mode (P6CR = 0, P6DR = 1). The reason why the output latch = 1 is because it is necessary to prevent current from flowing into the shared data input circuit. When using the port as an output port, set the P6CR Register's corresponding bits to 1. When using the port for analog input, set the corresponding bits for analog input (P6CR = 0, P6DR = 0). Then set ADCCRA<AINDS> = 0, and AD conversion will start.

The ports used for analog input must have their output latches set to 0 beforehand. The actual input channels for AD conversion are selected using ADCCRA<SAIN>.

Although the bits of P6 port not used for analog input can be used as input/output ports, do not execute output instructions on these ports during AD conversion. This is necessary to maintain the accuracy of AD conversion. Also, do not apply rapidly changing signals to ports adjacent to analog input during AD conversion.

If an input instruction is executed while the P6DR output latch is cleared to 0, data "0" is read in from said bits.

If high frequency oscillation stops or becomes abnormal in NORMAL/IDLE mode, the TMP88FW45AFG generates the oscillation frequency detection reset and Port P6 becomes high impedance.



Note 1: i = 7 to 0

Note 2: STOP exists in SYSCR1 register bit 7.

Note 3: SAIN selects AD input channel.

Note 4: OFDRST shows a reset signal of oscillation frequency detection.



	7	6	5	4	3	2	1	0			
P6DR	P67	P66	P65	P64	P63	P62	P61	P60	Dead		
(00006H)	AIN7	AIN6	AIN5	AIN4	AIN3	AIN2	AIN1	AIN0	(Initial value: 0000 (0000	
	DBOUT1									,000)	
P6CR	7	6	5	4	3	2	1	0			
(01F8CH)									(Initial value: 0000 0	0000)	
\sim (7/ \diamond										_	
						AINDS	AINDS = 1 (when not using AD) AINDS = 0 (when using AD)				
		P6 no	P6 port input/output control			P6DR	= "0"	P6DR = "1"	P6DR = "0"	P6DR = "1"	
	P6CR	(Specify bit wise)			0	Inputs fix	ed to 0	Input mode	Analog Input mode (Note2)	Input mode	R/W
					1		2	(Ou	tput mode	\sim	

P6 Port Input/Output Registers

Note 1: The pins used for analog input cannot be set for output mode (P6CR = 1) because they become shorted with external signals.

Note 2: When a read instruction is executed on bits of this port which are set for analog input mode, data "0" is read in.

Note 3: For DBOUT1 output, set the P6DR (P67) output latch to 1.

Note 4: When using this port in input mode (including analog input), do not use bit manipulating or other read-modify-write instructions. When a read instruction is executed on the bits of this port that are set for input, the contents of the pins are read in, so that if a read-modify-write instruction is executed, their output latches may be rewritten, making the pins unable to accept input. (A read-modify-write instruction first reads data from all of the eight bits and after modifying them (bit manipulation), writes data for all of the eight bits to the output latches.)

5.8 Port P7 (P77 to P70)

Port P7 is an 8-bit input/output port shared with AD converter analog input. This port is switched between input and output modes using the P7 port input/output control register (P7CR), P7 port output latch (P7DR), and ADC-CRA<AINDS>. When reset, the P7CR register and the P7DR output latch are initialized to 0 while ADC-CRA<AINDS> is set to 1, so that P77 to P70 have their inputs fixed low (= 0). When using the P7 port as an input port, set the corresponding bits for input mode (P7CR = 0, P7DR = 1). The reason why the output latch = 1 is because it is necessary to prevent current from flowing into the shared data input circuit. When using the port as an output port, set the P7CR Register's corresponding bits to 1. When using the port for analog input, set the corresponding bits for analog input (P7CR = 0, P7DR = 0). Then set ADCCRA<AINDS> = 0, and AD conversion will start.

The ports used for analog input must have their output latches set to 0 beforehand. The actual input channels for AD conversion are selected using ADCCRA<SAIN>.

Although the bits of P7 port not used for analog input can be used as input/output ports, do not execute output instructions on these ports during AD conversion. This is necessary to maintain the accuracy of AD conversion. Also, do not apply rapidly changing signals to ports adjacent to analog input during AD conversion.

If an input instruction is executed while the P7DR output latch is cleared to 0, data "0" is read in from said bits.

If high frequency oscillation stops or becomes abnormal in NORMAL/IDLE mode, the TMP88FW45AFG generates the oscillation frequency detection reset and Port P7 becomes high impedance.


	7	6	5	4	3	2	1	0			
P7DR	P77	P76	P75	P74	P73	P72	P71	P70	Pood/M/rito		
(00007H)	AIN15	AIN14	AIN13	AIN12	AIN11	AIN10	AIN9	AIN8	(Initial value: 0000 (0000	
	DBOUT2									,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,	
P7CR	7	6	5	4	3	2	1	0			
(01F8DH)									(Initial value: 0000 0	0000)	
·	\sim (7/ \diamond								_		
						AINDS = 1 (when not using AD) AINDS = 0 (when using				hen using AD)	
		P7 no	rt innut/outr	out control		P7DR -	= "0"	P7DR = "1"	P7DR = "0"	P7DR = "1"]
	P7CR	P7CR (Specify bit wise)		0	Inputs fix	ed to 0	Input mode	Analog Input mode (Note2)	Input mode	R/V	
				1				tput mode			

P7 Port Input/Output Registers

Note 1: The pins used for analog input cannot be set for output mode (P7CR = 1) because they become shorted with external signals.

Note 2: When a read instruction is executed on bits of this port which are set for analog input mode, data "0" is read in.

Note 3: For DBOUT2 output, set the P7DR (P77) output latch to 1.

Note 4: When using this port in input mode (including analog input), do not use bit manipulating or other read-modify-write instructions. When a read instruction is executed on the bits of this port that are set for input, the contents of the pins are read in, so that if a read-modify-write instruction is executed, their output latches may be rewritten, making the pins unable to accept input. (A read-modify-write instruction first reads data from all of the eight bits and after modifying them (bit manipulation), writes data for all of the 8 bits to the output latches.)

5.9 Port P8 (P87 to P80)

Port P8 is an 8-bit input/output port. This port is switched between input and output modes using the P8 port input/ output control register (P8CR). When reset, the P8CR register is initialized to 0, with the P8 port set for input mode. Also, the output latch (P8DR) is initialized to 0 when reset.

The P8 port contains bit wise programmable open-drain control. The P8 port open-drain control register (P8ODE) is used to select open-drain or tri-state mode for the port. When reset, the P8ODE register is initialized to 0, with tri-state mode selected for the port.

If high frequency oscillation stops or becomes abnormal in NORMAL/IDLE mode, the TMP88FW45AFG generates the oscillation frequency detection reset and Port P8 becomes high impedance.

	_				
P8ODE	P8CR	P8DR	Data input (by reading instruction)	Control input	Output data
0	0	0	Input Data from port	Input Data from port	Hi-Z
0	0	1	Input Data from port	Input Data from port	Hijz
0	1	0	"0" (output latch data)	"0" (output latch data)	"0 "
0	1	1	"1" (output latch data)	"1" (output latch data)	"1"
1	0	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	0	1	Input Data from port	Input Data from port	Hi-Z
1	1	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	1	1	Input Data from port	Input Data from port	Hi-Z

Table 5-6



Note 1: i = 7 to 2 Note 2: j = 1, 0 Note 3: OFDRST shows a reset signal of oscillation frequency detection.

Figure 5-10 Port P8

	7	6	5	4	3	2	1	0			
(00008H)	P87	P86	P85	P84	P83	P82	P81	P80	Read/Write		
(0000011)							TXD3	RXD3	(Initial value: 0000 0000)		
P8CR	7	6	5	4	3	2	1	0			
(01F8EH)									(Initial value: 0000 0000)		
I								1			
	DOOD	P8 pc	ort input/outp	out control	0: Inpi	ut mode		\sim	$(\mathcal{O}/\mathcal{A})$	DAA	
	P8CR	(Spec	(Specify bit wise)			1: Output mode					
P80DE	7	6	5	4	3	2	1	Q			
(01F86H)							($\langle \rangle$	(Initial value: 0000 0000)		
	P8ODE	P8 pc (Spec	ort open-drai cify bit wise)	in control	0: Tri- 1: Ope	state en-drain	(7)	\sim		R/W	

P8 Port Input/Output Registers

Note 1: Even when open-drain mode is selected, the protective diode remains connected. Therefore, do not apply voltages exceeding V_{DD}.

Note 2: Read-Modify-Write (RMW) operation executes at open-drain mode is selected, read out the output latch states. When any other instruction is executed, external pin states is read out.

5.10 Port P9 (P97 to P90)

Port P9 is an 8-bit input/output port. This port is switched between input and output modes using the P9 port input/ output control register (P9CR). When reset, the P9CR register is initialized to 0, with the P9 port set for input mode. Also, the output latch (P9DR) is initialized to 0 when reset.

The P9 port contains bit wise programmable open-drain control. The P9 port open-drain control register (P9ODE) is used to select open-drain or tri-state mode for the port. When reset, the P9ODE register is initialized to 0, with tri-state mode selected for the port.

If high frequency oscillation stops or becomes abnormal in NORMAL/IDLE mode, the TMP88FW45AFG generates the oscillation frequency detection reset and Port P9 becomes high impedance.

P9ODE	P9CR	P9DR	Data input (by reading instruction)	Control input	Output data
0	0	0	Input Data from port	Input Data from port	Hi-Z
0	0	1	Input Data from port	Input Data from port	Hi-Z
0	1	0	"0" (output latch data)	"0" (output latch data)	"0"
0	1	1	"1" (output latch data)	"1" (output latch data)	,"1"
1	0	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	0	1	Input Data from port	Input Data from port) Hi-Z
1	1	0	Input Data from port (Low)	Input Data from port (Low)	"0"
1	1	1	Input Data from port	Input Data from port	Hi-Z

Table 5-7



Figure 5-11 Port P9

Note 1: i = 7 to 0 Note 2: OFDRST shows a reset signal of oscillation frequency detection.

	7	6	5	4	3	2	1	0		
(00009H)	P97	P96	P95	P94	P93	P92	P91	P90	Read/Write (Initial value: 0000 0000)	
P9CR	7	6	5	4	3	2	1	0		
(01F8FH)									(Initial value: 0000 0000)	
	P9CR	P9 port input/output control			0: Inpu	ut mode		\sim	(/)	R/W
		(Spec	(Specify bit wise)			1: Output mode				
P90DE	7	6	5	4	3	2	1	Q		
(01F87H)							((Initial value: 0000 0000)	
		P9 pc	ort open-drai	n control	0: Tri-	0: Tri-state				D/M
	FBODE	(Spec	(Specify bit wise)			1: Open-drain				

P9 Port Input/Output Registers

Note 1: Even when open-drain mode is selected, the protective diode remains connected. Therefore, do not apply voltages exceeding V_{DD}.

Note 2: Read-Modify-Write (RMW) operation executes at open-drain mode is selected, read out the output latch states. When any other instruction is executed, external pin states is read out.

6. Time Base Timer (TBT) and Divider Output (\overline{DVO})

6.1 Time Base Timer

The time base timer generates time base for key scanning, dynamic displaying, etc. It also provides a time base timer interrupt (INTTBT).

An INTTBT (Time Base Timer Interrupt) is generated on the first falling edge of source clock (The divider output of the timing generator which is selected by TBTCK.) after time base timer has been enabled.

The divider is not cleared by the program; therefore, only the first interrupt may be generated ahead of the set interrupt period (Figure 6-2).

The interrupt frequency (TBTCK) must be selected with the time base timer disabled (TBTEN="0"). (The interrupt frequency must not be changed with the disable from the enable state.) Both frequency selection and enabling can be performed simultaneously.



Example :Set the time base timer frequency to fc/2¹⁶ [Hz] and enable an INTTBT interrupt.

LD	(TBTCR) , 00000010B	; TBTCK \leftarrow 010 (Freq. set)
LD	(TBTCR) , 00001010B	; TBTEN \leftarrow 1 (TBT enable)
DI		
SET	(EIRL) . 6	
EI		

Time Base Timer is controled by Time Base Timer control register (TBTCR).



Time Base Timer Control Register

Note 1: fc; High-frequency clock [Hz], *; Don't care Note 2: Always set "0" in bit4 on TBTCR register.

Table 6-1 Time Base Timer Interrupt Frequency (Example : fc = 20.0 MHz)

TETOY	Time Base Timer Interrupt Frequency [Hz] NORMAL, IDLE Mode				
IBICK					
	DV1CK = 0	DV1CK = 1			
000	2.38	1.20			
001	9.53	4.78			
010	305.18	153.50			
014	1220.70	610.35			
100	2441.40	1220.70			
101	4882.83	2441.40			
110	9765.63	4882.83			
	39063.00	19531.25			
	\mathcal{O}				

6.2 Divider Output ($\overline{\text{DVO}}$)

Approximately 50% duty pulse can be output using the divider output circuit, which is useful for piezoelectric buzzer drive. Divider output is from $\overline{\text{DVO}}$ pin.



Example : 2.44 kHz pulse output (fc = 20.0 MHz)

Port setting

LD	(TBTCR) , 0000000B	; DVOCK ← "00"
LD	(TBTCR) , 10000000B	; DVOEN \leftarrow "1"

6.2 Divider Output (DVO)

Divider Output Frequency [Hz]							
NORMAL, IDLE Mode							
DV1CK=0	DV1CK=1	\square					
2.4415 k	1.22075 k	Â					
4.8825 k	2.4415 k						
9.765 k	4.8825 k						
19.5325 k	9.765 k	$\left(\right)$					
	Divider Output NORMAL, DV1CK=0 2.4415 k 4.8825 k 9.765 k 19.5325 k	Divider Output Frequency [Hz] NORMAL, IDLE Mode DV1CK=0 DV1CK=1 2.4415 k 1.22075 k 4.8825 k 2.4415 k 9.765 k 4.8825 k 19.5325 k 9.765 k					

Table 6-2 Divider Output Frequency (Example : fc = 20.0 MHz)

7. Watchdog Timer (WDT)

The watchdog timer is a fail-safe system to detect rapidly the CPU malfunctions such as endless loops due to spurious noises or the deadlock conditions, and return the CPU to a system recovery routine.

The watchdog timer signal for detecting malfunctions can be programmed only once as "reset request" or "pseudo non-maskable interrupt request". Upon the reset release, this signal is initialized to "reset request".

When the watchdog timer is not used to detect malfunctions, it can be used as the timer to provide a periodic interrupt.

Note: Care must be taken in system design since the watchdog timer functions are not be operated completely due to effect of disturbing noise.

7.1 Watchdog Timer Configuration Reset release fc/223,fc/224 **Binary counters** fc/221,fc/222 R Selecto Clock fc/219,fc/220 Overflow WDT output fc/217,fc/218 Reset 1 2 S Clear Q request Interrupt request INTWDT interrupt request Internal reset Q S R WDTEN Writing Writing WDTOUT WDTT disable code clear code Controller 0034_H 0035_H WDTCR1 WDTCR2 Watchdog timer control registers Figure 7-1 Watchdog Timer Configuration

7.2 Watchdog Timer Control

The watchdog timer is controlled by the watchdog timer control registers (WDTCR1 and WDTCR2). The watchdog timer is automatically enabled after the reset release.

7.2.1 Malfunction Detection Methods Using the Watchdog Timer

The CPU malfunction is detected, as shown below.

- 1. Set the detection time, select the output, and clear the binary counter.
- 2. Clear the binary counter repeatedly within the specified detection time.

If the CPU malfunctions such as endless loops or the deadlock conditions occur for some reason, the watchdog timer output is activated by the binary-counter overflow unless the binary counters are cleared. When WDTCR1<WDTOUT> is set to "1" at this time, the reset request is generated and then internal hardware is initialized. When WDTCR1<WDTOUT> is set to "0", a watchdog timer interrupt (INTWDT) is generated.

The watchdog timer temporarily stops counting in the STOP mode including the warm-up or IDLE mode, and automatically restarts (continues counting) when the STOP/IDLE mode is inactivated.

Note: The watchdog timer consists of an internal divider and a two-stage binary counter. When the clear code 4EH is written, only the binary counter is cleared, but not the internal divider. The minimum binary-counter overflow time, that depends on the timing at which the clear code (4EH) is written to the WDTCR2 register, may be 3/4 of the time set in WDTCR1<WDTT>. Therefore, write the clear code using a cycle shorter than 3/4 of the time set to WDTCR1<WDTT>.

Example :Setting the watchdog timer detection time to $2^{21}/\text{fc}$ [s], and resetting the CPU malfunction detection



WDTCR1	7	6	5	4		3	2	1	0			
(0034H)					WD	TEN	WD	т	WDTOUT	(Initial value: **** 1001)		
*****									\sim			
	ſ	WDTEN	Watchdog timer enable/disable			0: Disa	0: Disable (Writing the disable code to WDTCR2 is required.)					
		MBTER	Waterlang till		abio	1: Ena	Enable					
									NORMAL r	node		
						C	0V1CK = 0	((//{	DV1CK = 1	1		
			WDTT	Watabdaatim	or datastian ti	00		2 ²⁵ /fc		2 ²⁶ /fc	Write	
		VUTI		01		2 ²³ /fc		2 ²⁴ /fc	only			
					10		2 ²¹ fc	\mathcal{I}	2 ²² fc			
						11		2 ¹⁹ /fc		2 ²⁰ /fc		
	ſ	WDTOUT	Watchdog tin	ner output sel	ect	0: Interrupt request					Write	
		WD1001	watchuog tin	1: Reset request					only			
Note 1	: Afte	er clearing W	/DTCR1 <wd< td=""><td>TOUT> to "</td><td>0", the</td><td>progra</td><td>m cannot s</td><td>et it to "1'</td><td></td><td>2ñ</td><td></td></wd<>	TOUT> to "	0", the	progra	m cannot s	et it to "1'		2ñ		
Note 2	· \\\\\			otor and mu	ot not	bo upo	duvith any	of road m	odifu write in	astructions If WDTCP1	a road a	

Watchdog Timer Control Register 1

Note 3: WDTCR1 is a write-only register and must not be used with any of read-modify-write instructions. If WDTCR1 is read, a unknown data is read.

Note 4: To activate the STOP mode, disable the watchdog timer or clear the counter immediately before entering the STOP mode. After clearing the counter, clear the counter again immediately after the STOP mode is inactivated.

- Note 5: To clear WDTCR1<WDTEN>, set the register in accordance with the procedures shown in "7.2.3 Watchdog Timer Disable".
- Note 6: If the watchdog timer is disabled during watchdog timer interrupt processing, the watchdog timer interrupt will never be cleared. Therefore, clear the watchdog timer (set the clear code (4EH) to WDTCR2) before disabling it, or disable the watchdog timer a sufficient time before it overflows.
- Note 7: The watchdog timer consists of an internal divider and a two-stage binary counter. When clear code (4EH) is written, only the binary counter is cleared, not the internal divider.

Depending on the timing at which clear code (4EH) is written on the WDTCR2 register, the overflow time of the binary counter may be at minimum 3/4 of the time set in WDTCR1<WDTT>. Thus, write the clear code using a shorter cycle than 3/4 of the time set in WDTCR1<WDTT>.

Watchdog Timer Control Register 2

WDTCR2 (0035H)	7	6 5	4	3 2	1	0	(Initial value: **** ****)	
\langle	WDTCR2	Write Watchdog timer c	control code	4EH: Clear the wares of the the B1H: Disable the Others: Invalid	atchdog tim watchdog t	ier binary co imer (Disab	ounter (Clear code) le code)	Write only
Note	1: The disab	ole code is valid o	nly when WD)TCR1 <wdten< td=""><td>> = 0.</td><td></td><td></td><td></td></wdten<>	> = 0.			

Note 2: *: Don't care

Note 3: The binary counter of the watchdog timer must not be cleared by the interrupt task.

Note 4: Write the clear code (4EH) using a cycle shorter than 3/4 of the time set in WDTCR1<WDTT>.

Note 5: WDTCR2 is a write-only register and must not be used with any of read-modify-write instructions. If WDTCR2 is read, a unknown data is read.

7.2.2 Watchdog Timer Enable

Setting WDTCR1<WDTEN> to "1" enables the watchdog timer. Since WDTCR1<WDTEN> is initialized to "1" during reset, the watchdog timer is enabled automatically after the reset release.

7.2.3 Watchdog Timer Disable

To disable the watchdog timer, set the register in accordance with the following procedures. Setting the register in other procedures causes a malfunction of the microcontroller.

- 1. Set the interrupt master flag (IMF) to "0".
- 2. Set WDTCR2 to the clear code (4EH).
- 3. Set WDTCR1<WDTEN> to "0".
- 4. Set WDTCR2 to the disable code (B1H).

Note: While the watchdog timer is disabled, the binary counters of the watchdog timer are cleared.

Example :Disabling the watchdog timer

DI		: IMF ← 0
LD	(WDTCR2), 04EH	: Clears the binary counter
LDW	(WDTCR1), 0B101H	: WDTEN \leftarrow 0, WDTCR2 \leftarrow Disable code
EI		: IMF = 1

Table 7-1 Watchdog Timer Detection Time (Example: fc = 20 MHz)

	Watchdog Timer	Detection Time[s]						
WDTT	NORMAL Mode							
	DV1CK = 0	DV1CK = 1						
00	1,678	3.355						
01	419.430 m	838.861 m						
10	104,858 m	209.715 m						
11	26.214 m	52.429 m						
		$\langle \rangle$						

Note: If the watchdog timer is disabled during watchdog timer interrupt processing, the watchdog timer interrupt will never be cleared. Therefore, clear the watchdog timer (set the clear code (4EH) to WDTCR2) before disabling it, or disable the watchdog timer a sufficient time before it overflows.

7.2.4 Watchdog Timer Interrupt (INTWDT)

When WDTCR1<WDTOUT> is cleared to "0", a watchdog timer interrupt request (INTWDT) is generated by the binary-counter overflow.

A watchdog timer interrupt is the non-maskable interrupt which can be accepted regardless of the interrupt master flag (IMF).

When a watchdog timer interrupt is generated while the other interrupt including a watchdog timer interrupt is already accepted, the new watchdog timer interrupt is processed immediately and the previous interrupt is held pending. Therefore, if watchdog timer interrupts are generated continuously without execution of the RETN instruction, too many levels of nesting may cause a malfunction of the microcontroller.

To generate a watchdog timer interrupt, set the stack pointer before setting WDTCR1<WDTOUT>.

Example :Setting watchdog timer interrupt

LD	SP, 010BFH	: Sets the stack pointer
LD	(WDTCR1), 00001000B	: WDTOUT \leftarrow 0

7.2.5 Watchdog Timer Reset

When a binary-counter overflow occurs while WDTCR1<WDTOUT> is set to "1", a watchdog timer reset request is generated. When a watchdog timer reset request is generated, the internal hardware is reset. The reset time is maximum 24/fc [s] (max. 1.2 µs @ fc = 20 MHz).





8. Oscillation Frequency Detector

8.1 Configuration

The oscillation frequency detector generates a reset for I/O if the oscillation of high frequency is lower than a lower detection frequency, or higher than an upper detection frequency. Each frequency is specified by CLKSMN and CLKSMX register. An initial value of lower detection frequency is 8.8MHz which is a harmonics of +10% of 16MHz, and that of upper detection frequency is 20MHz which is a maximum frequency in operating condition. For details, refer to Figure 8-1. To change the detection frequency, CLKSMN and CLKSMX registers are used. CLKSMN and CLKSMX can be written when the oscillation frequency detection is disabled and writing to CLKSMN/CLKSMX is enabled by setting "F9H" to CLKSCR1. Since the oscillation frequency detection is disabled after an external reset input, write "F9H" to CLKSCR1 and write "E4H" to CLKSCR2 register to enable its function.

When the TMP88FW45AFG detects the out of frequency specified CLKSMN and CLKSMX register, all I/Os become high impedance by reset. By the oscillation frequency detection reset, all I/Os except power supply pins, RESET, XIN and XOUT become high impedance. If oscillation frequency detection reset is generated by detecting the stopping of high frequency, the internal circuities such as registers hold the condition at the timing of oscillation stop. To initialize these internal circuitries, an at external re-starting of oscillation is needed.

- Note 1: Though the harmonics of 16MHz is 32MHz, upper detection frequency is set to 20MHz to avoid an erratic operation caused by exceeding 20MHz.
- Note 2: The oscillation frequency detection reset is available only in NORMAL and IDLE modes. In STOP modes, the oscillation frequency detection reset is disabled automatically.



If the calculated detection frequency is lower than 8MHz or higher than 20MHz, the detection frequency should be set within operating condition.





8.2 Control

The oscillation frequency detection is controlled by oscillation frequency detection control register 2 (CLKSCR2). The detection frequency is specified by lower/higher detection frequency setting register (CLKSMN, CLKSMX). Writing to CLKSCR2/CLKSMN/CLKSMX is controlled by oscillation frequency control register 1 (CLKSCR1).

Oscillation f	equency	/ dete	ction c	ontrol regi	ister 1					
CLKSCR1	7	6	5	4	3	2	1	0		
(1F7FH)									Initial value(0000 0110)	
L			:		:	:	:	\sim	$(\langle \rangle)$	
		CLł	KSCR1	Writing contro CLKSCR2, C and CLKSM>	ol of CLKSMN K registers	06H: Disa F9H: Ena Others: R	abling of writ bling of writi eserved (No	ing to CLK ing to CLK ote 1)	SCR2/CLKSMN/CLKSMX SCR2/CLKSMN/CLKSMX	R/W
Note 1:	Only "06l	H" and	"F9H" is	valid to CLK	(SCR1. If o	ther value	than "06H	" and "F9	OH" is written to CLKSCR1, "06H" is	;
Note 2:	CLKSCR	1 is no	t initialize	ed by an inte	ernal factor	reset inclu	iding oscilla	ation freq	uency detection reset. To initialize	
	this regis	ters, se	et the RE	SET pin (ex	ternal facto	or reset) to	the low lev	vel.	* 20	
Oscillation fi	requency	/ dete	ction c	ontrol regi	ister 2	20			C	
CLKSCR2	7	6	5	4	3	2	$>_1$	0	(\mathcal{S})	
(1F7CH)					(\frown	>	((Initial value(0000 0000)	
					G	$\overline{}$			∇)	
		CLł	KSCR2	Control the or quency detect behavior	scillation fre- ction circuit	00H: Disa E4H: Ena Others: R	able able seserved (No	ote 1)		R/W
Note 1:	Only "00	H" and	"E4H" is	valid to CLK	SCR2. Wr	iting other	value than	n "00H" ar	nd "E4H" to CLKSCR2 with	
Note 2:	Writing to	CLKS	CR2 is p	protected by	setting "06	H" to CLK	SCR1 but i	reading fr	rom CLKSCR2 is always enabled	
Note 3:	CLKSCR	2 is no	t initialize	ed by an inte	ernal factor	reset inclu	ding oscilla	ation freq	uency detection reset. To initialize	
	this regis	ters, se	et the RE	SET pin (ex	ternal facto	r reset) to	the low lev	vel.		
L ouver detec	tion from	\leq				\mathbb{V})			
Lower deled	lion ireq	uency	yseun	g register						
CLKSMN	7	6	5	4	3	2	1	0		
(1F7DH)		>							Read/Write	
		\geq)	A					Initial value(0010 0000)	
Higher deter	ction free	quenc	y settir	ng register	\sim					
CLKSMX	Z	6	(C5 ~	$\left(\begin{pmatrix} 4 \end{pmatrix} \right)$	3	2	1	0		
(1F7EH)		-							Read/Write	
	\geq			$\langle \rangle$. <u>I</u>				Initial value(0100 0000)	
Note 1	CLKSMI	N and C g is dis	CLKSMX abled wi	can not be with CLKSCR1	written whe I="06H". Ar	n the oscil n attempt t	lation frequ o write CLI	uency det KSMN ar	tection circuit is enabled (CLKSCR2 nd CLKSMX can not complete a wri	:="E4H") te oper-
Note 2	: Writing t	o CLKS	SMN/CLI	KSMX is pro	tected by s	etting "06ł	H" to CLKS	SCR1 but	reading from CLKSMN/CLKSMX is	always
Note 3	: Specify a of CLKS	an appi MN <c< td=""><td>ropriate v LKSMX.</td><td>value to CLK For how to c</td><td>SMN and C calculate th</td><td>CLKSMX d e value, re</td><td>epending o efer to "8.3.</td><td>on the clo .2 Setting</td><td>ck frequency to be used under the c g the Lower and Higher Frequency f</td><td>ondition or De-</td></c<>	ropriate v LKSMX.	value to CLK For how to c	SMN and C calculate th	CLKSMX d e value, re	epending o efer to "8.3.	on the clo .2 Setting	ck frequency to be used under the c g the Lower and Higher Frequency f	ondition or De-
Note 4	tection". Note 4: CLKSMN and CLKSMX are not initialized by an internal factor reset including oscillation frequency detection reset. To initialize these registers, set the RESET pin (external factor reset) to the low level.									

8.3 Function

8.3.1 Enabling and Disabling the Oscillation Frequency Detection

Writing "E4H" to CLKSCR2 with CLKSCR1="F9H" enables the oscillation frequency detection, and writing "00H" to CLKSCR2 with CLKSCR1="F9H" disables the oscillation frequency detection.

Setting "F9H" to CLKSCR1 enables writing to CLKSCR2 and setting "06H" to CLKSCR1 disables writing to CLKSCR2. Reading from CLKSCR2 is always enabled without setting of CLKSCR1. CLKSCR1 is initialized to "06H" by external reset and CLKSCR2 is initialized to "00H" by external reset. However, CLKSCR1 and CLKSCR2 are not initialized by internal reset which are system clock, address trap, watchdog timer reset and oscillation frequency detection reset.

Note: After writing data to CLKSCR2, set "06H" to CLKSCR1 to protect CLKSCR2 register.

When STOP mode is executed with CLKSCR2=E4H, the oscillation frequency detection is automatically disabled. After releasing STOP and warming up period, the oscillation frequency detection is enabled. In serial PROM mode for Flash, the oscillation frequency detection is disabled. The oscillation frequency detection is available only in NORMAL and IDLE mode. Table 8-1 shows the availability of oscillation frequency detector.

Operating Mode	Oscillation Frequency Detection	All I/Os condition after Oscillation Frequency Detection RESET					
NORMAL	Available	High impedance					
IDLE	Available	High impedance					
STOP (Including warming up period)	Oscillation	Frequency Detection is disabled automatically.					
RESET by oscillation frequency detection reset	Available	High impedance					
RESET by internal reset (Note 1)	Available	High impedance					
RESET by external reset	Disable						
Serial PROM	Disable	<u></u>					

Note 1: Internal reset ; Watchdog timer reset, Address trap reset, System clock reset and Oscillation frequency detection reset.



Figure 8-3 Availabirity of Oscillation Frequency Detection

8.3.2 Setting the Lower and Higher Frequency for Detection

The detection frequency is controlled by CLKSMN and CLKSMX registers. These registers can not be written while the oscillation frequency detection circuit is enabled or writing is disabled by setting "06H" to CLKSCR1. Therefore, to change the detection frequency, disable the oscillation frequency detection by setting "00H" to CLKSCR2 with CLKSCR1="F9H". The detection frequency is calculated by the formula shown below.

- Note 1: After writing data to CLKSMN and CLKSMX, set "06H" to CLKSCR1 to protect CLKSMN and CLKSMX.
- Note 2: Specify an appropriate value to CLKSMN and CLKSMX depending on the clock frequency to be used under the condition of CLKSMN<CLKSMX



Note 1: A denominator of formula will be determined after evaluation.

In the TMP88FW45AFG, the initial value of CLKSMN is 20H which is set to 8 8MHz and the initial value of CLKSMX is 40H which is set to 20MHz. The detection frequency should be set within the operation condition which is from 8MHz to 20MHz.

CLKSMN and CLKSMX are not initialized with an internal factor reset including the oscillation frequency detection reset, and the values are held. To initialize these registers, set the RESET pin (external factor reset) to the low level.

Oscillation Frequency Detection Reset 8.3.3

If the TMP88FW45AFG detects lower frequency specified by CLKSMN or higher frequency specified by CLKSMX, the oscillation frequency detector outputs a reset signal for all I/Os.

a. When the high frequency oscillation becomes abnormal

When an abnormal (lower or higher) frequency oscillation continues for some period (T_{OFD}), the oscillation frequency detection reset is generated. By oscillation frequency detection reset initilizes all I/Os except power supply pins, RESET, XIN and XOUT become high impedance.

b. When the high frequency oscillation stops

When the high frequency oscillation stops for some period (T_{OFD}), the oscillation frequency detection reset is generated. By oscillation frequency detection reset initilizes all I/Os except power supply pins, RESET, XIN and XOUT become high impedance. However, since the internal circuitries such as CPU are initilized by a reset signal latched by high frequency, the internal circuitries hold the state at the oscillation frequency detection.

When the oscillation resumes its normal frequency and continues for some period (T_{OFD}), the oscillation frequency detection reset is released.



- 9. 16-Bit TimerCounter 1 (TC1)
- 9.1 Configuration



Figure 9-1 TimerCounter 1 (TC1)

9.2 TimerCounter Control

The TimerCounter 1 is controlled by the TimerCounter 1 control register (TC1CR) and two 16-bit timer registers (TC1DRA and TC1DRB).

Timer Regist	ter												4	\langle				
	15	14	13	12	11	10		9	8		7	6	5	4	3	2	1	0
TC1DRA	тс	C1DRAH	H (0011H)								TC1D	RAL (001	0H)				
(0011H, 0010H)		(Init	tial valu	ie: 1111	1111 11	11 11	11)					~	(()	7/Ré	ad/Write			
TC1DRB			тс	C1DRBH	I (0013H)						\bigcirc	V	IC1D	RBL (001	2H)		
(0013H, 0012H)		(Init	tial valu	ie: 1111	1111 11	11 11	11)				Read	/Write (W	/rite e	enable	d only in	the PPG	output mo	de)
TimerCou	unter 1 C	Control F	Regis	ter							20		,		2		>	
	7	6	Ę	5	4		3	:	2	((1770	0			8			
TOLOD		ACAP1								4	\bigcirc)		>	\bigcirc			
(000EH)	TEE1	MCAP1		TC10			тс	101	A	$\overline{\ }$		4	Rea	ad/Wri	te	O		
		METT1		1018	5		10	IUK	24			n	(Init	ial val	ue: 0000	0000)		
		MPPG1						4	\bigcirc	\rightarrow				ſ))			
TFF1	Timer F/F1	control		0: Clear			-(\geq	\geq			1: Set	77	$\frac{\sim}{\sim}$				R/W
ACAP1	Auto captu	ire control		0 : Auto-	-capture	disab	le		\rightarrow			1 : Auto	-capt	ure er	nable			R/W
MCAP1	Pulse width measurement mode control			0 :Doubl	le edge c	aptur	e		7	1 : Single edge capture								
METT1	External trigger timer mode control			0 : Trigg	jer start	\bigcirc))					1 : Trigg	ger st	art an	d stop			R/W
MPPG1	PPG outpu	ut control	(0 : Conti	inuous pi	ulse g	jenera	tion		\wedge	1 : One-shot						1	
					\bigcirc))			$\langle \cdot$	$\langle \rangle$	Timer	Extrig- ger	E١	/ent	Win- dow	Pulse	PPG	
			00: Stop	and cou	inter c	clear	4	\sim	$\overline{7}$	0	0		0	0	0	0		
		6		01: Com	nmand sta	art		F	77.		0	-		-	-	-	0	1
TC1S	S TC1 start control			10: Risir (Ex-trigg Rising e	ng edge s ger/Pulse dge cour	start /PPG nt (Eve	i) ent)		9)	-	о		0	ο	ο	0	R/W
				Positive	logic cou	unt (W	Vindov	v)	7									
	\sim	\square		11: Falli	ng edge	start	$\langle \rangle$											
	Z	\sim	7	(Ex-trigg Falling e	ger/Pulse	/PPG	i) (ent)				-	0		0	0	0	0	
	\overline{C}	\sim		Negative	e logic co	ount (V	Windo	w)										
		NORMAL, IDLE mode								1								
	\sim	2	\bigcirc			$\overline{}$	DV1	1CK =	0		DV1CK = 1							
	TC1 cours	o clock sole		00	$ \rightarrow $		f	c/2 ¹¹										
TC1CK	[Hz]	e ciuck seit		01 fc/27						fc/2 ⁸						R/W		
	\searrow	\supset		10 fc/2 ³ fc/2 ⁴														
				11 External clock (TC1 nin input)									4					
				 00: Time	er/externa	al trio	qer tin	ner/ev	ent cou	Inter	mode	, - · P.	- - - -	,				
толи	TC1 opera	ting mode :	se-	01: Wind	dow mod	e												
IC1M	lect	5		10: Puls	e width n	neasu	ureme	nt moo	de									K/W
				11: PPG	6 (Progra	mmat	ble pul	lse ge	nerate)) outp	out mode	•						

Note 1: fc: High-frequency clock [Hz]

Note 2: The timer register consists of two shift registers. A value set in the timer register becomes valid at the rising edge of the first source clock pulse that occurs after the upper byte (TC1DRAH and TC1DRBH) is written. Therefore, write the lower byte and the upper byte in this order (it is recommended to write the register with a 16-bit access instruction). Writing only the lower byte (TC1DRAL and TC1DRBL) does not enable the setting of the timer register.

- Note 3: To set the mode, source clock, PPG output control and timer F/F control, write to TC1CR during TC1CR<TC1S>=00. Set the timer F/F1 control until the first timer start after setting the PPG mode.
- Note 4: Auto-capture can be used only in the timer, event counter, and window modes.
- Note 5: To set the timer registers, the following relationship must be satisfied.

TC1DRA > TC1DRB > 1 (PPG output mode), TC1DRA > 1 (other modes)

- Note 6: Set TC1CR<TFF1> to "0" in the mode except PPG output mode.
- Note 7: Set TC1DRB after setting TC1CR<TC1M> to the PPG output mode.
- Note 8: When the STOP mode is entered, the start control (TC1CR<TC1S>) is cleared to "00" automatically, and the timer stops. After the STOP mode is exited, set the TC1CR<TC1S> to use the timer counter again.
- Note 9: Use the auto-capture function in the operative condition of TC1. A captured value may not be fixed if it's read after the execution of the timer stop or auto-capture disable. Read the capture value in a capture enabled condition.
- Note 10: Since the up-counter value is captured into TC1DRB by the source clock of up-counter after setting TC1CR<ACAP1> to "1". Therefore, to read the captured value, wait at least one cycle of the internal source clock before reading TC1DRB for the first time.

9.3 Function

TimerCounter 1 has six types of operating modes: timer, external trigger timer, event counter, window, pulse width measurement, programmable pulse generator output modes.

9.3.1 Timer mode

In the timer mode, the up-counter counts up using the internal clock. When a match between the up-counter and the timer register 1A (TC1DRA) value is detected, an INTTC1 interrupt is generated and the up-counter is cleared. After being cleared, the up-counter restarts counting. Setting TC1CR<ACAP1> to "1" captures the up-counter value into the timer register 1B (TC1DRB) with the auto-capture function. Use the auto-capture function in the operative condition of TC1. A captured value may not be fixed if it's read after the execution of the timer stop or auto-capture disable. Read the capture value in a capture enabled condition. Since the up-counter value is captured into TC1DRB by the source clock of up-counter after setting TC1CR<ACAP1> to "1". Therefore, to read the captured value, wait at least one cycle of the internal source clock before reading TC1DRB for the first time.

Table 9-		k for TimerCC		npie: nc = 20 WH.					
TC1CK	NORMAL, IDLE Mode								
	DV1CK = 0 DV1CK = 1								
	Resolution [µs]	Maximum Time Setting [s]	Resolution [µs]	Maximum Time Setting [s]					
00	102.4	6.7108	204.8	13.4216					
01	6.4	0.4194	12.8	0.8388					
10	0.5	26.214 m	0.8	52.428 m					
				//					

Example 1 :Setting the timer mode with source clock $fc/2^{11}$ [Hz] and generating an interrupt 1 second later (fc = 20 MHz, CGCR<DV1CK> = "0")

LDW	(TC1DRA), 2625H	; Sets the timer register (1 s ÷ 2 ¹¹ /fc = 2625H)
DI		:1MF= "0"
SET	(EIRD). 2	; Enables INTTC1
EI		; IMF= "1"
LD	(TC1CR), 0000000B	; Selects the source clock and mode
U)	(TC1CR), 00010000B	; Starts TC1
	(TC1CR), 01010000B	; ACAP1 ← 1
: \		; Wait at least one cycle of the internal source clock
LD	WA, (TC1DRB)	; Reads the capture value
	LDW DI SET EI LD LD LD LD	LDW (TC1DRA), 2625H DI SET (EIRD). 2 EI LD (TC1CR), 0000000B LD (TC1CR), 00010000B LD (TC1CR), 00010000B LD (TC1CR), 01010000B : LD WA (TC1DRB)



9.3.2 External Trigger Timer Mode

In the external trigger timer mode, the up-counter starts counting by the input pulse triggering of the TC1 pin, and counts up at the edge of the internal clock. For the trigger edge used to start counting, either the rising or falling edge is defined in TC1CR<TC1S>.

• When TC1CR<METT1> is set to "1" (trigger start and stop)

When a match between the up-counter and the TC1DRA value is detected after the timer starts, the up-counter is cleared and halted and an INTTC1 interrupt request is generated.

If the edge opposite to trigger edge is detected before detecting a match between the up-counter and the TC1DRA, the up-counter is cleared and halted without generating an interrupt request. Therefore, this mode can be used to detect exceeding the specified pulse by interrupt.

After being halted, the up-counter restarts counting when the trigger edge is detected.

• When TC1CR<METT1> is set to "0" (trigger start)

When a match between the up-counter and the TC1DRA value is detected after the timer starts, the up-counter is cleared and halted and an INTTC1 interrupt request is generated.

The edge opposite to the trigger edge has no effect in count up. The trigger edge for the next counting is ignored if detecting it before detecting a match between the up-counter and the TC1DRA.

Since the TC1 pin input has the noise rejection, pulses of 4/fc [s] or less are rejected as noise. A pulse width of 12/fc [s] or more is required to ensure edge detection.

Example 1 :Generating an interrupt 1 ms after the rising edge of the input pulse to the TC1 pin (fc = 20 MHz, CGCR < DV1CK > = "1")









9.3.3 Event Counter Mode

In the event counter mode, the up-counter counts up at the edge of the input pulse to the TC1 pin. Either the rising or falling edge of the input pulse is selected as the count up edge in TC1CR<TC1S>.

When a match between the up-counter and the TC1DRA value is detected, an INTTC1 interrupt is generated and the up-counter is cleared. After being cleared, the up-counter restarts counting at each edge of the input pulse to the TC1 pin. Since a match between the up-counter and the value set to TC1DRA is detected at the edge opposite to the selected edge, an INTTC1 interrupt request is generated after a match of the value at the edge opposite to the selected edge.

Two or more machine cycles are required for the low-or high-level pulse input to the TC1 pin.

Setting TC1CR<ACAP1> to "1" captures the up-counter value into TC1DRB with the auto capture function. Use the auto-capture function in the operative condition of TC1. A captured value may not be fixed if it's read after the execution of the timer stop or auto-capture disable. Read the capture value in a capture enabled condition. Since the up-counter value is captured into TC1DRB by the source clock of up-counter after setting TC1CR<ACAP1> to "1". Therefore, to read the captured value, wait at least one cycle of the internal source clock before reading TC1DRB for the first time.



9.3.4 Window Mode

In the window mode, the up-counter counts up at the rising edge of the pulse that is logical ANDed product of the input pulse to the TC1 pin (window pulse) and the internal source clock. Either the positive logic (count up during high-going pulse) or negative logic (count up during low-going pulse) can be selected.

When a match between the up-counter and the TC1DRA value is detected, an INTTC1 interrupt is generated and the up-counter is cleared.

Define the window pulse to the frequency which is sufficiently lower than the internal source clock programmed with TC1CR<TC1CK>.



9.3.5 Pulse Width Measurement Mode

In the pulse width measurement mode, the up-counter starts counting by the input pulse triggering of the TC1 pin, and counts up at the edge of the internal clock. Either the rising or falling edge of the internal clock is selected as the trigger edge in TC1CR<TC1S>. Either the single- or double-edge capture is selected as the trigger edge in TC1CR<MCAP1>.

• When TC1CR<MCAP1> is set to "1" (single-edge capture)

Either high- or low-level input pulse width can be measured. To measure the high-level input pulse width, set the rising edge to TC1CR<TC1S>. To measure the low-level input pulse width, set the falling edge to TC1CR<TC1S>.

When detecting the edge opposite to the trigger edge used to start counting after the timer starts, the up-counter captures the up-counter value into TC1DRB and generates an INTTC1 interrupt request. The up-counter is cleared at this time, and then restarts counting when detecting the trigger edge used to start counting.

• When TC1CR<MCAP1> is set to "0" (double-edge capture)

The cycle starting with either the high- or low-going input pulse can be measured. To measure the cycle starting with the high-going pulse, set the rising edge to TC1CR<TC1S>. To measure the cycle starting with the low-going pulse, set the falling edge to TC1CR<TC1S>.

When detecting the edge opposite to the trigger edge used to start counting after the timer starts, the up-counter captures the up-counter value into TC1DRB and generates an INTTC1 interrupt request. The up-counter continues counting up, and captures the up-counter value into TC1DRB and generates an INTTC1 interrupt request when detecting the trigger edge used to start counting. The up-counter is cleared at this time, and then continues counting.

- Note 1: The captured value must be read from TC1DRB until the next trigger edge is detected. If not read, the captured value becomes a don't care. It is recommended to use a 16-bit access instruction to read the captured value from TC1DRB.
- Note 2: For the single-edge capture, the counter after capturing the value stops at "1" until detecting the next edge. Therefore, the second captured value is "1" larger than the captured value immediately after counting starts.
- Note 3: The first captured value after the timer starts may be read incorrectively, therefore, ignore the first captured value.

Example :Duty measurement (resolution fc/2⁷ [Hz], CGCR<DV1CK> = "0")

	CLR	(INTTC1SW). 0	; INTTC1 service switch initial setting Address set to convert INTTC1SW at each INTTC1
	LD	(TC1CR), 00000110B	; Sets the TC1 mode and source clock
	DI		; IMF= "0"
	SET	(EIRD). 2	; Enables INTTC1
	EI		; IMF= "1"
	LD	(TC1CR), 00100110B	; Starts TC1 with an external trigger at MCAP1 = 0
	:		\sim (7/ \diamond
PINTTC1:	CPL	(INTTC1SW). 0	; INTTC1 interrupt, inverts and tests INTTC1 service switch
	JRS	F, SINTTC1	
	LD	A, (TC1DRBL)	; Reads TC1DRB (High-level pulse width)
	LD	W,(TC1DRBH)	
	LD	(HPULSE), WA	; Stores high-level pulse width in RAM
	RETI		
SINTTC1:	LD	A, (TC1DRBL)	; Reads TC1DRB (Cycle)
	LD	W,(TC1DRBH)	
	LD	(WIDTH), WA	; Stores cycle in RAM
	:	4	$d(\rightarrow ())$
	RETI	6	; Duty calculation
	:	20	\searrow (\checkmark)
VINTTC1:	DW	PINTTC1	; INTTC1 Interrupt vector
		(())	WIDTH
		HPULSE	
то1,	ain		
ICI	וווכ		
INTT	C1 interrupt re	equest	
	C15W		
		$\rightarrow \longrightarrow \frown$	
	\sim		
\sim	>		
2~	\searrow	\sim	
	\sim	\triangleleft	
))		
		(())	
	4		
\sim		\sim	



9.3.6 Programmable Pulse Generate (PPG) Output Mode

In the programmable pulse generation (PPG) mode, an arbitrary duty pulse is generated by counting performed in the internal clock. To start the timer, TC1CR<TC1S> specifies either the edge of the input pulse to the TC1 pin or the command start. TC1CR<MPPG1> specifies whether a duty pulse is produced continuously or not (one-shot pulse).

• When TC1CR<MPPG1> is set to "0" (Continuous pulse generation)

When a match between the up-counter and the TC1DRB value is detected after the timer starts, the level of the PPG pin is inverted and an INTTC1 interrupt request is generated. The up-counter continues counting. When a match between the up-counter and the TC1DRA value is detected, the level of the PPG pin is inverted and an INTTC1 interrupt request is generated. The up-counter is cleared at this time, and then continues counting and pulse generation.

When TC1CR<TC1S> is cleared to "00" during PPG output, the PPG pin retains the level immediately before the counter stops.

• When TC1CR<MPPG1> is set to "1" (One-shot pulse generation)

When a match between the up-counter and the TC1DRB value is detected after the timer starts, the level of the \overline{PPG} pin is inverted and an INTTC1 interrupt request is generated. The up-counter continues counting. When a match between the up-counter and the TC1DRA value is detected, the level of the \overline{PPG} pin is inverted and an INTTC1 interrupt request is generated. TC1CR<TC1S> is cleared to "00" automatically at this time, and the timer stops. The pulse generated by PPG retains the same level as that when the timer stops.

Since the output level of the \overline{PPG} pin can be set with TC1CR<TFF1> when the timer starts, a positive or negative pulse can be generated. Since the inverted level of the timer F/F1 output level is output to the \overline{PPG} pin, specify TC1CR<TFF1> to "0" to set the high level to the \overline{PPG} pin, and "1" to set the low level to the \overline{PPG} pin. Upon reset, the timer F/F1 is initialized to "0".

- Note 1: To change TC1DRA or TC1DRB during a run of the timer, set a value sufficiently larger than the count value of the counter. Setting a value smaller than the count value of the counter during a run of the timer may generate a pulse different from that specified.
- Note 2: Do not change TC1CR<TFF1> during a run of the timer. TC1CR<TFF1> can be set correctly only at initialization (after reset). When the timer stops during PPG, TC1CR<TFF1> can not be set correctly from this point onward if the PPG output has the level which is inverted of the level when the timer starts. (Setting TC1CR<TFF1> specifies the timer F/F1 to the level inverted of the programmed value.) Therefore, the timer F/F1 needs to be initialized to ensure an arbitrary level of the PPG output. To initialize the timer F/F1, change TC1CR<TC1M> to the timer mode (it is not required to start the timer mode), and then set the PPG mode. Set TC1CR<TFF1> at this time.
- Note 3: In the PPG mode, the following relationship must be satisfied.
 - TC1DRA > TC1DRB

Note 4: Set TC1DRB after changing the mode of TC1M to the PPG mode.

Example :Generating a pulse which is high-going for 800 μ s and low-going for 200 μ s (fc = 20 MHz, CGCR<DV1CK> = "0")

	Setting port	
LD	(TC1CR), 10001011B	; Sets the PPG mode, selects the source clock
LDW	(TC1DRA), 04E2H	; Sets the cycle (1 ms ÷ 2 ⁴ /fc μ s = 04E2H)
LDW	(TC1DRB), 00FAH	; Sets the low-level pulse width (200 μs ÷ 24/fc = 00FAH)
LD	(TC1CR), 10010111B	; Starts the timer




TOSHIBA

10. 16-Bit Timer (CTC)

10.1 Configuration





10.2 Control

Compare timer/counter 1 is controlled using Compare timer/counter 1 Control Registers (CTC1CR1 and CTC1CR2), as well as three 16-bit Timer Registers (CTC1DRA, CTC1DRB, and CTC1DRC).

Compare	Tim	er Reg	giste	rs (C	TC1E	ORH:	0001	17h, C	TC1	DRL:	000	16h)				
	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1 0	Write only
CTC1DRA				CTC1	DRAH							CTC1	DRAL			(Initial value: ******** *******)
	15	14	13	12	11	10	9	8	7	6	5	4	3	2	71/0	Write only
CTC1DRB				CTC1	DRBH							CTC1	DRBL	\sim	\bigcirc	(Initial value: ******** *******)
[15	14	13	12	11	10	9	8	7	6	5	4	3	2	1 0	Write only
CTC1DRC				CTC1	DRCH							CTC1	DRCL	\supset)	(Initial value: ******** *******)
N Compare	Note:(CTC1DI write ins er/Cou	RA, C structi	TC1DF ons su	RB, an ch as ontrol	nd CTC SET, C I Reg i	1DRC CLR, e	are wi etc. 6 (CT(rite-or	nly regis	sters a	nd mus	at not b	e used	l with any of 0014h)	the read-modify-
CTC1CR1		7		6		5		4		23	$\langle \rangle$	2		1	$\left(\begin{array}{c} \\ \end{array} \right)$	R/W
lower addres	ss (CTC1RE	s	PPGFF		CTC1M	(CTC1CY	·	TC1SE	\mathbf{T}	CTC1E	СТ	C1SM	CTC1S	(Initial value: 00000000)
									1	\nearrow	\geq		(07		_
CTC1CP2		7		6		5		4	\square	3	~	2		1) o	
upper addres	ss	*		EX-		СТ	C1RE	G		>	ó	тсіск		$\overline{)}$	CTC1FF0	(Initial value: *0000000)
Ν		· *· Do	n't ca	are			())	~		$\overline{}$	\bigtriangledown	/		
N	lote 2	2: The	CTC1	ICR1<	CTC1	RES> <i>j</i> i	s 0 w	hen rea	ad.		\sim		\sim			
Ν	lote 3	3: Use	the L	DW ins	tructio	on for w	vrite to	o the C	TC1D	R H/L	Regis	ters. Se	et a va	lue eq	ual to or gre	ater than 2.
Ν	lote 4	: Write	e to C	TC1DF	RH/L	A, B, a	nd C	Registe	ers as	many	as set	with th	e CTC	1CR2	Register C	TC1REG bit.
Ν	lote 5	5: Data	are	written	to CT	C1DR/I	H/L R	egister	s in oi	rder of	CTCI	DRA, C	CTC1D	RB, a	nd CTC1DF	RC.
											5)					

Setting-up the CTC1CR1 Register

			Timer	Event	PPG	
CTC1S	Control start	0: Stop and clear counter 1: Command start	о	<u> </u>	о	
			0	0	o	
CTC1SM	Select start	0: Software start	o	0	0	
CTCTSW		1: External trigger start	o	X)) o	
CTC1E	Soloot ovtornal trigger edge	0: Enable one edge	0	228	0	
CICIE	Select external trigger edge	1: Enable both edges	o	()	о	
CTC18E	Select external trigger start	0: Rising edge	0		о	5.4.4
edge		1: Falling edge	(0)	> o	о	R/W
CTC1CV		0: Successive	•	o	0	
CICICI		1: One shot	P	×	0	
CTC1M	0: Timer/Event counter modes					
01011	1: PPG (programmable pulse generator) output mode					
PPGEE0	Select PPG output 0: Forward output immediately after start					
	1: Reverse output immediately after start					
CTC1RES	Reset all	0: Normal operation		7	$\supset \smile$	
0.0 millo		1: CTC1 reset	(($\langle \rangle$		

Setting-up the CTC1CR2 Register

CTC1FF0	Control timer output F/F0	0: Clear 1: Set				/		
			NORMAL and IDLE Modes					
			DV1CK = 0	DV1CK = 1	Timer	Event	PPG	
	((000	fc/211	fc/212	0	-	×	
		001	fc/27	fc/2 ⁸	o	-	×	
	Select timer/counter clock	010	fc/25	fc/2 ⁶	о	-	×	
CTC1CK	source	011	fc/23	fc/2⁴	о	-	×	
		100 🗸	fc/2 ²	fc/2 ³	o	-	O Note3	DAA
		101	fc/2	fc/2 ²	о	-	о	R/W
		110	$ \rightarrow $	-	×	×	×	
		111	External of (CTC1 p	clock input Din input)	-	0	×	
		00: CTC	1DRA		1REG			
CTC1REG	Set registers used by timer/	01: CTC	1DRA + CTC1DRE	3	2REG			
	Counter	10: CTC1DRA + CTC1DRB + CTC1DRC 3REG 11: Reserved						
EXTRGDIS	External trigger input Note4	0: Enabl 1: Disab	e external trigger i le external trigger i	nput				

Note 1: fc: Clock [Hz]

Note 2: Make sure the timer/counter is idle (CTC1CR1<CTC1SM, CTC1S> = 00) before setting operation mode, edge, start, source clock, external trigger timer mode control, and PPG output control.

Note 3: When DV1CK=1, CTC1CR2<CTC1CK>=100 cannot be used.

Note 4: When CTC1 input is not used in the CTC1 timer, external trigger input must be disabled (CTC1CR2<EXTRGDIS> = 1) regardless of the selected mode.

Note 5: The CTC1DRB and CTC1DRC Registers cannot be accessed for write unless they are set for PPG output mode and specified with CTC1CR2<CTC1REG>.

Note 6: CTC1CR1<CTC1E> is effective only when using an external clock as trigger (CTC1CR1<CTC1SM>).

Note 7: Data must be written to as many data registers as set with CTC1CR2<CTC1REG>.

Note 8: To write data to CTC1DRA/B/C, use the LDW instruction, or use the LD instruction writing in order of L, H.

Note 9: Data register values must be written to the respective registers before starting. To modify the values after starting, write the new data within an interval from an INTCTC1 interrupt to the next INTCTC1.

- Note 10: Specifying CTC1CR1<CTC1RES> = 1 causes all conditions to be reset. Even when the CTC circuit is operating, they are reset, and the PPG output becomes "0". However, only the INTCTC1 signal is not reset if the signal is being generated.
- Note 11: For event counter mode (when CTC pin input is selected in timer mode), the active edge of the external trigger to count can be selected with CTC1CR1<CTC1SE>.

Note 12: Disabling external trigger input with CTC1CR2<EXTRGDIS> creates the 0 input state.

Note 13: To stop the counter by software at trigger start, set CTC1CR2<CTC1SM, CTC1S> = 00.

Note 14: The number of registers set and the values set in the timer registers must meet the conditions shown below.

Number of Registers		Timer Register Value Conditions
	1 Register	CTC1DRA≥2
CTC1REG	2 Register	CTC1DRB > CTC1DRA + 1, and CTC1DRA ≥ 2
	3 Register	CTC1DRC > CTC1DRB + 1, CTC1DRB > CTC1DRA + 1, and CTC1DRA ≥ 2

			\sim
	$\overline{0}$		
			20)
		$\langle \rangle$	> _
		(75)	
\bigcirc))	
C		/	
	776		
	\bigcirc		
	>		
*			

10.3 Function

Compare timer/counter 1 has three modes: timer, event counter, and programmable pulse generator output modes.

10.3.1 Timer mode with software start

In this mode, the timer/counter (16-bit counter) counts up synchronously with the internal clock. When the counter value and the set value of Compare Timer Register 1A (CTC1DRA) match, an INTCTC1 interrupt is generated and the counter is cleared. After the counter is cleared, it restarts and continues counting up.

		NORMAL and IDLE Modes						
	CTC1CK	DV10	CK = 0	DV1C	Ж = 1			
		Resolution [µs]	Maximum Setting Time [s]	Resolution [µs]	Maximum Setting Time [s]			
	000	102.4	6.71	204.8	13.42			
	001	6.4	0.419	12.8	0.839			
	010	1.6	0.105	3.2	0.210			
	011	0.4	26.21 m	0.8	52.43 m			
	100	0.2	13.11 m	0.4	26.21 m			
	101	0.1	6.55 m	0.2	13.11 m			
	110	-	2(- ((// 5))	-			
			$\langle \langle \rangle \rangle$					
				$\langle \langle \rangle \rangle$				
	Internal clock							
	Counter $0 \sqrt{1} \sqrt{2} \sqrt{3} \sqrt{1} \sqrt{1} \sqrt{1} \sqrt{2} \sqrt{3} \sqrt{4} \sqrt{5} \sqrt{6} \sqrt{7} \sqrt{8} \sqrt{9}$							
	Timer Register A	X n	•					
	INTCTC1 interrup	t		~				
			Successive					
	Figure 10-2 Timer Mode Timing Chart							
	Note: If the CTC input port (P47) is set for input mode, the timer/counter is reset by an input edge on port. When using the timer/counter as an ordinary timer, set CTC1CR2 <extrgdis> to 1 or set P47 for output</extrgdis>							
	((mòdè.							
$\langle \rangle$)					
	\searrow	\searrow						

Table 10-1 Internal Clock Source for Compare Timer/Counter 1 (Example: fc = 20 MHz)

10.3.2 Timer mode with external trigger start

In this timer mode, the timer/counter starts counting as triggered by input on CTC pin (rising or falling edge selected with CTC1CR1<CTC1SE>). The source clock is an internal clock. For successive cycles, when the counter value and the set value of the CTC1DRA Register match, an INTCTC1 interrupt is generated and the counter is cleared and then restarted. The counter is stopped by a trigger input on CTC pin and restarted by the next trigger input. For a one-shot cycle, when the counter value and the set value of the CTC1DRA Register match, an INTCTC1 interrupt is generated and the counter is cleared and stopped. The counter restarts counting up by input on CTC pin. When CTC1CR1<CTC1E> = 1, the counter is cleared and stops counting at an edge on CTC pin input opposite the active edge that triggers the counter to start counting. In this mode, an interrupt can be generated by entering a pulse which has a certain width. When CTC1CR1<CTC1E> = 0, opposite edges on CTC input are ignored.



TOSHIBA



(II) When rising start edge is selected, with counting enabled on both edges (CTC1SE = 0, CTC1E = 1)

Figure 10-4 External Trigger Mode Timing Chart

10.3.3 Event counter mode

In this mode, the timer/counter counts up at the active edge on CTC pin input (rising or falling edge selected with the CTC1CR1<CTC1SE> which is provided for selecting external trigger edge). When the counter value and the set value of the CTC1DRA Register match, an INTCTC1 interrupt is generated and the counter is cleared. After the counter is cleared, it restarts and continues counting up at each edge on CTC pin input. The maximum applied frequency is shown in the table below. Because coincidence detection is made at an edge opposite the selected edge, the external clock signal on CTC pin must always be entered.



Figure 10-5 Event Counter Mode Timing Chart

Table 10-2 External Clock Source for Compare Timer/Counter 1

Up to fc/2 ²	
2²/fc and over	$\overline{)}$
•	Up to fc/2 ² 2 ² /fc and over

10.3.4 Programmable Pulse Generate (PPG) output mode

The timer/counter starts counting as a command or edge on CTC pin input (rising/falling edge and one/both edges respectively selected with the CTC1CR1<CTC1SE> and CTC1CR1<CTC1E>). The source clock is an internal clock. When matched with the CTC1DR A/B/C Registers, the timer output F/F corresponding to each mode is inverted. When matched with the CTC1DR A/B/C Registers next time, the timer output F/F is inverted again. An INTCTC1 interrupt request is generated when the counter value matches the maximum register value set by CTC1CR2<CTCREG>. The timer output F/F is cleared to 0 when reset. Because CTC1CR2<CTC1FF0> can be used to set the initial value for the timer output F/F, an active-high or active-low pulse whichever is desired can be output. The CTC1DRB and CTC1DRC Registers cannot be accessed for write unless they are set for PPG output mode and the registers used are selected with CTC1CR2<CTC1REG>. The number of registers set can be altered during operation. In this case, however, be sure to set the number of registers used and write values to the data registers before the next CTC1INIT1 is output after the first CTC1INIT1 output. Even when only altering the data register values while leaving the number of registers unchanged, be sure to do this within the same period of time.

	NORMAL and IDLE Modes						
CTC1CK	DV1C	K = 0	DV1CK = 1				
	Resolution [µs]	Maximum Setting Time [s]	Resolution [µs]	Maximum Setting Time [s]			
000	-	- /	-	-			
001	-((// 5))	-	-	-			
010	\bigcirc	~ - (7/\$	-	-			
011		\sim	-	-			
100	0.2	13.11 m	-	-			
101	0.1	6.55 m	0.2	13.11m			
110 🗸	-		-	-			

Table 10-3 Internal Clock Source for Compare Timer/Counter 1 (Example: fc = 20 MHz)

Note: When Port P47 is set as a CTC input port, an edge input resets the timer/counter. when PPG output mode is selected and external trigger start is not used, set CTC1CR2<EXTRGDIS> to "1" or set P47 as an output port.

(I) One register used (CTC1REG = 00) When set to command start. Command start CTC pin input Counter 0 3 Timer Register A n PPG2 pin output INTCTC1 interrupt Successive Figure 10-6 One Register Command Start Mode Timing Chart. \bigcirc (II) Two registers used (CTC1REG = 01) When set to the external trigger rising edge start and the one edge enable. a) Successive Start Stop CTC pin input Internal clock Counter 0 m 0 Timer Register A m Timer Register B n PPG2 pin output Initial value INTCTC1 interrupt Successive b) One shot Start Start CTC pin input Internal clock Counter 0 m 0 Timer Register A m Timer Register B n PPG2 pin output INTCTC1 interrupt One shot





When set to the external trigger rising edge start and the both edges enable.

Figure 10-8 Two Register Both edges Trigger Start Mode Timing Chart

(III) Three registers When set to co	s used (CTC1REG = 10) ommand start.
a) Successive	
CTC pin input	
Counter	$\frac{1}{2} \sum_{i,j} \frac{1}{2} \sum_{i$
Timer Register A	
Timer Register B	X n h
Timer Register C	
PPG2 pin output	
INTCTC1 interrupt	Successive
b) One shot	ommand start Command restart
CTC pin input	
Counter	$ \underbrace{0 \stackrel{!}{}{} \times 1 \times (3, \times m \times m+1) \times (3, \times n \times n+1) \times (3, \times n \times n+1) \times (3, \times n \times m+1) $
Timer Register A	
Timer Register B	X
Timer Register C	
PPG2 pin output	
INTCTC1 interrupt	One shot

Note: In the single-shot mode, the PPG pin output is not toggled at the last register match; it stays at the value specified with CTC1CR2<CTC1FF0>.

Figure 10-9 Three Register Command Start Mode Timing Chart

Detail operation at start that varies depending on how CTC1CR2<CTC1FF0> and CTC1CR1<PPGFF0> are set during PPG output.

CTC1FF0 = 0 PPGFF0 = 0	CTC1FF0 setting (write to CTC1CR1 Register) Or trigger start Internal clock Counter 0 1 2 3 0 n n+1 n+2 n+3 PPG output
CTC1FF0 = 1 PPGFF0 = 0	CTC1FF0 setting (write to CTC1CR1 Register) Command start or trigger, start Internal clock Counter 0 1 1 2 3 1 2 1 2 1 2 1 2 1 2 1 2 1 2 1 2
CTC1FF0 = 0 PPGFF0 = 1	CTC1FF0 setting (write to CTC1CR1 Register) or trigger start Internal clock Counter 0 1 2 3 () n n+1 n+2 n+3 PPG output
CTC1FF0 = 1 PPGFF0 = 1	CTC1FF0 setting (write to CTC1CR1 Register) or trigger start Internal clock Counter PPG output

Table 10 4	Vanina		ut Timina F	Jonondina	on Cottingo
Table 10-4	varying	PPG Oulp	истипид с	Jepending	on Settings

By changing the port-shared output for PPG output before the counter starts counting after setting CTC1CR2<CTC1FF0>, it is possible to determine the initial value of PPG output.

TOSHIBA

11. 8-Bit TimerCounter 3 (TC3)

11.1 Configuration



Note: Function input may not operate depending on I/O port setting. For more details, see the chapter "I/O Port".



11.2 TimerCounter Control

11.2 TimerCounter Control

The TimerCounter 3 is controlled by the TimerCounter 3 control register (TC3CR) and two 8-bit timer registers (TC3DRA and TC3DRB).



- Note 1: fc: High-frequency clock [Hz], *: Don't care
- Note 2: Set the operating mode and source clock when TimerCounter stops (TC3CR<TC3S> = 0).
- Note 3: To set the timer registers, the following relationship must be satisfied.
 - TC3DRA > 1 (Timer/event counter mode)
- Note 4: Auto-capture (TC3CR<ACAP>) can be used only in the timer and event counter modes.
- Note 5: When the read instruction is executed to TC3CR, the bit 5 and 7 are read as a don't care.
- Note 6: Do not program TC3DRA when the timer is running (TC3CR<TC3S> = 1).
- Note 7: When the STOP mode is entered, the start control (TC3CR<TC3S>) is cleared to 0 automatically, and the timer stops. After the STOP mode is exited, TC3CR<TC3S> must be set again to use the timer counter.

11.3 Function

TimerCounter 3 has three types of operating modes: timer, event counter and capture modes.

11.3.1 Timer mode

In the timer mode, the up-counter counts up using the internal clock. When a match between the up-counter and the timer register 3A (TC3DRA) value is detected, an INTTC3 interrupt is generated and the up-counter is cleared. After being cleared, the up-counter restarts counting. Setting TC3CR<ACAP> to 1 captures the up-counter value into the timer register 3B (TC3DRB) with the auto-capture function. The count value during timer operation can be checked by executing the read instruction to TC3DRB.

Note:00H which is stored in the up-counter immediately after detection of a match is not captured into TC3DRB. (Figure 11-2)



Table 11-1 Source Clock for TimerCounter 3 (Example: fc = 20 MHz)

	тсзск	$) \square$	NORMAL, IDLE mode					
			DV1CK = 0	\mathcal{I}	DV1CK = 1			
		Resolution	Maximum Time Setting	Resolution	Maximum Time Setting			
		[µs]	[ms]	[µs]	[ms]			
	000	409.6	104.45	819.2	208.90			
$\langle \rangle$	001	204.8	52.22	409.6	104.45			
\sim (\bigcirc	010	102.4	26.11	204.8	52.22			
\bigcirc	011	51.2	13.06	102.4	26.11			
	100	25.6	6.53	51.2	13.06			
	101	12.8	3.06	25.6	6.53			
	110	6.4	1.63	12.8	3.06			



11.3.2 Event Counter Mode

In the event counter mode, the up-counter counts up at the rising edge of the input pulse to the TC3 pin.

When a match between the up-counter and TC3DRA value is detected, an INTTC3 interrupt is generated and up-counter is cleared. After being cleared, the up-counter restarts counting at each rising edge of the input pulse to the TC3 pin. Since a match is detected at the falling edge of the input pulse to TC3 pin, an INTTC3 interrupt request is generated at the falling edge immediately after the up-counter reaches the value set in TC3DRA.

The maximum applied frequencies are shown in Table 11-2. The pulse width larger than one machine cycle is required for high-going and low-going pulses.

Setting TC3CR<ACAP> to 1 captures the up-counter value into TC3DRB with the auto-capture function. The count value during a timer operation can be checked by the read instruction to TC3DRB.

Note: 00H which is stored in the up-counter immediately after detection of a match is not captured into TC3DRB. (Figure 11-2)

Example :Inputting 50 Hz pulse to TC3, and generating interrupts every 0,5

LD	(TC3CR), 00001110B	: Sets the clock mode
LD	(TC3DRA), 19H	: 0.5 s ÷ 1/50 = 25 = 19H
LD	(TC3CR), 00011110B	: Starts TC3.

Table 11-2 Maximum Frequencies Applied to TC3



11.3.3 Capture Mode

In the capture mode, the pulse width, frequency and duty cycle of the pulse input to the TC3 pin are measured with the internal clock. The capture mode is used to decode remote control signals, and identify AC50/60 Hz.

When the falling edge of the TC3 input is detected after the timer starts, the up-counter value is captured into TC3DRB. Hereafter, whenever the rising edge is detected, the up-counter value is captured into TC3DRA and the INTTC3 interrupt request is generated. The up-counter is cleared at this time. Generally, read TC3DRB and TC3DRA during INTTC3 interrupt processing. After the up-counter is cleared, counting is continued and the next up-counter value is captured into TC3DRB.

When the rising edge is detected immediately after the timer starts, the up-counter value is captured into TC3DRA only, but not into TC3DRB. The INTTC3 interrupt request is generated. When the read instruction is executed to TC3DRB at this time, the value at the completion of the last capture (FF immediately after a reset) is read.

The minimum input pulse width must be larger than one cycle width of the source clock programmed in TC3CR<TC3CK>.

The INTTC3 interrupt request is generated if the up-counter overflow (FFH) occurs during capture operation before the edge is detected. TC3DRA is set to FFH and the up-counter is cleared. Counting is continued by the up-counter, but capture operation and overflow detection are stopped until TC3DRA is read. Generally, read TC3DRB first because capture operation and overflow detection resume by reading TC3DRA.

	Timer start		$\langle \rangle$				
TC3CR <tc3s< td=""><td>></td><td>/</td><td></td><td></td><td></td><td></td><td></td></tc3s<>	>	/					
Source clock			<u>n</u> "u		μη η η		
Counter		i X i+1 X <mark>%</mark> X K-1 X k @	X1 X ,"Xm1X		0123	X"XFEXFX	X1X2X3X
TC3 pin input							
Internal wavefo	rm	h	Capture		Capture		
TC3DRA		Capture	k	Capture	X n	Capture	FF (Overflow)
TC3DRB			\sim	m		FE	
INTTC3 interrupt reques	st				Л		Overflow
Read of TC3DF	RA	$\sum \alpha$					
		41					
		Figure 11-	5 Capture M	lode Timing (Chart		
\leq		\mathcal{C}					
		\sim					

TOSHIBA

12. 8-Bit TimerCounter 4 (TC4)

12.1 Configuration



12.2 TimerCounter Control

The TimerCounter 4 is controlled by the TimerCounter 4 control register (TC4CR) and timer registers 4 (TC4DR).



- Note 1: fc: High-frequency clock [Hz], *: Don't care
- Note 2: To set the timer registers, the following relationship must be satisfied. $1 \le TC4DR \le 255$
- Note 3: To start timer operation (TC4CR<TC4S> = $0 \rightarrow 1$) or disable timer operation (TC4CR<TC4S> = $1 \rightarrow 0$), do not change the TC4CR<TC4M, TC4CK> setting. During timer operation (TC4CR<TC4S> = $1 \rightarrow 1$), do not change it, either. If the setting is programmed during timer operation, counting is not performed correctly.
- Note 4: The event counter and PWM output modes are used only in the NOMAL and IDLE modes.
- Note 5: When the STOP mode is entered, the start control (TC4S) is cleared to "0" automatically.
- Note 6: The bit 6 and 7 of TC4CR are read as a don't care when these bits are read.
- Note 7: In the timer, event counter and PDO modes, do not change the TC4DR setting when the timer is running.
- Note 8: When the high-frequency clock fc exceeds 10 MHz, do not select the source clock of TC4CR< TC4CK> = 110.
- Note 9: For available source clocks depending on the operation mode, refer to the following table.

	<u> </u>	()				
$\langle \langle -$		\searrow	Timer Mode	Event Counter Mode	PDO Mode	PWM Mode
		000	0	-	0	-
\sim		001	> ₀	-	0	-
		010	0	-	0	-
	TC4CK	011	0	-	-	0
		100	-	-	-	0
		101	-	-	-	0
		110	-	-	-	0
		111	-	0	-	×

Note: O : Available source clock

12.3 Function

TimerCounter 4 has four types of operating modes: timer, event counter, programmable divider output (PDO), and pulse width modulation (PWM) output modes.

12.3.1 Timer Mode

In the timer mode, the up-counter counts up using the internal clock. When a match between the up-counter and the TC4DR value is detected, an INTTC4 interrupt is generated and the up-counter is cleared. After being cleared, the up-counter restarts counting.

TC4CK	NORMAL, IDLE Mode					
		DV1CK = 0	41	DV1CK = 1	$1(\sim$	
	Resolution	Maximum Time Setting	Resolution	Maximum Time Setting	\square	
	[µs]	[ms]	[µs]	[ms]	$) \sim$	
000	102.4	26.11	204.8	52.22	())	
001	6.4	1.63	12.8	3.28		
010	1.6	0.41	3.2	0.82		
011	0.4	0.10	0.8	0.20		

Table 12-1 Internal Source Clock for TimerCounter 4 (Example: fc = 20 MHz)

12.3.2 Event Counter Mode

In the event counter mode, the up-counter counts up at the rising edge of the input pulse to the TC4 pin.

When a match between the up-counter and the TC4DR value is detected, an INTTC4 interrupt is generated and the up-counter is cleared. After being cleared, the up-counter restarts counting at rising edge of the TC4 pin. Since a match is detected at the falling edge of the input pulse to the TC4 pin, the INTTC4 interrupt request is generated at the falling edge immediately after the up-counter reaches the value set in TC4DR.

The minimum pulse width applied to the TC4 pin are shown in Table 12-2. The pulse width larger than two machine cycles is required for high- and low-going pulses.

Note: The event counter mode can used in the NORMAL and IDLE modes only.



	Minimum Pulse Width
	NORMAL, IDLE mode
High-going	2³/fc
Low-going	2³/fc

Table 12-2/External Source Clock for TimerCounter 4

12.3.3 Programmable Divider Output (PDO) Mode

The programmable divider output (PDO) mode is used to generated a pulse with a 50% duty cycle by counting with the internal clock.

When a match between the up-counter and the TC4DR value is detected, the logic level output from the $\overline{PDO4}$ pin is switched to the opposite state and INTTC4 interrupt request is generated. The up-counter is cleared at this time and then counting is continued. When a match between the up-counter and the TC4DR value is detected, the logic level output from the $\overline{PDO4}$ pin is switched to the opposite state again and INTTC4 interrupt request is generated. The up-counter is cleared at this time, and then counting and PDO are continued.

When the timer is stopped, the $\overline{PDO4}$ pin is high. Therefore, if the timer is stopped when the $\overline{PDO4}$ pin is low, the duty pulse may be shorter than the programmed value.



12.3.4 Pulse Width Modulation (PWM) Output Mode

The pulse width modulation (PWM) output mode is used to generate the PWM pulse with up to 8 bits of resolution by an internal clock.

When a match between the up-counter and the TC4DR value is detected, the logic level output from the $\overline{PWM4}$ pin becomes low. The up-counter continues counting. When the up-counter overflow occurs, the $\overline{PWM4}$ pin becomes high. The INTTC4 interrupt request is generated at this time.

When the timer is stopped, the $\overline{PWM4}$ pin is high. Therefore, if the timer is stopped when the $\overline{PWM4}$ pin is low, one PMW cycle may be shorter than the programmed value.

TC4DR is serially connected to the shift register. If TC4DR is programmed during PWM output, the data set to TC4DR is not shifted until one PWM cycle is completed. Therefore, a pulse can be modulated periodically. For the first time, the data written to TC4DR is shifted when the timer is started by setting TC4CR<TC4S> to 1.

Note 1: The PWM output mode can be used only in the NORMAL and IDEL modes.

Note 2: In the PWM output mode, program TC4DR immediately after the INTTC4 interrupt request is generated (typically in the INTTC4 interrupt service routine.) When the programming of TC4DR and the INTTC4 interrupt occur at the same time, an unstable value is shifted, that may result in generation of pulse different from the programmed value until the next INTTC4 interrupt request is issued.

TOSHIBA



TOSHIBA

13. 8-Bit TimerCounter 5,6(TC5, 6)

13.1 Configuration



13.2 TimerCounter Control

TMP88FW45AFG

13.2 TimerCounter Control

The TimerCounter 5 is controlled by the TimerCounter 5 control register (TC5CR) and two 8-bit timer registers (TTREG5, PWREG5).



- Note 1: fc: High-frequency clock [Hz]
- Note 2: Do not change the TC5M, TC5CK and TFF5 settings while the timer is running.
- Note 3: To stop the timer operation (TC5S= $1 \rightarrow 0$), do not change the TC5M, TC5CK and TFF5 settings. To start the timer operation (TC5S= $0 \rightarrow 1$), TC5M, TC5CK and TFF5 can be programmed.
- Note 4: To use the TimerCounter in the 16-bit mode, set the operating mode by programming TC6CR<TC6M>, where TC5M must be fixed to 011.
- Note 5: To use the TimerCounter in the 16-bit mode, select the source clock by programming TC5CK. Set the timer start control and timer F/F control by programming TC6CR<TC6S> and TC6CR<TFF6>, respectively.
- Note 6: The operating clock settings are limited depending on the timer operating mode. For the detailed descriptions, see Table 13-1.
- Note 7: The timer register settings are limited depending on the timer operating mode. For the detailed descriptions, see Table 13-2.

The TimerCounter 6 is controlled by the TimerCounter 6 control register (TC6CR) and two 8-bit timer registers (TTREG6 and PWREG6).

TimerCounter 6 Timer Register



- Note 1: fc: High-frequency clock [Hz]
- Note 2: Do not change the TC6M, TC6CK and TFF6 settings while the timer is running.
- Note 3: To stop the timer operation (TC6S= 1 \rightarrow 0), do not change the TC6M, TC6CK and TFF6 settings.

To start the timer operation (TC6S= $0 \rightarrow 1$), TC6M, TC6CK and TFF6 can be programmed.

- Note 4: When TC6M= 1** (upper byte in the 16-bit mode), the source clock becomes the TC6 overflow signal regardless of the TC5CK setting.
- Note 5: To use the TimerCounter in the 16-bit mode, select the operating mode by programming TC6M, where TC5CR<TC5 M> must be set to 011.
- Note 6: To the TimerCounter in the 16-bit mode, select the source clock by programming TC5CR<TC5CK>. Set the timer start control and timer F/F control by programming TC6S and TFF6, respectively.

- Note 7: The operating clock settings are limited depending on the timer operating mode. For the detailed descriptions, see Table 13-1.
- Note 8: The timer register settings are limited depending on the timer operating mode. For the detailed descriptions, see Table 13-2.

Operating mode	fc/211	fc/27	fc/2⁵	fc/2 ³	TC5 pin input	TC6 pin input	
8-bit timer	0	0	0	O) -	
8-bit event counter	-	-	-	-		0	
8-bit PDO	0	0	0	o		-	
8-bit PWM	0	0	0	0	\sum	-	
16-bit timer	0	0	0	0	-	- ((\sim
16-bit event counter	-	-	- (0		
16-bit PWM	0	0	67		0	6	\geq
16-bit PPG	0	0	_ Q <	\mathcal{D}_{0}	⊘ ∧		

Table 13-1 Operating Mode and Selectable Source Clock (NORMAL and IDLE Modes)

Note 1: For 16-bit operations (16-bit timer/event counter, warm-up counter, 16-bit PWM and 16-bit PPG), set its source clock on lower bit (TC5CK).

Note 2: O : Available source clock

Table 13-2 Constraints on Register Values Being Compared

Operating mode	Register Value
8-bit timer/event counter	1≤ (TTREGn) ≤255
8-bit PDO	1≤ (TTREGn) ≤255
8-bit PWM	2≤ (PWREGn) ≤254
16-bit timer/event counter	1≤ (TTREG6, 5) ≤65535
16-bit PWM	2≤ (PWREG6, 5) ≤65534
16-bit PPG	1≤ (PWREG6, 5) < (TTREG6, 5) ≤65535 and
	(PWREG6, 5) + 1 < (TTREG6, 5)

Note: n = 5 to 6

13.3 Function

The TimerCounter 5 and 6 have the 8-bit timer, 8-bit event counter, 8-bit programmable divider output (PDO), 8-bit pulse width modulation (PWM) output modes. The TimerCounter 5 and 6 (TC5, 6) are cascadable to form a 16-bit timer. The 16-bit timer has the operating modes such as the 16-bit timer, 16-bit event counter, 16-bit pulse width modulation (PWM) output and 16-bit programmable pulse generation (PPG) modes.

13.3.1 8-Bit Timer Mode (TC5 and 6)

In the timer mode, the up-counter counts up using the internal clock. When a match between the up-counter and the timer register j (TTREGj) value is detected, an INTTCj interrupt is generated and the up-counter is cleared. After being cleared, the up-counter restarts counting.

- Note 1: In the timer mode, fix TCjCR<TFFj> to 0. If not fixed, the PDOj, PWM and PPGj pins may output pulses.
- Note 2: In the timer mode, do not change the TTREG setting while the timer is running. Since TTREG is not in the shift register configuration in the timer mode, the new value programmed in TTREG is in effect immediately after the programming. Therefore, if TTREG is changed while the timer is running, an expected operation may not be obtained.

Note 3: j = 5, 6

	A		
Source	e Clock	Resolution	Repeated Cycle
NORMAL,	IDLE mode	DV1CK = 0	DV1CK=0
DV1CK = 0	DV1CK = 1	fc = 20 MHz	fc = 20 MHz
fc/211 [Hz]	fc/212 [Hz]	128 µs	32.6 ms
fc/27	fc/2 ⁸	8 µs	2.0 ms
fc/2 ⁵	fc/2 ⁶	2 µs	510 μs
fc/2 ³	fc/2⁴	500 ns	V 127.5 μs

Table 13-3 Source Clock for TimerCounter 5, 6 (Internal Clock)









13.3.2 8-Bit Event Counter Mode (TC5, 6)

In the 8-bit event counter mode, the up-counter counts up at the falling edge of the input pulse to the TCj pin. When a match between the up-counter and the TTREGj value is detected, an INTTCj interrupt is generated and the up-counter is cleared. After being cleared, the up-counter restarts counting at the falling edge of the input pulse to the TCj pin. Two machine cycles are required for the low- or high-level pulse input to the TCj pin. Therefore, a maximum frequency to be supplied is $fc/2^4$ Hz in the NORMAL or IDLE mode.

- Note 1: In the event counter mode, fix TCjCR<TFFj> to 0. If not fixed, the PDOj, PWMj and PPGj pins may output pulses.
- Note 2: In the event counter mode, do not change the TTREG setting while the timer is running. Since TTREG is not in the shift register configuration in the event counter mode, the new value programmed in TTREG is in effect immediately after the programming. Therefore, if TTREG is changed while the timer is running, an expected operation may not be obtained.



13.3.3 8-Bit Programmable Divider Output (PDO) Mode (TC5, 6)

This mode is used to generate a pulse with a 50% duty cycle from the $\overline{\text{PDOj}}$ pin.

In the PDO mode, the up-counter counts up using the internal clock. When a match between the up-counter and the TTREGj value is detected, the logic level output from the \overline{PDOj} pin is switched to the opposite state and the up-counter is cleared. The INTTCj interrupt request is generated at the time. The logic state opposite to the timer F/Fj logic level is output from the \overline{PDOj} pin. An arbitrary value can be set to the timer F/Fj by TCjCR<TFFj>. Upon reset, the timer F/Fj value is initialized to 0.

To use the programmable divider output, set the output latch of the I/O port to 1.

Example :Generating 1024 Hz pulse using TC6 (fc = 20.0 MHz)

	Setting port	
LD	(TTREG6), 3DH	: 1/1024 ÷ 2 ⁷ /fc ÷ 2 = 3DH
LD	(TC6CR), 00010001B	: Sets the operating clock to fc/27, and 8-bit PDO mode.
LD	(TC6CR), 00011001B	: Starts TC6.

- Note 1: In the programmable divider output mode, do not change the TTREG setting while the timer is running. Since TTREG is not in the shift register configuration in the programmable divider output mode, the new value programmed in TTREG is in effect immediately after programming. Therefore, if TTREG is changed while the timer is running, an expected operation may not be obtained.
- Note 2: When the timer is stopped during PDO output, the PDOj pin holds the output status when the timer is stopped. To change the output status, program TCjCR<TFFj> after the timer is stopped. Do not change the TCjCR<TFFj> setting upon stopping of the timer.

Example: Fixing the PDOj pin to the high level when the TimerCounter is stopped CLR (TCjCR).3: Stops the timer.

CLR (TCjCR).7: Sets the \overline{PDOj} pin to the high level.

Note 3: j = 5, 6



Figure 13-4 8-Bit PDO Mode Timing Chart (TC6)

13.3.4 8-Bit Pulse Width Modulation (PWM) Output Mode (TC5, 6)

This mode is used to generate a pulse-width modulated (PWM) signals with up to 8 bits of resolution. The upcounter counts up using the internal clock.

When a match between the up-counter and the PWREGj value is detected, the logic level output from the timer F/Fj is switched to the opposite state. The counter continues counting. The logic level output from the timer F/Fj is switched to the opposite state again by the up-counter overflow, and the counter is cleared. The INTTCj interrupt request is generated at this time.

Since the initial value can be set to the timer F/Fj by TCjCR<TFFj>, positive and negative pulses can be generated. Upon reset, the timer F/Fj is cleared to 0.

(The logic level output from the <u>PWMj</u> pin is the opposite to the timer F/Fj logic level.)

Since PWREGj in the PWM mode is serially connected to the shift register, the value set to PWREGj can be changed while the timer is running. The value set to PWREGj during a run of the timer is shifted by the INTTCj interrupt request and loaded into PWREGj. While the timer is stopped, the value is shifted immediately after the programming of PWREGj. If executing the read instruction to PWREGj during PWM output, the value in the shift register is read, but not the value set in PWREGj. Therefore, after writing to PWREGj, the reading data of PWREGj is previous value until INTTCj is generated.

For the pin used for PWM output, the output latch of the I/O port must be set to 1.

- Note 1: In the PWM mode, program the timer register PWREG immediately after the INTTC interrupt request is generated (normally in the INTTC interrupt service routine.) If the programming of PWREG and the interrupt request occur at the same time, an unstable value is shifted, that may result in generation of the pulse different from the programmed value until the next INTTC interrupt request is generated.
- Note 2: When the timer is stopped during PWM output, the PWMj pin holds the output status when the timer is stopped. To change the output status, program TCjCR<TFFj> after the timer is stopped. Do not change the TCjCR<TFFj> upon stopping of the timer.

Example: Fixing the PWMj pin to the high level when the TimerCounter is stopped

CLR (TCjCR).3: Stops the timer.

CLR (TCjCR).7: Sets the PWMj pin to the high level.

- Note 3: To enter the STOP mode during PWM output, stop the timer and then enter the STOP mode. If the STOP mode is entered without stopping the timer when fc or fc/2 is selected as the source clock, a pulse is output from the PWMj pin during the warm-up period time after exiting the STOP mode.
- Note 4: j = 5, 6

	Source Clock		Resolution		Repeated Cycle	
	NORMAL, DV1CK=0	DLE mode	DV1CK = 0 fc = 20 MHz	DV1CK = 1 fc = 20 MHz	DV1CK = 0 fc = 20 MHz	DV1CK = 1 fc = 20 MHz
	fc/211 [Hz]	fc/212 [Hz]	102.4 µs	204.8 µs	26.21 ms	52.43 ms
\langle	fc/27	fc/28	6.4 µs	12.8 µs	1.64 ms	3.28 ms
	fc/25	fc/2 ⁶	1.6 µs	3.2 µs	410 µs	819 µs
$\langle \langle \langle \langle \langle \rangle \rangle \rangle$	fc/2 ³	fc/2 ⁴	0.4 µs	0.8 µs	102 µs	205 µs

Table 13-4 PWM Output Mode



Figure 13-5 8-Bit PWM Mode Timing Chart (TC6)

13.3.5 16-Bit Timer Mode (TC5 and 6)

In the timer mode, the up-counter counts up using the internal clock. The TimerCounter 5 and 6 are cascadable to form a 16-bit timer.

When a match between the up-counter and the timer register (TTREG5, TTREG6) value is detected after the timer is started by setting TC6CR<TC6S> to 1, an INTTC6 interrupt is generated and the up-counter is cleared. After being cleared, the up-counter continues counting. Program the lower byte and upper byte in this order in the timer register. (Programming only the upper or lower byte should not be attempted.)

Note 1: In the timer mode, fix TCjCR<TFFj> to 0. If not fixed, the PDOj, PWMj, and PPGj pins may output a pulse.

Note 2: In the timer mode, do not change the TTREG setting while the timer is running. Since TTREG is not in the shift register configuration in the timer mode, the new value programmed in TTREG is in effect immediately after programming of TTREG. Therefore, if TTREG is changed while the timer is running, an expected operation may not be obtained.

Note 3: j = 5, 6

Table 13-5 Source Clock for 16-Bit Timer Mode

			<u> </u>		
Source Clock		Resolution		Maximum Time Setting	
NORMAL,	IDLE mode	DV1CK = 0	DV1CK = 1	DV1CK = 0	DV1CK = 1
DV1CK = 0	DV1CK = 1	fc = 20 MHz	fc = 20 MHz	fc = 20 MHz	fc = 20 MHz
fc/211	fc/212	102.4 µs	204.8 µs	6.7 s	13.4 s
fc/2 ⁷	fc/2 ⁸	6.4 µs	12.8 µs	419.4 ms	838.8 ms
fc/2⁵	fc/2 ⁶	1.6 µs	3.2 µs	104.9 µs	209.7 ms
fc/2 ³	fc/2 ⁴	0.4 µs	0.8 µs	26.2 µs	52.4 ms

Example :Setting the timer mode with source clock $fc/2^7$ [Hz], and generating an interrupt 240 ms later (fc = 20.0 MHz)







13.3.6 16-Bit Event Counter Mode (TC5 and 6)

In the event counter mode, the up-counter counts up at the falling edge to the TCS pin. The TimerCounter 5 and 6 are cascadable to form a 16-bit event counter.

When a match between the up-counter and the timer register (TTREG5, TTREG6) value is detected after the timer is started by setting TC6CR<TC6S> to 1, an INTTC6 interrupt is generated and the up-counter is cleared.

After being cleared, the up-counter restarts counting at the falling edge of the input pulse to the TC5 pin. Two machine cycles are required for the low- or high-level pulse input to the TC5 pin.

Therefore, a maximum frequency to be supplied is $fc/2^4$ Hz in the NORMAL or IDLE mode. Program the lower byte (TTREG5), and upper byte (TTREG6) in this order in the timer register. (Programming only the upper or lower byte should not be attempted.)

- Note 1: In the event counter mode, fix TCjCR<TFFj> to 0. If not fixed, the PDOj, PWMj and PPGj pins may output pulses.
- Note 2: In the event counter mode, do not change the TTREG setting while the timer is running. Since TTREG is not in the shift register configuration in the event counter mode, the new value programmed in TTREG is in effect immediately after the programming. Therefore, if TTREG is changed while the timer is running, an expected operation may not be obtained.

13.3.7 16-Bit Pulse Width Modulation (PWM) Output Mode (TC5 and 6)

This mode is used to generate a pulse-width modulated (PWM) signals with up to 16 bits of resolution. The TimerCounter 5 and 6 are cascadable to form the 16-bit PWM signal generator.

The counter counts up using the internal clock or external clock.

When a match between the up-counter and the timer register (PWREG5, PWREG6) value is detected, the logic level output from the timer F/F6 is switched to the opposite state. The counter continues counting. The logic level output from the timer F/F6 is switched to the opposite state again by the counter overflow, and the counter is cleared. The INTTC6 interrupt is generated at this time.

Two machine cycles are required for the high- or low-level pulse input to the TC5 pin. Therefore, a maximum frequency to be supplied is $fc/2^4$ Hz in the NORMAL1 or IDLE1 mode.

Since the initial value can be set to the timer F/F6 by TC6CR<TFF6>, positive and negative pulses can be generated. Upon reset, the timer F/F6 is cleared to 0.

(The logic level output from the $\overline{PWM6}$ pin is the opposite to the timer F/F6 logic level.)

Since PWREG6 and 5 in the PWM mode are serially connected to the shift register, the values set to PWREG6 and 5 can be changed while the timer is running. The values set to PWREG6 and 5 during a run of the timer are

Note 3: j = 5, 6
TOSHIBA

shifted by the INTTCj interrupt request and loaded into PWREG6 and 5. While the timer is stopped, the values are shifted immediately after the programming of PWREG6 and 5. Set the lower byte (PWREG5) and upper byte (PWREG5) in this order to program PWREG6 and 5. (Programming only the lower or upper byte of the register should not be attempted.)

If executing the read instruction to PWREG6 and 5 during PWM output, the values set in the shift register is read, but not the values set in PWREG6 and 5. Therefore, after writing to the PWREG6 and 5, reading data of PWREG6 and 5 is previous value until INTTC6 is generated.

For the pin used for PWM output, the output latch of the I/O port must be set to 1.

- Note 1: In the PWM mode, program the timer register PWREG6 and 5 immediately after the INTTC6 interrupt request is generated (normally in the INTTC6 interrupt service routine.) If the programming of PWREGj and the interrupt request occur at the same time, an unstable value is shifted, that may result in generation of pulse different from the programmed value until the next INTTC6 interrupt request is generated.
- Note 2: When the timer is stopped during PWM output, the PWM6 pin holds the output status when the timer is stopped. To change the output status, program TC6CR<TFF6> after the timer is stopped. Do not program TC6CR<TFF6> upon stopping of the timer.

Example: Fixing the PWM6 pin to the high level when the TimerCounter is stopped

CLR (TC6CR).3: Stops the timer.

CLR (TC6CR).7 : Sets the PWM6 pin to the high level,

Note 3: To enter the STOP mode, stop the timer and then enter the STOP mode. If the STOP mode is entered without stopping of the timer when fc or fc/2 is selected as the source clock, a pulse is output from the PWM6 pin during the warm-up period time after exiting the STOP mode.

|--|

Source	e Clock	Reso	lution	Repeated Cycle		
NORMAL,	IDLE mode	DV1CK = 0	DV1CK = 1	DV1CK = 0	DV1CK = 1	
DV1CK = 0	DV1CK = 1	fc = 20 MHz	fc = 20 MHz	fc = 20 MHz	fc = 20 MHz	
fc/211[Hz]	fc/212 [Hz]	102.4 µs	204.8 µs	6.7 s	13.4 s	
fc/27	fc/28	6.4 µs	12.8 µs	419.4 ms	838.8 ms	
fc/2 ⁵	fc/2 ⁶	1.6 µs	3.2 µs	104.9 ms	209.7 ms	
fc/2 ³	fc/2⁴	0.4 µs	0.8 µs	26.2 ms	52.4 ms	

Example :Generating a pulse with 1-ms high-level width and a period of 32.768 ms (fc = 20.0 MHz)





Figure 13-7 16-Bit PWM Mode Timing Chart (TC5 and TC6)

13.3.8 16-Bit Programmable Pulse Generate (PPG) Output Mode (TC5 and 6)

This mode is used to generate pulses with up to 16-bits of resolution. The timer counter 5 and 6 are cascadable to enter the 16-bit PPG mode.

The counter counts up using the internal clock or external clock. When a match between the up-counter and the timer register (PWREG5, PWREG6) value is detected, the logic level output from the timer F/F6 is switched to the opposite state. The counter continues counting. The logic level output from the timer F/F6 is switched to the opposite state again when a match between the up-counter and the timer register (TTREG5, TTREG6) value is detected, and the counter is cleared. The INTTC6 interrupt is generated at this time.

Since the initial value can be set to the timer F/F6 by TC6CR<TFF6>, positive and negative pulses can be generated. Upon reset, the timer F/F6 is cleared to 0.

(The logic level output from the $\overline{PPG6}$ pin is the opposite to the timer F/F6.)

Set the lower byte and upper byte in this order to program the timer register. (TTREG5 \rightarrow TTREG6, PWREG5 \rightarrow PWREG6) (Programming only the upper or lower byte should not be attempted.)

For PPG output, set the output latch of the I/O port to 1.

Example :Generating a pulse with 1-ms high-level width and a period of 16.385 ms (fc = 20.0 MHz)

	Setting ports	
LDW	(PWREG5), 07D0H	: Sets the pulse width.
LDW	(TTREG5), 8002H	: Sets the cycle period.
LD	(TC5CR), 33H	: Sets the operating clock to fc/2 ³ , and16-bit PPG mode (lower byte).
LD	(TC6CR), 057H	: Sets TFF6 to the initial value 0, and 16-bit PPG mode (upper byte).
LD	(TC6CR), 05FH	: Starts the timer.

- Note 1: In the PPG mode, do not change the PWREGi and TTREGi settings while the timer is running. Since PWREGi and TTREGi are not in the shift register configuration in the PPG mode, the new values programmed in PWREGi and TTREGi are in effect immediately after programming PWREGi and TTREGi. Therefore, if PWREGi and TTREGi are changed while the timer is running, an expected operation may not be obtained.
- Note 2: When the timer is stopped during PPG output, the PPG6 pin holds the output status when the timer is stopped. To change the output status, program TC6CR<TFF6> after the timer is stopped. Do not change TC6CR<TFF6> upon stopping of the timer.

Example: Fixing the PPG6 pin to the high level when the TimerCounter is stopped

CLR (TC6CR).3: Stops the timer

CLR (TC6CR).7: Sets the PPG6 pin to the high level

Note 3: i = 5, 6



Figure 13-8 16-Bit PPG Mode Timing Chart (TC5 and TC60)

14. Motor Control Circuit (PMD: Programmable motor driver)

The TMP88FW45AFG contains two channels of motor control circuits used for sinusoidal waveform output. This motor control circuit can control brushless DC motors or AC motors with or without sensors. With its primary functions like those listed below incorporated in hardware, it helps to accomplish sine wave motor control easily, with the software load significantly reduced.

- 1. Rotor position detect function
 - Can detect the rotor position, with or without sensors
 - Can be set to determine the rotor position when detection matched a number of times, to prevent erroneous detection
 - · Can set a position detection inhibit period immediately after PWM-on
- 2. Independent timer and timer capture functions for motor control
 - Contains one-channel magnitude comparison timer and two-channel coincidence comparison timers that operate synchronously for position detection
- 3. PWM waveform generating function
 - Generates 12-bit PWM with 100 ns resolution
 - · Can set a frequency of PWM interrupt occurrence
 - Can set the dead time at PWM-on
- 4. Protective function
 - · Provides overload protective function based on protection signal input
- 5. Emergency stop function in case of failure
 - Can be made to stop in an emergency by EMG input or timer overflow interrupt
 - · Not easily cleared by software runaway
- 6. Auto commutation/Auto position detection start function
 - Comprised of dual-buffers, can activate auto commutation synchronously with position detection or timer
 - Can set a position detection period using the timer function and start auto position detection at the set time
- 7. Electrical angle timer function
 - Can count 360 degrees of electrical angle with a set period in the range of 0 to 383
 - Can output the counted electrical angle to the waveform arithmetic circuit
- 8. Waveform arithmetic circuit
 - Calculate the output duty cycle from the sine wave data and voltage data which are read from the RAM based on the electrical angle timer
 - · Output the calculation result to the waveform synthesis circuit

14.1 Outline of Motor Control

The following explains the method for controlling a brushless DC motor with sine wave drive. In a brushless DC motor, the rotor windings to which to apply electric current are determined from the rotor's magnetic pole position, and the current-applied windings are changed as the rotor turns. The rotor's magnetic pole position is determined using a sensor such as a hall IC or by detecting polarity change (zero-cross) points of the induced voltage that develops in the motor windings (sensorless control). For the sensorless case, the induced voltage is detected by applying electric current to two phases and not applying electric current to the remaining other phase. In this two-phase current on case, there are six current application patterns as shown in Table 14-1, which are changed synchronously with the phases of the rotor. In this two-phase current on case, the current on time in each phase is 120 degrees relative to 180 degrees of the induced voltage.

Current	Up	per Transis	stor	Lo	wer Transis	stor	Current on Winding
Application Pattern	u	v	w	x	x	z	Current on Winding
Mode 0	ON	OFF	OFF	OFF	ON	OFF	U→V
Mode 1	ON	OFF	OFF	OFF	OFF	ON	U-W
Mode 2	OFF	ON	OFF	OFF	OFF	ON	V→W
Mode 3	OFF	ON	OFF	ON	OFF	OFF	V-U
Mode 4	OFF	OFF	ON <	ON	OFF	OFF	₩→U
Mode 5	OFF	OFF	ON	OFF	ON	OFF	₩→V

Table 14-1 Current Application Patterns	Table 1	14-1	Current	Applica	tion P	atterns
---	---------	------	---------	---------	--------	---------

Note: One of the upper or lower transistors is PWM controlled.

For brushless DC motors, the number of revolutions is controlled by an applied voltage, and the voltage application is controlled by PWM. At this time, the current on windings need to be changed in synchronism with the phases of the voltage induced by revolutions. Control timing in cases where the current on windings are changed by means of sensorless control is illustrated in Figure 14-4. For three-phase motors, zero-crossing occurs six times during one cycle of the induced voltage (electrical angle 360 degrees), so that the electrical angle from one zero-cross point to the next is 60 degrees. Assuming that this period comprises one mode, the rotor position can be divided into six modes by zero-cross points. The six current application patterns shown above correspond one for one to these six modes. The timing at which the current application patterns are changed (commutation) is out of phase by 30 degrees of electrical angle, with respect to the position detection by an induced voltage.

Mode time is obtained by detecting a zero-cross point at some timing and finding an elapsed time from the preceding zero-cross point. Because mode time corresponds to 60 degrees of electrical angle, the following applies for the case illustrated in Figure 14-4.

1. Current on windings changeover (commutation) timing

30 degrees of electrical angle = mode time/2

Position detection start timing 45 degrees of electrical angle = mode time $\times 3/4$

3. Failure determination timing 120 degrees of electrical angle = mode time $\times 2$

Timings are calculated in this way. The position detection start timing in 2 is needed to prevent erroneous detection of the induced voltage for reasons that even after current application is turned off, the current continues flowing due to the motor reactance.

Control is exercised by calculating the above timings successively for each of the zero-cross points detected six times during 360 degrees of electrical angle and activating commutation, position detection start, and other operations according to that timing.

In this way, operations can be synchronized to the phases of the induced voltage of the motor.

The timing needed for motor control as in this example can be set freely as desired by using the internal timers of the microcontroller's PMD unit.

Also, sine wave control requires controlling the PWM duty cycle for each pulse. Control of PWM duty cycles is accomplished by counting degrees of electrical angle and calculating the sine wave data and voltage data at the counted degree of electrical angle.



Figure 14-2 Example of Sensorless DC Motor Control Timing Chart

14.2 Configuration of the Motor Control Circuit

The motor control circuit consists of various units. These include a position detection unit to detect the zero-cross points of the induced voltage or position sensor signal, a timer unit to generate events at three instances of electrical angle timing, and a three-phase PWM output unit to produce three-phase output PWM waveforms. Also included are an electrical angle timer unit to count degrees of electrical angle and a waveform arithmetic unit to calculate sinusoidal waveform output duty cycles. The input/output units are configured as shown in the diagram below. When using ports for the PMD function, set the Port input/output control register (P3CRi and P5CRi) to 0 for the input ports, and for the output ports, set the data output latch (P3i and P5i) to 1 and then the port input/output control register to 1. Other input/output ports can be set in the same way for use of the PMD function.



Figure 14-3 Block Diagram of the Motor Control Circuit

- Note 1: Always use the LDW instruction to set data in the 9, 12 and 16-bit data registers.
- Note 2: The EMG circuit initially is enabled. For PMD output, fix the EMG input port (P36 and P51) "H" high level or disable the EMG circuit before using for PMD output.
- Note 3: The EMG circuit initially is enabled. When using Port P3 and P5 as input/output IO ports, disable EMG.
- Note 4: When going to STOP mode, be sure to turn all of the PMD functions off before entering STOP mode.



14.3 Position Detection Unit

The Position Detection Unit identifies the motor's rotor position from input patterns on the position signal input port. Applied to this position signal input port is the voltage status of the motor windings for the case of sensorless DC motors or a Hall element signal for the case of DC motors with sensors included. The expected patterns corresponding to specific rotor positions are set in the PMD Output Register (MDOUT) beforehand, and when the input position signal and the expected value match as the rotation, a position detection interrupt (INTPDC) is generated. Also, unmatch detection mode is used to detect the direction of motor rotation, where when the status of the position detection interrupt is generated.

For three-phase brushless DC motors, there are six patterns of position signals, one for each mode, as summarized in Table 14-2 from the timing chart in Figure 14-2. Once a predicted position signal pattern is set in the MDOUT register, a position detection interrupt is generated the moment the position signal input port goes to mode indicated by this expected value. The position signals at each phase in the diagram are internal signals which cannot be observed from the outside.

Detection Mode	U Phase (PDU)	V Phase (PDV)	W Phase (PDW)
Mode 0	н	(/ L	H
Mode 1	н		
Mode 2	н	Н	(74)
Mode 3	L	Н	
Mode 4	L	У	Н
Mode 5		L)) н
	~ \ ((// < \	
17		\geq	





Figure 14-4 Configuration of the Position Detection Circuit

• The position detection unit is controlled by the Position Detection Control Register (PDCRA, PDCRB). After the position detection function is enabled, the unit starts sampling the position detection port with Timer 2 or in software. For the case of ordinary mode, when the status of the position detection input port matches the expected value of the PMD Output Register, the unit generates a position detection interrupt and finishes sampling, waiting for start of the next sampling.

When unmatch detection mode is selected for position detection, the unit stores the sampled status of the position detection port in memory at the time it started sampling. When the port input status changes from the status in which it was at start of sampling, an interrupt is generated.

- In unmatch detection mode, the port status at start of sampling can be read (PDCRC<PDTCT>).
- When starting and stopping position detection synchronously with the timer, position detection is started by Timer 2 and position detection is stopped by Timer 3.
- Sampling mode can be selected from three modes available: mode where sampling is performed only while PWM is on, mode where sensors such as Hall elements are sampled regularly, and mode where sampling is performed while the lower side is conducting current (when performing sampling only while PWM is on, DUTY must be set for all three phases in common).
- When sampling mode is selected for detecting position while the lower phases are conducting current, sampling is performed for a period from when the set sampling delay time has elapsed after the lower side started conducting current till when the current application is turned off. Sampling is performed independently at each phase, and the sampling result is retained while sampling is idle. If while sampling at some phase is idle, the input and the expected value at other phase being sampled match, position is detected and an interrupt is generated.

- A sampling delay is provided for use in modes where sampling is made while PWM is on or the lower phases are conducting current. It helps to prevent erroneous detection due to noise that occurs immediately after the transistor turns on, by starting sampling a set time after the PWM signal turned on.
- When detecting position while PWM is on or the lower phases are conducting current, a method can be selected whether to recount occurrences of matched position detection after being compared for each PWM signal on (logical sum of three-phase PWM signals) (e.g., starting from 0 in each PWM cycle) or counting occurrences of matching continuously (PDCRB<SPLMD> is used to enable/disable recounting occurrences of matching while PWM is on).

 $(\langle \frown \rangle$

14.3.2 Position Detection Circuit Register Functions

PDCRC			
5, 4	EMEM	Hold result of position detec- tion at PWM edge (Detect position detected po- sition)	These bits hold the comparison result of position detection at falling or rising edge of PWM pulse. Bits 5 and 4 are set to 1 when position is detected at the falling or the rising edge, respectively. They show whether position is detected in the current PWM pulse, during PWM off, or in the immediately preceding PWM pulse.
3	SMON	Monitor sampling status	When read, this bit shows the sampling status.
2 to 0	PDTCT	Hold position signal input sta- tus	This bit holds the status of the position signal input at the time position detection started in unmatch mode.

PDCRB			
7, 6	SPLCK	Sampling period	Select fc/2 ² , fc/2 ³ , fc/2 ⁴ , or fc/2 ⁵ for the position detection sampling period.
5, 4	SPLMD	Sampling mode	Select one of three modes: sampling only when PWM signal is active (when PWM is on), sampling regularly, or sampling when the lower side (X, Y, Z) phases are conducting current.
3 to 0	PDCMP	Sampling count	In ordinary mode, when the port status and the set expected value match and continuously match as many times as the sampling counts set, a position detection signal is output and an interrupt is generated. In unmatch detection mode, when the said status and value do not match and continuously unmatch as many times as the sampling counts set, a position detection signal is output and an interrupt is generated.

PDCRA	-		
7	SWSTP	Stop sampling in software	Sampling can be stopped in software by setting this bit to 1 (e.g., by writing to this register). Sampling is performed before stopping and when position detection results match, a position detection interrupt is generated, with sampling thereby stopped.
6	swstt <	Start sampling in software	Sampling can be started by setting this bit to 1 (e.g., by writing to this register).
5	SPTM3	Stop sampling using Timer 3	Sampling can be stopped by a trigger from Timer 3 by setting this bit to 1. Sampling is performed before stopping and when position detection results match, a po- sition detection interrupt is generated, with sampling thereby stopped.
4	STTM2	Start sampling using Timer 2	Sampling can be started by a trigger from Timer 3 by setting this bit to 1.
3	PDNUM	Number of position signal in- put pins	Select whether to use three pins (PDU/PDV/PDW) or one pin (PDU only) for position signal input. When one pin is selected, the expected values of PDV and PDW are ignored. When performing position detection with two pins or a pin other than PDU, position signal input can be masked as 0 by setting unused pin(s) for output.
2	RCEN	Recount occurrences of matching when PWM is on	When performing sampling while PWM is on, occurrences of matching are recounted each time PWM signal turns on by setting this bit to 1 (when recounting occurrences of matching, the count is reset each time PWM turns off). When this bit is set to 0, occurrences of matching are counted continuously regardless PWM interval.
1	DTMD	Position detection mode	Setting this bit to 0 selects ordinary mode where position is detected when the expected value set in the register and the port input unmatch and then match. Setting this bit to 1 selects unmatch detection mode where position is detected at the time the port status changes to another one from the status in which it was when sampling started.
0	PDCEN	Position detection function	The position detection function is activated by setting this bit to 1.

SDREG

6 to 0	SDREG	Sampling delay	Set a time for which to stop sampling in order to prevent erroneous detection due to noise that occurs immediately after PWM output turns on (immediately after the transistor turns on). (Figure 14-5)
--------	-------	----------------	---

14.3 Position Detection Unit



Figure 14-5 Position Detection Sampling Timing with the PWMON Period Selected



Position Detection Circuit Registers [Addresses (PMD1 and PMD2)]

PDCRC	7	6	5 4	3	2	1	0				
(01FA2H)) -	-	EMEM	SMON		PDTCT		(Initial value: **00 0000)			
(01FD2H))										
	5, 4	EMEM	Hold result of position at PWM edge (Deter detected position)	on detection ct position	00: Detect 01: Detect 10: Detect 11: Detect	ted in the cur ted while PW ted in the cur ted in the pre	rent pulse M off rent pulse ceding pu	e Contraction of the second se			
	3	SMON	Monitor sampling sta	atus	0: Samplir 1: Samplir	ng idle ng in progres	s		ĸ		
	2 to 0	PDTCT	Hold position signal	Holds the mode. Bits	status of the s 2 to 0 corre	position s spond to	signal input during unmatch detection W, V, and U phases.				
						\sim	\sim	\sim			
PDCRB	7	6	5 4	3	2	1	0				
(01FA1H)) 5	SPLCK	SPLMD		PDC	MP)	(Initial value: 0000 0000)			
(01FD1H))										
	7, 6	SPLCK	Select sampling inpu	ut clock	00: fc/2 ² [4 01: fc/2 ³ (4 10: fc/2 ⁴ (8 11: fc/2 ⁵ (1	Hz] (200 ns a 400 ns at 20 300 ns at 20 1.6 μs at 20 1	t 20 MHz) MHz) MHz) MHz)				
	5, 4	SPLMD	Sampling mode	Sampling mode		Sampling mode 00: Sample when PWM is on 01: Sample regularly 10: Sample when lower phases conducting current 11: Reserved					R/W
	3 to 0	PDCMP	Position detection m counts	Position detection matched counts) and 1 ar	e assumed to be one time.)			
))	5						
Not	te:When o	changing setti	ng, keep the PDCE	N bit reset	to "0" (dis	able positio	n detect	ion function).			
			$\langle (\vee \rangle) \rangle$								
				\sim	$(// \uparrow$)					
	7	6	5 4	3	2	1	0				
(01FA0H)	SWST	P SWSTT	SPTM3 STTM2	PDNUM	RCEN	DTMD	PDCEN	(Initial value: 0000 0000)			
(01FD0H))					Į	-	(,, ,			
	<	\searrow			>						
1			\land	\sim	0: No opo	ration					
	7	SWSTP	Stop sampling in sol	ftware	1: Stop sa	mplina					
\sim					0. No ope	ration			W		
	6	SWSTT	Start sampling in so	ftware	1: Start sa	Impling					
$\langle \langle \langle \rangle$	5	SPTM3	Stop sampling using	Stop sampling using Timer 3		0: Disable 1: Enable					
	4	STTM2	Start sampling using Timer 2		0: Disable 1: Enable						
	3	PDNUM	Number of position signal input pins		t 0: Compare three pins (PDU/PDV/PDW) 1: Compare one pin (PDU) only			V/PDW)	DAA		
	2	RCEN	Recount occurrence ing when PWM is or	s of match-	0: Continu 1: Recourt	e counting fr t each time F	om previc PWM turn	ously PWM on son	rt/VV		
	1	DTMD	Position detection m	iode	0: Ordinar 1: Unmato	y mode h detection r	node				
	0	PDCEN	Enable/Disable position function	tion detec-	0: Disable 1: Enable	(Sampling st	arts)				

14.3 Position Detection Unit

Note:Read-modify-write instructions, such as a bit manipulation instruction, cannot access the PDCRA because it contains a write only bit.



14.4 Timer Unit



The timer unit has an up counter (mode timer) which is cleared by a position detection interrupt (INTPDC). Using this counter, it can generate three types of timer interrupts (INTTMR1 to 3). These timer interrupts may be used to produce a commutation trigger, position detection start trigger, etc. Also, the mode timer has a capture function which automatically captures register data in synchronism with position detection or overload protection. This capture function allows motor revolutions to be calculated by measuring position detection intervals.

14.4.1 Configuration of the Timer Unit

The timer unit consists mainly of a mode timer, three timer comparator, and mode capture register, and is controlled by timer control registers and timer compare registers.

- The mode timer can be reset by a signal from the position detection circuit, Timer 3, or overload protective circuit. If the mode timer overflows without being reset, it stops at FFFFH and sets an overflow flag in the control register.
- The value of the mode timer during counting can be read by capturing the count in software and reading the capture register.
- Timer 1 and Timers 2 and 3 generate an interrupt signal by magnitude comparison and matching comparison, respectively. Therefore, Timer 1 can generate an interrupt signal even when it could not write to the compare register in time and the counter value at the time of writing happens to exceed the register's set value.
- When any one of Timers 1 to 3 interrupts occurs, the next interrupts can be enabled by writing a new value to the respective compare registers (CMP1, CMP2, CMP3).
- When capturing by position detection is enabled, the capture register has the timer value captured in it each time position is detected. In this way, the capture register always holds the latest value.

Page 147

14.4 Timer Unit

1

14.4.1.1 **Timer Circuit Register Functions**

MTCRB

ſ

7	DBOUT	Debug output	Debug output can be produced by setting this bit to 1. Because interrupt signals to the interrupt control circuit are used for each interrupt, hardware debugging without software delays are possible. See the debug output diagram (Figure 14-8). Output ports: P67 for PMD1, P77 for PMD2.
5	TMOF	Mode timer overflow	This bit shows that the timer has overflowed.
3	CLCP	Capture mode timer by over- load protection	When this bit is set to 1, the timer value can be captured using the overload protection signal (CL) as a trigger.
2	SWCP	Capture mode timer in soft- ware	When this bit is set to 1, the timer value can be captured in software (e.g., by writing to this register).
1	PDCCP	Capture mode timer by posi- tion detection	When this bit is set to 1, the timer value can be captured using the position detection signal as a trigger.

MTCRA			
7, 6, 5	ТМСК	Select clock	Select the timer clock.
4	RBTM3	Reset mode timer from Timer 3	When this bit is set to 1, the mode timer is reset by a trigger from Timer 3.
3	RBCL	Reset mode timer by overload protection	When this bit is set to 1, the mode timer is reset by the overload protection signal (CL) as a trigger.
2	SWRES	Reset mode timer in software	When this bit is set to 1, the mode timer is reset in software (e.g., by writing to this register)
1	RBPDC	Reset mode timer by position detection	When this bit is set to 1, the mode timer is reset by the position detection signal as a trigger.
0	TMEN	Enable/disable mode timer	The mode timer is started by setting this bit to 1. Therefore, Timers 1 to 3 must be set with CMP before setting this bit. If this bit is set to 0 after setting CMP, CMP settings become ineffective.

MCAP	Mode capture	Position detection interval can be read out.
CMP1	Timer 1 (commutation)	Timers 1 to 3 are enabled while the mode timer is operating. An interrupt can be generated
CMP2	Timer 2 (position detection start)	once by setting the corresponding bit in this register. The interrupt is disable when an in-
CMP3	Timer 3 (overflow)	even if data is same.



Figure 14-8 DBOUT Debug Output Diagram

Timer Circuit Registers [Addresses (PMD1 and PMD2)]

MTCRB	7	6	5	4	3	2	1	0		
(01FA5H)	DBOU	т -	TMOF	-	CLCP	SWCP	PDCCP	-	(Initial value: 0*0*0 000*)	
(01FD5H)					<u> </u>					
										-
ſ	7		Debug or	itout		0: Disabl	e		$\langle () \rangle$	R/W
	1	88001	Debug of	aipui		1: Enable	e (P67 for Pl	MD1, P77 fo	or PMD2)	1000
	5	TMOE	Mada tim	or overflow	,	0: No ove	erflow	\sim	$(// \land)$	Б
	5	TMOF	wode um	ler overnow		1: Overflo	owed		$\langle \mathcal{O} \rangle$	ĸ
	2		Capture r	node timer	by overload	0: Disabl	е	(C)		DAA
	3	ULUP	protection	n		1: Enable	e			R/W
	0	SWOD	Conture	mada timar	in coffwore	0: No ope	eration			
	2	SWCP	Capture	mode timer	in software	1: Captur	re	$(\)$		vv
Γ		DDOOD	Capture	mode timer	by position	0: Disabl	e			DAM
	1	PDCCP	detection		51	1: Enable		\sim	4	R/W
-))	Q (0)	

Note: Read-modify-write instructions, such as a bit manipulation instruction, cannot access the MTCRB because it contains a write-only bit.

MTCRA	7	6	5	4	3	2	1	0(((/ 5)
(01FA4H)		TMCK		RBTM3	RBCL	SWRES	RBPDC	TMEN	(Initial value: 0000 0000)
(01FD4H)				•	\sim				

				000: fc/2³ (400 ns at 20 MHz)	
				010: fc/2 ⁴ (800 ns at 20 MHz)	
				100: fc/2 ⁵ (1.6 μs at 20 MHz)	
	7, 6, 5	тиск	Salaat alaak	110: fc/2 ⁶ (3.2 µs at 20 MHz)	
		TNICK	Select Clock	001: fc/2 ⁷ (6.4 μs at 20 MHz)	
			$\left(\left(\right) \right)$	011: Reserved	
				101: Reserved	R/W
				111: Reserved	
		DDTMO	Densit mender timere from Timer 2	0. Disable	
	4	RBIM3	Reset mode timer from Timer 3	1: Enable	
	2	PPCI	Reset mode timer by overload	0: Disable]
	3 <	RBUL	protection	1: Enable	
	2		Deast mode times in astructo	0: No operation	10/
	2	SWRES	Reset mode timer in software	1: Reset	vv
\sim		PPPDC	Reset mode timer by position	0: Disable	
	$\bigcirc \bigcirc \bigcirc$	KBFDC	detection	1: Enable	DAA
			Enable/dicable mode timer	0: Disable	r./W
7				1: Enable timer start	

Note 1: When changing MTCRA<TMCK> setting, keep the MTCRA<TMEN> bit reset to "0" (disable mode timer).

Note 2: Read-modify-write instructions, such as a bit manipulation instruction, cannot access the MTCRA because it contains a write-only bit.

MCAP	F	E	D	С	В	A	9	8	7	6	5	4	3	2	1	0		2000
(01FD7H, 01FD6H)	DF	DE	DD	DC	DB	DA	D9	D8	D7	D6	D5	D4	D3	D2	D1	D0	(Initial value: 0000 0000 (0000)	0000
MC	AP		Mode	captu	re				P	osition	detect	tion int	terval		<	$\overline{}$		R
																Ĉ		
CMP1 (01FA9H, 01FA8H)	F	E	D	C	В	A	9	8	7	6	5	4	3	2	1	0	(Initial value: 0000 0000 (0000
(01FD9H, 01FD8H)	DF	DE	DD	DC	DB	DA	D9	D8	D7	Db	D5	D4				<u>}</u>	0000)	
CMP2	F	E	D	С	В	A	9	8	7	6	5	4	3	2	X	0	_	
(01FABH, 01FAAH) (01FDBH, 01FDAH)	DF	DE	DD	DC	DB	DA	D9	D8	D7	D6	D5	D4	D3	D2-	Ы	D0	(Initial value: 0000 0000 0 0000)	0000
01170							_					Z		\geq				
CMP3 (01FADH, 01FACH)	F	E	D	C	B	A	9	8	7	6	5	4	3	2	1	0	(Initial value: 0000 0000 (0000
(01FDDH, 01FDCH)	DF	DE		DC	DB	DA	Da	Do	Dī	Do			<u> </u>	02			0000)	
CMP1			Timer	1					М	agnitu	de con	nparis	on con	npare	registe	ər		
CMP2			Timer	2					м	atching	g com	parisor	n com	oare re	egister	6		R/W
CMP3			Timer	3					M	atching	g com	parisor	n com	oare re	gister	\sim		
regis			se the	se reç														



14.4.1.2 Outline Processing in the Timer Unit

14.5 Three-phase PWM Output Unit

The Three-phase PWM Output Unit has the function to generate three-phase PWM waves with any desired pulse width and the commutation function capable of brushless DC motor control. In addition, it has the protective functions such as overload protection and emergency stop functions necessary to protect the power drive unit, and the dead time adding function which helps to prevent the in-phase upper/lower transistors from getting shorted by simultaneous turn-on when switched over.

For the PWM output pin (U,V,W,X,Y,Z), set the port register PxDR and PxCR (x = 3,5) to 1. The PWM output initially is set to be active low, so that if the output needs to be used active high, set up the MDCRA Register accordingly.

14.5.1 Configuration of the three-phase PWM output unit

The three-phase PWM output unit consists of a pulse width modulation circuit, commutation control circuit, protective circuit (emergency stop and overload), and a dead time control circuit.

14.5.1.1 Pulse width modulation circuit (PWM waveform generating unit)

This circuit produces three-phase independent PWM waveforms with an equal PWM frequency. For PWM waveform mode, triangular wave modulation or sawtooth wave modulation can be selected by using the PMD Control Register (MDCRA) bit 1. The PWM frequency is set by using the PMD Period Register (MDPRD). The following shows the relationship between the value of this register and the PWM counter clock set by the MDCRB Register, PWMCK.

Sawtooth wave PWM [·] M	DPRD R	Register set value $=$ -		1
Sawtoour wave I will in		legister set value	PWM frequency	$[Hz] \times PWMCK$

Triangular wave PWM: MDPRD Register set value = $\frac{1}{PWM \text{ frequency } [H_Z] \times 2 \times PWMCK}$

The PMD Period Register (MDPRD) is comprised of dual-buffers, so that CMPU, V, W Register is updated with PWM period.

When the waveform arithmetic circuit is operating, the PWM waveform output unit receives calculation results from the waveform arithmetic circuit and by using the results as CMPU, V, W Register set value, it outputs independent three-phase PWM waveforms. When the waveform calculation function is enabled by the waveform arithmetic circuit and transfer of calculation results into the CMPU to W Registers is enabled (with EDCRA Register bit 2), the CMPU to W Registers are disabled against writing.

When the waveform calculation function is enabled (with EDCRA Register bit 1) and transfer of calculation results into the CMPU, V, W Registers is disabled (with EDCRA Register bit 4), the calculation results are transferred to the buffers of CMPU, V, W Registers, but not output to the port.

Read-accessing the CMPU, V, and W registers can read the calculation results of the waveform arithmetic circuit that have been input to a buffer. After changing the read calculation result data by software, writing the changed data to the CMPU, V, and W registers enables an arbitrary waveform other than a sinusoidal wave to be output. When the registers are read after writing, the values written to the registers are read out if accessed before the calculation results are transferred after calculation is finished.



The values of the PWM Compare Registers (CMPU/V/W) and the carrier wave generated by the PWM Counter (MDCNT) are compared for the relative magnitude by the comparator to produce PWM waveforms.

The PWM Counter is a 12-bit up/down counter with a 100 ns (at fc = 20 MHz) resolution.

For three-phase output control, two methods of generating three-phase PWM waveforms can be set.

- 1. Three-phase independent mode: Values are set independently in the three-phase PMD Compare Registers to produce three-phase independent PWM waveforms. This method may be used to produce sinusoidal or any other desired drive waveforms.
- 2. Three-phase common mode: A value is set in only the U-phase PMD Compare Register to produce three in-phase PWM waveforms using the U phase set value. This method may be used for DC motor square wave drive.

The three-phase PMD Compare Registers each have a comparison register to comprise a dual-buffer structure. The values of the PMD Compare Registers are loaded into their respective comparison registers synchronously with PWM period.



14.5.1.2 Commutation control circuit

Output ports are controlled depending on the contents set in the PMD Output Register (MDOUT). The contents set in this register are divided into two, one for selecting the synchronizing signal for port output, and one for setting up port output. The synchronizing signal can be selected from Timers 1 or 2, position detection signal, or without sync. Port output can be synchronized to this synchronizing signal before being further synchronized to the PWM signal sync. The MDOUT Register's synchronizing signal select bit becomes effective immediately after writing. Other bits are dual-buffered, and are updated by the selected synchronizing signal.

Example: Commutation timing for one timer period with PWM synchronization specified



Output on six ports can be set to be active high or active low independently of each other by using the MDCRA Register bits 5 and 4. Furthermore, the U, V, and W phases can individually be selected between PWM output and H/L output by using the MDOUT Register bits A to 8 and 5 to 0. When PWM output is selected, PWM waveforms are output; when H/L output is selected, a waveform which is fixed high or low is output. The MDOUT Register bits E to C set the expected position signal value for the position detection circuit.



Figure 14-10 Pulse Width Modulation Circuit





14.5.2 Register Functions of the Waveform Synthesis Circuit

MDCRB			\land
PWMCK	Select PWM counter clock	Select PWM counter clock.	
		/	
		\sim ()	\langle / \rangle
		$\mathcal{A}(\bigcirc)$	
		(O/\uparrow)	\sim
		()	
			())
			2
	(
		\leq \wedge \vee	
	$((\)$		
	$(\sqrt{2})$		
		$\sim (7/5)$	
	\sim		
		\searrow	
/			
$\langle \langle \rangle$		<u>></u>	
		\vee	
\checkmark	\sim		

TOSHIBA

MDCRA			
7	HLFINT	Select half-period interrupt	When this bit is set to 1, INTPWM is generated every half period (at triangular wave peak and valley) in the case of center PWM output and PINT = 00. In other cases, this setting has no meaning.
6	DTYMD	DUTY mode	Select whether to set the duty cycle independently for three phases using the CMPU to W Registers or in common for all three phases by setting the CMPU Register only.
5	POLH	Upper-phase port polarity	Select the upper-phase output port polarity. Make sure the waveform synthesis function (MDCRA Register bit 0) is idle before selecting this port polarity.
4	POLL	Lower-phase port polarity	Select the lower-phase output port polarity. Make sure the waveform synthesis function (MDCRA Register bit 0) is idle before selecting this port polarity.
3, 2	PINT	PWM interrupt frequency	Select the frequency at which to generate a PWM interrupt from four choices available: every PWM period or once every 2, 4, or 8 PWM periods. When setting of this bit is altered while operating, an interrupt may be generated at the time the bit is altered.
1	PWMMD	PWM mode	Select PWM mode. PWM mode 0 is an edge PWM (sawtooth wave), and PWM mode 1 is a center PWM (triangular wave)
0	PWMEN	Enable/Disable waveform generation circuit	When enabling this circuit (for waveform output), be sure to set the output port polarity and other bits of this register (other than MDCRA bit 0) beforehand.

		generation offeat	
DTR			
DTR	Dea	ad time	Set the dead time between the upper-phase and lower-phase outputs.
MDOUT			

MDOUT			
F	UPDWN	PWM counter flag	This bit indicates whether the PWM counter is counting up or down. When edge PWM (sawtooth wave) is selected, it is always set to 0.
E, D, C	PDEXP	Mode compare register	Set the data to be compared with the position detection input port. The comparison data is adopted as the expected value simultaneously when port output sync settings made with MDOUT are reflected in the ports. (This is the expected position detection input value for the output set with MDOUT next time.)
В	PSYNC	Select PWM synchronization	Select whether or not to synchronize port output to PWM period after being synchronized to the synchronizing signal selected with SYNCS. If selected to be synchronized to PWM, output is kept waiting for the next PWM after being synchronized with SYNCS. Waveform settings are overwritten if new settings are written to the register during this time, and output is generated with those settings.
А	WPWM		
9	VPWM	Control UVW-phase PWM	Set U, V, and W-phase port outputs. (See the Table 14-3)
8	UPWM	outputs	
7, 6	SYNCS	Select port output sync signal	Select the synchronizing signal with which to output UVW-phase settings to ports. The synchronizing signal can be selected from Timers 1 or 2, position detection, or asynchronous. Select asynchronous when the initial setting, otherwise the above setting isn't reflected immediately.
5, 4	woc		
3, 2	voc	Control UVW-phase outputs	Set U, V, and W-phase port outputs. (See the Table 14-3)
1, 0	UOC	$\sum $	~
MDC	T PWM c	ounter	This is a 12-bit read-only register used to count PWM periods.
			4
MDPF	RD Set PW	/M period	This register determines PWM period, and is dual-buffered, allowing PWM period to be altered even while the PWM counter is operating. The buffers are loaded every PWM period. When 100 ns is selected for the PWM counter clock, make sure the least significant bit is set to 0.

CMPU CMPV CMPW	Set PWM pulse width	This comparison register determines the pulse widths output in the respective UVW pha- ses. This register is dual-buffered, and the pulse widths are determined by comparing the buffer and PWM counter.
----------------------	---------------------	--

14.5 Three-phase PWM Output Unit

MDCRB	7		6	5	4	3	2	1	0		
(01FAFH)	-		-	-	-	-	-	PW	мск	(Initial value: **** **00)	
(01FDFH)											
	1, 0	PW	PWMCK	PWM c	counter Selec	ct clock	00: fc/2 01: fc/2 ² 10: fc/2 ³ 11: fc/2 ⁴	[Hz] (100 ns (200 ns at 2 (400 ns at 2 (800 ns at 2	at 20 MHz 20 MHz) 20 MHz) 20 MHz) 20 MHz)		R/W

Waveform Synthesis Circuit Registers [Addresses (PMD1 and PMD2)]

Note: When changing setting, keep the PWMEN bit reset to "0" (disable wave form synthesis function).

MDCRA	7	6	5	4	3	2	4	0	
(01FAEH)	HLFINT	DTYMD	POLH	POLL	PINT		PWMMD	PWMEN	(Initial value: 0000 0000)
(01FDEH)							27	\mathcal{I}	

	1	1		1
7	HLFINT	Select half-period interrupt	0: Interrupt as specified in PINT 1: Interrupt every half period when PINT = 00	
6	DTYMD	DUTY mode	0: U phase in common 1: Three phases independent]
5	POLH	Upper-phase port polarity	0: Active low 1: Active high	
4	POLL	Lower-phase port polarity	0: Active low 1: Active high	
3, 2	PINT	Select PWM interrupt (trigger)	00: Interrupt every period01: Interrupt once every 2 periods10: Interrupt once every 4 periods11: Interrupt once every 8 periods	
1	PWMMD	PWM mode	0: PWM mode0 (Edge: Sawtooth wave) 1: PWM mode1 (Center: Triangular wave)	
0	PWMEN	Enable/disable waveform syn- thesis function	0: Disable 1: Enable (Waveform output)	

DTR	7 6	5	4	3	2	1	0	_	
(01FBEH)	- 25- 1	D5	D4	D3	D2	D1	D0	(Initial value: **00 0000)	
(01FEEH)	\sim			••		•	•	-	
\sim	(\bigcirc)		\mathcal{A}						
	5 to 0 DTR	Dead tim	le	\diamond	2 ³ /fc × 6	bit (maximu	im 25.2 μs	at 20 MHz)	R/W

Note: When changing setting, keep the MDCRA<PWMEN> bit reset to "0" (disable wave form synthesis function).

TOSHIBA

MDOUT	F	E	D	С	В	Α	9	8					
(01FB3H	UPDW	N	PDEXP		PSYNC	WPWM	VPWM	UPWM					
(01FE2H)	7	6	5	4	3	2	1	0					
01FE2H)	S	SYNCS	WO	C	VC	C	UC	C	(Initial value: 00000000 00000000)				
						-							
	F	UPDWN	PWM cou	nter flag		0: Counti 1: Counti	ng up ng down		$\langle \bigcirc \rangle$	R			
	E, D, C	PDEXP	Comparis detection	on register	for position	bit E: W- bit D: V-p bit C: U-p	bit E: W-phase expected value bit D: V-phase expected value bit C: U-phase expected value						
	В	PSYNC	Select PV	VM synchro	onization	0: Asynchronous 1: Synchronized							
	А	WPWM	W-phase	PWM outp	out	0: H/L lev 1: PWM v	vel output waveform o	utput					
	9	VPWM	V-phase F	PWM outpu	ut	0: H/L level output 1: PWM waveform output							
	8	UPWM	U-phase F	PWM outpu	ut	0: H/L level output 1: PWM waveform output							
	7, 6	SYNCS	Select por synchroni	rt output zing signal	(00: Asynchronous 01: Synchronized to position detection 10: Synchronized to Timer 1							
	5, 4	WOC	Control W	/-phase ou	tput	$\langle \rangle$			$\bigcirc)$				
	3, 2	VOC	Control V	-phase out	put	See the table 1-3							
	1, 0	2 VOC Control V-phase output 0 UOC Control U-phase output		put	$\overline{\mathbf{A}}$ $(($ $))$								

14.5.3 Port output as set with UOC/VOC/WOC bits and UPWM/VPWM/WPWM bits

Table 14-3 Example of Pin Output Settings

U-phase output polarity: Active high (POLH.POLL = 1)

		(re	EII,I OLL	- (
			UP	мм	1	
	UOĈ	∕_1: PWN	1 output	0: H/L lev	vel output	
	Z	U phase	X phase	U phase	X phase	\sim
	00	PWM	PWM	5	L	
\sim	01))L	PWM	ť	H	
	10/1	PWM	\wedge (Н	Ĺ	
\square		PWM	PWM	P	н	
			\sim			

U-phase output polarity: Active low (POLH,POLL = 0)

	UPWM									
UOC	1: PWM	1 output	0: H/L level output							
	U phase	X phase	U phase	X phase						
0 0	PWM	PWM	Н	Н						
0 1	Н	PWM	Н	L						
10	PWM	Н	L	Н						
11	PWM	PWM	L	L						

MDCNT (01FB5H, 01F	B4H)	F -	E -	D -	C -	B DB	A DA	9 D9	8 D8	7 D7	6 D6	5 D5	4 D4	3 D3	2 D2	1 D1	0 D0	(Initial value:	
(01FE5H, 01F	E4H)	ii			<u>.</u>							1	ļ				I]	
																<	\sum		·
	В	to 0		PWM	count	er				F	PWM pe	eriod c	ounter	value			À	\rightarrow	R
		_	_	_		_				_		_					C	\bigcirc	
MDPRD		F	E	U	C	В	A	9	8	1	6	5	4	3	2	A		(Initial value:	
(01FB7H, 01F	B6H) E6H)	-	-	-	-	DB	DA	D9	D8	D7	D6	D5	D4	D3	D2	D1	<u>19</u>	****00000000000)	
	В	to 0		PWM	period					F	PWM pe	eriod N	IDPRE)≥010	H	Ŋ		\frown	R/W
CMPU		F	E	D	С	в	A	9	8	7	6	5	4	3	2	1	0		
(01FB9H, 01F	B8H)	-	-	-	-	DB	DA	D9	D8	D7	D6	D5(704	D3	D2	D1	DO	(Initial value: ****000000000000)	
(01FE9H, 01F	(01FE9H, 01FE8H)																		
											1	\bigcirc	\geq			6	7		
CMPV		F	Е	D	С	В	A	9	8	7	6	5	4	3	2	((0		
(01FBBH, 01F	BAH)	-	-	-	-	DB	DA	D9	D8	DZ	D6	D5	D4	D3	D2	_D1	DO	(Initial value: ****000000000000)	
(01FEBH, 01F	EAH)								6	$\left(\right)$	\searrow	~				75)		
								<	4(\geq		$(\ $				/		
CMPW		F	E	D	С	В	A	9	8	$\stackrel{7}{\checkmark}$	6	5	4	3		1	0	(Initial value:	
(01FBDH, 01F	BCH) ECH	-	-	-	-	DB	DA	(D9	D8	D7	D6	D5	D4	D3	D2	D1	D0	****000000000000)	
	ļ	CMPU		PWM	comp	are U r	egiste	Ŋ		s	Set U-pl	nase d	uty cy	cle					
B to 0 CMPV PWM compare V register									s	Set V-pl	nase d	uty cyc	cle					R/W	
CMPW PWM compare W register Set W-phase duty cycle																			
				Ň	\leq		_			\geq	$\overline{}$								
		\sim			\searrow			/	$\overline{\langle}$		/								

14.5.4 Protective Circuit

This circuit consists of an EMG protective circuit and overload protective circuit. These circuits are activated by driving their respective port inputs active.



a. EMG protective circuit

This protective circuit is used for emergency stop, when the EMG protective circuit is enabled. When the signal on EMG input port goes active (negative edge triggered), the six ports are immediately disabled high-impedance against output and an EMG interrupt (INTEMG) is generated. The EMG Control Register (EMGCRA) is used to set EMG protection. If the EMGCRA<EMGST> shows the value "1" when read, it means that the EMG protective circuit is operating. To return from the EMG protective state, reset the MDOUT Register bits A to 0 and set the EMGCRA<RTE> to 1. Returning from the EMG protective state is effective when the EMG protective input has been released back high. To disable the EMG function, set data "5AH" and "A5H"sequentially in the EMG disable Register (EMGREL) and reset the EMGCRA<EMGEN> to 0. When the EMG function is disabled, EMG interrupts (INTEMG) are not generated.

The EMG protective circuit is initially enabled. Before disabling it, fully study on adequacy.

b. Overload protective circuit

The overload protective circuit is set by using the EMG Control Registers (EMGCRA/B). To activate overload protection, set the EMGCRB<CLEN> to 1 to enable the overload protective circuit. The circuit starts operating when the overload protective input is pulled low.

To return from overload state, there are three methods to use: return by a timer (EMGCRB<RTTM1>), return by PWM sync (EMGCRB<RTPWM>), or return manually (EMGCRB<RTCL>). These methods are usable when the overload protective input has been released back high.

The number of times the overload protective input is sampled can be set by using the EMG-CRA<CLCNT>. The sampling times can be set in the range of 1 to 15 times at 200 ns period (when fc = 20 MHz). If a low level is detected as many times as the specified number, overload protection is assumed.

The output disabled phases during overload protection are set by using the EMGCRB<CLMD>. This facility allows selecting to disable no phases, all phases, PWM phases, or all upper phases/all lower phases. When selected to disable all upper phases/all lower phases, port output is determined by their turn-on status immediately before being disabled. When two or more upper phases are active, all upper phases are turned on and all lower phases are turned off; when two or more lower phases are active, all upper phases are turned off and all lower phases are turned on.

When output phase are cut off, output is inactive (low in the case of high active). When the overload protective circuit is disabled, overload protective interrupts (INTCLM) are not generated.



14.5.5 Functions of Protective Circuit Registers

EMGR	EL EMG d	lisable	The EMG protective circuit is disable from the disabled state by writing "5AH" and "A5H" to this register in that order. After that, the EMGCRA Register needs to be set.
EMGCRB			
			When this bit is set to 1, the motor control circuit is returned from overload protective state

7	RTCL	Return from overload protec- tive state	in software (e.g., by writing to this register). Also, the current state can be known by reading this bit. MDOUT outputs at return from the overload protective state remain as set before the overload protective input was driven active.
6	RTPWM	Return by PWM sync	When this bit is set to 1, the motor control circuit is returned from overload protective state by PWM sync. If RTCL is set to 1, RTCL has priority.
5	RTTM1	Return by timer sync	When this bit is set to 1, the motor control circuit is returned from overload protective state by Timer 1 sync. If RTCL is set to 1, RTCL has priority.
4	CLST	Overload protective state	The status of overload protection can be known by reading this bit.
3, 2	CLMD	Select output disabled phases during overload protection	Select the phases to be disabled against output during overload protection. This facility allows selecting to disable no phases, all phases, PWM phases, or all upper phases/all lower phases.
1	CNTST	Stop counter during overload protection	Can stop the PWM counter during overload protection.
0	CLEN	Enable/Disable overload pro- tection	Enable or disable the overload protective function.

EMGCRA

LINGOIN			
7 to 4	CLCNT	Overload protection sampling time	Set the length of time the overload protective input port is sampled.
2	EMGST	EMG protective state	The status of EMG protection can be known by reading this bit.
1	RTE	Return from EMG protective state	The motor control circuit is returned from EMG protective state by setting this bit to "1" . When returning, set the MDOUT Register A to 0 bits to "0" . Then set the EMGCRA Register bit 1 to "1" and set MDOUT waveform output. Then set up the MDCRA Register.
0	EMGEN	Enable/Disable EMG protec- tive circuit	The EMG protective circuit is activated by setting this bit to 1. This circuit initially is enabled. (To disable this circuit, make sure key code 5AH and A5H are written to the EMGREL1 Register beforehand.)
	<		

Protective	Protective Circuit Registers [Addresses (PMD1 and PMD2)]											
EMGREL	7	6	5	4	3	2	1	0				
(01FBFH)	D7	D6	D5	D4	D3	D2	D1	D0	(Initial value: 0000 0000)			
(01FEFH)												
~	$(\bigcirc$			41								
	7 to 0 EM	GREL	EMG dis	able	\rightarrow	Can disa	ble by writin	ig 5AH and	then A5H.	W		
	\sum	($\langle \rangle$	())								

Note: Read-modify-write instructions, such as a bit manipulation instruction, cannot access the EMGREL register because this register is write only.

C		

14.5 Three-phase PWM Output Unit

EMGCRB	7	6	5	4	3	2	1	0	
(01FB1H)	RTCL	RTPWM	RTTM1	CLST	CLMD		CNTST	CLEN	(Initial value: 0000 0000)
(01FE1H)							•		1

7	RTCL	Return from overload protective state	0: No operation 1: Return from protective state	w
6	RTPWM	Enable/Disable return from overload protective state by PWM sync	0: Disable 1: Enable	DAA
5	RTTM1	Enable/Disable return from overload protective state by tim- er 1	0: Disable 1: Enable	K/W
4	CLST	Overload protective state	0: No operation 1: Under protection	R
3, 2	CLMD	Select output disabled phases during overload protection	00: No phases disabled against output 01: All phases disabled against output 10: PWM phases disabled against output 11: All upper/All lower phases disabled against output (Note)	
1	CNTST	Stop PWM counter during over- load protection	0: Do not stop 1: Stop the counter	R/W
0	CLEN	Enable/Disable overload pro- tective circuit	0. Disable 1: Enable	

Note: If during overload protection the port output state in two or more upper phases is on, all lower phases are disabled and all upper phases are enabled for output; when two or more lower phases are on, all upper phases are disabled and all lower phases are enabled for output.

EMGCRA	7	6	5	4	3	2	<u>1</u>	0	
(01FB0H)		CLC	CNT)	EMGST	RTE	EMGEN	(Initial value: 0000 *001)
(01FE0H)			((776			\mathbb{Z}		

7 to 4	CLCNT	Overload protection sampling number of times.	2²/fc × n (n = 1 to 15, 0 and 1 are set as 1 at 20 MHz)	R/W
2	EMGST	EMG protective state	0: No operation 1: Under protection	R
1 <	RTE	Return from EMG state	0: No operation 1: Return from protective state (Note 1)	w
0	EMGEN	Enable/Disable EMG protective circuit	0: Disable 1: Enable	R/W

Note 1: An instruction specifying a return from the EMG state is invalid if the EMG input is "L".

Note 2: Read-modify-write instructions, such as a bit manipulation instruction, cannot access the EMGCRB or EMGCRA register because these registers contain write-only bits.

14.6 Electrical Angle Timer and Waveform Arithmetic Circuit

Electrical Angle Timer



14.6.1 Electrical Angle Timer and Waveform Arithmetic Circuit

The Electrical Angle Timer finishes counting upon reaching the value set by the Period Set Register (EDSET). The Electrical Angle Timer counts 360 degrees of electrical angle in the range of 0 to 383 (17FH) and is cleared to 0 upon reaching 383. In this way, it is possible to obtain the electrical angle of the frequency proportional to the value set by the Period Set Register. The period with which to count up can be corrected by using the Period Correction Register, allowing for fine adjustment of the frequency. The electrical angles counted by the Electrical Angle Timer are presented to the Waveform Arithmetic Circuit. An electrical angle timer interrupt signal is generated each time the Electrical Angle Timer finishes counting.

The Waveform Arithmetic Circuit has a sine wave data table, which is used to extract sine wave data based on the electrical angle data received from the Electrical Angle Timer. This sine wave data is multiplied by the value of the Voltage Amplitude Register. For 2-phase modulation, the product obtained by this multiplication is presented to the waveform synthesis circuit. For 3-phase modulation, waveform data is further calculated based on the product of multiplication and the electrical angle data and the value of the PWM Period Register. The calculation is performed each time the Electrical Angle Timer finishes counting or when a value is set in the Electrical Angle Register, and the calculation results consisting of the U phase, the V phase (+120 degrees), and the W phase (+240 degrees) are sequentially presented to the PWM waveform output circuit. The sine wave data table is stored in the RAM and requires initialization.

- To correct the period, set the number of times 'n' to be corrected in the Period Correction Register (EDSET Register F to C bits). The period is corrected by adding 1 to electrical angle counts 16 for 'n' times. For example, when a value 3 is set in the Period Correction Register, the period for 13 times out of electrical angle counts 16 is the value "mH" set in the Period Set Register, and that for 3 times is "m + 1H". (Correction is made almost at equal intervals.)
- Because the electrical angle counter (ELDEG) can be accessed even while the Electrical Angle Timer is operating, the electrical angles can be corrected during operation.
- The Electrical Angle Capture EDCAP captures the electrical angle value from the Electrical Angle Counter at the time the position is detected.
- When the waveform calculation function is enabled, waveform calculation is performed each time the electrical angle counter (ELDEG) are accessed for write or the Electrical Angle Timer finishes counting.
- The calculation is performed in 35 machine cycle of execution time, or 7 μs (at 20 MHz).
- When transfer of calculation result to the CMP Registers is enabled (EDCRA<RWREN>), the calculation results are transferred to the CMPU to W Registers. (This applies only when the waveform calculation function is enabled with the EDCRA<CALCEN>.) The CMPU to W Registers are disabled against write while the transfer remains enabled. The calculation results can be read from the CMPU to W Registers while the waveform calculation function e calculated results can be modified and the modified data can be set in the CMPU to W Registers in software. This makes it possible to output any desired waveform other than sine waves.

If a transfer (EDCRA register bit 2) of the calculated results to the CMP register is disabled, readaccessing the CMPU to W registers can read the calculated results. (Before read-accessing these registers, make sure that the calculation is completed.)

To initialize the entire RAM data of the sine wave data table, set the addresses at which to set, sequentially from 000H to 17FH, in the ELDEG Register, and write waveform data to the WFMDR Register each time. Make sure the Waveform Arithmetic Circuit is disabled when writing this data.

- Note 1: The value set in the Period Set Register (EDSET Register EDT bits) must be equal to or greater than 010H. Any value smaller than this is assumed to be 010H.
- Note 2: The sine wave data that is read consists of the U phase, the V phase whose electrical angle is +120 degrees relative to the U phase, and the W phase whose electrical angle is +240 degrees relative to the U phase.
- Note 3: If a period corresponding to an electrical angle of one degree is shorter than the required calculation time, the previously calculated results are used.
TOSHIBA

14.6.1.1 Functions of the Electrical Angle Timer and Waveform Arithmetic Circuit Registers

EDCRB

LDOILD			
3	CALCST	Start calculation by software	Forcefully start calculation. When this bit is written while the waveform arithmetic circuit is calculating, the calculation is terminated and then newly started.
2	CALCBSY	Calculation flag	By reading this bit, the operation status of the waveform arithmetic circuit can be obtained.
1	EDCALEN	Enable/disable calculation start synchronized with elec- trical angle	Select whether to start calculation when the electrical angle timer finishes counting or when a value is set in the electrical angle register. When disabled, calculation is only started when CALCST is set to 1.
0	EDISEL	Electrical angle interrupt	Set the electrical angle interrupt signal request timing to either when the electrical angle timer finishes counting or upon end of calculation.

EDCRA			
7	EDCNT	Electrical angle count up/ down	Set whether the electrical angle timer counts up or down.
6	EDRV	Select V-, W-phase	Select phase direction of V-phase and W-phase in relation to U-phase.
5, 4	EDCK	Select clock	Select the clock for the electrical angle timer. This setting can be altered even while the electrical angle timer is operating.
3	C2PEN	Switch between 2-phase and 3-phase modulations	Select the modulation method with which to perform waveform calculation. Two-phase modulation DATA = ramdata (ELDEG) × AMP Three-phase modulation: DATA = $\frac{MOPRD}{2} \pm \frac{ramdata(ELDEG) \times AMP}{2}$ Note: The ± sign during 3-phase modulation changes depending on the electrical angle. + for electrical angles 0 to 179 degrees (191) - for electrical angles 180 (192) to 360 (383) degrees
2	RWREN	Auto transfer calculation re- sults to CPM registers	Enable/disable transfer of calculation results by the waveform arithmetic circuit. When the waveform calculation function is enabled while at the same time transfer is enabled, calculation results are set as U, V, and W-phase duty cycles of the PWM generation circuit and are reflected in the ports.
1	CALCEN	Enable/disable waveform cal- culation function	Enable/disable the waveform calculation function. Calculations are performed by the waveform arithmetic circuit by enabling the waveform calculation function. When the waveform calculation function is enabled, the calculated results can be read from the U, V, and W-phase compare registers (CMPU, V, W) of the PWM generation circuit.
0	EDTEN	Electrical angle timer	Enable/disable the electrical angle timer. When enabled, the electrical angle timer starts counting; when disabled, the electrical angle timer stops counting and is cleared to 0.
			$\overline{(7)}$

EDSET				
F to C	ED	EDTH Correct electrical angle period		Correct the period by adding 1 to electrical angle counts 16 for "n" times. The timer counts the electrical angle period set value "m" for $(16 - n)$ times and counts $(m + 1)$ for "n" times
B to 0	E	EDT Electrical angle period		Set the electrical angle period.
		$\langle \rangle$		
ELDE	G	Electric	al angle	Read the electrical angle. This register can also be set to initialize or correct the angle while counting. Any value greater than 17FH cannot be set.
\sim		$\left(\right)$		
		Set volt	age amplitude	Set the voltage amplitude. The waveform arithmetic circuit multiplies the data set here by the sine wave data read out from the sine wave RAM. The amplitude has its upper limit determined by the set value of the MDPRD register when performing this multiplication.
EDCA	P	Capture	e electrical angle	Capture the value from the electrical angle timer when the position is detected.
WFMD	R	Set sine	e wave data	To initialize the entire RAM data of the sine wave table, set the addresses at which to set, sequentially from 000H to 17FH, in the ELDEG register, and write waveform data to the WFMDR register each time. Make sure the waveform arithmetic circuit is disabled when writing this data.

14.6 Electrical Angle Timer and Waveform Arithmetic Circuit

Typical Settings of Sine Wave Data



Note: During 3-phase modulation, the sign changes at 180 degrees of electrical angle.

Figure 14-17 Typical Settings of Sine Wave Data

List of the Electrical Angle Timer and Waveform Arithmetic Circuit Registers [Addresses (PMD1 and PMD2)]

EDCRB	7	6	5	4	3	2	1	0	_
(01FC1H)	-	-	-	-	CALCST	CALCBSY	EDCALEN	EDISEL	(Initial value: **** 0000)
(01FF1H)			\sim	$\overline{(7)}$		~	R		

3	CALCST	Start calculation by software	0: No operation 1: Start calculation	w
2	CALCBSY	Calculation flag	0: Waveform Arithmetic Circuit stopped 1: Waveform Arithmetic Circuit calculating	R
1 <	EDCALEN	Enable/disable calculation start synchronized with electrical an- gle	0: Start calculation insync with electrical angle 1: Do not calculation insync with electrical angle	R/W
0	EDISEL	Electrical angle interrupt	0: Interrupt when the Electrical Angle Timer finishes counting1: Interrupt upon end of calculation	

Note: Read-modify-write instructions, such as a bit manipulation instruction, cannot access the EDCRB register because this register is write only.

TOSHIBA

EDCRA	7	6	5	4	3	2	1	0	
(01FC0H)	EDCNT	EDRV	ED	СК	C2PEN	RWREN	CALCEN	EDTEN	(Initial value: 0000 0000)
(01FF0H)									

				_
7	EDCNT	Electrical angle count up/down	0: Count up 1: Count down	
				-
6	EDRV	Select V- W-phase	0: V = U + 120°, W = U + 240°	
Ů	25.00		1: V = U - 120°, W = U - 240°	
			00: fc/2 ³ (400 ns at 20 MHz)	
_			01: fc/2 ⁴ (800 ns at 20 MHz)	
5, 4	EDCK	Select clock	10: fc/2 ⁵ (1.6 µs at 20 MHz)	
			11: fc/26 (3.2 us at 20 MHz)	
				R/W
3	C2PEN	Switch between 2-/3-phase	0: 2-phase modulation	
Ű	02. 2.1	modulations	1: 3-phase modulation	
		Transfer calculation result to	0: Disable	
2	RWREN	CMP registers	1: Enable	
		Enable/disable waveform cal-	0: Disable	1
1	CALC	culation function	1: Enable	
				1
0	EDTEN	Electrical angle Enable/disable		
			11 Enable	

Note: When changing the EDCRA<EDCK> setting, keep the EDCRA<EDTEN> bit reset "0" (Disable electrical angle timer).

EDSET	F	Е	D	С	в	A	9	8	7	6	5	4 3 2	1	0	
(01FC3H, 01FC2H)		ED	TH			\square		>	/	E	т				(Initial value: 00000000 00010000)
(01FF3H, 01FF2H)					())			/	/				

F to C	EDTH	Correct period (n)	0 to 15 times	DAA
B to 0	EDT	Set period (m)	≥ 010H	
			$(\vee /))$	

One period of the Electrical Angle Timer, T, is expressed by the equation below.

= $\left(m + \frac{n}{16}\right) \times 384 \times \text{set clock[s]}$ where m = set period, n = period correction

ELDEG		F	E	D	С	В	А	9	8	7	6	5	4	3	2	1	0	_	
(01FC5H, 01F (01FF5H, 01F	C4H) F4H)	-	-	-	-	-	-	-	D8	D7	D6	D5	D4	D3	D2	D1	D0	(Initial value: ******0 000	00000)
Г	0.45.0	1-			F last						- 4 4 1		4			Ś	- 1 - 4 - 5		DAA
L	8 to 0		LDEG		Elect	rical a	ngie			5	et the I	nitially	and ti	ne cou	nt vait	les or	electri	cai angle.	R/W
AMP		F	Е	D	С	в	А	9	8	7	6	5	4	3	2	1	Q	50	
(01FC7H, 01F	C6H)	-	-	-	-	DB	DA	D9	D8	D7	D6	D5	D4	D3	D2	D1	DO	(Initial value: ****0000 00000000)	
(011111,011	1 011)		.ii		I	[!	Į				\langle	\leq	\swarrow	5)		
[B to 0	A	MP		Set v	oltage				S	et the v	voltage	e to be	used	during	wave	form c	alculation.	R/W
		_	_	_	_	_				_		_	. /		\leq	Ľ			
EDCAP (01FC9H, 01F	C8H)	F	E	D	С	В	A	9	8	7	6	5	4	Å	2	1	0		
(01FF9H, 01F	F8H)	-	-	-	-	-	-	-	D8	D7	D6	D5	D4	D3	D2	D1	D0		0000)
Γ		-			Cont	uradiv		foloot	rical a			_((<u> </u>	<u> </u>	, 	\sim	(Θ	
	8 to 0	E	DCAP		gle		alue o	i elect	ncai a	"" E	ectrica	al angle	e timer	value	when	positi	on is d	letected.	R
	_				_						a		\geq			6	7		
WFMDR (01ECAH)					5		4 D4		3 50		12		1	0		Unitial		. ********	
(01FFAH)				,	00				00	R		<u>} </u>			$\left(\right)$		Value	.)	
									(_	\sim	\sim				$\langle \rangle \langle \rangle$		/		
-									$\mathcal{A}($				(-		\sim				
[7 to 0	۷	VFMDR	8	Sine	wave	data		4		rite sir	ne wav	e data	to RA	M of s	ine wa	ave		W
[7 to 0	v	VFMDR	2	Sine	wave	data	(($\langle \langle \rangle$		rite sir	ne wav	e data	to RA	M of s	ine wa			W
[Note	7 to 0 e:Read- cause	v-mo	VFMDR dify-wi s regis	rite in	Sine structi write	wave ions, only.	data such	asa	bit ma	manipul	rite sir ation	ne wav instru	e data	to RA	M of s	ine wa	ave the W	/FMDR register be-	W
[Not	7 to 0 e:Read- cause	-mo this	VFMDF dify-wi s regis	rite in ter is	Sine struct write	wave ions, only.	data such	as a	bitma	anipul	rite sir	ne wav instru	ction,	to RA	M of s	ine wa	ave the W	/FMDR register be-	W
[Not	7 to 0 e:Read- cause	-mo e this	VFMDR dify-wi s regis	rite in ter is	Sine structi write	ions, ionly.	data such	as a	bitma	anipul	rite sir	instru	ction,	to RA	M of s	cess t	ave the W	/FMDR register be-	W
[Not	7 to 0 e:Read- cause	-mo e this	VFMDR dify-wi s regis	rite in ter is	Sine struct write	ions, only.	data such	as a	bitma	anipul	ation	instru	ction,	to RA	M of s	cess t	ave	/FMDR register be-	W
[Not	7 to 0	v-mo • this	VFMDF dify-wi s regis	rite in ter is	Sine struct write	ions, only.	data such	as a	bitma	anipul	ation	instru	ction,	cann	M of s	cess t	ave	/FMDR register be-	W
[Not	7 to 0 e:Read- cause	v-mo e this	VFMDF dify-wi s regis	rite in ter is	Sine struct write	ions, ionly.	such	as a	bitma	anipul	ation	instru	ction,	cann	ot act	cess f	the W	/FMDR register be-	W
[Not	7 to 0	v • mo • this	VFMDR dify-wi s regis	rite in ter is	Sine struct write	ions, ionly.	such		bitma	anipul	ation	instru	ction,	cann	ot act	cess t	the W	/FMDR register be-	W
[Not	7 to 0 e:Read- cause	-mo e this	dify-wi s regis	a rite in ter is	Sine structi write	wave of the second seco	data such	as a	bitme	anipul	ation	instru	e data	cann	M of s	ine wa	ave	/FMDR register be-	W
[Not	7 to 0	-mo e this	dify-wi s regis	a rite in ter is	Sine	ions, only.	data	as a	bitma	anipul	ation	instru	e data	cann	M of s	cess t	ave	/FMDR register be-	W
[Not	7 to 0	v this	VFMDR dify-wi s regis	R tite in ter is	Sine	wave	data		bit ma	anipul	ation	instru	e data	cann	M of s	cess f	ave	/FMDR register be-	W
[Not	7 to 0	-mo	dify-wi s regis	R rite in ter is	Sine	wave of the second seco	data	as a	bit ma	anipul	ation	instru	e data	cann	M of s	cess t	ave	/FMDR register be-	W
[Not	7 to 0	-mo e this	dify-wi s regis	R tite in ter is	Sine	wave	data		bit ma		ation	instru	e data	cann	M of s	cess f	ave	/FMDR register be-	W
[Not	7 to 0	v v	dify-wi s regis	R tite in ter is	Sine struct write	wave	data		bit ma	anipul	ation	instru	ction,	cann	M of s	cess f	ave	/FMDR register be-	W

TOSHIBA

14.6.1.2 List of PMD Related Control Registers

(1) Input/output Pins and Input/output Control Registers

PMD1 Input/Output Pins (P3, P4) and Port Input/Output Control Registers (P3CR, P4CR)

Name	Address	Bit	R or W	Description
		7	R/W	Overload protection (CL1)
P3DR	00003H	6	R/W	EMG input (EMG1)
		5 to 0	R/W	U1/V1/W1/X1/Y1/Z1 outputs.
P4DR	00004H	2 to 0	R/W	Position signal inputs (PDU1, PDV1, PDW1).
P3CR	01F89H	7 to 0	R/W	P3 port input/output control (can be set bitwise). 0: Input mode 1: Output mode
P4CR	01F8AH	2, 1, 0	R/W	P0 port input/output control (can be set bitwise) 0: Input mode 1: Output mode

PMD2 Input/Output Pins (P5, P1) and Port Input/Output Control Registers (P5CR, P1CR)

Name	Address	Bit	R or W	Description
		0	R/W	Overload protection (CL2)
P5DR	00005H	1	R/W	EMG input (EMG2)
		2 to 7	R/W	U2/V2/W2/X2/Y2/Z2 outputs.
P1DR	00001H	5 to 7	R/W	Position signal inputs (PDU2, PDV2, PDW2).
P5CR	01F8BH	7 to 0	R/W	P3 port input/output control (can be set bitwise). 0: Input mode 1: Output mode
P1CR	0000BH	5, 6, 7	R/W	P0 port input/output control (can be set bitwise). 0: Input mode 1: Output mode
			$\langle \langle \rangle$	$\langle \vee \rangle$)

Note: When using these pins as PMD function or input port, set the Output Latch (P*DR) to 1.

Example of the PMD Pin Port Setting

		>		-	
\bigcirc	Input/Output	P3DR	P3CR	P4DR	P4CR
CL1	Input	*	0	-	-
EMG1	Input	*	0	-	-
U1 (Output	/ 1	1	-	-
PDU1		-	-	*	0

	Input/Output	P5DR	P5CR	P1DR	P1CR
CL2	Input	*	0	-	-
EMG2	Input	*	0	-	-
U2	Output	1	1	-	-
PDU2	Input	-	-	*	0

(2) Motor Control Circuit Control Registers [Address Upper Stage: PMD1, Lower Stage: PMD2]

Position Detection Control Register (PDCR) and Sampling Delay Register (SDREG)

Name	Address	Bit	R or W	Description
		5, 4	R	Detect the position-detected position. 00: Within the current pulse 01: When PWM is off 10: Within the current pulse 11: Within the preceding pulse
PDCRC	01FA2H 01FD2H	3	R	Monitor the sampling status. 0: Sampling idle 1: Sampling in progress
		2 to 0	R	Holds the status of the position signal input during unmatch detection mode. Bits 2, 1, and 0: W, V, and U phases
		7, 6	R/W	Select the sampling input clock [Hz]. 00: fc/2² 01: fc/2³ 10: fc/2² 11: fc/2³
PDCRB	01FA1H 01FD1H	5, 4	R/W	Sampling mode. 00: When PWM is on 01: Regularly 10: When lower phases are turned on
		3 to 0	R/W	Detection position match counts 1 to 15.
		7	W	0: No operation 1: Stop sampling in software
		6 (0: No operation 1: Start sampling in software
		5	R/W	Stop sampling using Timer 3. 0: Disable 1: Enable
		4	R/W	Start sampling using Timer 2. 0: Disable 1: Enable
PDCRA	PDCRA 01FA0H 01FD0H		R/W	Number of position signal input pins. 0: Compare three pins (PDU/PDV/PDW) 1: Compare one pin (PDU) only
<		2	R/W	Count occurrences of matching when PWM is on. 0: Subsequent to matching counts when PWM previously was on 1: Recount occurrences of matching each time PWM is on
		1	R/W	Position detection mode. 0: Ordinary mode 1: Unmatch detection mode
			R/W	Enable/Disable position detection function. 0: Disable 1: Enable (Sampling starts)
SDREG	01FA3H 01FD3H	6 to 0	R/W	Sampling delay. 2³/fc × n bits (n = 0 to 6, maximum 50.8 μs at 20 MHz).

Name	Address	Bit	R or W	Description
		7	R/W	Debug output. 0: Disable 1: Enable (P67 for PMD1, P77 for PMD2)
		5	R	Mode timer overflow. 0: No overflow 1: Overflowed occurred
MTCRB	01FA5H 01FD5H	3	R/W	Capture mode timer by overload protection. 0: Disable 1: Enable
		2	w	Capture mode timer by software. 0: No operation 1: Capture
		1	R/W	Capture mode timer by position detection. 0: Disable 1: Enable
		7, 6, 5	R/W	Select clock for mode timer [Hz]. 000: fc/2 ³ (400 ns at 20 MHz) 1010: fc/2 ⁴ (800 ns at 20 MHz) 100: fc/2 ⁵ (1.6 µs at 20 MHz) 110: fc/2 ⁶ (3.2 µs at 20 MHz) 001: fc/2 ⁷ (6.4 µs at 20 MHz) 011: Reserved 101: Reserved 101: Reserved 111: Reserved
MTCRA	01FA4H 01FD4H	4	R/W R/W	Reset timer by Timer 3. 0: Disable 1: Enable Reset timer by overload protection. 0: Disable 4: Enable
		2	W	Reset timer by software. 0: No operation 1: Reset
<		1	R/W	Reset timer by position detection. 0: Disable 1: Enable
		0	R/W	Enable/Disable mode timer. 0: Disable 1: Enable (timer starts)
MCAP	01FA7H, 01FA6H 01FD7H, 01FD6H	F to 0	R	Mode capture register.
CMR1	01FA9H, 01FA8H 01FD9H, 01FD8H	F to 0	R/W	Compare Register 1.
CMP2	01FABH, 01FAAH 01FDBH, 01FDAH	F to 0	R/W	Compare Register 2.
CMP3	01FADH, 01FACH 01FDDH, 01FDCH	F to 0	R/W	Compare Register 3.

Mode Timer Control Register (MTCR), Mode Capture Register (MCAP), and Compare Registers (CMP1, CMP2, CMP3)

TMP88FW45AFG

Name	Address	Bit	R or W	Description
MDCRB	01FAFH 01FDFH	1, 0	R/W	Select clock for PWM counter. 00: fc/2 (100 ns at 20 MHz) 01: fc/2² (200 ns at 20 MHz) 10: fc/2³ (400 ns at 20 MHz) 11: fc/2⁴ (800 ns at 20 MHz)
		7	R/W	Select half-period interrupt 0: Interrupt every period as specified in PINT. 1: Interrupt every half-period only PINT=00.
		6	R/W	DUTY mode. 0: U phase in common 1: Three phases independent
		5	R/W	Upper-phase port polarity. 0: Active low 1: Active high
MDCRA	01FAEH	4	R/W	Lower-phase port polarity. 0: Active low 1: Active high
	UNDEN	3, 2	R/W	Select PWM interrupt (trigger). 00: Interrupt once every period 01: Interrupt once 2 periods 10: Interrupt once 4 periods 11: Interrupt once 8 periods
		1	R/W	PWM mode. 0: PWM mode0 (edge: sawtooth wave) 1: PWM mode1 (center: triangular wave)
		0	R/W	Enable/disable waveform synthesis function. 0: Disable 1: Enable (waveform output)
DTR	01FBEH 01FEEH	5 to 0	R/W	Set dead time. 2³/fc × 6bit (maximum 25.2 μs at 20 MHz).
		F	R	0: Count up 1: Count down
		E, D, C	RAW	Comparison register for position detection. 6: W 5: V
<		в	R/W	Select PWM synchronization. 0: Asynchronous with PWM period 1: Synchronized
		A	R/W	W-phase PWM output. 0: H/L level output 1: PWM waveform output
MDOUT	01FB3H, 01FB2H 01FE3H, 01FE2H	9	R/W	V-phase PWM output. 0: H/L level output 1: PWM waveform output
		8	R/W	U-phase PWM output. 0: H/L level output 1: PWM waveform output
		7, 6	R/W	Select port output synchronizing signal. 00: Asynchronous 01: Synchronized to position detection 10: Synchronized to Timer 1 11: Synchronized to Timer 2
		5, 4	R/W	Control W-phase output
		3, 2	R/W	Control V-phase output
		1, 0	R/W	Control U-phase output

PMD Control Register (MDCR), Dead Time Register (DTR), and PMD Output Register (MDOUT)

PWM Counter (MDCNT), PMD Period Register (MDPRD), and PMD Compare Registers (CMPU, CMPV, CMPW)

Name	Address	Bit	R or W	Description
MDCNT	01FB5H, 01FB4H 01FE5H, 01FE4H	B to 0	R	Read the PWM period counter value.
MDPRD	01FB7H, 01FB6H 01FE7H, 01FE6H	B to 0	R/W	PWM period MDPRD ≥ 010H.
CMPU	01FB9H, 01FB8H 01FE9H, 01FE8H	B to 0	R/W	Set U-phase PWM duty cycle.
CMPV	01FBBH, 01FBAH 01FEBH, 01FEAH	B to 0	R/W	Set V-phase PWM duty cycle.
CMPW	01FBDH, 01FBCH 01FEDH, 01FECH	B to 0	R/W	Set W-phase PWM duty cycle.



Name	Address	Bit	R or W	Description
EMGREL	01FBFH 01FEFH	7 to 0	w	Code input for disable EMG protection circuit. Can be disable by writing 5AH and then A5H.
		7	w	Return from overload protective state. 0: No operation 1: Return from protective state
		6	R/W	Condition for returning from overload protective state: Synchronized to PWM. 0: Disable 1: Enable
		5	R/W	Enable/Disable return from overload protective state by timer 1. 0: Disable 1: Enable
EMGCRB	01FB1H 01FE1H	4	R	Overload protective state. 0: No operation 1: Under protection
		3, 2	R/W	Select output disabled phases during overload protection. 00: No phases disabled against output 01: All phases disabled against output 10: PWM phases disabled against output 11: All upper/All lower phases disabled against output
		1	R/W	Stop PWM counter (MDCNT) during overload protection. 0: Do not stop 1: Stop
			RW	Enable/Disable overload protective circuit. 0: Disable 1: Enable
		7 to 4	R/W	Overload protection sampling time. $2^2/fc \times n (n = 1 to 15, at 20 MHz)$
	(2	R	EMG protective state. 0: No operation 1: Under protection
EMGCRA	01FB0H 01FE0H		w	Return from EMG protective state. 0: No operation 1: Return from protective state
<		0	RW	Enable/Disable function of the EMG protective circuit. 0: Disable 1: Enable (This circuit initially is enabled (= 1). To disable this circuit, make sure key code 5AH and A5H are written to the EMGREL1 Register before- hand.)
		$\langle \bigcirc \rangle$	\rightarrow	

Electrical Angle Control Register (EDCR), Electrical Angle Period Register (EDSET), Electrical Angle Set Register (ELDEG), Voltage Set Register (AMP), and Electrical Angle Capture Register (EDCAP).

EDCRB 01FC1H 01FF1H 3 W 0: No operation 1: Start calculation 2 R 0: Waveform Arithmetic Circuit stopped 1: Waveform Arithmetic Circuit calculation. 0 1 RW 0: Start calculation insync with electrical angle 1: Do not calculation insync with electrical angle 1: Do not calculation insync with electrical angle 0 RW 0: Interrupt when the Electrical Angle Timer finishes counting 1: Interrupt upon end of calculation 0 RW 0: Count up 1: Count down 6 RW 0: V = U + 120°; W = U + 240° 1: Count down 6 RW 0: V = U + 120°; W = U - 240° 5, 4 RW 0: fc/2* 01; fc/2* 10: fc/2* 01; fc/2* 0: fc/2* 01; fc/2* 10: fc/2* 01; fc/2* 0: fc/2* 01; fc/2* 10: fc/2* 01; fc/2* 2 RW 0: fc/2* 01; fc/2* 10: fc/2* 01; fc/2* 2 RW 0: fc/2* 01; fc/2* 10: fc/2* 1 RW 0: fc/2* 01; fc/2* 10: fc/2* 2 RW 0: fc/2* 01; fc/2* 10: fc/2* 2 RW 0: fc/2* 01; fc/2* 10: fc/2* 2 RW 0: fc/2* 01; fc/2* 10: fc/2* 1 RW 0: fc/2* 01; fc/2* 10: fc/2*	Name	Address	Bit	R or W	Description
EDCRB 01FC1H 01FF1H 2 R 0: Waveform Arithmetic Circuit stopped 1: Waveform Arithmetic Circuit calculation. 1 RW 0: Start calculation insync with electrical angle 1: Do not calculation insync with electrical angle 0 RW 0: Interrupt when the Electrical Angle Timer finishes counting 1: Interrupt when the Electrical Angle Timer finishes counting 1: Interrupt upon end of calculation RW 0: Count up 1: Count down 0: Count up 1: Count down 6 R/W 0: V = U + 120°, W = U + 240° 1: V = U + 240° 6 R/W 0: V = U + 120°, W = U + 240° 5.4 R/W 0: fo/2* 01; fo/2* 10: fo/2* 11: fo/2* 7 R/W 0: fo/2* 01; fo/2* 10: fo/2* 11: fo/2* 8 R/W 0: fo/2* 01; fo/2* 10: fo/2* 11: fo/2* 8 R/W 0: fo/2* 01; fo/2* 10: fo/2* 11: fo/2* 8 R/W 1 Transfer calculation 1 R/W 0: foisable 1: Enable Enable/disable waveform calculation function. 1 R/W 0: Disable 1: Enable Enable/disable waveform calculation function. 1 R/W 0: Disable 1: Enable Enable/disable waveform calculation function. 0: Disable 1: Enable Enable/disable wavefor			3	w	0: No operation 1: Start calculation
EDCRB 01FF1H 1 RW 0: Start calculation insync with electrical angle 0 RW 0: Brerupt when the Electrical Angle Timer finishes counting 0 RW 0: Interrupt when the Electrical Angle Timer finishes counting 1: Interrupt upon end of calculation 0: Count up 1: Count down 0: Count up 6 RW 0: V = U + 120°, W = U + 240° 1: Count down 0: fo/2* 01; fo/2* 5,4 RW 0: fo/2* 01; fo/2* 0: fo/2* 01; fo/2* 0: fo/2* 01; fo/2* 1: for the phase modulation 0: fo/2* 01; fo/2* 0: fo/2* 01; fo/2* 0: fo/2* 01; fo/2* 2 RW 0: Disable 1 RW 0: Disable 1: Enable 1 RW 0: Disable 1: Enable 1 RW 0: Disable 1: Enable 0 RW 0: Disable 1: Enable 1: Enable 0 RW 0: Disable 1: Enable 1: Enable 0 RW 0: Disable 1: Enable 0: Disable 1: Enable		01FC1H	2	R	0: Waveform Arithmetic Circuit stopped 1: Waveform Arithmetic Circuit calculation
Image: Book of the second s	EDCKB	01FF1H	1	R/W	0: Start calculation insync with electrical angle1: Do not calculation insync with electrical angle
$ EDCRA \begin{array}{ c c c c } \hline & & & & \\ \hline & & & \\ \hline & & & \\ \hline & & & \\ \hline & & & \\ \hline \\ \hline$			0	R/W	0: Interrupt when the Electrical Angle Timer finishes counting 1: Interrupt upon end of calculation
$EDCRA = \begin{bmatrix} 0.1FC0H \\ 0.1FF0H \\ 1 \\ EDSET \\ EDSE \\ EDSET \\ EDSE \\ EDSET \\ EDSE \\ $			7	R/W	0: Count up 1: Count down
EDCRA 01FC0H 01FF0H 5,4 R/W Select clock 00: fc/2* 01: fc/2* 10: fc/2* 01: fc			6	R/W	0: V = U + 120°, W = U + 240° 1: V = U - 120°, W = U - 240°
EDCRA 01FC0H 01FF0H 3 R/W Switch between 2/3-phase modulations. 0: Two-phase modulation 2 R/W 1: Three-phase modulation 1: Three-phase modulation 2 R/W 0: Disable 1: Enable 1 R/W 0: Disable 1: Enable EDSET 01FC3H, 01FC2H F to C R/W Correct period (n) 0 to 15 times. ELDEG 01FC5H, 01FC4H B to 0 R/W Set period (1/m counter) ≥ 010H ELDEG 01FC5H, 01FC4H 8 to 0 R/W Initially set and count values of electrical angle.			5, 4	R/W	Select clock. 00: fc/2 ³ 01: fc/2 ⁴ 10: fc/2 ⁵ 11: fc/2 ⁵
01FF0H 2 R/W 0: Disable 1: Enable 2 R/W 0: Disable 1: Enable 1 R/W Enable/disable waveform calculation function. 0 Disable 1: Enable Enable/disable waveform calculation function. 0 R/W 0: Disable 1: Enable 1 R/W 0: Disable 1: Enable 0 R/W 0: Disable 1: Enable EDSET 01FC3H, 01FC2H 01FF3H, 01FF2H F to C B to 0 R/W Correct period (n) 0 to 15 times. ELDEG 01FC5H, 01FC4H 01FF5H, 01FF4H 8 to 0 R/W Initially set and count values of electrical angle.	EDCRA	01FC0H 01FF0H	3	R/W	Switch between 2/3-phase modulations. 0: Two-phase modulation 1: Three-phase modulation
$EDSET = \begin{bmatrix} 01FC3H, 01FC2H \\ 01FF5H, 01FF2H \\ ELDEG \end{bmatrix} \begin{bmatrix} 01FC5H, 01FC4H \\ 01FF5H, 01FF2H \\ 01FF5H \\ 01FF5H \\ 01FF5H \\ 01FF5H \\ 01FF5H \\ 01FF5H \\ 01FF5H \\ 01FF5H \\ 01FF5H \\ 01FF5H \\ 01FF5H \\ 01FF5H \\ 01FF5H \\ 01FFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFF$			2	R/W	Transfer calculation result to CMP registers. 0: Disable 1: Enable
$EDSET = \begin{bmatrix} 0.1FC3H, 01FC2H \\ 0.1FF3H, 01FF2H \\ 0.1FF3$			1	R/W	Enable/disable waveform calculation function. 0: Disable 1: Enable
EDSET01FC3H, 01FC2HF to CR/WCorrect period (n) 0 to 15 times.01FF3H, 01FF2HB to 0R/WSet period (1/m counter) \geq 010HELDEG01FC5H, 01FC4H 01FF5H, 01FF4H8 to 0R/WInitially set and count values of electrical angle.			0	R/W	Electrical angle timer. 0: Disable 1: Enable
01FF3H, 01FF2HB to 0R/WSet period (1/m counter) \geq 010HELDEG01FC5H, 01FC4H 01FF5H, 01FF4H8 to 0R/WInitially set and count values of electrical angle.	EDSET	01FC3H, 01FC2H	F to C	R/W	Correct period (n) 0 to 15 times.
ELDEG 01FF5H, 01FF4H 8 to 0 R/W Initially set and count values of electrical angle.		01FF3H, 01FF2H 01FC5H, 01FC4H	B to 0	R/W	Set period (1/m counter) ≥ 010H
	ELDEG	01FF5H, 01FF4H	8 to 0	R/W	Initially set and count values of electrical angle.
AMP 01FC/H, 01FC6H B to 0 R/W Set voltage used during waveform calculation.	AMP	01FC7H, 01FC6H 01FF7H, 01FF6H	B to 0	R/W	Set voltage used during waveform calculation.
EDCAP 01FC9H, 01FC8H 01FF8H 8 to 0 R Electrical angle timer value when position is detected.	EDCAP	01FC9H, 01FC8H 01FF9H, 01FF8H	8 to 0	R	Electrical angle timer value when position is detected.
WFMDR 01FCAH 7 to 0 W Set sine wave data.	WFMDR	01FCAH 01FFAH	7 to 0	×	Set sine wave data.

15. Asynchronous Serial interface (UART1)

The TMP88FW45AFG has a asynchronous serial interface (UART). It can connect the peripheral circuits through TXD and RXD pin. TXD and RXD pin are also used as the general port. For TXD pin, the corresponding general port should be set output mode (Set its output control register to "1" after its output port latch to "1"). For RXD pin, should be set input mode.

The asynchronous serial interface (UART1) can select the connection pin with the peripheral circuits. RXD1 and TXD1 are correspond to P44 and P45 pins, RXD2 and TXD2 are to P00 and P01 pins. But the synchronous serial interface (SIO) also use P44 and P45 pins, therefore these P44 and P45 are not available for UART when SIO is on working.

15.1 Configuration



15.2 Control

UART1 is controlled by the UART1 Control Registers (UARTCR1, UARTCR2). The operating status can be monitored using the UART status register (UARTSR).

TXD pin and RXD pin can be selected a port assignment by UART Pin Select Register (UARTSEL).

UART1 Cor	ntrol R	egist	er1						
UARTCR1	7	6	5	4	3	2	1	0	
(01F91H)	TXE	RXI	E STBT	EVEN	PE		BR	G	(Initial value: 0000 0000)
_									
	тхі	F	Transfer on	eration			0:	Disable	
							1:	Enable	
		_	Pocoivo op	vration			0:	Disable	$\langle \rangle \rangle \langle \rangle \langle \rangle \rangle \langle \rangle \langle \rangle \rangle \langle \rangle \langle \rangle \langle \rangle \langle \rangle \rangle \langle \rangle $
			Receive ope	alion			1:	Enable	
	OTE	.	Transmit at	n hit longt	h		0:	1 bit	7/
		51		p bit lengt			1:	2 bits	
		-N	Even_numb	ared parity			0:	Odd-num	pered parity
				ered parity			1:	Even-num	bered parity
		.	Parity additi	on			0; (No parity	Write
		-	Fanty audit	011			1.	Parity	only
						(000:	fc/13 [Hz]	(0/5)
						Æ	001:	fc/26	
						$\mathcal{A}($	010:	fc/52	
	BR	G	Transmit clo	ck select		\sim	011:	fc/104	$\langle \rangle \rangle$
				\sim	100:	fc/208			
							101:	tc/416	
				/	\square	\leq	110:	Input INT	C4 V
				((\land)		111:	TC/96	

- Note 1: When operations are disabled by setting UARTCR1<TXE and RXE> bits to "0", the setting becomes valid when data transmit or receive complete. When the transmit data is stored in the transmit data buffer, the data are not transmitted. Even if data transmit is enabled, until new data are written to the transmit data buffer, the current data are not transmitted.
- Note 2: The transmit clock and the parity are common to transmit and receive.
- Note 3: UARTCR1<RXE> and UARTCR1<TXE> should be set to "0" before UARTCR1<BRG> is changed.
- Note 4: In case fc = 20MHz, the timer counter 4 (TC4) is available as a baud rate generator.

UART1 Cor	ntrol Regi	ster2			
UARTCR2 (01F92H)	7	6 5 4 3	2 RXDNC	1 0 STOPBR (Initial value: **** *000)	
		(0,0)	1		
			00:	No noise rejection (Hysteresis input)	
	PYDNC	Selection of RXD input noise	01:	Rejects pulses shorter than 31/fc [s] as noise	
	rejectio time		10:	Write	
			11:	Rejects pulses shorter than 127/fc [s] as noise	only
		Dessive stars hit las ath	0:	1 bit	
	STOPBR	Receive stop bit length	1:	2 bits	

Note 1: Settings of RXDNC are limited depending on the transfer clock specified by BRG. The combination "O" is available but please do not select the combination "-". The transfer clock is calculated by the following equation : Transfer clock [Hz] =INTTC4 sourcec clock [Hz] ÷ TC4DR set value

		RXDNC setting						
BRG setting	Transfer clock [Hz]	00 (No noise rejection)	01 (Reject pulses shorter than 31/fc[s] as noise)	10 (Reject pulses shorter than 63/fc[s] as noise)	11 (Reject pulses shorter than 127/fc[s] as noise)			
000	fc/13	0	0	0	-			
110	fc/8	0	-	-	-			
(When the transfer clock gen-	fc/16	0	0	$\frac{1}{2}$	- <			
rupt is the same as the right side column)	fc/32	0	0		-			
The setting except the above		0	0		0			

UART1 Status Register

JART1 Sta	atus Re	gister					
UARTSR	7	6	5	4	3	2	1 0
(01F91H)	PERR	FERR	OERR	RBFL	TEND	TBEP	(Initial value: 0000 11**)

PERR	Parity error flag	0: No parity error 1: Parity error	
FERR	Framing error flag	0: No framing error 1: Framing error	
OERR	Overrun error flag	0: No overrun error 1: Overrun error	Read
RBFL	Receive data buffer full flag	0: Receive data buffer empty 1: Receive data buffer full	only
TEND	Transmit end flag	0: On transmitting 1: Transmit end	
TBEP	Transmit data buffer empty flag	 0: Transmit data buffer full (Transmit data writing is finished) 1: Transmit data buffer empty 	
	/		

				\frown	\sim				
_			((7/	\wedge				7/
Note:	When an IN	ITTXD i	s gener	ated, 1	BEP fla	ig is se	t to "1"	auton	natically
)	$\overline{}$		\bigcirc		$\left(\right) \right)$)

		\langle				\searrow	\sim)	
UART1 Re	ceive D)ata Bu	ıffer	>			\geq		
RDBUF	7 <	6	5	4	3	2	1	0	Read only
(01F93H)	4	\sim	ノ		\wedge	~			(Initial value: 0000 0000)
\langle)		Ē		>			
UART1 Tra	ansmit	Data B	uffer	$\mathcal{N}_{\mathcal{A}}$))				
TDBUF	7	6	5	4	3	2	1	0	Write only
(01F93H)	\geq			$\langle \rangle$					(Initial value: 0000 0000)

UART Pin Select Register

	7	6 5	5	4	3	2	1	0		
(01E90H)							TXD	RXD	(Initial values **** **00)	
(011 0011)							SEL	SEL	(Initial value. 00)	
			noot nin	aalaat			0: RXE	01		
	RADSEL	RAD COIL	nect pil	Select			1: RXD	02		
			nont nin	aalaat			0: TXD	01	$\langle (\vee) \rangle$	F\$/ VV
	INDSEL		lect pin	Select			1: TXD	2		

Note 1: Do not change UARTSEL register during UART operation.

Note 2: Set UARTSEL register before performing the setting terminal of a I/O port when changing a terminal.

15.3 Transfer Data Format

In UART1, an one-bit start bit (Low level), stop bit (Bit length selectable at high level, by UARTCR1<STBT>), and parity (Select parity in UARTCR1<PE>; even- or odd-numbered parity by UARTCR1<EVEN>) are added to the transfer data. The transfer data formats are shown as follows.



Transfer Rate

15.4

154

Transfer Rate

The baud rate of UART1 is set of UARTCR1<BRG>. The example of the baud rate are shown as follows.

	()	
DDC	Sourc	ze Clock
BRG	16 MHz	8 MHz
000	76800 [baud]	38400 [baud]
001	38400	19200
010	19200	9600
011	9600	4800
100	4800	2400
101	2400	1200

Table 15	-1 Tran	sfer Rat	e (Example)
----------	---------	----------	-------------

When INTTC4 is used as the UART1 transfer rate (when UARTCR1<BRG>= 110"), the transfer clock and transfer rate are determined as follows:

Transfer clock [Hz] = TC4 source clock [Hz] / TC4DR setting value

Transfer Rate [baud] = Transfer clock [Hz] / 16

15.5 Data Sampling Method

The UART1 receiver keeps sampling input using the clock selected by UARTCR1<BRG> until a start bit is detected in RXD pin input. RT clock starts detecting "L" level of the RXD pin. Once a start bit is detected, the start bit, data bits, stop bit(s), and parity bit are sampled at three times of RT7, RT8, and RT9 during one receiver clock interval (RT clock). (RT0 is the position where the bit supposedly starts.) Bit is determined according to majority rule (The data are the same twice or more out of three samplings).



(b) With noise rejection circuit

Figure 15-4 Data Sampling Method

15.6 STOP Bit Length

Select a transmit stop bit length (1 bit or 2 bits) by UARTCR1<STBT>.

15.7 Parity

Set parity / no parity by UARTCR1<PE> and set parity type (Odd- or Even-numbered) by UARTCR1<EVEN>.

15.8 Transmit/Receive Operation

15.8.1 Data Transmit Operation

Set UARTCR1<TXE> to "1". Read UARTSR to check UARTSR<TBEP> = "1", then write data in TDBUF (Transmit data buffer). Writing data in TDBUF zero-clears UARTSR<TBEP>, transfers the data to the transmit shift register and the data are sequentially output from the TXD pin. The data output include a one-bit start bit, stop bits whose number is specified in UARTCR1<STBT> and a parity bit if parity addition is specified. Select the data transfer baud rate using UARTCR1<BRG>. When data transmit starts, transmit buffer empty flag UARTSR<TBEP> is set to "1" and an INTTXD interrupt is generated.

While UARTCR1<TXE> = "0" and from when "1" is written to UARTCR1<TXE> to when send data are written to TDBUF, the TXD pin is fixed at high level. When transmitting data, first read UARTSR, then write data in TDBUF. Otherwise, UARTSR<TBEP> is not zero-cleared and transmit does not start.

15.8.2 Data Receive Operation

Set UARTCR1<RXE> to "1". When data are received via the RXD pin, the receive data are transferred to RDBUF (Receive data buffer). At this time, the data transmitted includes a start bit and stop bit(s) and a parity bit if parity addition is specified. When stop bit(s) are received, data only are extracted and transferred to RDBUF (Receive data buffer). Then the receive buffer full flag UARTSR<RBFL> is set and an INTRXD interrupt is generated. Select the data transfer baud rate using UARTCR1<BRG>.

If an overrun error (OERR) occurs when data are received, the data are not transferred to RDBUF (Receive data buffer) but discarded; data in the RDBUF are not affected.

Note: When a receive operation is disabled by setting UARTCR1<RXE> bit to "0", the setting becomes valid when data receive is completed. However, if a framing error occurs in data receive, the receive-disabling setting may not become valid. If a framing error occurs, be sure to perform a re-receive operation.

15.9 Status Flag

15.9.1 Parity Error

When parity determined using the receive data bits differs from the received parity bit, the parity error flag UARTSR<PERR> is set to "1". The UARTSR<PERR> is cleared to "0" when the RDBUF is read after reading the UARTSR.



Figure 15-6 Generation of Framing Error

15.9.3 Overrun Error

When all bits in the next data are received while unread data are still in RDBUF, overrun error flag UARTSR<OERR> is set to "1". In this case, the receive data is discarded; data in RDBUF are not affected. The UARTSR<OERR> is cleared to "0" when the RDBUF is read after reading the UARTSR.

TOSHIBA





Note: Receive operations are disabled until the overrun error flag UARTSR<OERR> is cleared.

15.9.4 Receive Data Buffer Full

Loading the received data in RDBUF sets receive data buffer full flag UARTSR<RBFL> to "1". The UARTSR<RBFL> is cleared to "0" when the RDBUF is read after reading the UARTSR.

			$\langle \vee \rangle$))
RXD pin	Final bit	Stop		_
				-
Shift register	xxx0**	xxxx0*	X 1xxxx0	-
		\land	¥	_
RDBUF	уууу		X xxxx	_
UARTSR <rbfl></rbfl>	(7/5)		Af	ter reading UARTSR then
		$\overline{\Omega}$		DOF Clears RDFL.
INTRXD interrupt		(//)		_
Figu	ire 15-8 Generation	of Receive Da	ata Buffe	r Full

Note: If the overrun error flag UARTSR<OERR> is set during the period between reading the UARTSR and reading the RDBUF, it cannot be cleared by only reading the RDBUF. Therefore, after reading the RDBUF, read the UARTSR again to check whether or not the overrun error flag which should have been cleared still remains set.

15.9.5 Transmit Data Buffer Empty

When no data is in the transmit buffer TDBUF, that is, when data in TDBUF are transferred to the transmit shift register and data transmit starts, transmit data buffer empty flag UARTSR<TBEP> is set to "1". The UARTSR<TBEP> is cleared to "0" when the TDBUF is written after reading the UARTSR.

15.9

Status Flag





15.9.6 Transmit End Flag

When data are transmitted and no data is in TDBUF (UARTSR<TBEP> = "1"), transmit end flag UARTSR<TEND> is set to "1". The UARTSR<TEND> is cleared to "0" when the data transmit is stated after writing the TDBUF.

Shift register	***1xx X ****1x X ****1	Х 1уууу0 Х*1уууу
TXD pin	Stop	Start Bit 0
UARTSR <tbep></tbep>		/
UARTSR <tend></tend>		<u>\</u>
		-
INTTXD interrupt		

Figure 15-10 Generation of Transmit End Flag and Transmit Data Buffer Empty



16. Asynchronous Serial interface (UART2)

The TMP88FW45AFG has a asynchronous serial interface (UART). It can connect the peripheral circuits through TXD and RXD pin. TXD and RXD pin are also used as the general port. For TXD pin, the corresponding general port should be set output mode (Set its output control register to "1" after its output port latch to "1"). For RXD pin, should be set input mode.

RXD3 and TXD3 are correspond to P81 and P80 pins as the connection pins with the peripheral circuits in the asynchronous serial interface (UART2).

16.1 Configuration



16.2 Control

UART2 is controlled by the UART2 Control Registers (UARTCR21, UARTCR22). The operating status can be monitored using the UART status register (UARTSR2).



- Note 1: When operations are disabled by setting UARTCR21<TXE and RXE> bits to "0", the setting becomes valid when data transmit or receive complete. When the transmit data is stored in the transmit data buffer, the data are not transmitted. Even if data transmit is enabled, until new data are written to the transmit data buffer, the current data are not transmitted.
- Note 2: The transmit clock and the parity are common to transmit and receive.
- Note 3: UARTCR21<RXE> and UARTCR21<TXE> should be set to "0" before UARTCR21<BRG> is changed.
- Note 4: In case fc = 20MHz, the timer counter 4 (TC4) is available as a baud rate generator.

UART2 Control I	Register2				
UARTCR22 7	6 5 4	3 2 1	0	(1	
	$\sum_{i=1}^{n} \frac{1}{i} = \frac{1}{i}$		STOPBR	(initial value: ^^^^ *000)	
RXI	Selection of RXD input not rejectio time	00: No 01: Re 10: Re 11: Re	o noise rejectio ejects pulses s ejects pulses s ejects pulses s	on (Hysteresis input) shorter than 31/fc [s] as noise shorter than 63/fc [s] as noise shorter than 127/fc [s] as noise	Write
STO	PBR Receive stop bit length	0: 1 1: 2	bit bits		

Note 1: Settings of RXDNC are limited depending on the transfer clock specified by BRG. The combination "O" is available but please do not select the combination "-". The transfer clock is calculated by the following equation : Transfer clock [Hz] =INTTC4 sourcec clock [Hz] ÷ TC4DR set value

		RXDNC setting							
BRG setting	Transfer clock [Hz]	00 (No noise rejection)	01 (Reject pulses shorter than 31/fc[s] as noise)	10 (Reject pulses shorter than 63/fc[s] as noise)	11 (Reject pulses shorter than 127/fc[s] as noise)				
000	fc/13	0	0	0	-				
110 fc/8		0	-	-	-				
(When the transfer clock gen-	fc/16	0	0	$\frac{1}{2}$	- <				
rupt is the same as the right side column)	fc/32	0	0		-				
The setting except the above		0	0		0				

UART2 Status Register

JART2 Sta	atus Re	egister					
UARTSR2	7	6	5	4	3	2	1 0
(01F70H)	PERR	FERR	OERR	RBFL	TEND	TBEP	(Initial value: 0000 11**)
	<u></u>						

PERR	Parity error flag	0: No parity error 1: Parity error	
FERR	Framing error flag	0: No framing error 1: Framing error	
OERR	Overrun error flag	0: No overrun error 1: Overrun error	Read
RBFL	Receive data buffer full flag	0: Receive data buffer empty 1: Receive data buffer full	only
TEND	Transmit end flag	0: On transmitting 1: Transmit end	
TBEP	Transmit data buffer empty flag	 0: Transmit data buffer full (Transmit data writing is finished) 1: Transmit data buffer empty 	
	(7/5)		

		(7/5)		
Note: When	an INTTXD	s generated, TBEP	flag is set t	o/"1" automatically
			\sim	$(\vee /))$

						\searrow)			
UART2 Re	ceive D)ata Bu	ıffer	>			\geq				
RDBUF2	7 <	6	5	4	3	2	1	0	Read only		
(01F72H)	4	\sim	\mathcal{T}		\bigwedge				(Initial value: 0000 0000)		
\langle											
UART2 Tra	ansmit	Data B	uffer								
TDBUF2	7	6	5	4	3	2	1	0	Write only		
(01F72H)	\geq								(Initial value: 0000 0000)		

16.3 Transfer Data Format

16.3 Transfer Data Format

In UART2, an one-bit start bit (Low level), stop bit (Bit length selectable at high level, by UARTCR21<STBT>), and parity (Select parity in UARTCR21<PE>; even- or odd-numbered parity by UARTCR21<EVEN>) are added to the transfer data. The transfer data formats are shown as follows.



16.4 Transfer Rate

The baud rate of UART2 is set of UARTCR21<BRG>. The example of the baud rate are shown as follows.

· · · · ·	
Sourc	ce Clock
16 MHz	8 MHz
76800 [baud]	38400 [baud]
38400	19200
19200	9600
9600	4800
4800	2400
2400	1200
	Source 16 MHz 76800 [baud] 38400 19200 9600 4800 2400

Table 16-	1 Transfer	Rate	(Example)
-----------	------------	------	-----------

When INTTC4 is used as the UART2 transfer rate (when UARTCR21<BRG> 110"), the transfer clock and transfer rate are determined as follows:

Transfer clock [Hz] = TC4 source clock [Hz] / TC4DR setting value

Transfer Rate [baud] = Transfer clock [Hz] / 16

16.5 Data Sampling Method

The UART2 receiver keeps sampling input using the clock selected by UARTCR21<BRG> until a start bit is detected in RXD pin input. RT clock starts detecting "L" level of the RXD pin. Once a start bit is detected, the start bit, data bits, stop bit(s), and parity bit are sampled at three times of RT7, RT8, and RT9 during one receiver clock interval (RT clock). (RT0 is the position where the bit supposedly starts.) Bit is determined according to majority rule (The data are the same twice or more out of three samplings).



(b) With noise rejection circuit

Figure 16-4 Data Sampling Method

16.6 STOP Bit Length

Select a transmit stop bit length (1 bit or 2 bits) by UARTCR21<STBT>.

16.7 Parity

Set parity / no parity by UARTCR21<PE> and set parity type (Odd- or Even-numbered) by UARTCR21<EVEN>.

16.8 Transmit/Receive Operation

16.8.1 Data Transmit Operation

Set UARTCR21<TXE> to "1". Read UARTSR2 to check UARTSR2<TBEP> = "1", then write data in TDBUF2 (Transmit data buffer). Writing data in TDBUF2 zero-clears UARTSR2<TBEP>, transfers the data to the transmit shift register and the data are sequentially output from the TXD pin. The data output include a onebit start bit, stop bits whose number is specified in UARTCR21<STBT> and a parity bit if parity addition is specified. Select the data transfer baud rate using UARTCR21<BRG>. When data transmit starts, transmit buffer empty flag UARTSR2<TBEP> is set to "1" and an INTTXD interrupt is generated.

While UARTCR21<TXE> = "0" and from when "1" is written to UARTCR21<TXE> to when send data are written to TDBUF2, the TXD pin is fixed at high level. When transmitting data, first read UARTSR2, then write data in TDBUF2. Otherwise, UARTSR2<TBEP> is not zero-cleared and transmit does not start.

16.8.2 Data Receive Operation

Set UARTCR21<RXE> to "1". When data are received via the RXD pin, the receive data are transferred to RDBUF2 (Receive data buffer). At this time, the data transmitted includes a start bit and stop bit(s) and a parity bit if parity addition is specified. When stop bit(s) are received, data only are extracted and transferred to RDBUF2 (Receive data buffer). Then the receive buffer full flag UARTSR2<RBFL> is set and an INTRXD interrupt is generated. Select the data transfer baud rate using UARTCR21<BRG>.

If an overrun error (OERR) occurs when data are received, the data are not transferred to RDBUF2 (Receive data buffer) but discarded; data in the RDBUF2 are not affected.

Note: When a receive operation is disabled by setting UARTCR21<RXE> bit to "0", the setting becomes valid when data receive is completed. However, if a framing error occurs in data receive, the receive-disabling setting may not become valid. If a framing error occurs, be sure to perform a re-receive operation.

16.9 Status Flag

16.9.1 Parity Error

When parity determined using the receive data bits differs from the received parity bit, the parity error flag UARTSR2<PERR> is set to "1". The UARTSR2<PERR> is cleared to "0" when the RDBUF2 is read after reading the UARTSR2.



When all bits in the next data are received while unread data are still in RDBUF2, overrun error flag UARTSR2<OERR> is set to "1". In this case, the receive data is discarded; data in RDBUF2 are not affected. The UARTSR2<OERR> is cleared to "0" when the RDBUF2 is read after reading the UARTSR2.

UARTSR2 <rbfl></rbfl>	
RXD pin	Final bit Stop
Shift register	xxx0** xxxx0* 1xxxx0
RDBUF2	уууу
UARTSR2 <oerr></oerr>	After reading UARTSR2 then RDBUF2 clears OERR.
INTRXD interrupt	
	Figure 16-7 Generation of Overrun Error

Note: Receive operations are disabled until the overrun error flag UARTSR2<OERR> is cleared.

16.9.4 Receive Data Buffer Full

Loading the received data in RDBUF2 sets receive data buffer full flag UARTSR2<RBFL> to "1". The UARTSR2<RBFL> is cleared to "0" when the RDBUF2 is read after reading the UARTSR2.

RXD pin	Final bit	Stop	
Shift register	xxx0**	xxxx0*	X 1xxxx0
		\land	¥
RDBUF2	уууу		X xxxx
UARTSR2 <rbfl></rbfl>	(7/5)		After reading UARTSR2 then
		$\square \land$	
INTRXD interrupt		(\vee)	
Figu	re 16-8 Generation	of Receive Da	ta Buffer Full

Note: If the overrun error flag UARTSR2<OERR> is set during the period between reading the UARTSR2 and reading the RDBUF2, it cannot be cleared by only reading the RDBUF2. Therefore, after reading the RDBUF2, read the UARTSR2 again to check whether or not the overrun error flag which should have been cleared still remains set.

16.9.5 Transmit Data Buffer Empty

When no data is in the transmit buffer TDBUF2, that is, when data in TDBUF2 are transferred to the transmit shift register and data transmit starts, transmit data buffer empty flag UARTSR2<TBEP> is set to "1". The UARTSR2<TBEP> is cleared to "0" when the TDBUF2 is written after reading the UARTSR2.

TOSHIBA





16.9.6 Transmit End Flag

When data are transmitted and no data is in TDBUF2 (UARTSR2<TBEP> = "1"), transmit end flag UARTSR2<TEND> is set to "1". The UARTSR2<TEND> is cleared to "0" when the data transmit is stated after writing the TDBUF2.

		//		1
Shift register	***1xx X ****1x X ****1	χ	1уууу0	X*1уууу
				·
TXD pin	Stop	<u>}</u> _	Start	Bit 0
	Data write for TDBUF2	!		
UARTSR2 <tbep></tbep>		5		
		1		
UARTSR2 <tend></tend>		<u>\</u> _		
		Ŀ		
INTTXD interrupt		JL		

Figure 16-10 Generation of Transmit End Flag and Transmit Data Buffer Empty



17. Synchronous Serial Interface (SIO)

The TMP88FW45AFG has a clocked-synchronous 8-bit serial interface. Serial interface has an 8-byte transmit and receive data buffer that can automatically and continuously transfer up to 64 bits of data.

Serial interface is connected to outside peripheral devices via SO, SI, SCK port.

17.1 Configuration



17.2 Control

The serial interface is controlled by SIO control registers (SIOCR1/SIOCR2). The serial interface status can be determined by reading SIO status register (SIOSR).

The transmit and receive data buffer is controlled by the SIOCR2<BUF>. The data buffer is assigned to address 01F98H to 01F9FH for SIO in the DBR area, and can continuously transfer up to 8 words (bytes or nibbles) at one time. When the specified number of words has been transferred, a buffer empty (in the transmit mode) or a buffer full (in the receive mode or transmit/receive mode) interrupt (INTSIO) is generated.

When the internal clock is used as the serial clock in the 8-bit receive mode and the 8-bit transmit/receive mode, a fixed interval wait can be applied to the serial clock for each word transferred. Four different wait times can be selected with SIOCR2<WAIT>.

SIO Contr	rol Reg	ister 1					\mathcal{D}	\frown	
SIOCR1	7	6	5	4	3	2	0		
(1F96H)	SIOS	SIOINH		SIOM	l.	SCK		(Initial value: 0000 0000)	
							\diamond	<u>Q</u>	
	SIOS	Indicate transf	er start / sto	p 0:	Stop Start		C		
:	SIOINH	Continue / abo	ort transfer	0: 1:	Conti Abort	nuously transfer transfer (Automatically clea	red after	abort)	
	SIOM Transfer mode select 000: 8-bit transmit mode 100: 8-bit transmit / receive mode 101: 8-bit receive mode 101: 4-bit receive mode 101: 8-bit receive mode 110: 4-bit receive mode							Write only	
	SCK	Serial clock select			000 001 010 011	NORMAL, IDLE mode DV1CK = 0 DV1CK = 0 fc/2 ¹³ fc/2 ¹⁴ fc/2 ⁸ fc/2 ⁹ fc/2 ⁷ fc/2 ⁸ fc/2 ⁶ fc/2 ⁷			Write
				\sim	100 101	fc/2⁵ fc/2⁴		fc/2 ⁶ fc/2 ⁵	
~	\square		<		110		Reserv	ed	
	$\langle \ \rangle$	//		\searrow	111	External clo	ock (Inpu	t from SCK pin)	

Note 1: fc; High-frequency clock [Hz]

Note 2: Set SIOCR1<SIOS> to "0" and SIOCR1<SIOINH> to "1" when setting the transfer mode or serial clock.

Note 3: SIOCR1 is write-only register, which cannot access any of in read-modify-write instruction such as bit operate, etc.

TOSHIBA

SIOCR	2	7	6	5	4	3	2	1	0	_				
(1F97H)				WA	AIT.		BUF		(Initial value: ***0 0000)				
							-				_			
						Always	s sets "00" ex	cept 8-bit tr	ansmit / rec	eive mode.				
						00: T _f	= T _D (Non wa	ait)						
	WA	іт 🛛	Wait control			01: T _f	= 2T _D (Wait)	\sim		$\langle \wedge \rangle$				
						10: T _f	= 4T _D (Wait)))				
						11: T _f	11: T _f = 8T _D (Wait)							
						000: 1	000: 1 word transfer 01F98H							
						001: 2	words transf	er Ot	F98H ~ 01	F99H	Write			
						010: 3	010: 3 words transfer 01F98H ~ 01F9AH							
		_	Number of t	ansfer word	s	011: 4	011: 4 words transfer 01F98H ~ 01F9BH							
	BO		(Buffer addr	ess in use)		100: 5	words transf	er) 01	IF98H ~ 01I	F9CH				
						101: 6	words transf	er 01	IF98H ~ 01	E9DH				
						110: 7	words transf	er 01	IF98H ~ 01	F9EH				
						111:8	words transf	er 01	IF98H ~ 01I	F9FH				

SIO Control Register 2

Note 1: The lower 4 bits of each buffer are used during 4-bit transfers. Zeros (0) are stored to the upper 4bits when receiving.

- Note 2: Transmitting starts at the lowest address. Received data are also stored starting from the lowest address to the highest address. (The first buffer address transmitted is 01F98H).
- Note 3: The value to be loaded to BUF is held after transfer is completed.
- Note 4: SIOCR2 must be set when the serial interface is stopped (SIOF = 0).
- Note 5: *: Don't care
- Note 6: SIOCR2 is write-only register, which cannot access any of in read-modify-write instruction such as bit operate, etc.
- Note 7: T_f; Frame time, T_D; Data transfer time



Figure 17-2 Frame time (T_f) and Data transfer time (T_D)

SIO Status Register

SIOSR	7	6	5	4	3	2	1	0	
(1F97H)	SIOF	SEF							(Initial value: 00** ****)

SIOF	Serial transfer operating status monitor	0: 1:	Transfer terminated Transfer in process	Read
SEF	Shift operating status monitor	0: 1:	Shift operation terminated Shift operation in process	only

Note 1: After SIOCR1<SIOS> is cleared to "0", SIOSR<SIOF> is cleared to "0" at the termination of transfer or the setting of SIOCR1<SIOINH> to "1".

17.3 Serial clock

17.3.1 Clock source

Internal clock or external clock for the source clock is selected by SIOCR1<SCK>.

17.3.1.1 Internal clock

Any of six frequencies can be selected. The serial clock is output to the outside on the $\overline{\text{SCK}}$ pin. The $\overline{\text{SCK}}$ pin goes high when transfer starts.

When data writing (in the transmit mode) or reading (in the receive mode or the transmit/receive mode) cannot keep up with the serial clock rate, there is a wait function that automatically stops the serial clock and holds the next shift operation until the read/write processing is completed.



17.3.1.2 External clock

An external clock connected to the \overline{SCK} pin is used as the serial clock. In this case, the \overline{SCK} (P43) port should be set to input mode. To ensure shifting, a pulse width of more than 2^4 /fc is required. This pulse is needed for the shift operation to execute certainly. Actually, there is necessary processing time for interrupting, writing, and reading. The minimum pulse is determined by setting the mode and the program.
SCK pin (Input)



 $t_{SCKL}, t_{SCKH} > 2^4/fc$

Figure 17-4 External clock pulse width

17.3.2 Shift edge

The leading edge is used to transmit, and the trailing edge is used to receive

17.3.2.1 Leading edge

Transmitted data are shifted on the leading edge of the serial clock (falling edge of the \overline{SCK} pin input/output).

17.3.2.2 Trailing edge

Received data are shifted on the trailing edge of the serial clock (rising edge of the SCK pin input/output).



17.4 Number of bits to transfer

Either 4-bit or 8-bit serial transfer can be selected. When 4-bit serial transfer is selected, only the lower 4 bits of the transmit/receive data buffer register are used. The upper 4 bits are cleared to "0" when receiving.

The data is transferred in sequence starting at the least significant bit (LSB).

17.5 Number of words to transfer

Up to 8 words consisting of 4 bits of data (4-bit serial transfer) or 8 bits (8-bit serial transfer) of data can be transferred continuously. The number of words to be transferred can be selected by SIOCR2<BUF>.

An INTSIO interrupt is generated when the specified number of words has been transferred. If the number of words is to be changed during transfer, the serial interface must be stopped before making the change. The number of words can be changed during automatic-wait operation of an internal clock. In this case, the serial interface is not required to be stopped.



Figure 17-6 Number of words to transfer (Example: 1word = 4bit)

17.6 Transfer Møde

SIOCR1<SIOM> is used to select the transmit, receive, or transmit/receive mode.

17.6.1 4-bit and 8-bit transfer modes

In these modes, firstly set the SIO control register to the transmit mode, and then write first transmit data (number of transfer words to be transferred) to the data buffer registers (DBR).

After the data are written, the transmission is started by setting SIOCR1<SIOS> to "1". The data are then output sequentially to the SO pin in synchronous with the serial clock, starting with the least significant bit (LSB). As soon as the LSB has been output, the data are transferred from the data buffer register to the shift register. When the final data bit has been transferred and the data buffer register is empty, an INTSIO (Buffer empty) interrupt is generated to request the next transmitted data.

When the internal clock is used, the serial clock will stop and an automatic-wait will be initiated if the next transmitted data are not loaded to the data buffer register by the time the number of data words specified with the SIOCR2<BUF> has been transmitted. Writing even one word of data cancels the automatic-wait; therefore, when transmitting two or more words, always write the next word before transmission of the previous word is completed.

Note: Automatic waits are also canceled by writing to a DBR not being used as a transmit data buffer register; therefore, during SIO do not use such DBR for other applications. For example, when 3 words are transmitted, do not use the DBR of the remained 5 words. When an external clock is used, the data must be written to the data buffer register before shifting next data. Thus, the transfer speed is determined by the maximum delay time from the generation of the interrupt request to writing of the data to the data buffer register by the interrupt service program.

The transmission is ended by clearing SIOCR1<SIOS> to "0" or setting SIOCR1<SIOINH> to "1" in buffer empty interrupt service program.

SIOCR1<SIOS> is cleared, the operation will end after all bits of words are transmitted.

That the transmission has ended can be determined from the status of SIOSR<SIOF> because SIOSR<SIOF> is cleared to "0" when a transfer is completed.

When SIOCR1<SIOINH> is set, the transmission is immediately ended and SIOSR<SIOF> is cleared to "0".

When an external clock is used, it is also necessary to clear SIOCR1<SIOS> to "0" before shifting the next data; If SIOCR1<SIOS> is not cleared before shift out, dummy data will be transmitted and the operation will end.

If it is necessary to change the number of words, SIOCR1<SIOS> should be cleared to "0", then SIOCR2<BUF> must be rewritten after confirming that SIOSR<SIOF> has been cleared to "0".

Clear SIOS
SIOCR1 <sios></sios>
SIOSR <siof></siof>
SIOSR <sef></sef>
30 pin $\frac{1}{a_0 \sqrt{a_1 \sqrt{a_2 \sqrt{a_3 \sqrt{a_4 \sqrt{a_5 \sqrt{a_6 \sqrt{a_7 \sqrt{b_0 \sqrt{b_1 \sqrt{b_2 \sqrt{b_3 \sqrt{b_4 \sqrt{b_5 \sqrt{b_6 \sqrt{b_7}}}}}}}}}$
NTSIO interrupt
DBR
Mite Write (a)
Figure 17-7 Transfer Mode (Example: 8bit, 1word transfer, Internal clock)



17.6.2 4-bit and 8-bit receive modes

After setting the control registers to the receive mode, set SIOCR1<SIOS> to "1" to enable receiving. The data are then transferred to the shift register via the SI pin in synchronous with the serial clock. When one word of data has been received, it is transferred from the shift register to the data buffer register (DBR). When the number of words specified with the SIOCR2<BUF> has been received, an INTSIO (Buffer full) interrupt is generated to request that these data be read out. The data are then read from the data buffer registers by the interrupt service program.

When the internal clock is used, and the previous data are not read from the data buffer register before the next data are received, the serial clock will stop and an automatic-wait will be initiated until the data are read. A wait will not be initiated if even one data word has been read.

Note:Waits are also canceled by reading a DBR not being used as a received data buffer register is read; therefore, during SIO do not use such DBR for other applications.

When an external clock is used, the shift operation is synchronized with the external clock; therefore, the previous data are read before the next data are transferred to the data buffer register. If the previous data have not been read, the next data will not be transferred to the data buffer register and the receiving of any more data will be canceled. When an external clock is used, the maximum transfer speed is determined by the delay between the time when the interrupt request is generated and when the data received have been read.

The receiving is ended by clearing SIOCR1<SIOS> to "0" or setting SIOCR1<SIOINH> to "1" in buffer full interrupt service program.

When SIOCR1<SIOS> is cleared, the current data are transferred to the buffer. After SIOCR1<SIOS> cleared, the receiving is ended at the time that the final bit of the data has been received. That the receiving has ended can be determined from the status of SIOSR<SIOF>. SIOSR<SIOF> is cleared to "0" when the receiving is ended. After confirmed the receiving termination, the final receiving data is read. When SIOCR1<SIOINH> is set, the receiving is immediately ended and SIOSR<SIOF> is cleared to "0". (The received data is ignored, and it is not required to be read out.)

If it is necessary to change the number of words in external clock operation, SIOCR1<SIOS> should be cleared to "0" then SIOCR2<BUF> must be rewritten after confirming that SIOSR<SIOF> has been cleared to "0". If it is necessary to change the number of words in internal clock, during automatic-wait operation which occurs after completion of data receiving, SIOCR2<BUF> must be rewritten before the received data is read out.



Figure 17-10 Receive Mode (Example: 8bit, 1word transfer, Internal clock)

17.6.3 8-bit transfer / receive mode

After setting the SIO control register to the 8-bit transmit/receive mode, write the data to be transmitted first to the data buffer registers (DBR). After that, enable the transmit/receive by setting SIOCR1<SIOS> to "1". When transmitting, the data are output from the SO pin at leading edges of the serial clock. When receiving, the data are input to the SI pin at the trailing edges of the serial clock. When the all receive is enabled, 8-bit data are transferred from the shift register to the data buffer register. An INTSIO interrupt is generated when the number of data words specified with the SIOCR2<BUF> has been transferred. Usually, read the receive data from the buffer register in the interrupt service. The data buffer register is used for both transmitting and receiving; therefore, always write the data to be transmitted after reading the all received data.

When the internal clock is used, a wait is initiated until the received data are read and the next transfer data are written. A wait will not be initiated if even one transfer data word has been written.

When an external clock is used, the shift operation is synchronized with the external clock; therefore, it is necessary to read the received data and write the data to be transmitted next before starting the next shift operation. When an external clock is used, the transfer speed is determined by the maximum delay between generation of an interrupt request and the received data are read and the data to be transmitted next are written.

The transmit/receive operation is ended by clearing SIOCR1<SIOS> to "0" or setting SIOCR1<SIOINH> to "1" in INTSIO interrupt service program.

When SIOCR1<SIOS> is cleared, the current data are transferred to the buffer. After SIOCR1<SIOS> cleared, the transmitting/receiving is ended at the time that the final bit of the data has been transmitted.

That the transmitting/receiving has ended can be determined from the status of SIOSR<SIOF>. SIOSR<SIOF> is cleared to "0" when the transmitting/receiving is ended.

When SIOCR1<SIOINH> is set, the transmit/receive operation is immediately ended and SIOSR<SIOF> is cleared to "0".

If it is necessary to change the number of words in external clock operation, SIOCR1<SIOS> should be cleared to "0", then SIOCR2<BUF> must be rewritten after confirming that SIOSR<SIOF> has been cleared to "0".

If it is necessary to change the number of words in internal clock, during automatic-wait operation which occurs after completion of transmit/receive operation, SIOCR2<BUF> must be rewritten before reading and writing of the receive/transmit data.

Note: The buffer contents are lost when the transfer mode is switched. If it should become necessary to switch

	the transfer mode, and receiving by clearing SIOCR (<sios> to 0, read the last data and then switch the transfer mode.</sios>
	Clear SIOS
SIOCR1 <sios></sios>	
SIOSR <siof></siof>	
SIOSR <sef></sef>	
SCK pin (output)	
SO pin	$\begin{array}{c c} \hline & a_0 \\ \hline & a_1 \\ \hline & a_2 \\ \hline & a_3 \\ \hline & a_4 \\ \hline & a_5 \\ \hline & a_6 \\ \hline & a_7 \\ \hline & b_0 \\ \hline & b_1 \\ \hline & b_2 \\ \hline & b_3 \\ \hline & b_4 \\ \hline & b_5 \\ \hline & b_6 \\ \hline & b_7 \\ \hline \\ \hline & b_7 \\ \hline \\ \hline & b_1 \\ \hline & b_2 \\ \hline & b_3 \\ \hline & b_4 \\ \hline & b_5 \\ \hline & b_6 \\ \hline & b_7 \\ \hline \\ \hline & b_7 \\ \hline \\ \hline & b_7 \\ \hline \\ \hline & b_7 \\ \hline \\ \hline & b_7 \\ \hline \\ \\ & b_7 \\ \hline \\ \\ & b_7 \\ \hline \\ \\ & b_7 \\ \hline \\ \\ \\ & b_7 \\ \hline \\ \\ \\ \\ & b_7 \\ \hline \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ $
SI pin	$\underbrace{c_0 \land c_1 \land c_2 \land c_3 \land c_4 \land c_5 \land c_6 \land c_7} \land d_0 \land d_1 \land d_2 \land d_3 \land d_4 \land d_5 \land d_6 \land d_7}$
INTSIO interrupt	
DBR	a X c X b X d
	Write (a) Read out (c) Write (b) Read out (d)

Figure 17-11 Transfer / Receive Mode (Example: 8bit, 1word transfer, Internal clock)



Figure 17-12 Transmitted Data Hold Time at End of Transfer / Receive



18. 10-bit AD Converter (ADC)

The TMP88FW45AFG have a 10-bit successive approximation type AD converter.

18.1 Configuration

The circuit configuration of the 10-bit AD converter is shown in Figure 18-1.

It consists of control register ADCCRA and ADCCRB, converted value register ADCDRH and ADCDRL, a DA converter, a sample-hold circuit, a comparator, and a successive comparison circuit.





18.2 Register configuration

The AD converter consists of the following four registers:

1. AD converter control register 1 (ADCCRA)

This register selects the analog channels and operation mode (Software start or repeat) in which to perform AD conversion and controls the AD converter as it starts operating.

2. AD converter control register 2 (ADCCRB)

This register selects the AD conversion time and controls the connection of the DA converter (Ladder resistor network).

3. AD converted value register 1 (ADCDRH)

This register used to store the digital value after being converted by the AD converter.

4. AD converted value register 2 (ADCDRL)

This register monitors the operating status of the AD converter.

AD Converter Control Register 1



ADRS	AD conversion start	0:	- AD conversion start	
AMD	AD operating mode	00: 01: 10: 11:	AD operation disable Software start mode Reserved Repeat mode	
AINDS	Analog input control	0: 1:	Analog input enable Analog input disable	
SAIN	Analog input channel select	0000: 0001: 0010: 0011: 0100: 0101: 0110: 0111: 1000: 1011: 1100: 1101: 1100: 1111:	AIN0 AIN1 AIN2 AIN3 AIN4 AIN5 AIN6 AIN7 AIN6 AIN7 AIN8 AIN9 AIN10 AIN10 AIN11 AIN12 AIN12 AIN13 AIN14 AIN15	R/W

- Note 1: Select analog input channel during AD converter stops (ADCDRL<ADBF> = "0").
- Note 2: When the analog input channel is all use disabling, the ADCCRA<AINDS> should be set to "1".
- Note 3: During conversion, Do not perform port output instruction to maintain a precision for all of the pins because analog input port use as general input port. And for port near to analog input, Do not input intense signaling of change.
- Note 4: The ADCCRA<ADRS> is automatically cleared to "0" after starting conversion.
- Note 5: Do not set ADCCRA<ADRS> newly again during AD conversion. Before setting ADCCRA<ADRS> newly again, check ADCDRL<EOCF> to see that the conversion is completed or wait until the interrupt signal (INTADC) is generated (e.g., interrupt handling routine).
- Note 6: After STOP mode is started, AD converter control register1 (ADCCRA) is all initialized and no data can be written in this register. Therefore, to use AD converter again, set the ADCCRA newly after returning to NORMAL mode.
- Note 7: After RESET, ADCCRA<SAIN> is initialized Reserved setting. Therefore, set the appropriate analog input channel to ADCCRA<SAIN> when use AD converter.

TOSHIBA

Note 8: After ADCCRA is set to 00H, AD conversion can not be started for four cycles. Thus, four NOPs must be inserted before setting the ADCCRA<ADRS>.



AD Converter Control Register 2

Note 1: Always set bit0 in ADCCRB to "0" and set bit4 in ADCCRB to "1".

- Note 2: When a read instruction for ADCCRB, bit6 to 7 in ADCCRB read in as undefined data.
- Note 3: After STOP mode is started, AD converter control register2 (ADCCRB) is all initialized and no data can be written in this register. Therefore, to use AD converter again, set the ADCCRB newly after returning to NORMAL mode.

Condition ACK	Conversion time	20 MHz	16 MHz	8 MHz			
000	39/fc	-	<u> </u>	-			
001		Reser	rved				
010) 78/fc		\rightarrow	-			
011	156/fc	$\left(\frac{2}{3}\right)$	-	19.5 µs			
100	312/fc	15.6 µs	19.5 µs	39.0 µs			
101	624/fc	31.2 µs	39.0 µs	78.0 µs			
110	1248/fc	62.4 µs	78.0 µs	156.0 µs			
111		Reserved					
	~						

Table 18-1 ACK setting and Conversion time (at CGCR<DV1CK>="0")



Condition ACK	Conversion time	20 MHz	16 MHz	8 MHz				
000	39/fc	-	-	-				
001	Reserved							
010	78/fc	-	-	-				
011	156/fc	-	-	19.5 µs				
100	312/fc	15.6 µs	19.5 µs	39.0 µs				
101	624/fc	31.2 µs	39.0 µs	78.0 µs				
110	1248/fc	62.4 µs	78.0 µs	156.0 µs				
111	Reserved							

Note 1: Setting for "-" in the above table are inhibited. fc: High Frequency oscillation clock [Hz]

Note 2: Set conversion time setting should be kept more than the following time by Analog reference voltage (VAREF).

-	VAREF =	4.5 to 5.5 V	/ 15.6	δ µs and mo	ore									
AD Conver	ted valu	e Regist	er 1					4						
ADCDRH	7	6	5	4	3	2	1	0						
(0029H)	AD09	AD08	AD07	AD06	AD05	AD04	AD03	AD02	(Initial value: 0000 0000)					
						~	<		25)					
AD Conver	ted value	e Regist	er 2				(\rightarrow					
ADCDRL	7	6	5	4	3	2	1	O						
(0028H)	AD01	AD00	EOCF	ADBF			$\mathcal{A}()$	\searrow	(Initial value: 0000 ****)					
								>						
	EOCF	AD con	version end	flag		0: B 1: C	efore or duri onversion co	ing conversi ompleted	ion	Read				
	ADBF	AD con	version BUS	SY flag	(0: D 1: D	0: During stop of AD conversion only							
Note 1:	The ADC to ADCDI	DRL <eoc RL more fi</eoc 	CF> is clea rst than AI	red to "0" v DCDRH.	when readi	ng the AD	CDRH. The	erefore, th	e AD conversion result shoul	d be read				
Note 2:	The ADC cleared u	DRL <adb pon enteri</adb 	F> is set to ng STOP r	o "1" when node. 🛛 🏑	AD conve	rsion starts	s, and clea	red to "0"	when AD conversion finished	. It also is				
Note 3:	If a read i	instruction	is execute	d for ADC	DRL, read	data of bit	3 to bit0 ar	e unstable	9.					

Page 214

18.3 Function

18.3.1 Software Start Mode

After setting ADCCRA<AMD> to "01" (software start mode), set ADCCRA<ADRS> to "1". AD conversion of the voltage at the analog input pin specified by ADCCRA<SAIN> is thereby started.

After completion of the AD conversion, the conversion result is stored in AD converted value registers (ADCDRH, ADCDRL) and at the same time ADCDRL<EOCF> is set to 1, the AD conversion finished interrupt (INTADC) is generated.

ADRS is automatically cleared after AD conversion has started. Do not set ADCCRA<ADRS> newly again (Restart) during AD conversion. Before setting ADCCRA<ADRS> newly again, check ADCDRL<EOCF> to see that the conversion is completed or wait until the interrupt signal (INTADC) is generated (e.g., interrupt handling routine).



18.3.2 Repeat Mode

AD conversion of the voltage at the analog input pin specified by ADCCRA<SAIN> is performed repeatedly. In this mode, AD conversion is started by setting ADCCRA<ADRS> to "1" after setting ADCCRA<AMD> to "11" (Repeat mode).

After completion of the AD conversion, the conversion result is stored in AD converted value registers (ADCDRH, ADCDRL) and at the same time ADCDRL<EOCF> is set to 1, the AD conversion finished interrupt (INTADC) is generated.

In repeat mode, each time one AD conversion is completed, the next AD conversion is started. To stop AD conversion, set ADCCRA<AMD> to "00" (Disable mode) by writing 0s. The AD convert operation is stopped immediately. The converted value at this time is not stored in the AD converted value register.



- 1. Set up the AD converter control register 1 (ADCCRA) as follows:
 - Choose the channel to AD convert using AD input channel select (SAIN).
 - Specify analog input enable for analog input control (AINDS).
 - Specify AMD for the AD converter control operation mode (software or repeat mode).
- 2. Set up the AD converter control register 2 (ADCCRB) as follows:
 - Set the AD conversion time using AD conversion time (ACK). For details on how to set the conversion time, refer to Figure 18-1, Figure 18-2 and AD converter control register 2.
 Choose IREFON for DA converter control.
- 3. After setting up (1) and (2) above, set AD conversion start (ADRS) of AD converter control register 1 (ADCCRA) to "1". If software start mode has been selected, AD conversion starts immediately.
- 4. After an elapse of the specified AD conversion time, the AD converted value is stored in AD converted value register 1 (ADCDRH) and the AD conversion finished flag (EOCF) of AD converted value register 2 (ADCDRL) is set to "1", upon which time AD conversion interrupt INTADC is generated.
 - EOCF is cleared to "0" by a read of the conversion result. However, if reconverted before a register read, although EOCF is cleared the previous conversion result is retained until the next conversion is completed.

Example :After selecting the conversion time 15.6 µs at 20 MHz and the analog input channel AIN4 pin, perform AD conversion once. After checking EOCF, read the converted value, store the lower 2 bits in address 0009EH and store the upper 8 bits in address 0009FH in RAM. The operation mode is software start mode.

	: (port setting)	:	;Set port register appropriately before setting AD converter registers.
	:	:	; (Refer to section I/O port in details)
	LD	(ADCCRA) , 00100100B	; Select Software start mode, Analog input enable, and AIN4
	LD	(ADCCRB), 00011000B	;Select conversion time(312/fc) and operation mode
			$\sim (7/5)^{-1}$
	SET	(ADCCRA) . 7	; ADRS = 1(AD conversion start)
SLOOP :	TEST	(ADCDRB) . 5	; EOCF= 1 ?
	JRS	T, SLOOP	
		~	
	LD	A , (ADCDRL)	; Read result data
	LD	(9EH) , A	
	LD	A , (ADCDRH)	; Read result data
	LD	(9FH), A	

18.4 STOP mode during AD Conversion

When standby mode (STOP mode) is entered foreibly during AD conversion, the AD convert operation is suspended and the AD converter is initialized (ADCCRA and ADCCRB are initialized to initial value). Also, the conversion result is indeterminate. (Conversion results up to the previous operation are cleared, so be sure to read the conversion results before entering standby mode (STOP mode).) When restored from standby mode (STOP mode), AD conversion is not automatically restarted, so it is necessary to restart AD conversion. Note that since the analog reference voltage is automatically disconnected, there is no possibility of current flowing into the analog reference voltage.

18.5 Analog Input Voltage and AD Conversion Result

The analog input voltage is corresponded to the 10-bit digital value converted by the AD as shown in Figure 18-4.



TOSHIBA

18.6 Precautions about AD Converter

18.6.1 Analog input pin voltage range

Make sure the analog input pins (AIN0 to AIN15) are used at voltages within VAREF to AVSS. If any voltage outside this range is applied to one of the analog input pins, the converted value on that pin becomes uncertain. The other analog input pins also are affected by that.

18.6.2 Analog input shared pins

The analog input pins (AIN0 to AIN15) are shared with input/output ports. When using any of the analog inputs to execute AD conversion, do not execute input/output instructions for all other ports. This is necessary to prevent the accuracy of AD conversion from degrading. Not only these analog input shared pins, some other pins may also be affected by noise arising from input/output to and from adjacent pins.

18.6.3 Noise Countermeasure

The internal equivalent circuit of the analog input pins is shown in Figure 18-5. The higher the output impedance of the analog input source, more easily they are susceptible to noise. Therefore, make sure the output impedance of the signal source in your design is 5 k Ω or less. Toshiba also recommends attaching a capacitor external to the chip.



19. 8-Bit High-speed PWM (HPWM0 and HPWM1)

The TMP88FW45AFG contains two-channels of high-speed PWM. The high-speed PWM works in such a way that when data are written to the data registers for the respective channels, waveforms differing from each other can be output.

The high-speed PWM is shared with ports, P02 (HPWM0) and P03 (HPWM1). When using these pins for high-speed PWM, set the port output latches for P02 and P03 to 1.

19.1 Configuration



19.2 Control

Control Re	egister													
HPWMCR	7	6	5	4	3	2	1	0						
(000CH)	HPE1	HPE0			PWMST		PWM	MOD	R/W (Initial value: 00** 0*00)					
				4.5	00: Moo 01: Moo	le 0 (8 bits) le 1 (7 bits)		\langle						
	PWWWO	Selec		le	10: Moo 11: Res	10: Mode 2 (6 bits) 11: Reserved								
	PWMST Run/stop 8-bit up counter 0: STOP 1: RUN HPE0 Control HPWM0 output 0: Disable 1: Enable								R/W					
	HPE1	Contr	ol HPWM1	output	0: Disat 1: Enab	0: Disable 1: Enable								
Data Regi	ster					La Contra	\triangleright		C					
HPWMDR0	7	6	5	4	3	2	1	0	77					

HPWWDRU	1	0	5	-	3 ()			0	
(000DH)	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0	R/W (Initial value: **** ****)
HPWMDR1	7	6	5	4	3	2	/1	0	
(000EH)	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0	R/W (Initial value: **** ****)

Note 1: The PWM output pulse width varies with the clock duty cycle.

Note 2: For the data registers, set data 10H to F0H.

Note 3: When HPWMCR<PWMST> = 0, the internal counter is cleared and data "1" is output to the port.

Note 4: Before selecting PWM mode, make sure HPWMCR<PWMST> = 0.

Note 5: Before entering STOP mode, set HPWMCR<PWMST, HPE0, and HPE1> all to 0.

Note 6: If HPWMCR<HPE0 or HPE1> is altered in the middle of PWM period, the waveform may be distorted. To avoid waveform distortion, make sure HPWMCR<PWMST> = 0 when enabling HPWM output.

19.3 Functional Description

The high-speed PWM is controlled using the Control Register (HPWMCR) and Data Registers (HPWMDR0, 1). Before writing to these registers, set the HPWMCR<PWMST> = 1 to make them ready for setup. When the HPWMCR<PWMST> is set to 0, each control register is reset, so that the high-speed PWM can be reset in software.

19.3.1 Operation modes

The high-speed PWM has the following three modes of operation:

- 8-bit mode: (T = $2^8 \times \text{clock period}$, f \approx 78 kHz)
- 7-bit mode: (T = $2^7 \times \text{clock period}$, f $\approx 156 \text{ kHz}$)
- 6-bit mode: (T = $2^6 \times \text{clock period}$, f $\approx 313 \text{ kHz}$)

Note: These values apply to the case where the source clock (X1) is 20 MHz.

Use the HPWMCR<PWMMOD> to select operation mode. Note that operation mode is common to both channels, and cannot be set separately for each channel.

19.3.1.1 8-bit mode

In 8-bit mode, it is possible to generate a pulse with 12.8 μ s period and approximately 78 kHz frequency (when X1 = 20 MHz).



The minimum width of the pulse is $0.8 \ \mu s$ (data "10"), and the maximum width of the pulse is $12.0 \ \mu s$ (data "F0").

Pulse width = 8-bit data \times 50 ns

Figure 19-2 shows a typical waveform in 8-bit mode. (The values are for X1 = 20 MHz.)



In 7-bit mode, it is possible to generate a pulse with 6.4 μ s period and approximately 156 kHz frequency (when X1 = 20 MHz).



In 7-bit mode, the period is comprised of 7 bits (period = $2^7 \times 50$ ns) and one other bit provides a 25 ns resolution (half period of the source clock (X1)). Therefore, when the one low-order bit = 1, a plus-25 ns pulse is output.

The minimum width of the pulse is 0.4 μ s (data "10"), and the maximum width of the pulse is 6.0 μ s (data "F0": "78" + "0").



Pulse width = (7 high-order Bits of data \times 50 ns) + (1 low-order Bit of data \times 25 ns) Figure 19-3 shows a typical waveform in 7-bit mode. (The values are for X1 = 20 MHz.)





Note: The resolution of the LSB 1 bit (25 nsec) is a typical value and its precision is not guaranteed.

19.3.1.3 6-bit mode

In 6-bit mode, it is possible to generate a pulse with 3.2 μ s period and approximately 313 kHz frequency (when X1 = 20 MHz).



In 6-bit mode, the period is comprised of 6 bits (period = $2^6 \times 50$ ns) and two other bits provide a 12.5 ns resolution. However, because the actually obtained resolution is 25 ns, said resolution is accomplished artificially. To obtain a 12.5 ns resolution, the first, second, and third pulses are output by adding 25 ns, 0 ns, and 25 ns, respectively. In this way, a 12.5 ns resolution is realized as being "equivalent to."

The minimum equivalent width of the pulse is 0.2 μ s (data "10"), and the maximum equivalent width of the pulse is 3.0 μ s (data "F0": "3B"+ "0").



Pulse width = (6 high-order bits of data \times 50 ns) + (2 low-order bits of data *)

* The equivalent plus times in 2 low-order bits of data are shown below.

2-bit data	Equivalent plus time
0 0	0 ns
0 1	12.5 ns
10	25 ns
11	37.5 ns

Figure 19-4 Shows a typical waveform in 6-bit mode. (The values are for X1 = 20 MHz.)





Note: The resolution of the LSB 2 bit (12.5 nsec) is a typical value and its precision is not guaranteed.

19.3.2 Setting output data

To set output data, write it to the Data Registers (HPWMDR0 and 1).

Example: To output a 5.75 μ s waveform in 7-bit mode using $\overline{\text{HPWM0}}$ when the source clock (X1) = 20 MHz



Because the resolution/in 7-bit mode is 50 ns, to output a 5.75 µs pulse

$$5.75 \ \mu s \div 50 \ ns = 115 = 73H$$

Because 73H is placed in the 7 high-order bits, the value is shifted one bit to become E6H. Therefore, set E6H in the Data Register (HPWMDR0).





20. Flash Memory

TMP88FW45AFG has 122880 bytes flash memory (address: 04000H to 21EFFH and FFF00H to FFFFH). The write and erase operations to the flash memory are controlled in the following three types of mode.

- MCU mode

The flash memory is accessed by the CPU control in the MCU mode. This mode is used for software bug correction and firmware change after shipment of the device since the write operation to the flash memory is available by retaining the application behavior.

- Serial PROM mode

The flash memory is accessed by the CPU control in the serial PROM mode. Use of the serial interface (UART) enables the flash memory to be controlled by the small number of pins. TMP88FW45AFG in the serial PROM mode supports on-board programming which enables users to program flash memory after the microcontroller is mounted on a user board.

- Parallel PROM mode

The parallel PROM mode allows the flash memory to be accessed as a stand-alone flash memory by the program writer provided by the third party. High-speed access to the flash memory is available by controlling address and data signals directly. For the support of the program writer, please ask Toshiba sales representative.

In the MCU and serial PROM modes, the flash memory control register (FLSCR) is used for flash memory control. This chapter describes how to access the flash memory using the flash memory control register (FLSCR) in the MCU and serial PROM modes.

20.1 Flash Memory Control

The flash memory is controlled via the flash memory control register (FLSCR) and flash memory stanby control resister (FLSSTB).



Note 1: The command sequence of the flash memory can be executed only when FLSCR<FLSMD>="0011B". In other cases, any attempts to execute the command sequence are ineffective.

Note 2: FLSCR<FLSMD> must be set to either "1100B" or "0011B".

Note 3: Bits 3 to 0 in FLSCR register are always read as don't care

20.1.1 Flash Memory Command Sequence Execution Control (FLSCR<FLSMD>)

The flash memory can be protected from indvertent write due to program error or microcontroller misoperation. This write protection feature is realized by disabling flash memory command sequence execution via the flash memory control register (write protect). To enable command sequence execution, set FLSCR<FLSMD> to "0011B". To disable command sequence execution, set FLSCR<FLSMD> to "1100B". After reset, FLSCR<FLSMD> is initialized to "1100B" to disable command sequence execution. Normally, FLSCR<FLSMD> should be set to "1100B" except when the flash memory needs to be written or erased.

20.2 Command Sequence

The command sequence in the MCU and the serial PROM modes consists of six commands (JEDEC compatible), as shown in Table 20-1.

Table 20-1	Command	Sequence

	Command Sequence	1st Bus \ cl	1st Bus Write Cy- cle		2nd Bus Write Cy- cle		3rd Bus Write Cy- cle		4th Bus Write Cy- cle		5th Bus Write Cy- cle		6th Bus Write Cy- cle	
	-	Address	Data	Address	Data	Address	Data	Address	Data	Address	Data	Address	Data	
1	1 Byte program	04555H	AAH	04AAA H	55H	04555H	A0H	BA (Note 1)	Data (Note 1)	<u>)</u>	-	-	-	
2	Sector Erase (4-kbyte Erase)	04555H	AAH	04AAA H	55H	04555H	80H	04555H	AAH	04AAA H	55H	SA (Note 2)	30H	
3	Chip Erase (All Erase)	04555H	AAH	04AAA H	55H	04555H	80H	04555H	ААН	04AAA H	55H	04555H	10H	
4	Product ID Entry	04555H	AAH	04AAA H	55H	04555H	90H	75	<u>-</u> <	- (-	-	
	Product ID Exit	ХХН	F0H	-	-	-		\sum	-	Ľ	$\overline{1}^{\prime}$) -	-	
5	Product ID Exit	04555H	AAH	04AAA H	55H	04555H	F0H	> -	- (-	-	
6	Security Program	04555H	AAH	04AAA H	55H	04555H	A5H	04F7FH	00H	Ŋ	-	-	-	

Note 1: Set the address and data to be written.

Note 2: Set the address which is the specified sector. (The area to be erased is specified with the upper 8 bits of the address.) (Example) In case " Sector 1 ", SA is " 0x05yyy ".

20.2.1 Byte Program

This command writes the flash memory for each byte unit. The addresses and data to be written are specified in the 4th bus write cycle. Each byte can be programmed in a maximum of 40 μ s. The next command sequence cannot be executed until the write operation is completed. To check the completion of the write operation, perform read operations repeatedly until the same data is read twice from the same address in the flash memory. During the write operation, any consecutive attempts to read from the same address is reversed bit 6 of the data (toggling between 0 and 1).

Note: To rewrite data to Flash memory addresses at which data (including FFH) is already written, make sure to erase the existing data by "sector erase" or "chip erase" before rewriting data.

20.2.2 Sector Erase (4-kbyte Erase)

This command erases the flash memory in units of 4 kbytes. The flash memory area to be erased is specified by the upper 4 bits of the 6th bus write cycle address. For example, to erase 4 kbytes from F000H to FFFFH, specify one of the addresses in F000H-FFFFH as the 6th bus write cycle. The sector erase command is effective only in the MCU and serial PROM modes, and it cannot be used in the parallel PROM mode.

A maximum of 30 ms is required to erase 4 kbytes. The next command sequence cannot be executed until the erase operation is completed. To check the completion of the erase operation, perform read operations repeatedly for data polling until the same data is read twice from the same address in the flash memory. During the erase operation, any consecutive attempts to read from the same address is reversed bit 6 of the data (toggling between 0 and 1).

20.2.3 Chip Erase (All Erase)

This command erases the entire flash memory in approximately 30 ms. The next command sequence cannot be executed until the erase operation is completed. To check the completion of the erase operation, perform read operations repeatedly for data polling until the same data is read twice from the same address in the flash memory. During the erase operation, any consecutive attempts to read from the same address is reversed bit 6 of the data (toggling between 0 and 1). After the chip is erased, all bytes contain FFH.

20.2.4 Product ID Entry

This command activates the Product ID mode. In the Product ID mode, the vendor ID, the flash ID, and the security program status can be read from the flash memory.

Cell	Address	Meaning	Read Value
1	04000H	Vendor ID	98H
	04001H	Flash macro ID	41H
	04002H FI	Flash size	1DH: 120 kbytes 0EH: 60 kbytes 0BH: 48 kbytes
			07H: 32 kbytes 05H: 24 kbytes 03H: 16 kbytes
			01H: 8 kbytes 00H: 4 kbytes
	04F7FH	Security program status	FFH: Security program disabled Other than FFH: Security program enabled

Table 20-2 Values To Be Read in the Product ID Mode

Note: The value at address 04002H (flash size) depends on the size of flash memory incorporated in each product. For example, if the product has 16 kbyte flash memory, "03H" is read from address 04002H.

20.2.5 Product ID Exit

This command is used to exit the Product ID mode.

20.2.6 Security Program

This command enables the read/write protection setting in the flash memory. When the security program is enabled, the flash memory cannot be read and cannot be written in the parallel PROM mode. In the serial PROM mode, the flash write and RAM loader commands cannot be executed.

To disable the security program setting, it is necessary to execute the chip erase command sequence. Whether or not the security program is enabled can be checked by reading 04F7FH in the Product ID mode. For details, see Table 20-2.

It takes a maximum of 40 μ s to set security program in the flash memory. The next command sequence cannot be executed until this operation is completed. To check the completion of the sequrity program operation, perform read operations repeatedly for data polling until the same data is read twice from the same address in the flash memory. During the security program operation, any attempts to read from the same address is reversed bit 6 of the data (toggling between 0 and 1).

20.3 Toggle Bit (D6)

After the byte program, chip erase, and security program command sequence is executed, any consecutive attempts to read from the same address is reversed bit 6 (D6) of the data (toggling between 0 and 1) until the operation is completed. Therefore, this toggle bit provides a software mechanism to check the completion of each operation. Usually perform read operations repeatedly for data polling until the same data is read twice from the same address in the flash memory. After the byte program, chip erase, or security program command sequence is executed, the initial read of the toggle bit always produces a "1".

20.4 Access to the Flash Memory Area

When the write, erase and security program are set in the flash memory, read and fetch operations cannot be performed in the entire flash memory area. Therefore, to perform these operations in the entire flash memory area, access to the flash memory area by the control program in the BOOTROM or RAM area. (The flash memory.) The serial PROM or MCU mode is used to run the control program in the BOOTROM or RAM area.

- Note 1: The flash memory can be written or read for each byte unit. Erase operations can be performed either in the entire area or in units of 4 kbytes, whereas read operations can be performed by an one transfer instruction. However, the command sequence method is adopted for write and erase operations, requiring several-byte transfer instructions for each operation.
- Note 2: To rewrite data to Flash memory addresses at which data (including FFH) is already written, make sure to erase the existing data by "sector erase" or "chip erase" before rewriting data.

20.4.1 Flash Memory Control in the Serial PROM Mode

The serial PROM mode is used to access to the flash memory by the control program provided in the BOOT-ROM area. Since almost of all operations relating to access to the flash memory can be controlled simply by the communication data of the serial interface (UART), these functions are transparent to the user. For the details of the serial PROM mode, see "Serial PROM Mode."

To access to the flash memory by using peripheral functions in the serial PROM mode, run the RAM loader command to execute the control program in the RAM area. The procedures to execute the control program in the RAM area is shown in "20.4.1.1 How to write to the flash memory by executing the control program in the RAM area (in the RAM loader mode within the serial PROM mode)".

20.4.1.1 How to write to the flash memory by executing the control program in the RAM area (in the RAM loader mode within the serial PROM mode)

(Steps 1 and 2 are controlled by the BOOTROM, and steps 3 to 9 are controlled by the control program executed in the RAM area.)

- 1. Transfer the write control program to the RAM area in the RAM loader mode.
- 2. Jump to the RAM area.
- 3. Disable (DI) the interrupt master enable flag (IMF \leftarrow "0").
- 4. Set FLSCR<FLSMD> to "0011B" (to enable command sequence execution).
- 5. Execute the erase command sequence.
- 6. Read the same flash memory address twice.

(Repeat step 6 until the same data is read by two consecutive reads operations.)

- 7. Execute the write command sequence.
- 8. Read the same flash memory address twice.

(Repeat step 8 until the same data is read by two consecutive reads operations.)

- 9. Set FLSCR<FLSMD> to "1100B" (to disable command sequence execution).
- Note 1: Before writing to the flash memory in the RAM area, disable interrupts by setting the interrupt master enable flag (IMF) to "0". Usually disable interrupts by executing the DI instruction at the head of the write control program in the RAM area.

Note 2: Since the watchdog timer is disabled by the BOOTROM in the RAM loader mode, it is not required to disable the watchdog timer by the RAM loader program.

Example :After chip erasure, the program in the RAM area writes data 3FH to address F000H.

	DI		: Disable interrupts (IMF← "0")
	LD	(FLSCR),0011_1000B	: Enable command sequence execution.
	LD	IX,04555H	
	LD	IY,04AAAH	$\sim (7/5)$
	LD	HL,0F000H	
; #### Flas	sh Memory Chip erase	Process ####	
	LD	(IX),0AAH	: 1st bus write cycle
	LD	(IY),55H	: 2nd bus write cycle
	LD	(IX),80H	: 3rd bus write cycle
	LD	(IX),0AAH	: 4th bus write cycle
	LD	(IY),55H	: 5th bus write cycle
	LD	(IX),10H	: 6th bus write cycle
sLOOP1:	LD	A,(IX)	
	CMP	A,(IX)	$\langle \langle \rangle \rangle \langle \rangle \rangle$
	JR	NZ,sLOOP1	: Loop until the same value is read.
; #### Flas	sh Memory Write Proce	ess ####	
	LD	(IX),0AAH	:1st bus write cycle
	LD	(IY),55H	2nd bus write cycle
	LD	(IX),0A0H (())	: 3rd bus write cycle
	LD	(HL),3FH	: 4th bus write cycle, (F000H) = 3FH
sLOOP2:	LD	A,(HL)	
	CMP	A,(HL)	
	JR	NZ,sLOOP2	: Loop until the same value is read.
	LD	(FLSCR),1100_1000B	: Disable command sequence execution.
sLOOP3:	JP	sLOOP3	$\langle \mathcal{O} \rangle$
	~ 2		
		$\langle \rangle$	~
(4(
$\langle \langle \rangle$	\bigcirc		
$\langle - \rangle$		$\chi \bigcirc$	
	4		
\sim		\sim	

20.4.2 Flash Memory Control in the MCU mode

In the MCU mode, write operations are performed by executing the control program in the RAM area. Before execution of the control program, copy the control program into the RAM area or obtain it from the external using the communication pin. The procedures to execute the control program in the RAM area in the MCU mode are described below.

20.4.2.1 How to write to the flash memory by executing a user write control program in the RAM area (in the MCU mode)

(Steps 1 and 2 are controlled by the program in the flash memory, and steps 3 through 11 are controlled by the control program in the RAM area.)

- 1. Transfer the write control program to the RAM area.
- 2. Jump to the RAM area.
- 3. Disable (DI) the interrupt master enable flag (IMF \leftarrow "0").
- 4. Disable the watchdog timer, if it is used.
- 5. Set FLSCR<FLSMD> to "0011B" (to enable command sequence execution),
- 6. Execute the erase command sequence.
- 7. Read the same flash memory address twice.

(Repeat step 7 until the same data is read by two consecutive read operations.)

- 8. Execute the write command sequence.
- 9. Read the same flash memory address twice.

(Repeat step 9 until the same data is read by two consecutive read operations.)

- 10. Set FLSCR<FLSMD> to "1100B" (to disable command sequence execution).
- 11. Jump to the flash memory area.
- Note 1: Before writing to the flash memory in the RAM area, disable interrupts by setting the interrupt master enable flag (IMF) to "0". Usually disable interrupts by executing the DI instruction at the head of the write control program in the RAM area.
- Note 2: When writing to the flash memory, do not intentionally use non-maskable interrupts (the watchdog timer must be disabled if it is used). If a non-maskable interrupt occurs while the flash memory is being written, unexpected data is read from the flash memory (interrupt vector), resulting in malfunction of the micro-controller.

Example : After sector erasure (E000H-EFFFH), the program in the RAM area writes data 3FH to address E000H.

	DI		: Disable interrupts (IMF←"0")
	LD	(WDTCR2),4EH	: Clear the WDT binary counter.
	LDW	(WDTCR1),0B101H	: Disable the WDT.
	LD	(FLSCR),0011_1000B	: Enable command sequence execution.
	LD	IX,04555H	
	LD	IY,04AAAH	(())
	LD	HL,0E000H	
; #### Flash Mer	nory Sector Era	se Process ####	$\langle (//) \rangle$
	LD	(IX),0AAH	: 1st bus write cycle
	LD	(IY),55H	: 2nd bus write cycle
	LD	(IX),80H	: 3rd bus write cycle
	LD	(IX),0AAH	: 4th bus write cycle
	LD	(IY),55H	: 5th bus write cycle
	LD	(HL),30H	: 6th bus write cycle
sLOOP1:	LD	A,(IX)	
	CMP	A,(IX)	
	JR	NZ,sLOOP1	: Loop until the same value is read.
; #### Flash Mer	mory Write Proc	ess ####	
	LD	(IX),0AAH	:1st bus write cycle
	LD	(IY),55H	: 2nd bus write cycle
	LD	(IX),0A0H	· 3rd bus write cycle
	LD	(HL),3FH	: 4th bus write cycle, (E000H)=3FH
sLOOP2:	LD	A,(HL)	
	CMP	A,(HL)	\sim
	JR	NZ,SLOOP2	: Loop until the same value is read.
	LD	(FLSCR),1100_1000B	: Disable command sequence execution.
	JP	(XXXXH	: Jump to the flash memory area.
	$\langle \rangle$		(7)

Example : This write control program reads data from address F000H and stores it to 98H in the RAM area.



: Read data from address F000H.

: Store data to address 98H.

21. Serial PROM Mode

21.1 Outline

The TMP88FW45AFG has a 4096 byte BOOTROM (Mask ROM) for programming to flash memory. The BOOT-ROM is available in the serial PROM mode, and controlled by TEST, BOOT, RESET and some pins. Communication is performed via UART. The serial PROM mode has seven types of operating mode. Flash memory writing, RAM loader, Flash memory SUM output, Product ID code output, Flash memory status output, Flash memory erasing and Flash memory security program setting. Memory address mapping in the serial PROM mode differs from that in the MCU mode. Figure 21-1 shows memory address mapping in the serial PROM mode.

Table 21-1 Operating Range in the Serial PROM Mode

Parameter	Min	Max	Unit
Power supply	4.5	5.5	X
High frequency (Note)	8	20	MHz

Note 1: Though included in above operating range, some of high frequencies are not supported in the serial PROM mode. For details, refer to "Table 21-5".

21.2 Memory Mapping

The Figure 21-1 shows memory mapping in the Serial PROM mode and MCU mode.

In the serial PROM mode, the BOOTROM (Mask ROM) is mapped in addresses from 3000H to 3FFFH.



Figure 21-1 Memory Address Maps

Note 2: In Serial PROM mode, accessing to registers of oscillation frequency detection is disabled. Therefore oscillation frequency detection is not available in the Serial PROM mode.

21.3 Serial PROM Mode Setting

21.3.1 Serial PROM Mode Control Pins

To execute on-board programming, activate the serial PROM mode. Table 21-2 shows pin setting to activate the serial PROM mode.

Table 21-2 Serial PRC	DM Mode Setting
Pin	Setting
P10, P11	Low
TEST pin	High
BOOT/RXD1 pin	High
RESET pin	

Note: The BOOT pin is shared with the UART communication pin (RXD1 pin) in the serial PROM mode. This pin is used as UART communication pin after activating serial PROM mode

21.3.2 Pin Function

In the serial PROM mode, TXD1 (P45) and RXD1 (P44) are used as a serial interface pin.

 $\langle \cdot \rangle$

Table 21-3 Pin	Function	in the	Serial	PROM	Mode
	i anouon		Contai	11/0101	10000

Pin Name (Serial PROM Mode)	Input/ Output	Fünction		Pin Name (MCU Mode)	
TXD1	Output	Serial data output (Note 3)		P45	
BOOT/RXD1	Input/Input	Serial PROM mode control/Serial data input	(Note 1)	P44	
RESET	Input	Serial PROM mode control		RESET	
TEST	Input	Fixed to high		TEST	
VDD, AVDD	Power supply	4.5 to 5.5 V			
VSS, AVSS	Power supply	0 V			
VAREF	Power supply	Leave open or apply input reference voltage.			
P10, P11	Input (Fixed to low			
I/O ports except P45, P44	I/O	These ports are in the high-impedance state in the serial PROM mode. The input level is fixed to the port inputs with a hardware feature to prevent overlap current. (The port inputs are invalid.) To make the port inputs valid, set the pin of the SPCR register to "1" by the RAM loader control program.			
XIN	Input	Self-oscillate with an oscillator. (Note 2)			
XOUT	Output				

Note 1: During on-board programming with other parts mounted on a user board, be careful no to affect these communication control pins.

Note 2: Operating range of high frequency in serial PROM mode is 8 MHz to 20 MHz.

Note 3: TXD port is set a open-drain port in seriarl PROM mode and it needs pull-up resistor.



Figure 21-3 Example Connection for On-Board Writing

- Note 1: When other parts on the application board effect the UART communication in the serial PROM mode, isolate these pins by a jumper or switch.
- Note 2: When the reset control circuit on the application board effects activation of the serial PROM mode, isolate the pin by a jumper or switch.
- Note 3: For connection of other pins, refer to "Table 21-3 Pin Function in the Serial PROM Mode".

21.3.4 Activating the Serial PROM Mode

The following is a procedure to activate the serial PROM mode. "Figure 21-4 Serial PROM Mode Timing" shows a serial PROM mode timing.

- 1. Supply power to the VDD pin.
- 2. Set the $\overline{\text{RESET}}$ pin to low.
- 3. Set the TEST pin and BOOT/RXD1 pins to high.And set P10,P11 pins to low.
- 4. Wait until the power supply and clock oscillation stabilize.
- 5. Set the $\overline{\text{RESET}}$ pin to high.
- 6. Input the matching data (5AH) to the BOOT/RXD1 pin after setup sequence. For details of the setup timing, refer to "21.16 UART Timing".


21.4 Interface Specifications for UART

The following shows the UART communication format used in the serial PROM mode.

To perform on-board programming, the communication format of the write controller must also be set in the same manner.

The default baud rate is 9600 bps regardless of operating frequency of the microcontroller. The baud rate can be modified by transmitting the baud rate modification data shown in Table 21-4 to TMP88FW45AFG. The Table 21-5 shows an operating frequency and baud rate. The frequencies which are not described in Table 21-5 can not be used.

- Baud rate (Default): 9600 bps
- Data length: 8 bits
- Parity addition: None
- Stop bit: 1 bit

Table 21-4 Baud Rate Modification Data

Baud rate modification data	04H	05H	06H	07H	0AH	18H	28H
Baud rate (bps)	76800	62500	57600	38400	31250	19200	9600

Table 21-5 Operating Frequency and Baud Rate in the Serial PROM Mode

	Reference	Baud Rate (bps)	76	800	62	500	57	600	384	400	312	250	192	200	96	00
(Note 3)	Baud Rate	Modification Da- ta	04	4H	05	БН	06	6H	07	TH /	04	АH	18	3H	28	3H
(Note 3)	Ref. Fre- quency (MHz)	Rating (MHz)	Baud rate (bps)	(%)	(bps)	(%)	(bps)	(%)	(bps)	(%)	(bps)	(%)	(bps)	(%)	(bps)	(%)
1	8	7.64 to 8.39	-	6	62500	0.00	-	<u></u>)	38462	+0.16	31250	0.00	19231	+0.16	9615	+0.16
2	9.8304	9.40 to 10.32	76800	0.00	()	-	-	-	38400	0.00	-	-	19200	0.00	9600	0.00
2	10	9.40 to 10.32	78125	+1.73	<u> </u>		()	$\langle \rangle$	39063	+1.73	-	-	19531	+1.73	9766	+1.73
	12	11.75 to 12.90	-//	-	7 -	-	57692	+0.16	-	-	31250	0.00	18750	-2.34	9375	-2.34
3	12.288	11.75 to 12.90	-	-	- <	-	59077	+2.56	-	-	32000	+2.40	19200	0.00	9600	0.00
	12.5	11.75 to 12.90	-	<u> </u>	60096	-3.85	60096	+4.33	-	-	30048	-3.85	19531	+1.73	9766	+1.73
4	14.7456	14.10 to 15.48	-	-	-	-	57600	0.00	38400	0.00	-	-	19200	0.00	9600	0.00
5	16	15.27 to 16.77	76923	+0.16	62500	0.00	-	-	38462	+0.16	31250	0.00	19231	+0.16	9615	+0.16
c	18	17.62 to 19.35	-	-	41	-	-	-	-	-	-	-	20089	+4.63	9975	+2.34
0	19.668	18.80 to 20.64	76800	0.00		$\langle \rangle$	-	-	38400	0.00	30720	-1.70	19200	0.00	9600	0.00
7	20	18.80 to 20.64	76923	+1.73	(-)	-	-	-	39063	+0.16	31250	0.00	19531	+1.73	9766	+1.73

Note 1: "Ref. Frequency" and "Rating" show frequencies available in the serial PROM mode. Though the frequency is supported in the serial PROM mode, the serial PROM mode may not be activated correctly due to the frequency difference in the external controller (such as personal computer) and oscillator, and load capacitance of communication pins.

Note 2: It is recommended that the total frequency difference is within ±3% so that auto detection is performed correctly by the reference frequency.

Note 3: The external controller must transmit the matching data (5AH) repeatedly till the auto detection of baud rate is performed. This number indicates the number of times the matching data is transmitted for each frequency. **Operation Command**

215

21.5 Operation Command

The eight commands shown in Table 21-6 are used in the serial PROM mode. After reset release, the TMP88FW45AFG waits for the matching data (5AH).

Table 21-6 Operation Command in the Seri	al PROM Mode
--	--------------

Command Data	Operating Mode	Description
5AH	Setup	Matching data. Execute this command after releasing the reset.
F0H	Flash memory erasing	Erases the flash memory area (address 4000H to 21EFFH, and FFF00 to FFFFFH).
30H	Flash memory writing	Writes to the flash memory area (address 4000H to 21EFFH, and FFF00 to FFFFFH) .
60H	RAM loader	Writes to the specified RAM area (address 0040H to 10BFH).
90H	Flash memory SUM output	Outputs the 2-byte checksum upper byte and lower byte in this order for the entire area of the flash memory (address 4000H to 21EFFH, and FFF00 to FFFFFH).
С0Н	Product ID code output	Outputs the product /D code (13-byte data).
СЗН	Flash memory status output	Outputs the status code (7-byte data) such as the security program condition.
FAH	Flash memory security program setting	Enables the security program.

21.6 Operation Mode

The serial PROM mode has seven types of modes, that are (1) Flash memory erasing, (2) Flash memory writing, (3) RAM loader, (4) Flash memory SUM output, (5) Product ID code output, (6) Flash memory status output and (7) Flash memory security program setting modes. Description of each mode is shown below.

1. Flash memory erasing mode

The flash memory is erased by the chip erase (erasing an entire flash area) or sector erase (erasing sectors in 4-kbyte units). The erased area is filled with FFH. When the security program is enabled, the sector erase in the flash erasing mode can not be performed. To disable the security program, perform the chip erase. Before erasing the flash memory, TMP88FW45AFG checks the passwords except a blank product. If the password is not matched, the flash memory erasing mode is not activated.

2. Flash memory writing mode

Data is written to the specified flash memory address for each byte unit. The external controller must transmit the write data in the Intel Hex format (Binary). If no error is encountered till the end record, TMP88FW45AFG calculates the checksum for the entire flash memory area (4000H to 21EFFH, and FFF00H to FFFFFH), and returns the obtained result to the external controller. When the security program is enabled, the flash memory writing mode is not activated. In this case, perform the chip erase command beforehand in the flash memory erasing mode. Before activating the flash memory writing mode, TMP88FW45AFG checks the password except a blank product. If the password is not matched, flash memory writing mode is not activated.

RAM loader mode

The RAM loader transfers the data in Intel Hex format sent from the external controller to the internal RAM. When the transfer is completed normally, the RAM loader calculates the checksum. After transmitting the results, the RAM loader jumps to the RAM address specified with the first data record in order to execute the user program. When the security program is enabled, the RAM loader mode is not activated. In this case, perform the chip erase beforehand in the flash memory erasing mode. Before activating the RAM loader mode, TMP88FW45AFG checks the password except a blank product. If the password is not matched, flash RAM loader mode is not activated.

4. Flash memory SUM output mode

The checksum is calculated for the entire flash memory area (4000H to 21EFFH, and FFF00H to FFFFFH), and the result is returned to the external controller. Since the BOOTROM does not support the operation command to read the flash memory, use this checksum to identify programs when managing revisions of application programs.

5. Product ID code output mode

The code used to identify the product is output. The code to be output consists of 21-byte data, which includes the information indicating the area of the ROM incorporated in the product. The external controller reads this code, and recognizes the product to write.

(In the case of TMP88FW45AFG, the addresses from 4000H to 21EFFH, and FFF00H to FFFFFH become the ROM area.)

6. Flash memory status output mode

The status of the area from FFFE0H to FFFFFH, and the security program condition are output as 7-byte code. The external controller reads this code to recognize the flash memory status.

7. Flash memory security program setting mode

This mode disables reading and writing the flash memory data in parallel PROM mode. In the serial PROM mode, the flash memory writing and RAM loader modes are disabled. To disable the flash memory security program, perform the chip erase in the flash memory erasing mode.

21.6.1 Flash Memory Erasing Mode (Operating command: F0H)

Table 21-7 shows the flash memory erasing mode.

Table	21-7	Flash	Memory	Frasing	Mode
Iable	21-1	1 10311	INCLUOI Y	LIASING	INIOUE

	Transfer Byte	Transfer Data from the External Controller to TMP88FW45AFG	Baud Rate	Transfer Data from TMP88FW45AFG to the External Controller
	1st byte 2nd byte	Matching data (5AH) -	9600 bps 9600 bps	- (Automatic baud rate adjustment) OK: Echo back data (5AH) Error: No data transmitted
	3rd byte 4th byte	Baud rate change data (Table 21-4) -	9600 bps 9600 bps	OK: Echo back data Error: A1H × 3, A3H × 3, 62H × 3 (Note 1)
	5th byte 6th byte	Operation command data (F0H) -	Modified baud rate Modified baud rate	- OK: Echo back data (F0H) Error: A1H × 3, A3H × 3, 63H × 3 (Note 1)
	7th byte 8th byte	Password count storage address bit 23 to 16 (Note 4, 5)	Modified baud rate Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	9th byte 10th byte	Password count storage address bit 15 to 08 (Note 4, 5)	Modified baud rate Modified baud rate	OK: Nothing transmitted Error: Nothing transmitted
	11th byte 12th byte	Password count storage address bit 07 to 00 (Note 4, 5)	Modified baud rate Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
BOOT ROM	13th byte 14th byte	Password comparison start address bit 23 to 16 (Note 4, 5)	Modified baud rate Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	15th byte 16th byte	Password comparison start address bit 15 to 08 (Note 4, 5)	Modified baud rate Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	17th byte 18th byte	Password comparison start address bit 07 to 00 (Note 4, 5)	Modified baud rate Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	19th byte : m'th byte	Password string (Note 4, 5)	Modified baud rate Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	n'th - 2 byte	Erase area specification (Note 2)	Modified baud rate	-
	n'th - 1 byte		Modified baud rate	OK: Checksum (Upper byte) (Note 3) Error: Nothing transmitted
	n'th byte		Modified baud rate	OK: Checksum (Lower byte) (Note 3) Error: Nothing transmitted
~	n'th + 1 byte	(Wait for the next operation command data)	Modified baud rate	-

Note 1: "xxH × 3" indicates that the device enters the halt condition after transmitting 3 bytes of xxh.

Note 2: Refer to "21.13 Specifying the Erasure Area".

Note 3: Refer to "21.8 Checksum (SUM)".

Note 4: Refer to "21.10 Passwords".

Note 5: Do not transmit the password string for a blank product.

Note 6: When a password error occurs, TMP88FW45AFG stops UART communication and enters the halt mode. Therefore, when a password error occurs, initialize TMP88FW45AFG by the RESET pin and reactivate the serial PROM mode.

Note 7: If an error occurs during transfer of a password address or a password string, TMP88FW45AFG stops UART communication and enters the halt condition. Therefore, when a password error occurs, initialize TMP88FW45AFG by the RESET pin and reactivate the serial PROM mode. Description of the flash memory erasing mode

- 1. The 1st through 4th bytes of the transmitted and received data contain the same data as in the flash memory writing mode.
- 2. The 5th byte of the received data contains the command data in the flash memory erasing mode (F0H).
- 3. When the 5th byte of the received data contains the operation command data shown in Table 21-6, the device echoes back the value which is the same data in the 6th byte position of the received data (in this case, F0H). If the 5th byte of the received data does not contain the operation command data, the device enters the halt condition after sending 3 bytes of the operation command error code (63H).
- 4. The 7th thorough m'th bytes of the transmitted and received data contain the same data as in the flash memory writing mode. In the case of a blank product, do not transmit a password string. (Do not transmit a dummy password string.)
- 5. The n'th 2 byte contains the erasure area specification data. The upper 4 bits and lower 4 bits specify the start address and end address of the erasure area, respectively. For the detailed description, see "21.13 Specifying the Erasure Area".
- 6. The n'th 1 byte and n'th byte contain the upper and lower bytes of the checksum, respectively. For how to calculate the checksum, refer to "21.8 Checksum (SUM)". Checksum is calculated unless a receiving error or Intel Hex format error occurs. After sending the end record, the external controller judges whether the transmission is completed correctly by receiving the checksum sent by the device.
- 7. After sending the checksum, the device waits for the next operation command data.

Page 243

21.6.2 Flash Memory Writing Mode (Operation command: 30H)

Table 21-8 shows flash memory writing mode process.

Table 21-8 Flash Memory Writing Mode Process

	Transfer Byte	Transfer Data from External Controller to TMP88FW45AFG	Baud Rate	Transfer Data from TMP88FW45AFG to External Controller
	1st byte 2nd byte	Matching data (5Ah) -	9600 bps 9600 bps	- (Automatic baud rate adjustment) OK: Echo back data (5AH) Error: Nothing transmitted
	3rd byte 4th byte	Baud rate modification data (See Table 21-4) -	9600 bps 9600 bps	- OK: Echo back data Error: A1H × 3, A3H × 3, 62H × 3 (Note 1)
	5th byte 6th byte	Operation command data (30H) -	Modified baud rate Modified baud rate	- OK: Echo back data (30H) Error: A1H × 3, A3H × 3, 63H × 3 (Note 1)
	7th byte 8th byte	Password count storage address bit 23 to 16 (Note 4)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	9th byte 10th byte	Password count storage address bit 15 to 08 (Note 4)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
BOOT ROM	11th byte 12th byte	Password count storage address bit 07 to 00 (Note 4)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	13th byte 14th byte	Password comparison start address bit 23 to 16 (Note 4)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	15th byte 16th byte	Password comparison start address bit 15 to 08 (Note 4)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	17th byte 18th byte	Password comparison start address bit 07 to 00 (Note 4)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	19th byte : m'th byte	Password string (Note 5)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
4	m'th + 1 byte n'th - 2 byte	Intel Hex format (binary) (Note 2)	Modified baud rate	-
~	n'th - 1 byte	-	Modified baud rate	OK: SUM (Upper byte) (Note 3) Error: Nothing transmitted
	n'th byte	-	Modified baud rate	OK: SUM (Lower byte) (Note 3) Error: Nothing transmitted
	n'th + 1 byte	(Wait state for the next operation command data)	Modified baud rate	-

Note 1: "xxH × 3" indicates that the device enters the halt condition after sending 3 bytes of xxH. For details, refer to "21.7 Error Code".

Note 2: Refer to "21.9 Intel Hex Format (Binary)".

Note 3: Refer to "21.8 Checksum (SUM)".

Note 4: Refer to "21.10 Passwords".

Note 5: If addresses from FFFE0H to FFFFFH are filled with "FFH", the passwords are not compared because the device is considered as a blank product. Transmitting a password string is not required. Even in the case of a blank product, it is required to specify the password count storage address and the password comparison start address. Transmit these data

from the external controller. If a password error occurs due to incorrect password count storage address or password comparison start address, TMP88FW45AFG stops UART communication and enters the halt condition. Therefore, when a password error occurs, initialize TMP88FW45AFG by the RESET pin and reactivate the serial ROM mode.

- Note 6: If the security program is enabled or a password error occurs, TMP88FW45AFG stops UART communication and enters the halt confition. In this case, initialize TMP88FW45AFG by the RESET pin and reactivate the serial ROM mode.
- Note 7: If an error occurs during the reception of a password address or a password string, TMP88FW45AFG stops UART communication and enters the halt condition. In this case, initialize TMP88FW45AFG by the RESET pin and reactivate the serial PROM mode.
- Note 8: Do not write only the address from FFFE0H to FFFFFH when all flash memory data is the same. If only these area are written, the subsequent operation can not be executed due to password error.
- Note 9: To rewrite data to Flash memory addresses at which data (including FFH) is already written, make sure to erase the existing data by "sector erase" or "chip erase" before rewriting data.

Description of the flash memory writing mode

- 1. The 1st byte of the received data contains the matching data. When the serial PROM mode is activated, TMP88FW45AFG (hereafter called device), waits to receive the matching data (5AH). Upon reception of the matching data, the device automatically adjusts the UART's initial baud rate to 9600 bps.
- 2. When receiving the matching data (5AH), the device transmits an echo back data (5AH) as the second byte data to the external controller. If the device can not recognize the matching data, it does not transmit the echo back data and waits for the matching data again with automatic baud rate adjustment. Therefore, the external controller should transmit the matching data repeatedly till the device transmits an echo back data. The transmission repetition count varies depending on the frequency of device. For details, refer to Table 21-5.
- 3. The 3rd byte of the received data contains the baud rate modification data. The five types of baud rate modification data shown in Table 21-4 are available. Even if baud rate is not modified, the external controller should transmit the initial baud rate data (28H: 9600 bps).
- 4. Only when the 3rd byte of the received data contains the baud rate modification data corresponding to the device's operating frequency, the device echoes back data the value which is the same data in the 4th byte position of the received data. After the echo back data is transmitted, baud rate modification becomes effective. If the 3rd byte of the received data does not contain the baud rate modification data, the device enters the halts condition after sending 3 bytes of baud rate modification error code (62H).
- 5. The 5th byte of the received data contains the command data (30H) to write the flash memory.
- 6. When the 5th byte of the received data contains the operation command data shown in Table 21-6, the device echoes back the value which is the same data in the 6th byte position of the received data (in this case, 30H). If the 5th byte of the received data does not contain the operation command data, the device enters the halt condition after sending 3 bytes of the operation command error code (63H).
- 7. The 7th byte contains the data for 23 to 16 bits of the password count storage address. When the data received with the 7th byte has no receiving error, the device does not send any data. If a receiving error or password error occurs, the device does not send any data and enters the halt condition.

The 9th byte contains the data for 15 to 8 bits of the password count storage address. When the data received with the 9th byte has no receiving error, the device does not send any data. If a receiving error or password error occurs, the device does not send any data and enters the halt condition.

- 9. The 11th byte contains the data for 7 to 0 bits of the password count storage address. When the data received with the 11th byte has no receiving error, the device does not send any data. If a receiving error or password error occurs, the device does not send any data and enters the halt condition.
- 10. The 13th byte contains the data for 23 to 16 bits of the password comparison start address. When the data received with the 13th byte has no receiving error, the device does not send any data. If a receiving error or password error occurs, the device does not send any data and enters the halt condition.
- 11. The 15th byte contains the data for 15 to 8 bits of the password comparison start address. When the data received with the 15th byte has no receiving error, the device does not send any data. If a receiving error or password error occurs, the device does not send any data and enters the halt condition.
- 12. The 17th byte contains the data for 7 to 0 bits of the password comparison start address. When the data received with the 17th byte has no receiving error, the device does not send any data. If a receiving error or password error occurs, the device does not send any data and enters the halt condition.
- 13. The 19th through m'th bytes contain the password data. The number of passwords becomes the data (N) stored in the password count storage address. The external password data is compared with N-byte

data from the address specified by the password comparison start address. The external controller should send N-byte password data to the device. If the passwords do not match, the device enters the halt condition without returning an error code to the external controller. If the addresses from FFFE0H to FFFFFH are filled with "FFH", the passwords are not conpared because the device is considered as a blank product.

- 14. The m'th + 1 through n'th 2 bytes of the received data contain the binary data in the Intel Hex format. No received data is echoed back to the external controller. After receiving the start mark (3AH for ":") in the Intel Hex format, the device starts data record reception. Therefore, the received data except 3AH is ignored until the start mark is received. After receiving the start mark, the device receives the data record, that consists of data length, address, record type, write data and checksum. Since the device starts checksum calculation after receiving an end record, the external controller should wait for the checksum after sending the end record. If a receiving error or Intel Hex format error occurs, the device enters the halts condition without returning an error code to the external controller.
- 15. The n'th 1 and n'th bytes contain the checksum upper and lower bytes. For details on how to calculate the SUM, refer to "21.8 Checksum (SUM)". The checksum is calculated only when the end record is detected and no receiving error or Intel Hex format error occurs. After sending the end record, the external controller judges whether the transmission is completed correctly by receiving the checksum sent by the device.
- 16. After transmitting the checksum, the device waits for the next operation command data.

21.6.3 RAM Loader Mode (Operation Command: 60H)

Table 21-9 shows RAM loader mode process.

Table 21-9 RAM Loader Mode Process

	Transfer Bytes	Transfer Data from External Controller to TMP88FW45AFG	Baud Rate	Transfer Data from TMP88FW45AFG to External Controller
	1st byte 2nd byte	Matching data (5AH) -	9600 bps 9600 bps	- (Automatic baud rate adjustment) OK: Echo back data (5AH) Error: Nothing transmitted
	3rd byte 4th byte	Baud rate modification data (See Table 21-4) -	9600 bps 9600 bps	OK: Echo back data Error: A1H x/3, A3H x/3, 62H x/3 (Note 1)
	5th byte 6th byte	Operation command data (60H) -	Modified baud rate Modified baud rate	- OK: Echo back data (60H) Error: A1H × 3, A3H × 3, 63H × 3 (Note 1)
	7th byte 8th byte	Password count storage address bit 23 to 16 (Note 4)	Modified baud rate	OK: Nothing transmitted Error; Nothing transmitted
	9th byte 10th byte	Password count storage address bit 15 to 08 (Note 4)	Modified baud rate	OK: Nothing transmitted Error: Nothing transmitted
5007	11th byte 12th byte	Password count storage address bit 07 to 00 (Note 4)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
ROM	13th byte 14th byte	Password comparison start address bit 23 to 16 (Note 4)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	15th byte 16th byte	Password comparison start address bit 15 to 08 (Note 4)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	17th byte 18th byte	Password comparison start address bit 07 to 00 (Note 4)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	19th byte : m'th byte	Password string (Note 5)	Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	m'th + 1 byte : n'th - 2 byte	Intel Hex format (Binary) (Note 2)	Modified baud rate	-
	n'th - 1 byte	- 1	Modified baud rate	OK: SUM (Upper byte) (Note 3) Error: Nothing transmitted
	n'th byte	-	Modified baud rate	OK: SUM (Lower byte) (Note 3) Error: Nothing transmitted
RAM	-	The program jumps to the start address	of RAM in which the first transfe	rred data is written.

Note 1: "xxH × 3" indicates that the device enters the halt condition after sending 3 bytes of xxH. For details, refer to "21.7 Error Code".

Note 2: Refer to "21.9 Intel Hex Format (Binary)".

- Note 3: Refer to "21.8 Checksum (SUM)".
- Note 4: Refer to "21.10 Passwords".
- Note 5: If addresses from FFFE0H to FFFFFH are filled with "FFH", the passwords are not compared because the device is considered as a blank product. Transmitting a password string is not required. Even in the case of a blank product, it is required to specify the password count storage address and the password comparison start address. Transmit these data

from the external controller. If a password error occurs due to incorrect password count storage address or password comparison start address, TMP88FW45AFG stops UART communication and enters the halt condition. Therefore, when a password error occurs, initialize TMP88FW45AFG by the RESET pin and reactivate the serial ROM mode.

- Note 6: After transmitting a password string, the external controller must not transmit only an end record. If receiving an end record after a password string, the device may not operate correctly.
- Note 7: If the security program is enabled or a password error occurs, TMP88FW45AFG stops UART communication and enters the halt condition. In this case, initialize TMP88FW45AFG by the RESET pin and reactivate the serial PROM mode.
- Note 8: If an error occurs during the reception of a password address or a password string, TMP88FW45AFG stops UART communication and enters the halt condition. In this case, initialize TMP88FW45AFG by the RESET pin and reactivate the serial PROM mode.
- Note 9: To re-write data for the address of flash memory which has already written data (include "EF"), make sure to erase the data first by the sector erase or chip erase, and then write new data to the flash memory.

Description of RAM loader mode

- 1. The 1st through 4th bytes of the transmitted and received data contains the same data as in the flash memory writing mode.
- 2. In the 5th byte of the received data contains the RAM loader command data (60H).
- 3. When th 5th byte of the received data contains the operation command data shown in Table 21-6, the device echoes back the value which is the same data in the 6th byte position (in this case, 60H). If the 5th byte does not contain the operation command data, the device enters the halt condition after sending 3 bytes of operation command error code (63H).
- 4. The 7th through m'th bytes of the transmitted and received data contain the same data as in the flash memory writing mode.
- 5. The m'th + 1 through n'th 2 bytes of the received data contain the binary data in the Intel Hex format. No received data is echoed back to the external controller. After receiving the start mark (3AH for ":") in the Intel Hex format, the device starts data record reception. Therefore, the received data except 3AH is ignored until the start mark is received. After receiving the start mark, the device receives the data record, that consists of data length, address, record type, write data and checksum. The writing data of the data record is written into RAM specified by address. Since the device starts checksum calculation after receiving an end record, the external controller should wait for the checksum after sending the end record. If a receiving error or Intel Hex format error occurs, the device enters the halts condition without returning an error code to the external controller.
- 6. The n'th 1 and n'th bytes contain the checksum upper and lower bytes. For details on how to calculate the SUM, refer to "21.8 Checksum (SUM)". The checksum is calculated only when the end record is detected and no receiving error or Intel Hex format error occurs. After sending the end record, the external controller judges whether the transmission is completed correctly by receiving the checksum sent by the device.
- 7. After transmitting the checksum to the external controller, the boot program jumps to the RAM address that is specified by the first received data record.

Note 1: To rewrite data to Flash memory addresses at which data (including FFH) is already written, make sure to erase the existing data by "sector erase" or "chip erase" before rewriting data.

21.6.4 Flash Memory SUM Output Mode (Operation Command: 90H)

Table 21-10 shows flash memory SUM output mode process.

Tahle	21-10	Flash	Memory	MUR V	Outou	It Process
Iable	21-10	газн	IVIEITIOI y	SUIVI	Outpt	

	Transfer Bytes	Transfer Data from External Control- ler to TMP88FW45AFG	Baud Rate	Transfer Data from TMP88FW45AFG to External Controller
	1st byte	Matching data (5AH)	9600 bps	- (Automatic baud rate adjustment)
	2nd byte	-	9600 bps	OK: Echo back data (5AH)
	3rd byte	Baud rate modification data	9600 bps	
	4th byte - 96		9600 bps	OK: Echo back data
				Error: ATH × 3, A3H × 3, 62H × 3 (Note 1)
BOOT	5th byte	Operation command data (90H)	Modified baud rate	-
ROM	6th byte	-	Modified baud rate	OK: Echo back data (90H)
			$(\overline{\alpha})$	Error: A1H × 3, A3H × 3, 63H × 3 (Note 1)
	7th byte	-	Modified baud rate	OK: SUM (Upper byte) (Note 2)
				Error: Nothing transmitted
	8th byte	-	Modified baud rate	OK: SUM (Lower byte) (Note 2)
				Error: Nothing transmitted
	9th byte	(Wait for the next operation command data)	Modified baud rate	

Note 1: "xxH × 3" indicates that the device enters the halt condition after sending 3 bytes of xxH. For details, refer to "21.7 Error Code".

Note 2: Refer to "21.8 Checksum (SUM)".

Description of the flash memory SUM output mode

- 1. The 1st through 4th bytes of the transmitted and received data contains the same data as in the flash memory writing mode.
- 2. The 5th byte of the received data contains the command data in the flash memory SUM output mode (90H).
- 3. When the 5th byte of the received data contains the operation command data shown in Table 21-6, the device echoes back the value which is the same data in the 6th byte position of the received data (in this case, 90H). If the 5th byte of the received data does not contain the operation command data, the device enters the halt condition after transmitting 3 bytes of operation command error code (63H).
- 4. The 7th and the 8th bytes contain the upper and lower bits of the checksum, respectively. For how to calculate the checksum, refer to "21.8 Checksum (SUM)".

After sending the checksum, the device waits for the next operation command data.

21.6.5 Product ID Code Output Mode (Operation Command: C0H)

Table 21-11 shows product ID code output mode process.

Table 21-11 Product ID Code Output Process

	Transfer Bytes	Transfer Data from External Controller to TMP88FW45AFG	Baud Rate	Transfei	Data from TMP88FW45AFG to External Controller		
	1st byte 2nd byte	Matching data (5AH) -	9600 bps 9600 bps	- (Automa OK: Echo Error: No	atic baud rate adjustment) back data (5AH) thing transmitted		
	3rd byte 4th byte	Baud rate modification data (Table 21-4) 9600 bps 0K: 9600 bps 0K:			K: Echo back data rror: A1H × 3, A3H × 3, 62H × 3 (Note 1)		
	5th byte 6th byte	Operation command data (C0H) -	Modified baud rate Modified baud rate	- OK: Echo Error: A1	o back data (C0H) H × 3, A3H × 3, 63H × 3 (Note 1)		
	7th byte	((Modified baud rate	зан	Start mark		
	8th byte		Modified baud rate	12H	The number of transfer data (from 9th to 26th bytes)		
	9th byte		Modified baud rate	-03H (Length of address (3 bytes)		
	10th byte		Modified baud rate	3DH	Reserved data		
	11th byte		Modified baud rate	00H	Reserved data		
	12th byte		Modified baud rate	00H	Reserved data		
	13th byte		Modified baud rate	00H	Reserved data		
	14th byte		Modified baud rate	02H	ROM block count (2 block)		
	15th byte	(C)	Modified baud rate	00H	First address of ROM block 1 (Upper byte)		
DOOT	16th byte		Modified baud rate	40H	First address of ROM block 1 (Middle byte)		
ROM	17th byte		Modified baud rate	00H	First address of ROM block 1 (Lower byte)		
	18th byte		Modified baud rate	02H	End address of ROM block 1 (Upper byte)		
	19th byte		Modified baud rate	1EH	End address of ROM block 1 (Middle byte)		
	20th byte		Modified baud rate	FFH	End address of ROM block 1 (Lower byte)		
\langle	21st byte		Modified baud rate	0FH	First address of ROM block 2 (Upper byte)		
	22nd byte	$(\underline{\boldsymbol{\mathcal{S}}})$	Modified baud rate	FFH	First address of ROM block 2 (Middle byte)		
	23rd byte		Modified baud rate	00H	First address of ROM block 2 (Lower byte)		
	24th byte		Modified baud rate	0FH	End address of ROM block 2 (Upper byte)		
	25th byte		Modified baud rate	FFH	End address of ROM block 2 (Middle byte)		
	26th byte		Modified baud rate	FFH	End address of ROM block 2 (Lower byte)		
	27th byte		Modified baud rate	44H	Checksum of transferred data (9th through 26th byte)		
	28th byte	(Wait for the next operation command data)	Modified baud rate	-			

Note: "xxH × 3" indicates that the device enters the halt condition after sending 3 bytes of xxH. For details, refer to "21.7 Error Code".

Description of Product ID code output mode

- 1. The 1st through 4th bytes of the transmitted and received data contain the same data as in the flash memory writing mode.
- 2. The 5th byte of the received data contains the product ID code output mode command data (C0H).
- 3. When the 5th byte contains the operation command data shown in Table 21-6, the device echoes back the value which is the same data in the 6th byte position of the received data (in this case, C0H). If the 5th byte data does not contain the operation command data, the device enters the halt condition after sending 3 bytes of operation command error code (63H).
- 4. The 9th through 26th bytes contain the product ID code. For details, refer to "21.11 Product ID Code".
- 5. After sending the checksum, the device waits for the next operation command data.

21.6.6 Flash Memory Status Output Mode (Operation Command: C3H)

Table 21-12 shows Flash memory status output mode process.

Table 21-12 Flash Memory Status Output Mode Process

	Transfer Bytes	Transfer Data from External Con- troller to TMP88FW45AFG	Baud Rate	Transfer Data from TMP88FW45AFG to Ex- ternal Controller
	1st byte	Matching data (5AH)	9600 bps	- (Automatic baud rate adjustment)
	2nd byte -		9600 bps	OK: Echo back data (5AH)
			(Error: Nothing transmitted
	3rd byte	Baud rate modification data	9600 bps	
		(See Table 21-4)		
	4th byte	-	9600 bps	OK: Echo back data
				Error: A1H × 3, A3H × 3, 62H × 3 (Note 1)
	5th byte	Operation command data (C3H)	Modified baud rate	
	6th byte	-	Modified baud rate	OK: Echo back data (C3H)
				Error: A1H × 3, A3H × 3, 63H × 3 (Note 1)
	7th byte		Modified baud rate	3AH Start mark
	8th byte		Modified baud rate	04H Byte count
		C		(from 9th to 12th byte)
BOOT	9th byte	9th byte		00H Status code 1
ROM				to
				03H
	10th byte		Modified baud rate	00H Reserved data
	11th byte		Modified baud rate	00H Reserved data
	12th byte		Modified baud rate	00H Reserved data
	13th byte		Modified baud rate	Checksum 2's complement for the sum of 9th through 12th bytes
				9th byte Checksum
		$(\sqrt{5})$		00H: 00H
			$(0/\delta)$	01H: FFH
			$\langle \vee \rangle$	02H: FEH
				03H: FDH
	14th byte	(Wait for the next operation com-	Modified baud rate	-
		mand data)		

Note 1: "xxH × 3" indicates that the device enters the halt condition after sending 3 bytes of xxH. For details, refer to "21.7 Error Code".

Note 2: For the details on status code 1, refer to "21.12 Flash Memory Status Code".

Description of Flash memory status output mode

- 1. The 1st through 4th bytes of the transmitted and received data contain the same data as in the Flash memory writing mode.
- 2. The 5th byte of the received data contains the flash memory status output mode command data (C3H).
- 3. When the 5th byte contains the operation command data shown in Table 21-6, the device echoes back the value which is the same data in the 6th byte position of the received data (in this case, C3H). If the 5th byte does not contain the operation command data, the device enters the halt condition after sending 3 bytes of operation command error code (63H).
- 4. The 9th through 13th bytes contain the status code. For details on the status code, refer to "21.12 Flash Memory Status Code".
- 5. After sending the status code, the device waits for the next operation command data.

21.6.7 Flash Memory Security Program Setting Mode (Operation Command: FAH)

Table 21-13 shows Flash memory security program setting mode process.

 Table 21-13 Flash Memory Security Program Setting Mode Process

	Transfer Bytes	Transfer Data from External Control- ler to TMP88FW45AFG	Baud Rate	Transfer Data from TMP88FW45AFG to Ex- ternal Controller
	1st byte 2nd byte	Matching data (5AH) -	9600 bps 9600 bps	- (Automatic baud rate adjustment) OK: Echo back data (5AH) Error: Nothing transmitted
	3rd byte 4th byte	Baud rate modification data (See Table 21-4) -	9600 bps 9600 bps	OK: Echo back data
	5th byte 6th byte	Operation command data (FAH) -	Modified baud rate Modified baud rate	- OK: Echo back data (FAH) Error: A1H × 3, A3H × 3, 63H × 3 (Note 1)
	7th byte 8th byte	Password count storage address 23 to 16 (Note 2)	Modified baud rate Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
BOOT ROM	9th byte 10th byte	Password count storage address 15 to 08 (Note 2)	Modified baud rate Modified baud rate	OK: Nothing transmitted Error: Nothing transmitted
	11th byte 12th byte	Password count storage address 07 to 00 (Note 2)	Modified baud rate Modified baud rate	OK: Nothing transmitted Error: Nothing transmitted
	13th byte 14th byte	Password comparison start address 23 to 16 (Note 2)	Modified baud rate Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	15th byte 16th byte	Password comparison start address 15 to 08 (Note 2)	Modified baud rate Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
1	17th byte 18th byte	Password comparison start address 07 to 00 (Note 2)	Modified baud rate Modified baud rate	- OK: Nothing transmitted Error: Nothing transmitted
	19th byte	Password string (Note 2)	Modified baud rate	-
	m'th byte		Modified baud rate	OK: Nothing transmitted Error: Nothing transmitted
	n'th byte		Modified baud rate	OK: FBH (Note 3) Error: Nothing transmitted
V/	n'+1th byte	(Wait for the next operation com- mand data)	Modified baud rate	-

Note 1: "xxH × 3" indicates that the device enters the halt condition after sending 3 bytes of xxH. For details, refer to "21.7 Error Code".

Note 2: Refer to "21.10 Passwords".

Note 3: If the security program is enabled for a blank product or a password error occurs for a non-blank product, TMP88FW45AFG stops UART communication and enters the halt mode. In this case, initialize TMP88FW45AFG by the RESET pin and reactivate the serial PROM mode.

Note 4: If an error occurs during reception of a password address or a password string, TMP88FW45AFG stops UART communication and enters the halt mode. In this case, initialize TMP88FW45AFG by the RESET pin and reactivate the serial PROM mode. Description of the Flash memory security program setting mode

- 1. The 1st through 4th bytes of the transmitted and received data contain the same data as in the Flash memory writing mode.
- 2. The 5th byte of the received data contains the command data in the flash memory status output mode (FAH).
- 3. When the 5th byte of the received data contains the operation command data shown in Table 21-6, the device echoes back the value which is the same data in the 6th byte position of the received data (in this case, FAH). If the 5th byte does not contain the operation command data, the device enters the halt condition after transmitting 3 bytes of operation command error code (63H).
- 4. The 7th through m'th bytes of the transmitted and received data contain the same data as in the flash memory writing mode.
- 5. The n'th byte contains the status to be transmitted to the external controller in the case of the successful security program.

21.7 Error Code

When detecting an error, the device transmits the error code to the external controller, as shown in Table 21-14.

Table	21-14	Error	Code
-------	-------	-------	------

Transmit Data	Meaning of Error Data
62H, 62H, 62H	Baud rate modification error.
63H, 63H, 63H	Operation command error.
A1H, A1H, A1H	Framing error in the received data.
A3H, A3H, A3H	Overrun error in the received data.

Note: If a password error occurs, TMP88FW45AFG does not transmit an error code.

21.8 Checksum (SUM)

21.8.1 Calculation Method

The checksum (SUM) is calculated with the sum of all bytes, and the obtained result is returned as a word. The data is read for each byte unit and the calculated result is returned as a word.

Example:



The checksum which is transmitted by executing the flash memory write command, RAM loader command, or flash memory SUM output command is calculated in the manner, as shown above.

21.8.2 Calculation data

The data used to calculate the checksum is listed in Table 21-15.

Table 21-15 Checksum Calculation Data

Operating Mode	Calculation Data	Description		
Flash memory writing mode		Even when a part of the flash memory is written, the checksum		
	Data in the entire area of the flash memory	of the entire flash memory area (04000H to 21EFFH, and FFF00H to FFFFFH) is calculated.		
Flash memory SUM output mode		The data length, address, record type and checksum in Intel Hex format are not included in the checksum.		
RAM loader mode	RAM data written in the first received RAM ad- dress through the last received RAM address	The length of data, address, record type and checksum in Intel Hex format are not included in the checksum.		
Product ID Code Output mode	9th through 18th bytes of the transferred data	For details, refer to "21.11 Product ID Code".		
Flash Memory Status Output mode	9th through 12th bytes of the transferred data	For details, refer to "21.12 Flash Memory Status Code"		
Flash Memory Erasing mode	All data in the erased area of the flash memory (the whole or part of the flash memory)	When the sector erase is executed, only the erased area is used to calculate the checksum. In the case of the chip erase, an entire area of the flash memory is used.		

21.9 Intel Hex Format (Binary)

- 1. After receiving the checksum of a data record, the device waits for the start mark (3AH ":") of the next data record. After receiving the checksum of a data record, the device ignores the data except 3AH transmitted by the external controller.
- 2. After transmitting the checksum of end record, the external controller must transmit nothing, and wait for the 2-byte receive data (upper and lower bytes of the checksum).
- 3. If a receiving error or Intel Hex format error occurs, the device enters the halt condition without returning an error code to the external controller. The Intel Hex format error occurs in the following case:

When the record type is not 00H, 01H, or 02H

When a checksum error occurs

When the data length of an extended record (record type = 02H) is not 02H

When the device receives the data record after receiving an extended record (record type = 02H) with

extended address of 1000H or larger.

When the data length of the end record (record type $\neq 01$ H) is not 00H

21.10 Passwords

The consecutive eight or more-byte data in the flash memory area can be specified to the password. TMP88FW45AFG compares the data string specified to the password with the password string transmitted from the external controller. The area in which passwords can be specified is located at addresses 04000H to 21EFFH, and FFF00H to FFFFFH. The area from FFA0H to FFFFFH can not be specified as the passwords area.

If addresses from FFFE0H through FFFFFH are filled with "FFH", the passwords are not compared because the product is considered as a blank product. Even in this case, the password count storage addresses and password comparison start address must be specified. Table 21-16 shows the password setting in the blank product and non-blank product.

	Table 21-16 Password S	etting in the Blank Prod	luct and Non-Blank Product
--	------------------------	--------------------------	----------------------------

Password	Blank Product (Note 1)	Non-Blank Product
PNSA (Password count storage address)	04000H ≤ PNSA ≤ 21EFFH	04000H ≤ PNSA ≤ 21EFFH
PCSA (Password comparison start address)	04000H ≤ PCSA ≤ 21EFFH	04000H ≤ PCSA ≤ 21F00H - N
(Password count)		8 ≤ N
Password string setting	Not required (Note 5)	Required (Note 2)

Note 1: When addresses from FFFE0H through FFFFFH are filled with "FFH", the product is recognized as a blank product. Note 2: The data including the same consecutive data (three or more bytes) can not be used as a password. (This causes a password error data.TMP88FW45AFG transmits no data and enters the halt condition.)

Note 3: *: Don't care.

Note 4: When the above condition is not met, a password error occurs. If a password error occurs, the device enters the halt condition without returning the error code.

Note 5: In the flash memory writing mode or RAM loader mode, the blank product receives the Intel Hex format data immediately after receiving PCSA without receiving password strings. In this case, the subsequent processing is performed correctly because the blank product ignores the data except the start mark (3AH ":") as the Intel Hex format data, even if the external controller transmits the dummy password string. However, if the dummy password string contains "3AH", it is detected as the start mark erroneously. The microcontroller enters the halt mode. If this causes the problem, do not transmit the dummy password strings.

Note 6: In the flash memory erasing mode, the external controller must not transmit the password string for the blank product.



21.10.1 Password String

The password string transmitted from the external controller is compared with the specified data in the flash memory. When the password string is not matched to the data in the flash memory, the device enters the halt condition due to the password error.

21.10.2 Handling of Password Error

If a password error occurs, the device enters the halt condition. In this case, reset the device to reactivate the serial PROM mode.

21.10.3 Password Management during Program Development

If a program is modified many times in the development stage, confusion may arise as to the password. Therefore, it is recommended to use a fixed password in the program development stage.

Example :Specify PNSA to F000H, and the password string to 8 bytes from address F001H (PCSA becomes F001H.)

Password Section code abs = 0F000H

DB	08H	: PNSA definition
DB	"CODE1234"	: Password string definitior

21.11 Product ID Code

The product ID code is the 21-byte data containing the start address and the end address of ROM. Table 21-17 shows the product ID code format.

		\geq
Data	Description	In the Case of TMP88FW45AFG
1st	Start Mark (3AH)	ЗАН
2nd	The number of transfer data (18 bytes from 3rd to 20th byte)	
3rd	Address length (3 bytes)	03H
4th	Reserved data	3DH
5th	Reserved data	оон
6th	Reserved data	ООН
7th	Reserved data	оон
8th	ROM block count	02H
9th	The first address of ROM block 1 (Upper byte)	ООН
10th	The first address of ROM block 1 (Middle byte)	40H
11th	The first address of ROM block 1 (Lower byte)	бон
12th	The end address of ROM block 1 (Upper byte)	02H)
13th	The end address of ROM block 1 (Middle byte)	TEH
14th	The end address of ROM block 1 (Lower byte)	FFH
15th	The first address of ROM block 2 (Upper byte)	0FH
16th	The first address of ROM block 2 (Middle byte)	FFH
17th	The first address of ROM block 2 (Lower byte)	оон
18th	The end address of ROM block 2 (Upper byte)	0FH
19th	The end address of ROM block 2 (Middle byte)	FFH
20th	The end address of ROM block 2 (Lower byte)	FFH
21th	Checksum of the transferred data (2's compliment for the sum of 3rd through 20th bytes)	44H

Table 21-17 Product ID Code Format

21.12 Flash Memory Status Code

The flash memory status code is the 7-byte data including the security program status and the status of the data from FFFE0H to FFFFFH. Table 21-18 shows the flash memory status code.



	Data	Description	In the Case of TMP88FW45AFG
	1st	Start mark	ЗАН
	2nd	Transferred data count (3rd through 6th byte)	04H
	3rd	Status code	00H to 03H (See figure below)
	4th	Reserved data	00H
	5th	Reserved data	00Н
	6th	Reserved data	HOO
	7th	Checksum of the transferred data (2's compliment for the sum of 3rd through 6th data)	3rd byte checksum 00H 00H 01H FFH 02H FEH 03H FDH
Status Code 1			
7	6	5 4 3 2	1 0
			RPENA BLANK (Initial Value: 0000 00**)
	_		
	RPENA	Flash memory read se- curity program status 0: Security program 1: Security program	gram is disabled. gram is enabled.
	BLANK	The status from FFFE0H 0: All data is Ff to FFFFFH 1: The value ex	FH in the area from FFFE0H to FFFFFH. ccept FFH is included in the area from FFFE0H to FFFFFH.

Table 21-18 Flash Memory Status Code

Some operation commands are limited by the flash memory status code 1. If the security program is enabled, flash memory writing mode command and RAM loader mode command can not be executed. Erase all flash memory before executing these command.

RPENA	BLANK	Flash Memory Writing Mode	RAM Loader Mode	Flash memory SUM Output Mode	Product ID Code Output Mode	Flash Memory Status Output Mode	Flash Memory Erasing Mode	Security pro- gram Setting Mode
0	0		0	0	0	0	0	×
0	1((Pass	Pass	0	0	0	Pass	Pass
1 <	0)) ×	×	0	0	0	0	×
1	1	×	× ((x	0	0	0	Pass	Pass

Note: O: The command can be executed.

Pass: The command can be executed with a password.

×: The command can not be executed.

(After echoing the command back to the external controller, TMP88FW45AFG stops UART communication and enters

the halt condition.)

21.13 Specifying the Erasure Area

In the flash memory erasing mode, the erasure area of the flash memory is specified by n-2 byte data.

The address of an erasure area is specified by ERAREA.

The sector erase (flash memory erasing every 4K bytes) is performed if the address data from "00H" to "1DH" is specified by ERAREA.

The chip erase (all flash memory erasing) is performed if the address data from "COH" to "FFH" is specified by ERAREA. At the same time, the security program for flash memory is also disabled.

Therefore, make sure to execute the chip erase (not sector erase) to disable the security program for flash memory. Executing the sector erase while the security program is enabled results in an infinite loop.

Erasure Area Specification Data (n-2 byte data)



- Note 1: When the sector erase is executed for the area containing no flash cell, TMP88FW45AFG stops the UART communi cation and enters the halt condition.
- Note 2: Executing the sector erase while the security program is enabled results in an infinite loop.



21.14 Port Input Control Register

In the serial PROM mode, the input level is fixed to the all ports except P45 and P44 ports with a hardware feature to prevent overlap current to unused ports. (All port inputs and peripheral function inputs shared with the ports become invalid.) Therefore, to access to the flash memory in the RAM loader mode without UART communication, port inputs must be valid. To make port inputs valid, set the pin of the port input control register (SPCR) to "1".

The SPCR register is not operated in the MCU mode.

Port Input Control Register 6 5 2 SPCR 7 4 3 (1FFEH) PIN (Initial value: **** ***0) 0 : Invalid port inputs (The input level is fixed with a hardware feature.) PIN Port input control in the serial PROM mode R/W 1 : Valid port inputs Note 1: The SPCR register can be read or written only in the serial PROM mode. When the write instruction is executed to the SPCR register in the MCU mode, the port input control can not be performed. When the read instruction is executed for the SPCR register in the MCU mode, read data of bit7 to 1 are unstable. Note 2: All I/O ports except P45 and P44 ports are controlled by the SPCR register.

21.15 Flowchart



21.16 UART Timing

Table 21-19 UART Timing-1 (VDD = 4.5 to 5.5 V, fc = 8 to 20 MHz, Topr = -10 to 40°C)

Decemeter	Sumbol		Minimum Required Time		
Parameter	Symbol	Clock Frequency (fc)	At fc = 8 MHz	At fc = 20 MHz	
Time from matching data reception to the echo back	CMeb1	Approx. 930	116.3µs	46.5 µs	
Time from baud rate modification data reception to the echo back	CMeb2	Approx. 980	122.5 µs	49.0 µs	
Time from operation command reception to the echo back	CMeb3	Approx. 800	100 µs	40 µs	
Checksum calculation time	CKsm	Approx. 7864500	0.98 s	0.39 s	
Erasure time of an entire flash memory	CEall	-	30 ms	30 ms	
Erasure time for a sector of a flash memory (in 4-kbyte units)	CEsec	- ((15 ms	15 ms	

Table 21-20 UART Timing-2 (VDD = 4.5 to 5.5 V, fc = 8 to 20 MHz, Topr = -10 to 40°C)

Description			Minimum Required Time	
Parameter	Symbol	Clock Frequency (fc)	At fc = 8 MHz	At fc = 20 MHz
Time from the reset release to the acceptance of start bit of RXD pin	RXsup	2100	262.5 µs	105.0 µs
Matching data transmission interval	CMtr1	28500	3.56 ms	1.43 ms
Time from the echo back of matching data to the acceptance of baud rate modification data	CMtr2	380	47.5 µs	19.0 µs
Time from the echo back of baud rate modification data to the acceptance of an operation command	CMtr3	650	81.25 μs	32.5 µs
Time from the echo back of operation command to the acceptance of pass- word count storage addresses (Upper byte)	CMtr4	800	100 µs	40 µs



TOSHIBA

22. Input/Output Circuitry

22.1 Control pins

The input/output circuitries of the TMP88FW45AFG control pins are shown below.



22.2 Input/output ports

Port	1/0	Input/output Circuit	Remark
P0 P3 P4 P5 P8		Initial "High-Z" Data output Output control Disable Pin input	Tri-state output Programmable open-drain P3, P4, P5: Large-current port Hysteresis input
P9	I/O	Initial "High-Z" Data output Output control Disable Pin input	Tri-state output Programmable open-drain

Port	I/O	Input/output Circuit	Remark
P6 P7	I/O	Initial "High-Z" Data output Disable Pin input	Tri-state output
P1	I/O	Initial "High-Z" Data output Disable Pin input	Tri-state output Hysteresis input
P2	I/O	Initial "High-Z"	Open-drain output Hysteresis input

TOSHIBA

23. Electrical Characteristics

23.1 Absolute Maximum Ratings

The absolute maximum ratings are rated values which must not be exceeded during operation, even for an instant. Any one of the ratings must not be exceeded. If any absolute maximum rating is exceeded, a device may break down or its performance may be degraded, causing it to catch fire or explode resulting in injury to the user. Thus, when designing products which include this device, ensure that no absolute maximum rating value will ever be exceeded.

					(V _{SS} = 0 V)
Parameter	Symbol	Pins	Ratings	Unit	
Supply voltage	V _{DD}		-0.3 to 6.0)^ (V_	
Input voltage	V _{IN}		-0.3 to V _{DD} + 0.3	×	
Output voltage	V _{OUT1}		-0.3 to V _{DD} + 0.3	∕ v	
	I _{ОН}	P0,P1,P3,P4,P5,P6, P7,P8,P9 ports	-1.8	2	
Output current (Per 1 pin)	I _{OL1}	P0,P1,P2,P6,P7,P8, P9 ports	3.2		
	I _{OL2}	P3,P4,P5 ports	30	((
	Σ I _{OUT1}	P0,P1,P2,P6,P7,P8,P9 ports	60	mA	Total current (Normal ports) (Except P3,P4,P5)
	Σ I _{OUT2}	P3 port	60	\bigcirc	Total current (8 pins) P3 large current port
Output current (Total)	Σ I _{OUT3}	P4 port	60		Total current (8 pins) P4 large current port
	Σ I _{OUT4}	P5 port	60	/	T5tal current (8 pins) P3 large current port
Power dissipation	P _D ((Topr = 85 °C	350	mW	QFP
Soldering temperature (time)	Tsld		260 (10 s)		
Storage temperature	Tstg	$\langle \langle \rangle$	-55 to 125	°C	
Operating temperature	Topr		-40 to 85		

23.2 **Operating Conditions**

The Operating Conditions show the conditions under which the device be used in order for it to operate normally while maintaining its quality. If the device is used outside the range of Operating Conditions (power supply voltage, operating temperature range, or AC/DC rated values), it may operate erratically. Therefore, when designing your application equipment, always make sure its intended working conditions will not exceed the range of Operating Conditions.

$(V_{SS} = 0 \text{ V}, \text{ Topr} = -40 \text{ to } 85^{\circ}\text{C}$							
Parameter	Symbol	Pins	Ratings	(Min 🔿	Max	Unit	
Supply voltage	V _{DD}		NORMAL / IDLE / STOP modes	4.5	5.5		
	V _{IH1}	Normal input ports (P6,P7,P9)		V _{DD} × 0.70			
Input high level	V _{IH2}	Hysteresis input ports (P0,P1,P2,P3,P4,P5, P8, RESET)	V _{DD} ≥ 4.5 V	V _{DD} × 0.75	VDD	v	
	V _{IL1}	Normal input ports (P6,P7,P9)	(75)	\diamond	V _{DD} × 0.30		
Input low level	V _{IL2}	Hysteresis input ports (P0,P1,P2,P3,P4,P5, P8, RESET)	V _{DD} ≥ 4.5 V	0	V _{DD} × 0.25		
Clock frequency	fc	XIN, XOUT	V _{DD} = 4.5 to 5.5 V	8.0	20.0	MHz	

MCU mode (Flash Programming or erasing) 23.2.1

			\wedge	(V _S	$_{\rm S} = 0$ V, 1 opr = -?	10 to 40°C)
Parameter	Symbol	Pins	Ratings	Min	Max	Unit
Supply voltage	V _{DD}		NORMAL / IDLE / STOP modes	4.5	5.5	
	VIH1	Normal input ports (P6,P7,P9)		V _{DD} × 0.70		
Input high level	V _{IH2}	Hysteresis input ports (P0,P1,P2,P3,P4,P5, P8, RESET)	V _{DD} ≥4.5′V	$V_{DD} \times 0.70$ $V_{DD} \times 0.75$ $V_{DD} \times 0.30$	V	
V _{IL1}	V _{IL1}	Normal input ports (P6,P7,P9)			V _{DD} × 0.30	
Input low level	V _{1L2}	Hysteresis input ports (P0,P1,P2,P3,P4,P5, P8, RESET)	V _{DD} ≥ 4.5 V	0	V _{DD} × 0.25	
Clock frequency) fc	XIN, XOUT	V _{DD} = 4.5 to 5.5 V	8.0	20.0	MHz
_						

23.2.2 MCU mode (Except Flash Programming or erasing)

(V _{SS} = 0 V, Topr = -40 to 85°C)							
Parameter	Symbol	Pins	Ratings	Min	Max	Unit	
Supply voltage	V _{DD}		NORMAL / IDLE / STOP modes	4.5	5.5		
	V _{IH1}	Normal input ports (P6,P7,P9)		V _{DD} × 0.70			
Input high level	V _{IH2}	Hysteresis input ports (P0,P1,P2,P3,P4,P5, P8, RESET)	V _{DD} ≥ 4.5 V	V _{DD} -× 0:75	V _{DD}	V	
Input low level	V _{IL1}	Normal input ports (P6,P7,P9)			V _{DD} × 0.30		
	V _{IL2}	Hysteresis input ports (P0,P1,P2,P3,P4,P5, P8, RESET)	V _{DD} ≥ 4.5 V		V _{DD} × 0.25		
Clock frequency	fc	XIN, XOUT	V _{DD} = 4.5 to 5.5 V	8.0	20.0	MHz	

23.2.3 Serial PROM mode

					_S = 0 V, Topr = -	10 to 40°C)
Parameter	Symbol	Pins	Ratings	Min	Max	Unit
Supply voltage	V _{DD}		NORMAL / IDLE / STOP modes	4.5	5.5	
	V _{IH1}	Normal input ports (P6,P7,P9)		V _{DD} × 0.70		• •
Input high level	V _{IH2}	V _{IH2} Hysteresis input ports (P0,P1,P2,P3,P4,P5, P8, $\overline{\text{RESET}}$) V _{DD} \geq 4.5 V		V _{DD} × 0.75	V _{DD}	v
Input low level	V _{IL1}	Normal input ports (P6,P7,P9)			V _{DD} × 0.30	
	VIL2	Hysteresis input ports (P0,P1,P2,P3,P4,P5, P8, RESET)	V _{DD} 24.5 V	0	V _{DD} × 0.25	
Clock frequency	fc	XIN, XOUT	V _{DD} = 4.5 to 5.5 V	8.0	20.0	MHz

23.3 DC Characteristics

				(VSS	- 0 V, 10	pi – -40 li	0 65 ()
Parameter	Symbol	Pins	Condition	Min	Тур.	Max	Unit
	I _{IN1}	TEST					
Input current	I _{IN2}	Sink open drain, tri - state port	V _{DD} = 5.5 V, V _{IN} = 5.5 V/0 V	$\overline{)}$	-	±2	μA
	I _{IN3}	RESET, STOP	($\left(\right)$	\mathbf{P}		
Input resistance	R _{IN2}	RESET	V _{DD} = 5.5 V, V _{IN} = 5.5 V	90	220	510	kΩ
Output leakage current	I _{LO1}	Sink open drain, tri - state port	V _{DD} = 5.5 V, V _{OUT} = 5.5 V/0 V	5)-	-	±2	μA
Output high voltage	V _{OH}	Tri - state port	V _{DD} = 4.5 V, I _{OH} = -0.7 mA	4.1	-	-	V
	I _{OL1}	P0,P1,P2,P6,P7,P8,P9 ports	V _{DD} = 4.5 V, V _{OL} = 0.4 V	-	1.6	-	
Output low current	I _{OL2}	P3,P4,P5 ports	V _{DD} = 4.5 V, V _{OL} = 1.0 V	-	20	-	mA
Peak current on inter- mittent operation (Note 4)	I _{DD-P}		V _{DD} = 5.5 V	-	10	<u>></u>	
Supply current in NORMAL mode			V _{DD} = 5.5 V V _{IN} = 5.3 V/0.2 V	O_{j}	15	22	mA
Supply current in IDLE mode	I _{DD}		fc = 16 MHz V _{TEST} = 5.3 V / 0.1 V (Note 6)	\mathbb{Z}	8	14.5	
Supply current in STOP mode			V _{DD} = 5.5 V V _{IN} = 5.3 V/0.2 V V _{TEST} = 5.3 V / 0.1 V (Note 6)	9)	2	100	μΑ

Note 1: Typical values show those at Topr = $25 \degree C$ and $V_{DD} = 5 \lor V$.

Note 2: Input current (I_{IN1}, I_{IN3}): The current through pull-up or pull-down resistor is not included.

Note 3: I_{DD} does not include I_{REF} .

- Note 4: When a program is executing in the flash memory or when data is being read from the flash memory, the flash memory operates in an intermittent manner, causing peak currents in the operation current, as shown in Figure 23-1. In this case, the supply current I_{DD} (in NORMAL mode) is defined as the sum of the average peak current and MCU current.
- Note 5: The circuit of a power supply must be designed such as to enable the supply of a peak current. This peak current causes the supply voltage in the device to fluctuate. Connect a bypass capacitor of about 0.1µF near the power supply of the device to stabilize its operation.
- Note 6: V_{TEST} shows input low voltage to TEST pin.
- Note 7: To execute the Protram, Erase and Security Program commands on the flash memory, the temperature must be kept within Topr = 10 to 40 degree celsius. If this temperature range is not observed, operation cannot be guaranteed.





23.4 AD Characteristics

Parameter	Symbol	Condition	Min	Тур.	M 8 bit	ax 10 bit	Unit
Analog reference voltage	V _{AREF}	$AV_{DD} = V_{AREF}$, $V_{SS} = 0.0 V$	V _{DD} - 1.0	- /	V _I	סכ	V
Analog input voltage	V _{AIN}		V _{ASS}	- (REF	v
Power supply current of analog refer- ence voltage	I _{REF}	$V_{DD} = AV_{DD} = V_{AREF} = 5.5 V$ $V_{SS} = AV_{SS} = 0.0 V$	- <	0.5		.0	mA
Non linearity error			-		±1	±2	
Zero point error		$V_{DD} = AV_{DD} = 5.0 \text{ V},$	- (\bigcirc	±1	±2	
Full scale error		$V_{SS} = AV_{SS} = 0.0$ V VAREE = 5.0 V	-	\mathcal{O}	±1	±2	LOB
Total error		ANER) -	±2	±4	

(V_{SS} = 0.0 V, 4.5 V \leq V_{DD} \leq 5.5 V, Topr = -40 to 85 °C)

Note 1: The total error includes all errors except a quantization error, and is defined as a maximum deviation from the ideal conversion line.

Note 2: Conversion time is different in recommended value by power supply voltage.

Note 3: The voltage to be input on the AIN input pin must not exceed the range between V_{AREF} and V_{SS}. If a voltage outside this range is input, conversion values will become unstable and conversion values of other channels will also be affected.

Note 4: Analog reference voltage range: $\Delta V_{AREF} = V_{AREF} - V_{SS}$

Note 5: When AD converter is not used, fix the AV_{DD} and V_{AREF} pin on the V_{DD} level.

23.5 AC Characteristics

 $(V_{SS} = 0 \text{ V}, 4.5 \text{ V} \le V_{DD} \le 5.5 \text{ V}, \text{ Topr} = -40 \text{ to } 85^{\circ}\text{C})$

Parameter	Symbol	Condition	Min	Тур.	Max	Unit
Machine cycle time	t¢y	NORMAL mode	0.2	-	0.5	μs
High-level clock pulse width	twcн	For external clock operation (XIN input)	05			
Low-level clock pulse width	twcL	fc = 20 MHz	25	-	-	ris

23.6 Oscillation Frequency Detection AC Characteristics


23.8 Recommended Oscillating Conditions



- Note 1: To ensure stable oscillation, the resonator position, load capacitance, etc. must be appropriate. Because these factors are greatly affected by board patterns, please be sure to evaluate operation on the board on which the device will actually be mounted.
- Note 2: The product numbers and specifications of the resonators by Murata Manufacturing Co., Ltd. are subject to change. For up-to-date information, please refer to the following URL: http://www.murata.com

23.9 Handling Precaution

- The solderability test conditions for lead-free products (indicated by the suffix G in product name) are shown below.
 - 1. When using the Sn-37Pb solder bath

Solder bath temperature = $230^{\circ}C$

Dipping time = 5 seconds

Number of times = once

R-type flux used

2. When using the Sn-3.0Ag-0.5Cu solder bath

Solder bath temperature = $245^{\circ}C$

Dipping time = 5 seconds

Number of times = once

- R-type flux used
- Note: The pass criterion of the above test is as follows: Solderability rate until forming \geq 95 %
- When using the device (oscillator) in places exposed to high electric fields such as cathode-ray tubes, we recommend electrically shielding the package in order to maintain normal operating condition.



24. Package Dimensions

QFP80-P-1420-0.80B Rev 01



This is a technical document that describes the operating functions and electrical specifications of the 8-bit microcontroller series TLCS-870/X (LSI).

Toshiba provides a variety of development tools and basic software to enable efficient software development.

These development tools have specifications that support advances in microcomputer hardware (LSI) and can be used extensively. Both the hardware and software are supported continuously with version updates.

The recent advances in CMOS LSI production technology have been phenomenal and microcomputer systems for LSI design are constantly being improved. The products described in this document may also be revised in the future. Be sure to check the latest specifications before using.

Toshiba is developing highly integrated, high-performance microcomputers using advanced MOS production technology and especially well proven CMOS technology.

We are prepared to meet the requests for custom packaging for a variety of application areas.

We are confident that our products can satisfy your application needs now and in the future.