

Linear Systems replaces discontinued Siliconix 2N4119A

The 2N4119A is an Ultra-High Input Impedance N-Channel JFET

The 2N4119A provides ultra-high input impedance. The device is specified with a 1-pA limit and typically operates at 0.2 pA. The part is ideal for use as a high-impedance sensitive front-end amplifier.

2N4119A Benefits:

- Insignificant Signal Loss / Error Voltage with High-Impedance Source
- Low Power Consumption (Battery)
- Maximum Signal Output, Low Noise
- High Sensitivity to Low-Level Signals

2N4119A Applications:

- High-Impedance Transducer
- Smoke Detector Input
- Infrared Detector Amplifier
- Precision Test Equipment

FEATURES

DIRECT REPLACEMENT FOR SILICONIX 2N4119A

LOW POWER $I_{DSS} < 90 \mu A$

MINIMUM CIRCUIT LOADING $I_{GSS} < 1 pA$

ABSOLUTE MAXIMUM RATINGS
@ 25°C (unless otherwise noted)

Maximum Temperatures

Storage Temperature -65°C to +175°C

Operating Junction Temperature -55°C to +150°C

Maximum Power Dissipation

Continuous Power Dissipation 300mW

MAXIMUM CURRENT

Gate Current (Note 1) 50mA

MAXIMUM VOLTAGES

Gate to Drain or Gate to Source (Note 2) -40V

2N4119A ELECTRICAL CHARACTERISTICS @ 25°C (unless otherwise noted)

SYMBOL	CHARACTERISTIC	MIN	TYP.	MAX	UNITS	CONDITIONS
BV_{GSS}	Gate to Source Breakdown Voltage	-40	--	--	V	$I_G = -1 \mu A, V_{DS} = 0V$
$V_{GS(off)}$	Gate to Source Cutoff Voltage	-2	--	-6	V	$V_{DS} = 10V, I_D = 1nA$
I_{DSS}	Gate to Source Saturation Current	0.20	--	0.60	mA	$V_{DS} = 10V, V_{GS} = 0V$
I_{GSS}	Gate Leakage Current	--	--	-1	pA	$V_{GS} = -20V, V_{DS} = 0V$
		--	--	-2.5		$V_{GS} = -20V, V_{DS} = 0V, 150^\circ C$
g_{fs}	Forward Transconductance (Note 3)	100	--	330	μmho	$V_{DS} = 10V, V_{GS} = 0V, f = 1kHz$
g_{os}	Output Conductance	--	--	10		
C_{iss}	Input Capacitance	--	--	3		
C_{rss}	Reverse Transfer Capacitance	--	--	1.5	pF	$V_{DS} = 10V, V_{GS} = 0V, f = 1MHz$

NOTES

1. Absolute maximum ratings are limiting values above which 2N4119A serviceability may be impaired.
2. Due to symmetrical geometry, these units may be operated with source and drain leads interchanged
3. This parameter is measured during a 2ms interval 100ms after power is applied. (Not a JEDEC condition.)

Micross Components Europe

Available Packages:


TO-71 (Bottom View)



2N4119A in TO-71
2N4119A in bare die.

Tel: +44 1603 788967
Email: chipcomponents@micross.com
Web: <http://www.micross.com/distribution>

Please contact Micross for full package and die dimensions



Information furnished by Linear Integrated Systems and Micross Components is believed to be accurate and reliable. However, no responsibility is assumed for its use; nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Linear Integrated Systems.