



n-channel JFETs designed for . . .

**Performance Curves NRL/NPA
See Section 4**

- Small-Signal Amplifiers
- VHF Amplifiers
- Oscillators
- Mixers



BENEFITS

- High Gain
- Low Receiver Noise Figure

***ABSOLUTE MAXIMUM RATINGS (25°C)**

Gate-Drain or Gate-Source Voltage (Note 1)	-30 V
Gate Current	10 mA
Drain Current	15 mA
Total Device Dissipation at (or below) 25°C		
Free-Air Temperature	300 mW
Derate Linearly to 175°C Free-Air Temperature at Rate of 2 mW/°C		
Storage Temperature Range	-65 to +200°C
Lead Temperature	300°C
(1/16" from case for 10 seconds)		

TO-72
See Section 6



***ELECTRICAL CHARACTERISTICS (25°C unless otherwise noted)**

Characteristic	2N4220, 2N4220A		2N4221, 2N4221A		2N4222, 2N4222A		Units	Test Conditions	
	Min	Max	Min	Max	Min	Max			
1 I _{GSS} Gate Reverse Current		-0.1		-0.1		-0.1	nA	V _{GS} = -15 V, V _{DS} = 0	150°C
2		-0.1		-0.1		-0.1	μA		
3 S BV _{GSS} Gate-Source Breakdown Voltage	-30		-30		-30		V	I _G = -10 μA, V _{DS} = 0	
4 T V _{GS(off)} Gate-Source Cutoff Voltage		-4		-6		-8			
5 A V _{GS} Gate-Source Voltage	-0.5	-2.5	-1	-5	-2	-6	V	V _{DS} = 15 V, I _D = ()	
6 I I _{DSS} Saturation Drain Current (Note 2)	(50)	(50)	(200)	(200)	(500)	(500)			
7 D g _{fs} Common-Source Forward Transconductance (Note 2)	1000	4000	2000	5000	2500	6000	μmho	V _{DS} = 15 V, V _{GS} = 0	f = 1 kHz
8 Y v _{fs} Common-Source Forward Transadmittance	750		750		750				f = 100 MHz
9 N g _{os} Common-Source Output Conductance (Note 2)		10		20		40	pF	V _{DS} = 15 V, V _{GS} = 0	f = 1 kHz
10 A C _{iss} Common-Source Input Capacitance		6		6		6			f = 1 MHz
11 M C _{rss} Common-Source Reverse Transfer Capacitance		2		2		2			
12 I NF Noise Figure, Only 2N4220A, 2N4221A, 2N4222A		2.5		2.5		2.5	dB	V _{DS} = 15 V, V _{GS} = 0 R _{gen} = 1 meg	f = 100 Hz

*JEDEC registered data.

NRL/NPA

NOTES:

1. Due to symmetrical geometry, these units may be operated with source and drain leads interchanged.
2. These parameters are measured during a 2 msec interval 100 msec after d-c power is applied.