

# 2SB1183 / 2SB1239

- 1) Darlington connection for high DC current gain.
- 2) Built-in  $4k\Omega$  resistor between base and emitter.
- 3) Complements the 2SD1759 / 2SD1861.

C : Collector  
B : Base  
E : Emitter

| Parameter                   |         | Symbol    | Limits  | Unit                    |
|-----------------------------|---------|-----------|---------|-------------------------|
| Collector-base voltage      |         | $V_{CB0}$ | -40     | V                       |
| Collector-emitter voltage   |         | $V_{CE0}$ | -40     | V                       |
| Emitter-base voltage        |         | $V_{EB0}$ | -5      | V                       |
| Collector current           |         | $I_C$     | -2      | A(DC)                   |
|                             |         |           | -3      | A(Pulse) *1             |
| Collector power dissipation | 2SB1183 | $P_C$     | 1       | W                       |
|                             |         |           | 10      | W(T <sub>C</sub> =25°C) |
|                             | 2SB1239 |           | 1       | W *2                    |
| Junction temperature        |         | $T_J$     | 150     | °C                      |
| Storage temperature         |         | $T_{stg}$ | -55→150 | °C                      |

\*1 Single pulse  $P_w=10\text{ms}$   
\*2 Printed circuit board 1.7 mm thick, collector plating 100mm<sup>2</sup> or larger.

- (1) Base(Gate)
- (2) Collector(Drain)
- (3) Emitter(Source)

- (1) Emitter
- (2) Collector
- (3) Base

| Type                         | 2SB1183 | 2SB1239 |
|------------------------------|---------|---------|
| Package                      | CPT3    | ATV     |
| $h_{FE}$                     | 1k~200k | 1k~     |
| Code                         | TL      | T146    |
| Basic ordering unit (pieces) | 2500    | 2500    |

| Parameter                            |         | Symbol        | Min. | Typ. | Max.  | Unit    | Conditions                                |
|--------------------------------------|---------|---------------|------|------|-------|---------|-------------------------------------------|
| Collector-base breakdown voltage     |         | $BV_{CBO}$    | -40  | -    | -     | V       | $I_{CB} = 50\mu A$                        |
| Collector-emitter breakdown voltage  |         | $BV_{CER}$    | -40  | -    | -     | V       | $I_{CE} = 1mA$ , $R_{BE} = 10k\Omega$     |
| Emitter-base breakdown voltage       |         | $BV_{EBO}$    | -5   | -    | -     | V       | $I_{EB} = 50\mu A$                        |
| Collector cutoff current             |         | $I_{CBO}$     | -    | -    | -1    | $\mu A$ | $V_{CB} = 24V$                            |
| Emitter cutoff current               |         | $I_{EBO}$     | -    | -    | -1    | $\mu A$ | $V_{EB} = 4V$                             |
| Collector-emitter saturation voltage |         | $V_{CE(sat)}$ | -    | -    | -1.5  | V       | $I_C/I_B = 0.6A/-1.2mA$                   |
| DC current transfer ratio            | 2SB1183 | $h_{FE}$      | 1000 | -    | 20000 | -       | $V_{CE}/I_C = 2V/-0.5A$                   |
|                                      | 2SB1239 |               | 1000 | -    | -     | -       |                                           |
| Output capacitance                   |         | $C_{ob}$      | -    | 11   | -     | pF      | $V_{CB} = -10V$ , $I_E = 0A$ , $f = 1MHz$ |