


## TUNG-SOL



GLASS BULB  
MINIATURE BUTTON  
7 PIN BASE E7-1  
OUTLINE DRAWING  
JEDEC 5-2


TETRODE  
MINIATURE TYPE

COATED UNIPOTENTIAL CATHODE

HEATER

6.3±0.6 VOLTS 0.2 AMP. ←  
AC OR DC

ANY MOUNTING POSITION



BOTTOM VIEW  
BASING DIAGRAM  
JEDEC 7EW

THE 6CY5 IS A SHARP-CUTOFF TETRODE IN THE 7-PIN MINIATURE CONSTRUCTION AND IS DESIGNED FOR SERVICE IN VHF TUNERS OF TELEVISION RECEIVERS. EXCEPT FOR HEATER RATINGS AND HEATER WARM-UP TIME, THE 6CY5 IS IDENTICAL TO THE 2CY5, 3CY5 AND 4CY5.

DIRECT INTERELECTRODE CAPACITANCES<sup>A</sup>

GRID #1 TO PLATE	0.03	μf
INPUT	4.5	μf
OUTPUT	3.0	μf

RATINGS

INTERPRETED ACCORDING TO DESIGN CENTER SYSTEM

MAXIMUM PLATE VOLTAGE	180	VOLTS
MAXIMUM GRID #2 (SCREEN) SUPPLY VOLTAGE	180	VOLTS
MAXIMUM GRID #2 VOLTAGE	SEE GRID #2 INPUT RATING CHART	
MAXIMUM PLATE DISSIPATION	2.0	WATTS
MAXIMUM GRID #2 DISSIPATION	0.5	WATTS
MAXIMUM GRID #1 (CONTROL GRID) VOLTAGE		
POSITIVE VALUE	0	MA.
MAXIMUM CATHODE CURRENT	20	MA.
MAXIMUM HEATER-CATHODE VOLTAGE		
HEATER POSITIVE WITH RESPECT TO CATHODE	100	VOLTS
HEATER NEGATIVE WITH RESPECT TO CATHODE	100	VOLTS

<sup>A</sup> WITH SHIELD #316 CONNECTED TO CATHODE.

→ INDICATES A CHANGE.

CONTINUED ON FOLLOWING PAGE

CONTINUED FROM PRECEDING PAGE

## TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS

PLATE VOLTAGE	125	VOLTS
GRID #2 VOLTAGE	80	VOLTS
GRID #1 VOLTAGE	-1	VOLTS
PLATE RESISTANCE	0.1	MEGOHM
TRANSCONDUCTANCE	8 000	$\mu$ MHOS
GRID #1 CUTOFF BIAS <sup>C</sup>	-6	VOLTS
PLATE CURRENT	10	MA.
GRID #2 CURRENT	1.5	MA.

<sup>C</sup> PLATE CURRENT 20  $\mu$ A.