




2SA1331/2SC3361

High-Speed Switching Applications

Features

- Fast switching speed.
- High breakdown voltage.
- Small-sized package permitting the 2SA1331/2SC3361-applied sets to be made small and slim.

Switching Time Test Circuit



() : 2SA1331

Specifications

Absolute Maximum Ratings at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Collector-to-Base Voltage	V_{CBO}		(-)60	V
Collector-to-Emitter Voltage	V_{CEO}		(-)50	V
Emitter-to-Base Voltage	V_{EBO}		(-)5	V
Collector Current	I_C		(-)150	mA
Collector Current (Pulse)	I_{CP}		(-)400	mA
Base Current	I_B		(-)40	mA
Collector Dissipation	P_C		150	mW
Junction Temperature	T_J		125	°C
Storage Temperature	T_{stg}		-55 to +125	°C

Electrical Characteristics at Ta = 25°C

Parameter	Symbol	Conditions	Ratings		Unit
			min	typ	
Collector Cutoff Current	I_{CBO}	$V_{CB}=(-)40V, I_E=0$		(-)0.1	µA
Emitter Cutoff Current	I_{EBO}	$V_{EB}=(-)4V, I_C=0$		(-)0.1	µA
DC Current Gain	h_{FE}	$V_{CE}=(-)6V, I_C=(-)1mA$	90*	400*	
Gain-Bandwidth Product	f_T	$V_{CE}=(-)6V, I_C=(-)1mA$		100	MHz
Common Base Output Capacitance	C_{ob}	$V_{CB}=(-)6V, f=1MHz$		(3.5) 2.7	pF
Collector-to-Emitter Saturation Voltage	$V_{CE(sat)}$	$I_C=(-)10mA, I_B=(-)1mA$	(-)0.1	(-)0.4	V
Base-to-Emitter Saturation Voltage	$V_{BE(sat)}$	$I_C=(-)10mA, I_B=(-)1mA$	(-)0.75	(-)1.1	V
Collector-to-Base Breakdown Voltage	$V_{(BR)CBO}$	$I_C=(-)10µA, I_E=0$	(-)60		V
Collector-to-Emitter Breakdown Voltage	$V_{(BR)CEO}$	$I_C=(-)1mA, R_{BE}=\infty$	(-)50		V
Emitter-to-Base Breakdown Voltage	$V_{(BR)EBO}$	$I_E=(-)10µA, I_C=0$	(-)5		V
Delay Time	t_d	See specified Test Circuit		40	ns
Rise Time	t_r	See specified Test Circuit		(120) 80	ns
Storage Time	t_{stg}	See specified Test Circuit		(190) 230	ns
Fall Time	t_f	See specified Test Circuit		(200) 160	ns

* : The 2SA1331/2SC3361 are classified by 1mA h_{FE} as follows :

90	4	180	135	5	270	200	6	400
----	---	-----	-----	---	-----	-----	---	-----


Marking 2SA1331 : O, 2SC3361 : S

h_{FE} rank : 4, 5, 6

Package Dimensions

unit:mm









2018A










C : Collector
B : Base
E : Emitter

SANYO : CP

2SA1331/2SC3361



2SA1331/2SC3361



- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use:
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of July, 1998. Specifications and information herein are subject to change without notice.