


**AOD404****N-Channel Enhancement Mode Field Effect Transistor****General Description**


The AOD404 uses advanced trench technology to provide excellent  $R_{DS(ON)}$ , low gate charge and low gate resistance. This device is ideally suited for use as a high side switch in CPU core power conversion. Standard Product AOD404 is Pb-free (meets ROHS & Sony 259 specifications). AOD404L is a Green Product ordering option. AOD404 and AOD404L are electrically identical.

**Features**

$V_{DS}$  (V) = 30V  
 $I_D$  = 85A ( $V_{GS}$  = 10V)  
 $R_{DS(ON)} < 7m\Omega$  ( $V_{GS}$  = 10V)  
 $R_{DS(ON)} < 8m\Omega$  ( $V_{GS}$  = 4.5V)



Top View  
Drain Connected to Tab

**Absolute Maximum Ratings  $T_A=25^\circ C$  unless otherwise noted**

Parameter	Symbol	Maximum	Units
Drain-Source Voltage	$V_{DS}$	30	V
Gate-Source Voltage	$V_{GS}$	$\pm 12$	V
Continuous Drain Current <sup>B,G</sup>	$I_D$	85	A
$T_C=25^\circ C$ <sup>G</sup>		65	
Pulsed Drain Current	$I_{DM}$	200	
Avalanche Current <sup>C</sup>	$I_{AR}$	30	A
Repetitive avalanche energy $L=0.1mH$ <sup>C</sup>	$E_{AR}$	120	mJ
Power Dissipation <sup>B</sup>	$P_D$	100	W
$T_C=100^\circ C$		50	
Power Dissipation <sup>A</sup>	$P_{DSM}$	2.5	W
$T_A=25^\circ C$		1.6	
Junction and Storage Temperature Range	$T_J, T_{STG}$	-55 to 175	°C

**Thermal Characteristics**

Parameter	Symbol	Typ	Max	Units
Maximum Junction-to-Ambient <sup>A</sup>	$R_{\theta JA}$	14.2	20	°C/W
Steady-State		39	50	°C/W
Maximum Junction-to-Case <sup>C</sup>	$R_{\theta JL}$	0.8	1.5	°C/W

**Electrical Characteristics ( $T_J=25^\circ\text{C}$  unless otherwise noted)**

Symbol	Parameter	Conditions	Min	Typ	Max	Units
<b>STATIC PARAMETERS</b>						
$\text{BV}_{\text{DSS}}$	Drain-Source Breakdown Voltage	$I_D=250\mu\text{A}, V_{GS}=0\text{V}$	30			V
$I_{\text{DSS}}$	Zero Gate Voltage Drain Current	$V_{DS}=24\text{V}, V_{GS}=0\text{V}$ $T_J=55^\circ\text{C}$		0.002	1	$\mu\text{A}$
$I_{\text{GSS}}$	Gate-Body leakage current	$V_{DS}=0\text{V}, V_{GS}=\pm 12\text{V}$			5	nA
$V_{\text{GS(th)}}$	Gate Threshold Voltage	$V_{DS}=V_{GS}, I_D=250\mu\text{A}$	1	1.6	2	V
$I_{\text{D(ON)}}$	On state drain current	$V_{GS}=10\text{V}, V_{DS}=5\text{V}$	85			A
$R_{\text{DS(ON)}}$	Static Drain-Source On-Resistance	$V_{GS}=10\text{V}, I_D=20\text{A}$ $T_J=125^\circ\text{C}$		5.4	7	$\text{m}\Omega$
		$V_{GS}=4.5\text{V}, I_D=20\text{A}$		8.4	10.5	$\text{m}\Omega$
$g_{\text{FS}}$	Forward Transconductance	$V_{DS}=5\text{V}, I_D=20\text{A}$		6.6	8	$\text{m}\Omega$
$V_{\text{SD}}$	Diode Forward Voltage	$I_S=1\text{A}, V_{GS}=0\text{V}$		0.74	1	V
$I_S$	Maximum Body-Diode Continuous Current				85	A
<b>DYNAMIC PARAMETERS</b>						
$C_{\text{iss}}$	Input Capacitance			2100	2520	pF
$C_{\text{oss}}$	Output Capacitance	$V_{GS}=0\text{V}, V_{DS}=15\text{V}, f=1\text{MHz}$		536		pF
$C_{\text{rss}}$	Reverse Transfer Capacitance			165		pF
$R_g$	Gate resistance	$V_{GS}=0\text{V}, V_{DS}=0\text{V}, f=1\text{MHz}$		0.95	1.2	$\Omega$
<b>SWITCHING PARAMETERS</b>						
$Q_g(4.5\text{V})$	Total Gate Charge			19.7	24	nC
$Q_{\text{gs}}$	Gate Source Charge	$V_{GS}=4.5\text{V}, V_{DS}=15\text{V}, I_D=20\text{A}$		3.6		nC
$Q_{\text{gd}}$	Gate Drain Charge			7.9		nC
$t_{\text{D(on)}}$	Turn-On DelayTime			5.9	10	ns
$t_r$	Turn-On Rise Time	$V_{GS}=10\text{V}, V_{DS}=15\text{V}, R_L=0.75\Omega,$		11	17	ns
$t_{\text{D(off)}}$	Turn-Off DelayTime	$R_{\text{GEN}}=3\Omega$		36.2	55	ns
$t_f$	Turn-Off Fall Time			12	18	ns
$t_{\text{rr}}$	Body Diode Reverse Recovery Time	$I_F=20\text{A}, dI/dt=100\text{A}/\mu\text{s}$		35	42	ns
$Q_{\text{rr}}$	Body Diode Reverse Recovery Charge	$I_F=20\text{A}, dI/dt=100\text{A}/\mu\text{s}$		33	50	nC

A: The value of  $R_{\text{JJA}}$  is measured with the device mounted on 1 in<sup>2</sup> FR-4 board with 2oz. Copper, in a still air environment with  $T_A=25^\circ\text{C}$ . The Power dissipation  $P_{\text{DSM}}$  is based on steady-state  $R_{\text{JJA}}$  and the maximum allowed junction temperature of 150°C. The value in any given application depends on the user's specific board design, and the maximum temperature of 175°C may be used if the PCB or heatsink allows it.

B: The power dissipation  $P_D$  is based on  $T_{\text{J(MAX)}}=175^\circ\text{C}$ , using junction-to-case thermal resistance, and is more useful in setting the upper dissipation limit for cases where additional heatsinking is used. It is used to determine the current rating, when this rating falls below the package limit.

C: Repetitive rating, pulse width limited by junction temperature  $T_{\text{J(MAX)}}=175^\circ\text{C}$ .

D: The  $R_{\text{JJA}}$  is the sum of the thermal impedance from junction to case  $R_{\text{JJC}}$  and case to ambient.

E: The static characteristics in Figures 1 to 6 are obtained using <300  $\mu\text{s}$  pulses, duty cycle 0.5% max.

F: These tests are performed with the device mounted on 1 in<sup>2</sup> FR-4 board with 2oz. Copper, in a still air environment with  $T_A=25^\circ\text{C}$ . The SOA curve provides a single pulse rating.

G: The maximum current rating is limited by the package current capability.

Rev5: August 2005

THIS PRODUCT HAS BEEN DESIGNED AND QUALIFIED FOR THE CONSUMER MARKET. APPLICATIONS OR USES AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS ARE NOT AUTHORIZED. AOS DOES NOT ASSUME ANY LIABILITY ARISING OUT OF SUCH APPLICATIONS OR USES OF ITS PRODUCTS. AOS RESERVES THE RIGHT TO IMPROVE PRODUCT DESIGN, FUNCTIONS AND RELIABILITY WITHOUT NOTICE

## TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS




Fig 1: On-Region Characteristics




Figure 2: Transfer Characteristics




Figure 3: On-Resistance vs. Drain Current and Gate Voltage




Figure 4: On-Resistance vs. Junction Temperature




Figure 5: On-Resistance vs. Gate-Source Voltage









Figure 6: Body-Diode Characteristics

## TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS



---


**TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS**

Figure 12: Single Pulse Avalanche capability




Figure 13: Power De-rating (Note B)




Figure 14: Current De-rating (Note B)