



3.0A Low Dropout Voltage Regulator

B1085

Adjustable

Description

The Bay Linear B1085 is Monolithic low power 3.0A Adjustable and fixed NPN voltage regulator that are easy to use with minimum external components. All internal circuitry is designed to operate down to 1V input to output differential and the dropout voltage is fully specified as a function of load current. Dropout is guaranteed at a maximum of 1.5V at a maximum output current. Current limit is trimmed, minimizing the stress on both the regulator and power source circuitry under overload conditions. It is suitable for applications requiring a well-regulated positive output voltage with low input-output differential voltage.

The B1085 Outstanding features include full power usage up to 3.0Amp of load current internal current limiting and thermal shutdown. A 10 μ F output capacitor is required on these new devices; however, this is usually included in most regulator design.

The B1085 is offered in a 3-pin TO-220, TO-263 & TO-252 packages compatible with other 3 terminal regulators. For 5A Low dropout Regulator refer to the BL1084 data sheet.

Features

- Adjustable Output Down to 1.2V
- Output Current of 3.0A
- Low Dropout Voltage 1.0V Typ.
- 0.015% Line Regulation
- 0.01% Load Regulation
- Current & Thermal Limiting
- Standard 3-Terminal Low Cost TO-220, D², D Packages
- Similar to industry Standard LT1085


Applications

- Constant Current Regulators
- SMPS Post Regulator
- High Efficiency Linear Regulator
- High Efficiency Linear Power Supplies
- Battery Charger
- Adjustable Power Supplies

Pin Connection




TO-263-3 (S)



Top View

TO-252 (D)



Front View

Ordering Information

Devices	Package	Temp.
B1085T	TO-220	0 °C to 70 °C
B1085S	TO-263	0 °C to 70 °C
B1085D	TO-252	0 °C to 70 °C

Absolute Maximum Rating

Parameter	Symbol	Value	Unit
Maximum Input Voltage	V_{IN}	30	V
Power Dissipation	P_O	Internally Limited	W
Thermal Resistance Junction to Case	θ_{JC}	3	°C/W
Thermal Resistance Junction to Ambient	θ_{JA}	50	
Operating Junction Temperature Range Control Section Power Transistor	T_J	0 to 125 0 to 150	°C
Storage Temperature Range	T_{STG}	-65 to 150	
Lead Temperature (Soldering 10 Sec.)	T_{LEAD}	300	

Electrical Characteristics

($V_{IN} = 4.75V$ to $5.25V$; $I_O = 10mA$ to $3.0Amp$, unless otherwise specified)

Parameter	Symbol	Conditions	MIN	TYP	MAX	UNIT
Reference Voltage	V_O	$I_O = 10mA, T = 25\text{ }^\circ\text{C}, V_{in} - V_{out} = 3V$ $10mA \leq I_{OUT} \leq I_{FULL\ LOAD}$ $1.5V \leq (V_{in} - V_{out}) \leq 25V$ (Note3)	1.238	1.250	1.262	V
			1.225		1.270	
Line Regulation (1)	$REG_{(line)}$	$I_{LOAD} = 10mA, 1.5V \leq (V_{IN} - V_{OUT}) \leq 15V$ $T = 25\text{ }^\circ\text{C}$ $15V \leq (V_{in} - V_{out}) \leq 30V$		0.015 0.035 0.05	0.20 0.20 0.50	%
Load Regulation (1)	$REG_{(LOAD)}$	$(V_{in} - V_{out}) = 3V$ $10mA \leq I_{OUT} \leq I_{FULL\ LOAD}$ $T = 25\text{ }^\circ\text{C}$		0.1 0.2	0.30 0.40	
Dropout Voltage	V_D	$T = 25\text{ }^\circ\text{C}$ Over Temperature		1.3	1.5	V
Current Limit	I_S	$(V_{in} - V_{out}) = 5V$ $(V_{in} - V_{out}) = 25V$		3.2 0.2	4 0.5	A
Minimum Load Current	$I_{MIN\ LOAD}$	$(V_{in} - V_{out}) = 25V$		10	10	mA
Temperature Regulation	T_A	$T = 25\text{ }^\circ\text{C}, 30ms$ pulse		0.004	0.02	%/W
Long Term Stability	-	$T = 25\text{ }^\circ\text{C}, 1000Hrs$		0.3	1	
Temperature Stability	T_S			0.5		%
Adjust pin Current	-	$T = 25\text{ }^\circ\text{C}$ Over Temp.		55	120	μA
Ripple Rejection	R_A	$F = 120Hz, C_{ADJ} = 25\mu\text{F}, C_{OUT} = 25\mu\text{F}$ Tantalum $I_{OUT} = I_{FULL\ LOAD}, (V_{in} - V_{out}) = 3V$ (Note 5)	60	75		dB
Thermal Resistance	-	TO-220	Junction to Tab	3.0	3.0	°C/W
			Junction to Ambient	60	60	
		DD Package	Junction to Tab	3.0	3.0	
			Junction to Ambient	60	60	

Note: Output Switch tests are performed under pulsed conditions to minimize power dissipation

Advance Information- These data sheets contain descriptions of products that are in development. The specifications are based on the engineering calculations, computer simulations and/ or initial prototype evaluation.

Preliminary Information- These data sheets contain minimum and maximum specifications that are based on the initial device characterizations. These limits are subject to change upon the completion of the full characterization over the specified temperature and supply voltage ranges.

The application circuit examples are only to explain the representative applications of the devices and are not intended to guarantee any circuit design or permit any industrial property right to other rights to execute. Bay Linear takes no responsibility for any problems related to any industrial property right resulting from the use of the contents shown in the data book. Typical parameters can and do vary in different applications. Customer's technical experts must validate all operating parameters including "Typical" for each customer application.

LIFE SUPPORT AND NUCLEAR POLICY

Bay Linear products are not authorized for and should not be used within life support systems which are intended for surgical implants into the body to support or sustain life, in aircraft, space equipment, submarine, or nuclear facility applications without the specific written consent of Bay Linear President.
