

isc Silicon NPN Power Transistor
BD135
DESCRIPTION

- DC Current Gain-
: $h_{FE} = 40(\text{Min}) @ I_C = 0.15\text{A}$
- Collector-Emitter Sustaining Voltage -
: $V_{CEO(\text{SUS})} = 45\text{V}(\text{Min})$
- Complement to type BD136
- Minimum Lot-to-Lot variations for robust device performance and reliable operation

APPLICATIONS



- Designed for use as audio amplifiers and drivers utilizing complementary or quasi complementary circuits.

ABSOLUTE MAXIMUM RATINGS($T_a = 25^\circ\text{C}$)

SYMBOL	PARAMETER	VALUE	UNIT
V_{CBO}	Collector-Base Voltage	45	V
V_{CEO}	Collector-Emitter Voltage	45	V
V_{EBO}	Emitter-Base Voltage	5	V
I_C	Collector Current-Continuous	1.5	A
I_B	Base Current-Continuous	0.5	A
P_C	Collector Power Dissipation @ $T_a = 25^\circ\text{C}$	1.25	W
	Collector Power Dissipation @ $T_c = 25^\circ\text{C}$	12.5	
T_J	Junction Temperature	150	$^\circ\text{C}$
T_{stg}	Storage Temperature Range	-55~150	$^\circ\text{C}$

THERMAL CHARACTERISTICS

SYMBOL	PARAMETER	MAX	UNIT
$R_{th\ j-c}$	Thermal Resistance, Junction to Case	10	$^\circ\text{C/W}$
$R_{th\ j-a}$	Thermal Resistance, Junction to Ambient	100	$^\circ\text{C/W}$



isc Silicon NPN Power Transistor

BD135

ELECTRICAL CHARACTERISTICS

T_C=25°C unless otherwise specified

SYMBOL	PARAMETER	CONDITIONS	MIN	TYP.	MAX	UNIT
V _{CEQ(SUS)}	Collector-Emitter Sustaining Voltage	I _C = 30mA ; I _B =0	45			V
V _{CE(sat)}	Collector-Emitter Saturation Voltage	I _C = 0.5A; I _B = 50mA			0.5	V
V _{BE(on)}	Base-Emitter On Voltage	I _C = 0.5A; V _{CE} = 2V			1.0	V
I _{CBO}	Collector Cutoff Current	V _{CB} = 30V; I _E = 0 V _{CB} = 30V; I _E = 0, T _C =125°C			0.1 10	μ A
I _{EBO}	Emitter Cutoff Current	V _{EB} = 5V; I _C =0			10	μ A
h _{FE-1}	DC Current Gain	I _C = 5mA ; V _{CE} = 2V	25			
h _{FE-2}	DC Current Gain	I _C = 0.5A ; V _{CE} = 2V	25			
h _{FE-3}	DC Current Gain	I _C = 0.15A ; V _{CE} = 2V	40		250	

NOTICE:

ISC reserves the rights to make changes of the content herein the datasheet at any time without notification. The information contained herein is presented only as a guide for the applications of our products.

ISC products are intended for usage in general electronic equipment. The products are not designed for use in equipment which require specialized quality and/or reliability, or in equipment which could have applications in hazardous environments, aerospace industry, or medical field. Please contact us if you intend our products to be used in these special applications.

ISC makes no warranty or guarantee regarding the suitability of its products for any particular purpose, nor does ISC assume any liability arising from the application or use of any products, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages.