


### Product Overview

The CMD204 die is a general purpose broadband high isolation non-reflective MMIC SPST switch. Covering DC to 20 GHz, the CMD204 features a low insertion loss of 1.0 dB and high isolation of 50 dB at 10 GHz. The switch operates using complementary control voltage logic lines of 0/-5 V and requires no bias supply. The CMD204 offers full passivation for increased reliability and moisture protection.

### Functional Block Diagram



### Key Features

- Low Loss Broadband Performance
- High Isolation
- Fast Switching Speed
- Non-Reflective Design - RF1 and RF2
- Small Die Size: 1350 um x 850 um

### Ordering Information

Part No.	Description
CMD204	DC-20 GHz SPST Non-reflective Switch, 100 Piece WP Sample

### Electrical Performance ( $V_{ctl} = 0/-5 V, T_A = 25 ^\circ C, F = 10 GHz$ )

Parameter	Min	Typ	Max	Units
Frequency Range		DC - 20		GHz
Insertion Loss		1.0		dB
Isolation		50		dB
Return Loss - On State		17		dB
Return Loss - Off State		17		dB
Input P0.1dB		25		dBm
Switching Characteristics				
tRISE, tFALL (10/90% RF)		1.8		ns
tON, tOFF (50% CTL to 10/90% RF)		18/7		ns

## Absolute Maximum Ratings

Parameter	Rating
RF Input Power	+27 dBm
Control Voltage Range (A, B)	+0.5V to -7.5V
Channel Temperature, T <sub>ch</sub>	150 °C
Operating Temperature	-55 to 85 °C
Storage Temperature	-55 to 150 °C
Power Dissipation, P <sub>diss</sub> (isolation state)	631 mW
Thermal Resistance, θ <sub>JC</sub> (isolation state)	96.2 °C/W

Exceeding any one or combination of the maximum ratings may cause permanent damage to the device.

## Control Voltages

State	Bias Condition
Low	0 to -0.5V @ 1 uA Typ
High	-3V @ 1 uA Typ to -7V @ 6 uA Typ

## Truth Table


Control Input		Signal Path State
A	B	RF1 to RF2
High	Low	On
Low	High	Off

## Electrical Specifications (V<sub>ctl</sub> = 0/-5 V, T<sub>A</sub> = 25 °C)


Parameter	Min	Typ	Max	Min	Typ	Max	Units
Frequency Range		DC - 10			10 - 20		GHz
Insertion Loss		0.9	1.4		1.0	1.6	dB
Isolation	45	50		36	43		dB
Return Loss - On State		17			17		dB
Return Loss - RF1, 2 - Off State		17			17		dB
Input P0.1dB		24			22		dBm
Input IP3		38			37		dBm
Switching Characteristics							
tRISE, tFALL (10/90% RF)		1.8			1.8		ns
tON, tOFF (50% CTL to 10/90% RF)		18/7			18/7		ns

Typical Performance

Insertion Loss vs. Temperature




Return Loss




Typical Performance

Isolation Between Ports RF1 and RF2 vs. Temperature




Input P0.1dB Compression Point vs. Temperature




Typical Performance

Input Third Order Intercept Point vs. Temperature



Mechanical Information

Die Outline (all dimensions in microns)




Notes:

1. No connection required for unlabeled pads
2. Backside is RF and DC ground
3. Backside and bond pad metal: Gold
4. Die is 85 microns thick
5. DC bond pads (3, 4) are 100 x 100 microns
6. RF bond pads (1, 2) are 100 x 150 microns

**Pad Description**

**Pad Diagram**




**Functional Description**

Pin	Function	Description	Schematic
1, 2	RF1, RF2	These pins are DC coupled and matched to 50 ohm. Blocking capacitors are required if RF line potential is not equal to 0 V	
3	CTLB	See truth table and control voltage table	
4	CTLA	See truth table and control voltage table	
Backside	Ground	Connect to RF / DC ground	

Applications Information

Suggested Driver Circuit



GaAs MMIC devices are susceptible to damage from Electrostatic Discharge. Proper precautions should be observed during handling, assembly and test.

## Applications Information

---


### Assembly Guidelines

The backside of the CMD204 is RF ground. Die attach should be accomplished with electrically and thermally conductive epoxy only. Eutectic attach is not recommended. Standard assembly procedures should be followed for high frequency devices. The top surface of the semiconductor should be made planar to the adjacent RF transmission lines, and the RF decoupling capacitors placed in close proximity to the DC connections on chip.

RF connections should be made as short as possible to reduce the inductive effect of the bond wire. Use of a 0.8 mil thermosonic wedge bonding is highly recommended as the loop height will be minimized. The RF input and output require a double bond wire as shown.

The semiconductor is 85 um thick and should be handled by the sides of the die or with a custom collet. Do not make contact directly with the die surface as this will damage the monolithic circuitry. Handle with care.

### Assembly Diagram



**Handling Precautions**

Parameter	Rating	Standard
ESD – Human Body Model (HBM)	Class 1A	ESDA / JEDEC JS-001-2012



Caution!  
 ESD-Sensitive Device

**RoHS Compliance**

This part is compliant with 2011/65/EU RoHS directive (Restrictions on the Use of Certain Hazardous Substances in Electrical and Electronic Equipment) as amended by Directive 2015/863/EU.

This product also has the following attributes:

- Lead Free
- Antimony Free
- TBBP-A (C<sub>15</sub>H<sub>12</sub>Br<sub>4</sub>O<sub>2</sub>) Free
- SVHC Free
- Halogen Free
- PFOS Free

**Contact Information**

For the latest specifications, additional product information, worldwide sales and distribution locations:

**Web:** [www.qorvo.com](http://www.qorvo.com)

**Tel:** 1-844-890-8163

**Email:** [customer.support@qorvo.com](mailto:customer.support@qorvo.com)

**Important Notice**

The information contained in this Data Sheet and any associated documents (“Data Sheet Information”) is believed to be reliable; however, Qorvo makes no warranties regarding the Data Sheet Information and assumes no responsibility or liability whatsoever for the use of said information. All Data Sheet Information is subject to change without notice. Customers should obtain and verify the latest relevant Data Sheet Information before placing orders for Qorvo® products. Data Sheet Information or the use thereof does not grant, explicitly, implicitly or otherwise any rights or licenses to any third party with respect to patents or any other intellectual property whether with regard to such Data Sheet Information itself or anything described by such information.

DATA SHEET INFORMATION DOES NOT CONSTITUTE A WARRANTY WITH RESPECT TO THE PRODUCTS DESCRIBED HEREIN, AND QORVO HEREBY DISCLAIMS ANY AND ALL WARRANTIES WITH RESPECT TO SUCH PRODUCTS WHETHER EXPRESS OR IMPLIED BY LAW, COURSE OF DEALING, COURSE OF PERFORMANCE, USAGE OF TRADE OR OTHERWISE, INCLUDING THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Without limiting the generality of the foregoing, Qorvo® products are not warranted or authorized for use as critical components in medical, life-saving, or life-sustaining applications, or other applications where a failure would reasonably be expected to cause severe personal injury or death. Applications described in the Data Sheet Information are for illustrative purposes only. Customers are responsible for validating that a particular product described in the Data Sheet Information is suitable for use in a particular application.

© 2022 Qorvo US, Inc. All rights reserved. This document is subject to copyright laws in various jurisdictions worldwide and may not be reproduced or distributed, in whole or in part, without the express written consent of Qorvo US, Inc. | QORVO® is a registered trademark of Qorvo US, Inc.