

Features:

→ Operating voltage: 5.0V
 → I/O-Isolation 2500 VDC
 → Baud rate: 1Mbps(MAX)

- Baudrate : TWDp3(WAX)

- → Instantaneous bus over voltage protection
- → Compatible with ISO11898 standard
- → No External Components Required
- → ESD Protection (Contact model: ±4KV)
- → No power on, bus without electricity
- → Prevent bettery short circuit occurred in the 24VDC power supply system
- → Operating temperature : -40 ~ +85



DESCRIPTION

CTM1040T is the differential level high speed transceiver which integrates with DC and DC 2500 isolation, which makes the controller output high low logic level programming of CAN bus, meeting the standard of ISO11898. Using CTM1040T transceiver in Can-bus system, which builds the completely isolated interface between the Can-bus controller and the physical layer bus, and to improve the ability of anti common mode interference. The Can-bus outlet end for this product is with TVS tube, which increases the chip prohibit the bus from overvoltage capability(Note: CTM1040 is without this function).

| Model Selection Guide | | | | | |
|-----------------------|---------------|------------|-----------------|------------------|---------|
| Order Code | Input Voltage | | Baud rate(Kbps) | Bus Over Voltage | Package |
| Order Code | Vin(VDC) | Range(VDC) | Bauu rate(KDPS) | Protection | Гаскаде |
| CTM1040 | Е | 4.75-5.25 | 1024 | No | DIP8 |
| CTM1040T | 5 | | 1024 | Yes | DIP8 |

| Parameter | | | | | |
|---------------------------------|-------------|------|------|------|-------|
| | | | | | |
| Input Voltage | | 4.75 | 5.0 | 5.25 | VDC |
| Operating Temperature | | -40 | | +85 | |
| Storage Temperature | | -55 | | +125 | |
| Isolation voltage | | | 2500 | | VDC |
| Isolation capacitance | | | 40 | | pF |
| Humidity | No frosting | 10 | | 95 | % |
| Quiescent Current | | 17 | | 35 | mA |
| Device Amounts | | 110 | | | Point |
| Propagation delay time | | 50 | | 150 | μS |
| TXD/RXD pin current | | | | 3 | mA |
| Bus voltage | | -26 | | +40 | V |
| Instantaneous bus voltage range | | -200 | | +200 | V |

Page 1 of 2 www.reicu.com
E-mail:service@reicu.com

REV:13.3



Rec-Send


| | CTM1040(T) | Series |
|---|------------|--------|
| • | | |


| Receiver Function | | | |
|------------------------------|-----------|-------------|--|
| V _{CANH-CANL} (VDC) | Bus state | Output(RXD) | |
| 0.9 | Dominant | 0 | |
| 0.5 | Recessive | 1 | |
| | | | |

| Driver Func | tion | | |
|-------------|-----------|--------|--------|
| Input(TXD) | Bus state | CANH | CANL |
| 0 | Dominant | 1 | 0 |
| 1 | Recessive | 0.5Vin | 0.5Vin |
| | | | |

Application Industrial automation system CTM1040(T) MCU Automatic control on electrical power system Cartronics ∘ +Vin CAN-GND ∘ Communication o GND CANH o Mining o TXD CANL Instrument and meter o RXD RXD Medical equipment Isolation 2500VDC

Mechanical Dimension





Units: mm (inch) Tolerances: ± 0.25 mm (± 0.01 inch)

| Pin Connections | | | |
|-----------------|----------|-------------------------|--|
| Pin | Function | Description | |
| 1 | +Vin | positive pole | |
| 2 | GND | negative pole | |
| 3 | TXD | Driver input date | |
| 4 | RXD | Receiver output data | |
| 6 | CANH | High electrical level | |
| 7 | CANL | Low electrical level | |
| 8 | CAN-GND | CAN Bus Isolated Ground | |
| | | | |

E-mail:service@reicu.com