

5.0A



TO-92

- AF OUTPUT AMPLIFIER
- FOR DC-DC CONVERTER
- FOR CAMERA ELECTRONIC FLASH UNIT
- HIGH PERFORMANCE AT LOW SUPPLY VOLTAGE
- LOW $V_{CE(SAT)}$

MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS ($T_a=25^\circ\text{C}$)

PARAMETERS	SYMBOL	MIN	TYP	MAX	UNIT	CONDITION
Collector-Emitter Breakdown Voltage	BV_{ceo}	20			V	$I_c=1\text{mA}$
Collector-Base Breakdown Voltage	BV_{cbo}	40			V	$I_c=5\mu\text{A}$
Emitter-Base Breakdown Voltage	BV_{ebo}	6			V	$I_e=50\mu\text{A}$
Collector-Base Leakage	I_{cbo}			0.1	μA	$V_{cb}=30\text{V}$
Emitter-Base Leakage	I_{ebo}			0.1	μA	$V_{eb}=5\text{V}$
Collector-Emitter Saturation Voltage	$V_{ce(sat)}$			0.5	V	$I_c=3\text{A}, I_b=0.1\text{A}$
DC Current Gain	H_{fe1} H_{fe2}	340 180		600		$V_{ce}=2\text{V}, I_c=0.5\text{A}$ $V_{ce}=2\text{V}, I_c=4\text{A}$
Collector Current	I_c			5	A	
Peak Collector Current	I_{cp}			8	A(Pulse)	
Current Gain Bandwidth	f_r		170		MHz	$V_{cb}=6\text{V}, I_c=50\text{mA}$
Output Capacitance	C_{ob}			32	pF	$V_{cb}=20\text{V}, I_e=0, f=1\text{MHz}$
Power Dissipation	P_c			0.75	W	
Junction Temperature	T_j			150		
Storage Temperature	T_{stg}	-55		150		

**STANSON TECHNOLOGY**

120 Bentley Square, Mountain View, Ca 94040 USA

TEL: (650) 9389294 FAX: (650) 9389295