

# MINIATURE GROUNDED GRID TRIODE

# EC91

Miniature screened triode for use  
as a grounded grid amplifier.

## HEATER

$V_h$	6.3	V
$I_h$	0.3	A

## CAPACITANCES

ca-g	2.5	$\mu\mu\text{F}$
ca-k+h	<0.2	$\mu\mu\text{F}$
cg-k+h	8.5	$\mu\mu\text{F}$



## OPERATING CONDITIONS

$V_a$	250	V
$V_g$	-1.5	V
$R_k$	150	$\Omega$
$I_a$	10	mA
$S_m$	8.5	mA/V
$\mu$	100	
$r_a$	12000	$\Omega$
Equivalent Noise Resistance.	400	$\Omega$

## LIMITING VALUES


$V_a$ max.	250	V
$w_a$ max.	2.5	W
$I_k$ max.	15	mA
$V_h$ -k	150	V
$V_g$ -k	100	V
Maximum Operating Frequency	250	Mc/s

## ARRANGEMENT OF ELECTRODES AND BASE CONNECTIONS



B7G BASE


## DIMENSIONS



# EC91

## MINIATURE GROUNDED GRID TRIODE

*Miniature screened triode for use  
as a grounded grid amplifier.*



# MINIATURE GROUNDING GRID TRIODE

# EC91

Miniature screened triode for use  
as a grounded grid amplifier.

