



# EZ 81

## DOUBLE ANODE RECTIFYING TUBE

**Base:** NOVAL

$$U_f = 6,3 \text{ V}$$

$$I_f = 1 \text{ A}$$

### Typical characteristic:

Capacitor input

$$f = 50 \text{ Hz}$$

$$U_{tr \text{ eff}} = 2 \times 250 \quad 2 \times 350 \quad 2 \times 450 \quad \text{V}$$

$$R_t = 2 \times 150 \quad 2 \times 230 \quad 2 \times 310 \quad \Omega$$

$$I_- = 160 \quad 150 \quad 100 \quad \text{mA}$$

$$C = 50 \quad 50 \quad 50 \quad \mu\text{F}$$

$$U_- = 245 \quad 352 \quad 497 \quad \text{V}$$

Choke input

$$f = 50 \text{ Hz}$$

$$U_{tr \text{ eff}} = 2 \times 250 \quad 2 \times 350 \quad 2 \times 450 \quad \text{V}$$

$$I_- = 180 \quad 180 \quad 150 \quad \text{mA}$$

$$L = 10 \quad 10 \quad 10 \quad \text{H}$$

$$U_- = 199 \quad 288 \quad 378 \quad \text{V}$$

### Limiting values:

$$-U_{a \text{ invp}} = 1300 \text{ V}$$

$$I_{a \text{ invp}} = 500 \text{ mA}$$

$$U_{kf} = 500 \text{ V}$$

$$C_{filt \text{ max.}} = 50 \mu\text{F}$$

$$L_{min.} = 1 \text{ H}$$

## Dimension and connections:

