



Type	EIAJ No.		V _{DRM} (V)	I _{T(RMS)} (A)	I _{TSM} (A)	V _{TM} (V)	I _{GT} * (mA)	T _j (°C)	Package	Note
FR08/09C	2SM159-200	2SM160-200	200	16	150	1.4	50(I Q+) 50(I Q-) 50(III Q-)	-40 ~ +125	08type ⁽²⁶⁾ 09type ⁽²⁷⁾	
FR08/09D	2SM159-300	2SM160-300	300							
FR08/09E	2SM159-400	2SM160-400	400							
FR08/09F	2SM159-500	2SM160-500	500							
FR08/09G	2SM159-600	2SM160-600	600							
FSM16C2			200	16	150	1.5	50(I Q+) 50(I Q-) 50(III Q-)	-40 ~ +125	37	Isolated Base
FSM16C4			400							
FSM16C6			600							
FQ08/09C	2SM161-200	2SM162-200	200	20	180	1.35	50(I Q+) 50(I Q-) 50(III Q-)	-40 ~ +125	08type ⁽²⁶⁾ 09type ⁽²⁷⁾	
FQ08/09D	2SM161-300	2SM162-300	300							
FQ08/09E	2SM161-400	2SM162-400	400							
FQ08/09F	2SM161-500	2SM162-500	500							
FQ08/09G	2SM161-600	2SM162-600	600							
FSM20C2			200	20	180	1.5	50(I Q+) 50(I Q-) 50(III Q-)	-40 ~ +125	37	Isolated Base
FSM20C4			400							
FSM20C6			600							
FP08/09C	2SM163-200	2SM164-200	200	30	250	1.4	50(I Q+) 50(I Q-) 50(III Q-)	-40 ~ +125	08type ⁽²⁶⁾ 09type ⁽²⁷⁾	
FP08/09D	2SM163-300	2SM164-300	300							
FP08/09E	2SM163-400	2SM164-400	400							
FP08/09F	2SM163-500	2SM164-500	500							
FP08/09G	2SM163-600	2SM164-600	600							
FSM30C2			200	30	275	1.5	50(I Q+) 50(I Q-) 50(III Q-)	-40 ~ +125	37	Isolated Base
FSM30C4			400							
FSM30C6			600							

* I Q+ : MT₂(+), G(+)
 I Q- : MT₂(+), G(-)
 III Q- : MT₂(-), G(-)

●トライアック用制御モジュール (Triac Gate Control Module)

Type	V _{DRM} (V)	f (Hz)	DC Input Voltage (V)	T _{op} (°C)	Connection Diagram	Package	Note
UFZ01A4A1 UFZ01A6A1	400 600	50/60	6	-30 ~ +80		52	
UFZ01B4A1 UFZ01B6A1	400 600	50/60	6	-30 ~ +80		52	