


PRELIMINARY
 Notice: This is not a final specification.
 Some parametric limits are subject to change.

MITSUBISHI Pch POWER MOSFET

FX3UMJ-06

HIGH-SPEED SWITCHING USE



FX3UMJ-06



- 4V DRIVE
- V_{DS} -60V
- $r_{DS(ON)}(MAX)$ 0.46Ω
- I_D -3A
- Integrated Fast Recovery Diode (TYP.) 40ns

OUTLINE DRAWING

Dimensions in mm



TO-220

APPLICATION

Motor control, Lamp control, Solenoid control
 DC-DC converter, etc.





MAXIMUM RATINGS (T_c = 25 °C)

Symbol	Parameter	Conditions	Ratings	Unit
V_{DS}	Drain-source voltage	$V_{GS} = 0V$	-60	V
V_{GSS}	Gate-source voltage	$V_{DS} = 0V$	±20	V
I_D	Drain current		-3	A
I_{DM}	Drain current (Pulsed)		-12	A
I_{DA}	Avalanche drain current (Pulsed)	$L = 100\mu H$	-3	A
I_S	Source current		-3	A
I_{SM}	Source current (Pulsed)		-12	A
P_D	Maximum power dissipation		20	W
T_{ch}	Channel temperature		-55 ~ +150	°C
T_{stg}	Storage temperature		-55 ~ +150	°C
—	Weight	Typical value	2.0	g

ELECTRICAL CHARACTERISTICS ($T_{ch} = 25^{\circ}\text{C}$)

Symbol	Parameter	Test conditions	Limits			Unit
			Min.	Typ.	Max.	
$V_{(BR)DSS}$	Drain-source breakdown voltage	$I_D = -1\text{mA}$, $V_{GS} = 0\text{V}$	-60	—	—	V
I_{GSS}	Gate-source leakage current	$V_{GS} = \pm 20\text{V}$, $V_{DS} = 0\text{V}$	—	—	± 0.1	μA
I_{DSS}	Drain-source leakage current	$V_{DS} = -60\text{V}$, $V_{GS} = 0\text{V}$	—	—	-0.1	mA
$V_{GS(th)}$	Gate-source threshold voltage	$I_D = -1\text{mA}$, $V_{DS} = -10\text{V}$	-1.3	-1.8	-2.3	V
$r_{DS(ON)}$	Drain-source on-state resistance	$I_D = -1\text{A}$, $V_{GS} = -10\text{V}$	—	0.35	0.46	Ω
$r_{DS(ON)}$	Drain-source on-state resistance	$I_D = -1\text{A}$, $V_{GS} = -4\text{V}$	—	0.57	0.80	Ω
$V_{DS(ON)}$	Drain-source on-state voltage	$I_D = -1\text{A}$, $V_{GS} = -10\text{V}$	—	-0.35	-0.46	V
$ y_{fs} $	Forward transfer admittance	$I_D = -1\text{A}$, $V_{DS} = -5\text{V}$	—	2.0	—	S
C_{iss}	Input capacitance	$V_{DS} = -10\text{V}$, $V_{GS} = 0\text{V}$, $f = 1\text{MHz}$	—	520	—	pF
C_{oss}	Output capacitance		—	104	—	pF
C_{rss}	Reverse transfer capacitance		—	31	—	pF
$t_d(\text{on})$	Turn-on delay time	$V_{DD} = -30\text{V}$, $I_D = -1\text{A}$, $V_{GS} = -10\text{V}$, $R_{GEN} = R_{GS} = 50\Omega$	—	8	—	ns
t_r	Rise time		—	5	—	ns
$t_d(\text{off})$	Turn-off delay time		—	35	—	ns
t_f	Fall time		—	15	—	ns
V_{SD}	Source-drain voltage	$I_S = -1\text{A}$, $V_{GS} = 0\text{V}$	—	-1.0	-1.5	V
$R_{th(ch-c)}$	Thermal resistance	Channel to case	—	—	6.25	$^{\circ}\text{C/W}$
t_{rr}	Reverse recovery time	$I_S = -3\text{A}$, $di/dt = 100\text{A}/\mu\text{s}$	—	40	—	ns

PERFORMANCE CURVES




PRELIMINARY
 Notice: This is not a final specification.
 Some parametric limits are subject to change.

MITSUBISHI Pch POWER MOSFET


FX3UMJ-06

HIGH-SPEED SWITCHING USE


**ON-STATE VOLTAGE VS.
GATE-SOURCE VOLTAGE
(TYPICAL)**




**ON-STATE RESISTANCE VS.
DRAIN CURRENT
(TYPICAL)**




**TRANSFER CHARACTERISTICS
(TYPICAL)**




**FORWARD TRANSFER ADMITTANCE
VS. DRAIN CURRENT
(TYPICAL)**



**CAPACITANCE VS.
DRAIN-SOURCE VOLTAGE
(TYPICAL)**




**SWITCHING CHARACTERISTICS
(TYPICAL)**




Jan.1999


GATE-SOURCE VOLTAGE
VS. GATE CHARGE
(TYPICAL)




SOURCE-DRAIN DIODE
FORWARD CHARACTERISTICS
(TYPICAL)




ON-STATE RESISTANCE VS.
CHANNEL TEMPERATURE
(TYPICAL)



THRESHOLD VOLTAGE VS.
CHANNEL TEMPERATURE
(TYPICAL)



BREAKDOWN VOLTAGE VS.
CHANNEL TEMPERATURE
(TYPICAL)



TRANSIENT THERMAL IMPEDANCE
CHARACTERISTICS

