
32-Channel, Serial-to-Parallel Converter with High-Voltage Push-Pull Outputs

Features

- Processed with High-Voltage CMOS technology
- Low power-level shifting
- Source/sink current minimum 20mA
- Shift register speed 8.0 MHz
- Latched data outputs
- CMOS compatible inputs
- Forward and reverse shifting options
- Diode to V_{PP} allows efficient power recovery

Description


HV5308 and HV5408 are low-voltage serial to high-voltage parallel converters with push-pull outputs. These devices have been designed for use as a driver for AC-electroluminescent displays. HV5308 / HV5408 can also be used in any application requiring multiple output high-voltage, current sourcing, and sinking capabilities such as driving plasma panels, vacuum fluorescent, or large matrix LCD displays.

These devices consist of a 32-bit shift register, 32 latches, and control logic to enable outputs. Data is shifted through the shift register on the low-to-high transition of the clock. HV5308 shifts in the clockwise direction, when viewed from the top of the package, and HV5408 shifts in the counter-clockwise direction.


A data output buffer is provided for cascading devices. This output reflects the current status of the last bit of the shift register (32). Operation of the shift register is not affected by the $\overline{LE}$ (latch enable) or the $\overline{OE}$ (output enable) inputs. Transfer of data from the shift register to the latch occurs when the $\overline{LE}$ input is high. The data in the latch is retained when $\overline{LE}$ is low.

HV5308 / HV5408

Package Type




44-Lead PQFP




44-Lead PLCC

See [Table 2-1](#) for pin information

Functional Block Diagram



Typical Application Circuit



HV5308 / HV5408

1.0 ELECTRICAL CHARACTERISTICS

ABSOLUTE MAXIMUM RATINGS†

Supply voltage, V_{DD}	-0.5V to +16V
Supply voltage, V_{PP}	-0.5V to +90V
Logic input levels	-0.5V to $V_{DD}+0.5V$
Ground current ¹	1.5A
Continuous total power dissipation ²	1200mW
Operating temperature range	-40°C to +85°C
Storage temperature range	-65°C to +150°C

† **Notice:** Stresses above those listed under “Maximum Ratings” may cause permanent damage to the device. This is a stress rating only and functional operation of the device at those or any other conditions above those indicated in the operational listings of this specification is not implied. Exposure to maximum rating conditions for extended periods may affect device reliability.

- 1: Duty cycle is limited by the total power dissipated in the package.
- 2: For operation above 25°C ambient derate linearly to maximum operating temperature at 20mW/°C.

ELECTRICAL CHARACTERISTICS

Electrical Specifications: V _{PP} = 60V, V _{DD} = 12V, T _A = 25°C						
Parameter		Symbol	Min	Max	Units	Conditions
DC Characteristics						
V _{PP} supply current		I _{PP}	-	0.5	mA	HV _{OUTPUTS} high to low
I _{DD} supply current (quiescent)		I _{DDQ}	-	100	μA	All inputs = V _{DD} or GND
I _{DD} supply current (operating)		I _{DD}	-	15	mA	V _{DD} = V _{DD} max, f _{CLK} = 8.0MHz
High level logic input current		I _{IH}	-	1.0	μA	V _{IN} = V _{DD}
Low level logic input current		I _{IL}	-	-1.0	μA	V _{IN} = 0
High level output voltage	HV _{OUT}	V _{OH}	52	-	V	I _{OH} = -20mA, -40 to 85°C I _{OH} = -15mA, -55 to 125°C
	Data out		10.5	-	V	I _O = -100μA
Low level output voltage	HV _{OUT}	V _{OL}	-	8.0	V	I _{OL} = 20mA, -40 to 85°C I _{OL} = 15mA, -55 to 125°C
	Data out		-	1.0	V	I _O = 100μA
HV output clamp diode voltage		V _{OC}	-	-1.5	V	I _{OL} = -100mA
AC Characteristics						
Clock frequency		f _{CLK}	-	8.0	MHz	---
Clock width, High or Low		t _{WL} or t _{WH}	62	-	ns	---
Setup time before CLK rises		t _{SU}	25	-	ns	---
Hold time after CLK rises		t _H	10	-	ns	---
Data output delay after L to H CLK		t _{DLH} (Data)	-	110	ns	C _L = 15pF, (Note 1)
Data output delay after H to L CLK		t _{DHL} (Data)	-	110	ns	C _L = 15pF, (Note 1)
LE delay after L to H CLK		t _{DLE}	50	-	ns	(Note 1)
Width of LE pulse		t _{WLE}	50	-	ns	---
LE setup time before L to H CLK		t _{SLE}	50	-	ns	(Note 1)
Delay from LE to HV _{OUT} , L to H		t _{ON}	-	500	ns	(Note 1)
Delay from LE to HV _{OUT} , H to L		t _{OFF}	-	500	ns	(Note 1)

Note 1: L to H = Low to High; H to L = High to Low.

TEMPERATURE SPECIFICATIONS

Electrical Specifications: Unless otherwise specified, for all specifications $T_A = T_J = +25^{\circ}\text{C}$						
Parameter	Symbol	Min	Typ	Max	Units	Conditions
Temperature Ranges						
Operating Temperature		-40	–	85	$^{\circ}\text{C}$	
Storage Temperature		-65	–	150	$^{\circ}\text{C}$	
Package Thermal Resistances						
Thermal Resistance, 44-Lead PQFP	θ_{ja}	–	51	–	$^{\circ}\text{C/W}$	
Thermal Resistance, 44-Lead PLCC	θ_{ja}	–	37	–	$^{\circ}\text{C/W}$	

HV5308 / HV5408

2.0 PIN DESCRIPTION

The locations of the pins are listed in [Package Type](#).

TABLE 2-1: PIN DESCRIPTION PQFP

Pin #	HV5308	HV5408	Description
1	HV _{OUT} 22	HV _{OUT} 11	High voltage outputs. High voltage push-pull outputs, which, depending on controlling low voltage data, can drive loads either to GND, or to V _{PP} rail levels.
2	HV _{OUT} 21	HV _{OUT} 12	
3	HV _{OUT} 20	HV _{OUT} 13	
4	HV _{OUT} 19	HV _{OUT} 14	
5	HV _{OUT} 18	HV _{OUT} 15	
6	HV _{OUT} 17	HV _{OUT} 16	
7	HV _{OUT} 16	HV _{OUT} 17	
8	HV _{OUT} 15	HV _{OUT} 18	
9	HV _{OUT} 14	HV _{OUT} 19	
10	HV _{OUT} 13	HV _{OUT} 20	
11	HV _{OUT} 12	HV _{OUT} 21	
12	HV _{OUT} 11	HV _{OUT} 22	
13	HV _{OUT} 10	HV _{OUT} 23	
14	HV _{OUT} 9	HV _{OUT} 24	
15	HV _{OUT} 8	HV _{OUT} 25	
16	HV _{OUT} 7	HV _{OUT} 26	
17	HV _{OUT} 6	HV _{OUT} 27	
18	HV _{OUT} 5	HV _{OUT} 28	
19	HV _{OUT} 4	HV _{OUT} 29	
20	HV _{OUT} 3	HV _{OUT} 30	
21	HV _{OUT} 2	HV _{OUT} 31	
22	HV _{OUT} 1	HV _{OUT} 32	
23	DATA OUT	DATA OUT	Serial data output. Data output for cascading to the data input of the next device.
24	N/C	N/C	No connect.
25			
26			
27	CLK	CLK	Data shift register clock Input are shifted into the shift register on the positive edge of the clock.
28	GND	GND	Logic and high voltage ground
29	VPP	VPP	High voltage power rail.
30	VDD	VDD	Low voltage logic power rail.
31	$\overline{\text{LE}}$	$\overline{\text{LE}}$	Latch enable input. When $\overline{\text{LE}}$ is High, shift register data is transferred into a data latch. When $\overline{\text{LE}}$ is Low, data is latched, and new data can be clocked into the shift register.
32	DATA IN	DATA IN	Serial data input. Data needs to be present before each rising edge of the clock.
33	OE	OE	Output enable input. When OE is Low, all HV outputs are forced into a Low state, regardless of data in each channel. When OE is High, all HV outputs reflect data latched.
34	N/C	N/C	No connect.

TABLE 2-1: PIN DESCRIPTION PQFP (CONTINUED)

Pin #	HV5308	HV5408	Description
35	HV _{OUT} 32	HV _{OUT} 1	High voltage outputs. High voltage push-pull outputs, which, depending on controlling low voltage data, can drive loads either to GND, or to V _{PP} rail levels.
36	HV _{OUT} 31	HV _{OUT} 2	
37	HV _{OUT} 30	HV _{OUT} 3	
38	HV _{OUT} 29	HV _{OUT} 4	
39	HV _{OUT} 28	HV _{OUT} 5	
40	HV _{OUT} 27	HV _{OUT} 6	
41	HV _{OUT} 26	HV _{OUT} 7	
42	HV _{OUT} 25	HV _{OUT} 8	
43	HV _{OUT} 24	HV _{OUT} 9	
44	HV _{OUT} 23	HV _{OUT} 10	

TABLE 2-2: PIN DESCRIPTION PLCC

Pin #	HV5308	HV5408	Description
1	HV _{OUT} 17	HV _{OUT} 16	High voltage outputs. High voltage push-pull outputs, which, depending on controlling low voltage data, can drive loads either to GND, or to V _{PP} rail levels.
2	HV _{OUT} 16	HV _{OUT} 17	
3	HV _{OUT} 15	HV _{OUT} 18	
4	HV _{OUT} 14	HV _{OUT} 19	
5	HV _{OUT} 13	HV _{OUT} 20	
6	HV _{OUT} 12	HV _{OUT} 21	
7	HV _{OUT} 11	HV _{OUT} 22	
8	HV _{OUT} 10	HV _{OUT} 23	
9	HV _{OUT} 9	HV _{OUT} 24	
10	HV _{OUT} 8	HV _{OUT} 25	
11	HV _{OUT} 7	HV _{OUT} 26	
12	HV _{OUT} 6	HV _{OUT} 27	
13	HV _{OUT} 5	HV _{OUT} 28	
14	HV _{OUT} 4	HV _{OUT} 29	
15	HV _{OUT} 3	HV _{OUT} 30	
16	HV _{OUT} 2	HV _{OUT} 31	
17	HV _{OUT} 1	HV _{OUT} 32	
18	DATA OUT	DATA OUT	Serial data output. Data output for cascading to the data input of the next device.
19	N/C	N/C	No connect.
20			
21			
22	CLK	CLK	Data shift register clock Input are shifted into the shift register on the positive edge of the clock.
23	GND	GND	Logic and high voltage ground
24	VPP	VPP	High voltage power rail.
25	VDD	VDD	Low voltage logic power rail.
26	LE	LE	Latch enable input. When $\overline{LE}$ is High, shift register data is transferred into a data latch. When $\overline{LE}$ is Low, data is latched, and new data can be clocked into the shift register.

HV5308 / HV5408

TABLE 2-2: PIN DESCRIPTION PLCC (CONTINUED)

Pin #	HV5308	HV5408	Description
27	DATA IN	DATA IN	Serial data input. Data needs to be present before each rising edge of the clock.
28	OE	OE	Output enable input. When OE is Low, all HV outputs are forced into a LOW state, regardless of data in each channel. When OE is High, all HV outputs reflect data latched.
29	N/C	N/C	No connect.
30	HVOUT32	HV _{OUT1}	High voltage outputs. High voltage push-pull outputs, which, depending on controlling low voltage data, can drive loads either to GND, or to V _{PP} rail levels.
31	HVOUT31	HV _{OUT2}	
32	HVOUT30	HV _{OUT3}	
33	HVOUT29	HV _{OUT4}	
34	HVOUT28	HV _{OUT5}	
35	HVOUT27	HV _{OUT6}	
36	HVOUT26	HV _{OUT7}	
37	HVOUT25	HV _{OUT8}	
38	HVOUT24	HV _{OUT9}	
39	HVOUT23	HV _{OUT10}	
40	HVOUT22	HV _{OUT11}	
41	HVOUT21	HV _{OUT12}	
42	HVOUT20	HV _{OUT13}	
43	HVOUT19	HV _{OUT14}	
44	HVOUT18	HV _{OUT15}	

3.0 FUNCTIONAL DESCRIPTION

Table 3-1 provides functional information about HV5308 / HV5408.

TABLE 3-1: FUNCTIONAL TABLE CLK

DATA IN	CLK	DATA OUT
H	↑	H
L	↑	L
X	No ↑	No change

Note: H = High level, L = Low level, ↑ = Low-to-High transition

TABLE 3-2: FUNCTIONAL TABLE $\overline{LE}$, OE

DATA IN	$\overline{LE}$	OE	HV _{OUT}
X	X	L	All HV _{OUT} = Low
X	L	H	Previous latched data
H	H	H	H
L	H	H	L

Note: H = High level, L = Low level, X= Don't Care

TABLE 3-3: RECOMMENDED OPERATING CONDITIONS (-40°C to 85°C)

Symbol	Parameter	Min	Max	Units
V _{DD}	Logic voltage supply	10.8	13.2	V
V _{PP}	High voltage supply	8.0	80	V
V _{IH}	Input high voltage	V _{DD} - 2.0	V _{DD}	V
V _{IL}	Input low voltage	0	2.0	V
f _{CLK}	Clock frequency	0	8.0	MHz

3.1 Power-Up and Recommended Operating Conditions

To power-up HV5308 / HV5408, perform the following power-up sequence:

1. Connect ground
2. Apply V_{DD}
3. Set all inputs (Data, CLK, $\overline{LE}$, etc.) to a known state
4. Apply V_{PP}
5. The V_{PP} should not fall below V_{DD} or float during operation.

To power-down the device, reverse the steps above.




FIGURE 3-1: Input and Output Equivalent Circuits

HV5308 / HV5408





FIGURE 3-2: Switching Waveforms


4.0 PACKAGING INFORMATION

4.1 Package Marking Information


44-lead PQFP



Example



44-lead PLCC



Example




Legend:	XX...X	Product Code or Customer-specific information
	Y	Year code (last digit of calendar year)
	YY	Year code (last 2 digits of calendar year)
	WW	Week code (week of January 1 is week '01')
	NNN	Alphanumeric traceability code
	(e3)	Pb-free JEDEC® designator for Matte Tin (Sn)
	*	This package is Pb-free. The Pb-free JEDEC designator (e3) can be found on the outer packaging for this package.

Note: In the event the full Microchip part number cannot be marked on one line, it will be carried over to the next line, thus limiting the number of available characters for product code or customer-specific information. Package may or not include the corporate logo.

44-Lead PQFP Package Outline (PG)

10.00x10.00mm body, 2.35mm height (max), 0.80mm pitch



Note: For the most current package drawings, see the Microchip Packaging Specification at www.microchip.com/packaging.

Note:

1. A Pin 1 identifier must be located in the index area indicated. The Pin 1 identifier can be: a molded mark/identifier; an embedded metal marker; or a printed indicator.


Symbol		A	A1	A2	b	D	D1	E	E1	e	L	L1	L2	θ
Dimension (mm)	MIN	1.95*	0.00	1.95	0.30	13.65*	9.80*	13.65*	9.80*	0.80 BSC	0.73	1.95 REF	0.25 BSC	0°
	NOM	-	-	2.00	-	13.90	10.00	13.90	10.00		0.88			3.5°
	MAX	2.35	0.25	2.10	0.45	14.15*	10.20*	14.15*	10.20*		1.03			7°

JEDEC Registration MO-112, Variation AA-2, Issue B, Sep.1995.

* This dimension is not specified in the JEDEC drawing.

Drawings not to scale.

44-Lead PLCC Package Outline (PJ) .653x.653in body, .180in height (max), .050in pitch



Note: For the most current package drawings, see the Microchip Packaging Specification at www.microchip.com/packaging.

Notes:

1. A Pin 1 identifier must be located in the index area indicated. The Pin 1 identifier can be: a molded mark/identifier; an embedded metal marker; or a printed indicator.
2. Actual shape of this feature may vary.

Symbol		A	A1	A2	b	b1	D	D1	E	E1	e	R
Dimension (inches)	MIN	.165	.090	.062	.013	.026	.685	.650	.685	.650	.050 BSC	.025
	NOM	.172	.105	-	-	-	.690	.653	.690	.653		.035
	MAX	.180	.120	.083	.021	.036†	.695	.656	.695	.656		.045

JEDEC Registration MS-018, Variation AC, Issue A, June, 1993.

† This dimension differs from the JEDEC drawing.

Drawings not to scale.

APPENDIX A: REVISION HISTORY

Revision A (December 2015)

- Updated file to Microchip format

PRODUCT IDENTIFICATION SYSTEM

To order or obtain information, e.g., on pricing or delivery, refer to the factory or the listed sales office.

<u>PART NO.</u>	<u>XX</u>	<u>X</u>	<u>-</u>	<u>X</u>	<u>-</u>	<u>X</u>
Device	Package Options	Version		Environmental		Media Type
Device:	HV5308 = 32-Channel Serial to Parallel Converter, with High-voltage Push-pull Outputs data shifts in clockwise direction HV5408 = 32-Channel Serial to Parallel Converter, with High-voltage Push-pull Outputs data shifts in counter-clockwise direction					
Package:	PG = 44-Lead PQFP PJ = 44-Lead PLCC					
Version	B = Revision B					
Environmental	G = Lead (Pb)-free/ROHS-compliant package					
Media Type:	(blank) = 96/Tray for PG package = 27/Tube for PJ package M903 = 500/Reel for PG package M919 = 500/Reel for PJ package					

Examples:		
a)	HV5308PG-B-G	Clockwise data shift, 44-Lead PQFP package, 96/Tray
b)	HV5308PG-B-G-M919	Clockwise data shift, 44-Lead PQFP package, 500/Reel
c)	HV5308PJ-B-G	Clockwise data shift, 44-Lead PLCC package, 27/Tube
d)	HV5308PJ-B-G-M903	Clockwise data shift, 44-Lead PLCC package, 500/Reel
e)	HV5408PG-B-G	Counter-clockwise data shift, 44-Lead PQFP package, 96/Tray
f)	HV5408PJ-B-G	Counter-clockwise data shift, 44-Lead PLCC package, 27/Tube

Note the following details of the code protection feature on Microchip devices:

- Microchip products meet the specification contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is one of the most secure families of its kind on the market today, when used in the intended manner and under normal conditions.
- There are dishonest and possibly illegal methods used to breach the code protection feature. All of these methods, to our knowledge, require using the Microchip products in a manner outside the operating specifications contained in Microchip's Data Sheets. Most likely, the person doing so is engaged in theft of intellectual property.
- Microchip is willing to work with the customer who is concerned about the integrity of their code.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of their code. Code protection does not mean that we are guaranteeing the product as "unbreakable."

Code protection is constantly evolving. We at Microchip are committed to continuously improving the code protection features of our products. Attempts to break Microchip's code protection feature may be a violation of the Digital Millennium Copyright Act. If such acts allow unauthorized access to your software or other copyrighted work, you may have a right to sue for relief under that Act.

Information contained in this publication regarding device applications and the like is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION, INCLUDING BUT NOT LIMITED TO ITS CONDITION, QUALITY, PERFORMANCE, MERCHANTABILITY OR FITNESS FOR PURPOSE. Microchip disclaims all liability arising from this information and its use. Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights unless otherwise stated.

Trademarks

The Microchip name and logo, the Microchip logo, dsPIC, FlashFlex, flexPWR, JukeBlox, KEELOQ, KEELOQ logo, Klear, LANCheck, MediaLB, MOST, MOST logo, MPLAB, OptoLyzer, PIC, PICSTART, PIC³² logo, RightTouch, SpyNIC, SST, SST Logo, SuperFlash and UNI/O are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

The Embedded Control Solutions Company and mTouch are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Analog-for-the-Digital Age, BodyCom, chipKIT, chipKIT logo, CodeGuard, dsPICDEM, dsPICDEM.net, ECAN, In-Circuit Serial Programming, ICSP, Inter-Chip Connectivity, KlearNet, KlearNet logo, MiWi, MPASM, MPF, MPLAB Certified logo, MPLIB, MPLINK, MultiTRAK, NetDetach, Omniscient Code Generation, PICDEM, PICDEM.net, PICkit, PICtail, RightTouch logo, REAL ICE, SQI, Serial Quad I/O, Total Endurance, TSHARC, USBCheck, VariSense, ViewSpan, WiperLock, Wireless DNA, and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

Silicon Storage Technology is a registered trademark of Microchip Technology Inc. in other countries.

GestIC is a registered trademark of Microchip Technology Germany II GmbH & Co. KG, a subsidiary of Microchip Technology Inc., in other countries.

All other trademarks mentioned herein are property of their respective companies.

© 2015, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved.

ISBN: 978-1-5224-0073-8

QUALITY MANAGEMENT SYSTEM
CERTIFIED BY DNV
= ISO/TS 16949 =

Microchip received ISO/TS-16949:2009 certification for its worldwide headquarters, design and wafer fabrication facilities in Chandler and Tempe, Arizona; Gresham, Oregon and design centers in California and India. The Company's quality system processes and procedures are for its PIC® MCUs and dsPIC® DSCs, KEELOQ® code hopping devices, Serial EEPROMs, microperipherals, nonvolatile memory and analog products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001:2000 certified.

Worldwide Sales and Service

AMERICAS

Corporate Office
2355 West Chandler Blvd.
Chandler, AZ 85224-6199
Tel: 480-792-7200
Fax: 480-792-7277
Technical Support:
<http://www.microchip.com/support>
Web Address:
www.microchip.com

Atlanta
Duluth, GA
Tel: 678-957-9614
Fax: 678-957-1455

Austin, TX
Tel: 512-257-3370

Boston
Westborough, MA
Tel: 774-760-0087
Fax: 774-760-0088

Chicago
Itasca, IL
Tel: 630-285-0071
Fax: 630-285-0075

Cleveland
Independence, OH
Tel: 216-447-0464
Fax: 216-447-0643

Dallas
Addison, TX
Tel: 972-818-7423
Fax: 972-818-2924

Detroit
Novi, MI
Tel: 248-848-4000

Houston, TX
Tel: 281-894-5983

Indianapolis
Noblesville, IN
Tel: 317-773-8323
Fax: 317-773-5453

Los Angeles
Mission Viejo, CA
Tel: 949-462-9523
Fax: 949-462-9608

New York, NY
Tel: 631-435-6000

San Jose, CA
Tel: 408-735-9110

Canada - Toronto
Tel: 905-673-0699
Fax: 905-673-6509

ASIA/PACIFIC

Asia Pacific Office
Suites 3707-14, 37th Floor
Tower 6, The Gateway
Harbour City, Kowloon

Hong Kong
Tel: 852-2943-5100
Fax: 852-2401-3431

Australia - Sydney
Tel: 61-2-9868-6733
Fax: 61-2-9868-6755

China - Beijing
Tel: 86-10-8569-7000
Fax: 86-10-8528-2104

China - Chengdu
Tel: 86-28-8665-5511
Fax: 86-28-8665-7889

China - Chongqing
Tel: 86-23-8980-9588
Fax: 86-23-8980-9500

China - Dongguan
Tel: 86-769-8702-9880

China - Hangzhou
Tel: 86-571-8792-8115
Fax: 86-571-8792-8116

China - Hong Kong SAR
Tel: 852-2943-5100
Fax: 852-2401-3431

China - Nanjing
Tel: 86-25-8473-2460
Fax: 86-25-8473-2470

China - Qingdao
Tel: 86-532-8502-7355
Fax: 86-532-8502-7205

China - Shanghai
Tel: 86-21-5407-5533
Fax: 86-21-5407-5066

China - Shenyang
Tel: 86-24-2334-2829
Fax: 86-24-2334-2393

China - Shenzhen
Tel: 86-755-8864-2200
Fax: 86-755-8203-1760

China - Wuhan
Tel: 86-27-5980-5300
Fax: 86-27-5980-5118

China - Xian
Tel: 86-29-8833-7252
Fax: 86-29-8833-7256

ASIA/PACIFIC

China - Xiamen
Tel: 86-592-2388138
Fax: 86-592-2388130

China - Zhuhai
Tel: 86-756-3210040
Fax: 86-756-3210049

India - Bangalore
Tel: 91-80-3090-4444
Fax: 91-80-3090-4123

India - New Delhi
Tel: 91-11-4160-8631
Fax: 91-11-4160-8632

India - Pune
Tel: 91-20-3019-1500

Japan - Osaka
Tel: 81-6-6152-7160
Fax: 81-6-6152-9310

Japan - Tokyo
Tel: 81-3-6880-3770
Fax: 81-3-6880-3771

Korea - Daegu
Tel: 82-53-744-4301
Fax: 82-53-744-4302

Korea - Seoul
Tel: 82-2-554-7200
Fax: 82-2-558-5932 or
82-2-558-5934

Malaysia - Kuala Lumpur
Tel: 60-3-6201-9857
Fax: 60-3-6201-9859

Malaysia - Penang
Tel: 60-4-227-8870
Fax: 60-4-227-4068

Philippines - Manila
Tel: 63-2-634-9065
Fax: 63-2-634-9069

Singapore
Tel: 65-6334-8870
Fax: 65-6334-8850

Taiwan - Hsin Chu
Tel: 886-3-5778-366
Fax: 886-3-5770-955

Taiwan - Kaohsiung
Tel: 886-7-213-7828

Taiwan - Taipei
Tel: 886-2-2508-8600
Fax: 886-2-2508-0102

Thailand - Bangkok
Tel: 66-2-694-1351
Fax: 66-2-694-1350

EUROPE

Austria - Wels
Tel: 43-7242-2244-39
Fax: 43-7242-2244-393

Denmark - Copenhagen
Tel: 45-4450-2828
Fax: 45-4485-2829

France - Paris
Tel: 33-1-69-53-63-20
Fax: 33-1-69-30-90-79

Germany - Dusseldorf
Tel: 49-2129-3766400

Germany - Karlsruhe
Tel: 49-721-625370

Germany - Munich
Tel: 49-89-627-144-0
Fax: 49-89-627-144-44

Italy - Milan
Tel: 39-0331-742611
Fax: 39-0331-466781

Italy - Venice
Tel: 39-049-7625286

Netherlands - Drunen
Tel: 31-416-690399
Fax: 31-416-690340

Poland - Warsaw
Tel: 48-22-3325737

Spain - Madrid
Tel: 34-91-708-08-90
Fax: 34-91-708-08-91

Sweden - Stockholm
Tel: 46-8-5090-4654

UK - Wokingham
Tel: 44-118-921-5800
Fax: 44-118-921-5820