


isc Silicon PNP Power Transistor
KTB1367
DESCRIPTION


- Collector-Emitter Breakdown Voltage-
: $V_{(BR)CEO} = -100V(\text{Min})$
- Collector Power Dissipation-
: $P_C = 30W @ T_C = 25^\circ C$
- Low Collector Saturation Voltage-
: $V_{CE(sat)} = -2.0V(\text{Max}) @ (I_C = -4A, I_B = -0.4A)$
- Complement to Type KTD2059
- Minimum Lot-to-Lot variations for robust device performance and reliable operation


APPLICATIONS

- Designed for general purpose applications.

ABSOLUTE MAXIMUM RATINGS($T_a = 25^\circ C$)

SYMBOL	PARAMETER	VALUE	UNIT
V_{CBO}	Collector-Base Voltage	-100	V
V_{CEO}	Collector-Emitter Voltage	-100	V
V_{EBO}	Emitter-Base Voltage	-5	V
I_C	Collector Current-Continuous	-5	A
I_B	Base Current-Continuous	-0.5	A
P_C	Collector Power Dissipation @ $T_C = 25^\circ C$	30	W
T_J	Junction Temperature	150	$^\circ C$
T_{stg}	Storage Temperature	-55~150	$^\circ C$



isc Silicon PNP Power Transistor

KTB1367

ELECTRICAL CHARACTERISTICS

T_j=25°C unless otherwise specified

SYMBOL	PARAMETER	CONDITIONS	MIN	TYP.	MAX	UNIT
V _{(BR)CEO}	Collector-Emitter Breakdown Voltage	I _C = -50mA; I _B = 0	-100			V
V _{CE(sat)}	Collector-Emitter Saturation Voltage	I _C = -4A; I _B = -0.4A			-2.0	V
V _{BE(on)}	Base-Emitter On Voltage	I _C = -4A; V _{CE} = -5V			-1.5	V
I _{CBO}	Collector Cutoff Current	V _{CB} = -100V; I _E = 0			-100	μA
I _{EBO}	Emitter Cutoff Current	V _{EB} = -5V; I _C = 0			-1	mA
h _{FE-1}	DC Current Gain	I _C = -1A; V _{CE} = -5V	40		240	
h _{FE-2}	DC Current Gain	I _C = -4A; V _{CE} = -5V	20			

◆ h_{FE-1} Classifications

R	O	Y
40-80	70-140	120-240

NOTICE:

ISC reserves the rights to make changes of the content herein the datasheet at any time without notification. The information contained herein is presented only as a guide for the applications of our products.

ISC products are intended for usage in general electronic equipment. The products are not designed for use in equipment which require specialized quality and/or reliability, or in equipment which could have applications in hazardous environments, aerospace industry, or medical field. Please contact us if you intend our products to be used in these special applications.

ISC makes no warranty or guarantee regarding the suitability of its products for any particular purpose, nor does ISC assume any liability arising from the application or use of any products, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages.