

High Ripple-Rejection Low Dropout CMOS Voltage Regulator

■ General Description

The LN1130 Series is a positive voltage regulator with a low dropout voltage, high output voltage accuracy, and low current consumption developed based on CMOS technology.

A built-in low on-resistance transistor provides a low dropout voltage and large output current, and a built-in overcurrent protector prevents the load current from exceeding the current capacitance of the output transistor. Small SOT-89-3, SOT23-3 package realize high-density mounting..

■ Applications

- Power supply for DVD and CD-ROM drives
- Power supply for battery-powered devices
- Power supply for personal communication devices
- Power supply for note PCs

■ Features

- Output voltage: 1.5 V to 5.5 V, selectable in 0.1 V steps.
- High-accuracy output voltage: $\pm 2.0\%$
- Low dropout voltage: 250mV typ. (3.0V output product, $I_{OUT} = 100 \text{ mA}$)
- Low current consumption during operation: 60 μA (typ.), 80 μA (max.)
- During shutdown: 0.1 μA (typ.), 1.0 μA (max.)
- High peak current capability: 300mA output is possible (at $V_{IN} \geq V_{OUT(S)} + 1.0 \text{ V}$)
- Built-in ON/OFF circuit: ensures long battery life.
- High ripple rejection: 55dB typ. (at 1.0 kHz)
- Built-in overcurrent protector: overcurrent of output transistor can be restricted.
- Small package: SOT-89-3, SOT-23-3, other required

■ Package




- SOT-89-3L
- SOT-23-3L, SOT-23-3B

■ Ordering Information

LN1130P ①②③④⑤

Designator	Symbol	Description	Designator	Symbol	Description
① ②	Integer	Output Voltage: eg: ①=3, ②=0 \Rightarrow 3.0V	④	P	SOT-89-3L (B Type)
②	2	Accuracy: $\pm 2\%$		R	SOT-89-3L (A Type)
③		Package Type	⑤		Embossed Tape
	M	SOT-23-3L		R	Standard Feed
	V	SOT-23-3B		L	Reverse Feed

■ Pin Configuration




■ Pin Assignment


Pin Number			Pin Name	Function
SOT-23-3L/B	SOT-89-3(A)	SOT-89-3(B)		
3	3	2	VIN	Power Supply
1	2	1	VSS	Ground
2	1	3	VOUT	Output Pin

■ Marking Rule

- SOT-89-3L and SOT-23-3L/B



SOT-89-3L
(Top View)



SOT-23-3L/SOT-23-3B
(Top View)

① Represents the product name

Symbol	Product Name
S	LN1130◆◆◆◆◆◆

② Represents the range of output voltage

Output Voltage Range (V)	0.1~3.0	3.1~6.0	6.1~9.0
Symbol	5	6	7


③ Represents the Output Voltage

Symbol	Output Voltage (V)		Symbol	Output Voltage (V)			
0	-	3.1	-	F	1.6	4.6	-
1	-	3.2	-	H	1.7	4.7	-
2	-	3.3	-	K	1.8	4.8	-
3	-	3.4	-	L	1.9	4.9	-
4	-	3.5	-	M	2	5.0	-
5	-	3.6	-	N	2.1	5.1	-
6	-	3.7	-	P	2.2	5.2	-
7	-	3.8	-	R	2.3	5.3	-
8	-	3.9	-	S	2.4	5.4	-
9	-	4	-	T	2.5	5.5	-
A	-	4.1	-	U	2.6	5.6	-
B	1.2	4.2	-	V	2.7	5.7	-
C	1.3	4.3	-	X	2.8	5.8	-
D	1.4	4.4	-	Y	2.9	5.9	-
E	1.5	4.5	-	Z	3	6.0	-

④ Represents the assembly lot no.

0~9, A~Z repeated (G, I, J, O, Q, W excepted)

■ Function Block Diagram




■ Absolute Maximum Ratings

Parameter	Symbol	Maximum Rating		Unit
Input Voltage	V _{IN}	V _{ss} -0.3~V _{ss} +8		V
Output Current	V _{OUT}	V _{ss} -0.3~V _{IN} +0.3		
Power Dissipation	P _D	SOT-23-3	250	mW
		SOT-89-3	500	
Operating Ambient Temperature	T _{opr}	-40~+85		°C
Storage Temperature	T _{stg}	-40~+125		

Caution: The absolute maximum ratings are rated values exceeding which the product could suffer physical damage.

These values must therefore not be exceeded under any conditions.

■ Typical Application Circuit







Caution: The above connection diagram and constant will not guarantee successful operation.

Perform thorough evaluation using the actual application to set the constant.

■ Electrical Characteristics

Item	Symbol	Condition	Min	Typ	Max	Unit	Test circuit
Output voltage	V _{OUT(E)1}	V _{IN} =V _{OUT(S)} +1.0 V, I _{OUT} =30 mA	V _{OUT(S)} x0.99	V _{OUT(S)}	V _{OUT(S)} x1.01	V	1
	V _{OUT(E)2}	V _{IN} =V _{OUT(S)} +1.0 V, I _{OUT} =80 mA	V _{OUT(S)} x0.98	V _{OUT(S)}	V _{OUT(S)} x1.02	V	
Output current ^{*2}	I _{OUT}	V _{IN} ≥V _{OUT(S)} +1.0 V		300	—	—	mA 3
Dropout voltage	V _{drop}	I _{OUT} =100 mA	2.2 V ≤V _{OUT(S)} ≤2.5 V	—	0.30	0.49	V
			2.6 V ≤V _{OUT(S)} ≤3.3 V	—	0.25	0.34	
			3.4 V ≤V _{OUT(S)} ≤5.5 V	—	0.20	0.28	
Line regulation	$\frac{\Delta V_{OUT1}}{\Delta V_{IN} \bullet V_{OUT}}$	V _{OUT(S)} +0.5 V ≤V _{IN} ≤7 V I _{OUT} =80 mA	—	0.05	0.2	%/V	1
Load regulation	ΔV _{OUT2}	V _{IN} =V _{OUT(S)} +1.0 V 1.0 mA ≤I _{OUT} ≤80 mA	—	20	40	mV	
temperature coefficient	$\frac{\Delta V_{OUT}}{\Delta T_a \bullet V_{OUT}}$	V _{IN} =V _{OUT(S)} +1.0 V, I _{OUT} =10 mA -40°C ≤T _a ≤85°C	—	±100	—	ppm/°C	
Current consumption during operation	I _{SS1}	V _{IN} =V _{OUT(S)} +1.0 V,	—	60	80	μA	2
Input voltage	V _{IN}	—	2.0	—	7	V	—
Ripple rejection	RR	V _{IN} =V _{OUT(S)} +1.0 V, f=1.0 kHz V _{rip} =0.5 Vrms, I _{OUT} =80 mA	—	55	—	dB	4
Short-circuit current	I _{short}	V _{IN} =V _{OUT(S)} +1.0 V, ON/OFF pin ON, V _{OUT} =0 V	—	30	—	mA	3


■ Test Circuits

Circuit 1

Circuit 2

Circuit 3

Circuit 4



■ Typical Performance Characteristics

1、Output voltage vs. Output current (when load current increases)


LN1130 (1.5V)



LN1130 (3.0V)




LN1130 (5.0V)




2、Output voltage vs. Input voltage


LN1130 (1.5V)




LN1130 (3.0V)




LN1130 (5.0V)





3、Dropout voltage vs. Output current




4、Dropout voltage vs. Set output voltage



5、Output voltage vs. Ambient temperature




LN1130 (5.0V)




6、Ripple rejection


LN1130 (1.5V)



LN1130 (3.0V)




LN1130 (5.0V)



7、Transient response characteristics


Input transient response characteristics

$I_{out} = 80\text{ mA}$, $t_r = t_f = 5.0\text{ }\mu\text{s}$, $C_{out} = 2.2\text{ }\mu\text{F}$, $C_{in} = 0\text{ }\mu\text{F}$




Load transient response characteristics

$V_{in} = 4.0\text{ V}$, $C_{out} = 2.2\text{ }\mu\text{F}$, $C_{in} = 1.0\text{ }\mu\text{F}$, $I_{out} = 50 \leftrightarrow 100\text{ mA}$




■ Package Information

- SOT-89-3L




Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	1.400	1.600	0.055	0.063
b	0.320	0.520	0.013	0.020
b1	0.400	0.580	0.016	0.023
c	0.350	0.440	0.014	0.017
D	4.400	4.600	0.173	0.181
D1	1.550 REF.		0.061 REF.	
E	2.300	2.600	0.091	0.102
E1	3.940	4.250	0.155	0.167
e	1.500 TYP.		0.060 TYP.	
e1	3.000 TYP.		0.118 TYP.	
L	0.900	1.200	0.035	0.047

● SOT-23-3L



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	1.050	1.250	0.041	0.049
A1	0.000	0.100	0.000	0.004
A2	1.050	1.150	0.041	0.045
b	0.300	0.500	0.012	0.020
c	0.100	0.200	0.004	0.008
D	2.820	3.020	0.111	0.119
E	1.500	1.700	0.059	0.067
E1	2.650	2.950	0.104	0.116
e	0.950(BSC)		0.037(BSC)	
e1	1.800	2.000	0.071	0.079
L	0.300	0.600	0.012	0.024
θ	0°	8°	0°	8°

● SOT-23-3B



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min.	Max.	Min.	Max.
A	0.900	1.150	0.035	0.045
A1	0.000	0.100	0.000	0.004
A2	0.900	1.050	0.035	0.041
b	0.300	0.500	0.012	0.020
c	0.080	0.150	0.003	0.006
D	2.800	3.000	0.110	0.118
E	1.200	1.400	0.047	0.055
E1	2.250	2.550	0.089	0.100
e	0.950 TYP.		0.037 TYP.	
e1	1.800	2.000	0.071	0.079
L	0.550 REF.		0.022 REF.	
L1	0.300	0.500	0.012	0.020
θ	0°	8°	0°	8°