

Linear Systems replaces discontinued Siliconix LSJ204

The LSJ204 is a high gain N-Channel JFET

This n-channel JFET is optimised for high gain. The part is particularly suitable for use in low power or high impedance amplifiers. The SOT-23 package is well suited for cost sensitive applications and mass production.

(See Packaging Information).

LSJ204 Benefits:

- High Input Impedance
- Low Cutoff Voltage
- Low Noise

LSJ204 Applications:

- Battery powered amplifiers
- Audio Pre-Amplifiers
- Infra-Red Detector Amplifiers

FEATURES	
DIRECT REPLACEMENT FOR SILICONIX LSJ204	
LOW CUT OFF VOLTAGE	$V_{GS(off)} \leq 1.5$
HIGH GAIN	$A_V = 80 \text{ V/V}$
ABSOLUTE MAXIMUM RATINGS @ 25°C (unless otherwise noted)	
Maximum Temperatures	
Storage Temperature	-65°C to +150°C
Operating Junction Temperature	-55°C to +135°C
Maximum Power Dissipation	
Continuous Power Dissipation	350mW
MAXIMUM CURRENT	
Forward Gate Current (Note 1)	50mA
MAXIMUM VOLTAGES	
Gate to Drain Voltage	$V_{GDS} = -40\text{V}$
Gate to Source Voltage	$V_{GSS} = -40\text{V}$

LSJ204 ELECTRICAL CHARACTERISTICS @ 25°C (unless otherwise noted)

SYMBOL	CHARACTERISTIC	MIN	TYP.	MAX	UNITS	CONDITIONS
BV_{GSS}	Gate to Source Breakdown Voltage	-25	--	--		$I_G = 1\mu\text{A}, V_{DS} = 0\text{V}$
$V_{GS(off)}$	Gate to Source Cutoff Voltage	-0.3	--	2	V	$V_{DS} = 15\text{V}, I_D = 10\text{nA}$
I_{DSS}	Drain to Source Saturation Current (Note 2)	0.2	--	3	mA	$V_{DS} = 15\text{V}, V_{GS} = 0\text{V}$
I_{GSS}	Gate Reverse Current	-2	--	-100		$V_{GS} = -20\text{V}, V_{DS} = 0\text{V}$
I_G	Gate Operating Current	--	-2	--	pA	$V_{DG} = 10\text{V}, I_D = 0.1\text{mA}$
$I_{D(off)}$	Drain Cutoff Current	--	2	--		$V_{DS} = 15\text{V}, V_{GS} = -5\text{V}$
g_{fs}	Forward Transconductance	0.5	--	--	mS	$V_{DS} = 15\text{V}, V_{GS} = 0\text{V}, f = 1\text{kHz}$
C_{iss}	Input Capacitance	--	4.5	--	pF	$V_{DS} = 15\text{V}, V_{GS} = 0\text{V}, f = 1\text{MHz}$
C_{rss}	Reverse Transfer Capacitance	--	1.3	--		
e_n	Equivalent Noise Voltage	--	6	--	nV/√Hz	$V_{DS} = 10\text{V}, I_D = 1\text{mA}, f = 1\text{kHz}$

Note 1 - Absolute maximum ratings are limiting values above which LSJ204 serviceability may be impaired.

Note 2 – Pulse test: $PW \leq 300 \mu\text{s}$, Duty Cycle $\leq 3\%$

Micross Components Europe




Tel: +44 1603 788967
Email: chipcomponents@micross.com
Web: <http://www.micross.com/distribution>

Available Packages:

LSJ204 in SOT-23
LSJ204 in bare die.

Please contact Micross for full package and die dimensions

SOT-23 (Top View)



Information furnished by Linear Integrated Systems and Micross Components is believed to be accurate and reliable. However, no responsibility is assumed for its use; nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Linear Integrated Systems.