

# MB88510 SERIES

## CMOS SINGLE CHIP 4-BIT MICROCOMPUTER WITH A/D CONVERTER

### DESCRIPTION

The Fujitsu MB88510 series is a CMOS single-chip 4-bit microcomputer family is a CMOS version of the conventional NMOS MB88410 series. Its architecture and instruction set are upward the MB88500 series.


The MB88510 series consists of MB88511, MB88512, and MB88513. MB88511 contains a 4K by 8-bit mask ROM (program memory) and 256 by 4-bit static RAM (data memory) whereas, the MB88513 contains a 2K by 8-bit ROM and a 192 x 4-bit RAM. Besides the on-chip memory, each device has 34 I/O lines (including a serial port with a 4/8-bit buffer), an 8-bit timer/counter, a clock generator, and an 8-bit 4 channel programmable approximation type A/D converter. Otherwise, MB88512 contains 2K by 8-bit mask ROM and 128 by 4-bit static RAM. And 12 I/O lines, an 8-bit timer/counter, a clock generator, and an 8-bit 8-channel programmable approximation type A/D converter.

They are fabricated in silicon-gate CMOS process. MB88511 and MB88513 are housed in a 42-pin plastic standard/shrink DIP or 48-pin plastic flat package. Whereas MB88512 is housed in a 28-pin plastic standard DIP. They require +5V power supply and maximum 3MHz clock (6MHz clock with the prescaler), they operate 2.0µs minimum over a temperature range of -40°C to +85°C.

CMOS technology allows the device to operate with low power dissipation (6 mA max. using  $f_c=1$  MHz) and further the standby function (if implemented) enables data retention with lower current (15 µA max. using  $f_c = 0$  MHz.)


For user's development of the MB88510 series based system, Fujitsu provides the MB88400/500 cross assembler and host emulator which run on the PC-DOS machine, the MB2115 series evaluation tool system, and the MB88PG511/MB88PG512 piggyback devices which have an external 8K x 8-bit EPROM (MBM27C64). These development tools enables users to minimize their development time and cost.

MB88511-P/MB88513-P




42-PIN PLASTIC STANDARD DIP  
(DIP-42P-M01)

MB88511-PSH/MB88513-PSH




42-PIN PLASTIC SHRINK DIP  
(DIP-42P-M02)

MB88512-P



28-PIN PLASTIC STANDARD DIP  
(DIP-28P-M02)

MB88511-PF/MB88513-PF



48-PIN PLASTIC FLAT PACKAGE  
(FPT-48P-M02)

MB88PG511-C

MB88PG512-C

(See page 41, 42)

42-PIN CERAMI  
MODULE  
(MDP-42C-P04)

28-PIN CERAMIC  
MODULE  
(MDP-28C-P01)

This device contains circuitry to protect the inputs against damage due to high static voltages or electric fields. However, it is advised that normal precautions be taken to avoid application of any voltage higher than maximum rated voltages to this high impedance circuit.


# FEATURES

- CMOS Single-chip 4-bit Microcomputer
- Program Memory:
  - o MB88511 :4K x 8-bit mask ROM
  - o MB88512 and MB88513 :2K x 8-bit mask ROM
- Data Memory:
  - o MB88511 :256 x 4-bit static RAM
  - o MB88512 :128 x 4-bit static RAM
  - o MB88513 :192 x 4-bit static RAM
- I/O Lines:
  - o MB88511 and MB88513: 34 I/O lines
    - R-Port: Three 4-bit/One 1-bit parallel input/output or 13 individual input/output
    - E-Port: Five 4-bit/One 1-bit parallel input/output or 21 individual output
    - Following ports have an other features.
    - E16–E19 :Serial I/O, interrupt input, timer/counter input, and timing output
    - E11–E15 :8-bit 4-channel A/D converter input
    - E20 :Standby release input
  - o MB88512: 12 I/O lines
    - R-Port: Three 4-bit parallel input/output or 12 individual input/output
    - Following ports have an other features.
    - R8, R9 :Interrupt input and timing output
- 8-bit Programmable Successive Approximation Type A/D Converter with Sample-hold Circuit:
  - o MB88511 and MB88513 :4 channel
  - o MB88512 :8 channel
- Five (Two) Selectable Output Port Types for E-, and R-Ports with Mask Option:
  - o Standard open-drain
  - o Standard pull-up
  - o 12V interface open-drain (Only applied to MB88511 and MB88513)
  - o High-current interface open-drain (Only applied to MB88511 and MB88513)
  - o High-current pull-up (Only applied to MB88511 and MB88513)
- 8-bit Programmable Timer/Counter with Two Clock Modes:
  - o Internal clock (Timer)
  - o External clock (Counter)
- Software Selectable 4-/8-bit Serial Buffer with Three Software Selectable Shift Clock Modes (Only applied to MB88511 and MB88513):
  - o Internal clock
  - o External clock
  - o Software clock
- On-chip Clock Generator with 2 Mask Options:
  - o External crystal/ceramic resonator or external clock drive
  - o External RC-network or external clock drive
- Divide-by-two Clock Prescaler for Expanding Clock Range with Mask Option
- Single Level Four Prior Source Maskable Interrupt:
  - o External
  - o Clock
  - o Timer/counter overflow
  - o Serial buffer full/empty
- 8-nesting Levels for Subroutine Calls
- Instruction Set: Upward compatible with the MB88500 series instruction set
  - o Number of instructions : – MB88511 and MB88513: 79  
– MB88512 : 69
  - o Instruction length/cycle : – 1 byte/1 cycle, 2 byte/2 cycle, and 2 byte/3 cycle


- o Execution time : 2.0  $\mu$ s min. using 6.0 MHz clock with prescaler
- On-chip Power-on Reset Circuit
- Low Power Standby Function with Mask Option:
  - o No standby function
  - o Software-initiation standby function
- Two Output States During Standby with Mask Option:
  - o Hold
  - o High Impedance
- Two Software Selectable Oscillator States During Standby:
  - o Idle
  - o Stop
- Standby Off Reset with Mask Option:
- Watch Dog Timer Function with Mask Option
- Low Power Dissipation:
  - o 6 mA at  $V_{CC} = 5.5$  V at  $f_c = 1$  MHz max. (Active mode)
  - o 15  $\mu$ A at  $V_{CC} = 6.0$  V at  $f_c = 0$  MHz max. (Standby mode)
- +5V Power Supply:
  - o 4.5 V to 5.5 V (Active mode)
  - o 3.5 V to 6.0 V (Standby mode)
- Wide Operation Temperature Range:  $T_A = -40^\circ\text{C}$  to  $+85^\circ\text{C}$
- Silicon Gate CMOS Technology
- Package Options:
  - o MB88511 and MB88513
    - 42-pin plastic standard DIP :suffix –P
    - 42-pin plastic shrink DIP :suffix –PSH
    - 48-pin plastic flat package :suffix –PF
  - o MB88512
    - 28-pin plastic standard DIP :suffix –P
- Powerful Development Support:
  - o PC-DOS cross-assembler (SM07615–AXXX)
  - o PC-DOS host emulator software for monitoring evaluation tool and symbolic debugging (SM07615–GXXX)
  - o MB2115 series evaluation tool for software debugging
    - MB88511 and MB88513 : MB2115–01, –02, –04 (–100), and –38
    - MB88512 : MB2115–01, –02, –04 (–100), and –44
  - o CMOS piggyback EPROM evaluation devices:
    - MB88511 and MB88513 :MB88PG511
    - MB88512 :MB88PG512

Figure 1 MB88511, MB88513, and MB88PG511 Pin Assignment


**MB88511-P/-PSH and MB88513-P/PSH**  
(Top view)



**MB88511-PF and MB88513-PF**  
(Top view)




**MB88PG511-C**  
(Top view)



Notes: \*1 Either E20 or START pin is selected using mask option.


Figure 2 MB88512 and MB88PG512 Pin Assignment



Notes: \*1 Either AN0 or START pin is selected using mask option.


\*2 Either AV<sub>R-</sub> or AV<sub>R+</sub> pin is selected using mask option.

Figure 3 MB88511 and MB88513 Logic Symbol



Note: \* Either E20 or START pin is selected using mask option.

Figure 4 MB88512 Logic Symbol



Notes: \*1 Either E20 or START pin is selected using mask option.  
\*2 Either AVR+ or AVR- pin is selected using mask option.

### Figure 5 MB88511 and MB88513 Block Diagram






Figure 6 MB88512 Block Diagram



# PIN DESCRIPTION

Figure 1 and Table 1 show the pin assignment and pin description of the MB88510 series.

Table 1 Pin Description

| Symbol         | Pin No.            |         | Type | Name & Function                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|----------------|--------------------|---------|------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                | MB88511<br>MB88513 | MB88512 |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| Power Supply   |                    |         |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| Vcc            | 42(18)             | 28      | —    | +5V DC power supply pin.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
| Vss            | 21(42)             | 14      | —    | Ground pin.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| Clock          |                    |         |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| EX             | 16(36)             | 11      | I    | <b>Oscillator Input:</b> Input to the inverting amplifier that forms the on-chip oscillator. An external crystal/ceramic resonator or RC-network is connected between the EX and X pins. Either of these two oscillation types can be selected using mask option. When an external oscillator is used, the EX pin receives the external oscillator signal.<br><br>This pin is a non-hysteresis input when the crystal/ceramic oscillator is selected, and a hysteresis input when the RC-network oscillator is selected.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
| X              | 17(37)             | 12      | O    | <b>Oscillator Output:</b> Output of the inverting amplifier that forms the on-chip oscillator, and input to the internal clock generator. An external crystal/ceramic resonator or RC-network is connected between the EX and X pins. Either of these two oscillator types can be selected using mask option. When an external oscillator is used, the X pin should be left open.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| Device Control |                    |         |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| RESET          | 18(38)             | 13      | I    | <b>Reset:</b> This pin functions as an external reset input or power-on reset output.<br><br><b>External reset input:</b> A reset input to the internal reset circuit. A low level on the RESET pin forcedly stops the MCU's operations, and initializes its internal state. After the RESET pin returns high, the MCU restarts execution of program from address #0. The RESET pulse must be low for at least two instruction cycles while the oscillator is stably running after power on. This pin is a hysteresis input with an internal pullup resistor. An external capacitor from the RESET pin to the Vss pin (and the internal pull-up resistor), whose time constant should be greater than the reset time required (12 clock periods) composes the external reset circuit.<br><br><b>Power on reset output:</b> A reset output from the on-chip reset control circuit. Normally this output is high during the active operation except the reset mode. The rising of the Vcc voltage after power on outputs a low level on the RESET pin, and them automatically returns high 2 <sup>8</sup> clock periods (62ms), after the oscillator starts by power on.<br><br>This pin is a hysteresis input with an internal pull-up resistor. |
| START          | 20(40)             | 27      | I    | <b>Start:</b> A standby release input to the internal standby control and status registers that control and monitor the on-chip standby control circuit. A high level on the START pin during the standby mode sets the standby release flag (STF) in the standby status register, resets the standby enable flag (STBE) in the standby control register, and triggers the standby release sequence to return the MCU to the active mode. Before the START pulse is applied, the Vcc voltage must return to the active operation range when the battery back up is used. Also, the START pin must be low before the standby mode is initiated.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |

Table 1 Pin Discription (Continued)

| Symbol                                      | Pin No.            |         | Type | Name & Function                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
|---------------------------------------------|--------------------|---------|------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                                             | MB88511<br>MB88513 | MB88512 |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| Device Control (Continued)                  |                    |         |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| START                                       | 20(40)             | 27      | I    | <p>The START pin state (logical level) is reflected in the standby release input (START) flag (STIF) in the standby status register, regardless of during the standby mode or active mode, and besides even when the standby function is not implemented using mask option. Therefore, the START pin state can be sensed by reading the standby status register using IN instruction (with Y=8).</p> <p>This pin is a hysteresis input with an internal pull-down resistor. This pin is common to the E20 or AN0 pins, case of the MB88511/513 or MB88512.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| C-Port                                      |                    |         |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| $\overline{\text{IRQ}}$                     | 13(33)             | 9       | I    | <p><b>Interrupt Request:</b> A maskable external interrupt input to the on-chip interrupt control circuit. The falling edge of the <math>\overline{\text{IRQ}}</math> pulse sets the external interrupt request flag (IRF) in the interrupt flag register regardless of enabling or disabling the external interrupt. If the external interrupt is enabled in advance by EN instruction, the interrupt sequence starts at once. Otherwise, the IRF flag is internally held as an interrupt source. Also, the <math>\overline{\text{IRQ}}</math> pin state (logical level), which is reflected in the external interrupt input flag (IF) regardless of enabling or disabling the external interrupt, is testable using TSTI instruction. (When <math>\overline{\text{IRQ}} = \text{L}</math>, <math>\text{IF} = 1</math>; otherwise <math>\text{IF} = 0</math>.)</p> <p>This pin is a hysteresis input with an internal pull-up resistor. This pin is common to the E12 or R8 pins, case of the MB88511/513 or MB88512.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| $\overline{\text{TC}}$                      | 12(32)             | 10      | I    | <p><b>Timer/Counter:</b> An external count clock input to the on-chip 8-bit timer/counter. The falling edge of the <math>\overline{\text{TC}}</math> pulse increments the timer/counter by one bit, when the external count clock (counter) mode is enabled by EN instruction programming, the timer/counter prescaler select register using OUT instruction (with Y=B). Also the <math>\overline{\text{TC}}</math> pin state (logical level), which is reflected in the timer/counter input flag (TCIF) in the timer/counter prescaler select register regardless of enabling or disabling the external count clock (counter mode, is testable by reading the prescaler select register using IN instruction (with Y = B). (When <math>\overline{\text{TC}} = \text{L}</math>, <math>\text{TCIF} = 1</math>; otherwise <math>\text{TCIF} = 0</math>.) This pin is inactive as a count clock input when the external count clock mode is not selected or the timer/counter is disabled by DIS instruction or reset.</p> <p>This pin is a hysteresis input with an internal pull-up resistor. This pin is common to the E11 pin.</p>                                                                                                                                                                                                                                                                                                                                                                                              |
| $\overline{\text{SC}}/\overline{\text{TO}}$ | 19(39)             | —       | I/O  | <p><b>Shift Clock/Timing Output:</b> One of the shift clock input (<math>\overline{\text{SC}}</math>), shift clock output (<math>\overline{\text{SC}}</math>), or synchronous timing output (<math>\overline{\text{TO}}</math>) is enabled using EN instruction.</p> <p><math>\overline{\text{SC}}</math>:</p> <p>1) Shift clock input to the on-chip serial port: When the external shift clock mode is enabled for the serial port, the falling edge of the external <math>\overline{\text{SC}}</math> clock shifts the contents of the internal serial buffer one bit right (from MSB to LSB). This input is inactive when the external clock mode is not selected or the serial port disabled by DIS instruction or reset. This pin is a hysteresis input.</p> <p>2) Shift clock output from the on-chip serial port: When the internal shift clock mode is enabled, the internal shift clock shifts the contents of the serial buffer one bit right. In this mode, the internal timing signal selected is output onto the <math>\overline{\text{SC}}</math> pin for synchronization.</p> <p><math>\overline{\text{TO}}</math>:</p> <p>Synchronous timing output: When the timing output is enabled, the internal timing signal (which is generated by the on-chip state counter outputs, <math>\phi 1</math> and <math>\phi 2</math>) is output onto the <math>\overline{\text{TO}}</math> pin. By DIS instruction or reset, the <math>\overline{\text{TO}}</math> pin is disabled and stops issuing the timing output.</p> |

Table 1 Pin Description (Continued)

| Symbol                                                             | Pin No.                                                                                                   |                                    | Type | Name & Function                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
|--------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------|------------------------------------|------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                                                                    | MB88511<br>MB88513                                                                                        | MB88512                            |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| C-Port (Continued)                                                 |                                                                                                           |                                    |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| $\overline{SC}/\overline{TO}$                                      | 19(39)                                                                                                    | —                                  | I/O  | This pin is a hysteresis input with an internal pullup resistor. This pin is a common to the E15 pin.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| SI                                                                 | 14(34)                                                                                                    | —                                  | I    | <b>Serial Data Input:</b> Data input to the on-chip serial port. The rising edge of the external ( $\overline{SC}$ ) or internal shifts the data bit on the SI pin into the MSB of the serial buffer register when the serial port is enabled by EN instruction. Also, the SI pin state (logical level) is reflected in the serial data input flag (SIF) in the serial port prescaler select register regardless of enabling or disabling the serial port. Therefore, the SI pin can be sensed by reading the prescaler register using IN instruction (with Y=A).<br><br>This pin is a common to the E13 pin.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| SO                                                                 | 15(35)                                                                                                    | —                                  | O    | <b>Serial Data Output:</b> Data output with latch of the on-chip serial port. The falling edge of the external ( $\overline{SC}$ ) or internal shift clock shifts the LSB data of the serial buffer register to the serial port output latch, regardless of enabling or disabling to serial port. The content of the output latch directly appears on the SO pin. This pin is a CMOS pull-up output, and is set high by reset.<br><br>This pin is a common to the E14 pin.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| I/O Ports                                                          |                                                                                                           |                                    |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| R3-R0,<br>R7-R4,<br>R10-R8,<br>R11,<br>R15-R12                     | 25-22(47-44),<br>29-26(3-1,48),<br>—<br>37(12),<br>41-38(16-13)                                           | 4-1,<br>8-5<br>15,10,9,<br>16<br>— | I/O  | <b>R-Port:</b> This port functions as 4-bit parallel input (non-latched)/output (latched) ports, or individual input (non-latched)/output (latched) lines, depending on instructions.<br><br>Parallel I/O: Each 4-bit (1-bit) port is named R-Port #0 (R3-R0), R-Port #1 (R7-R4), R-Port #2 (R11-R8), and R-Port #3 (R15-R12), and is indirectly addressed by the Y-register (Port #). 4-bit data in the accumulator is output to an addressed port of R-Ports #0 to #3 by OUT instruction. 4-bit data on the addressed port is input into the accumulator by IN instruction. (Before IN instruction, the port to be addressed must be set up to "1" state (input) mode.)<br><br>Individual I/O: Each line from R15 to R0 is indirectly addressed by the Y-register (Bit #). The addressed line is individually set/reset by SETR/RSTR instruction, and especially each line of R-Port #0 (R3-R0) is directly set/reset by SETD/RSTD instruction. The addressed line is individually testable by TSTR instruction, and each line of R-Port #2 (R11-R8) is directly testable in particular by TSTD instruction. (Before the TSTR and TSTD instructions, the line to be addressed must be set up to "1" (input) mode.)<br><br>Refer to Table 3 User mask options for available making option. |
| E3-E0,<br>E7-E4,<br>E11-E8,<br><br>E15-E12,<br><br>E19-E16,<br>E20 | 4-1(23-20),<br>8-5(27-24),<br>12-9(32,31,<br>29,28),<br>19,15-13(39,<br>35-33),<br>33-36(7-10),<br>20(40) | —                                  | I/O  | <b>E-Port:</b> This port functions as five 4-bit parallel input (non-latched)/output (latched) ports, or 21 individual input (non-latched)/output (latched) lines, depending on instructions.<br><br>Each 4-bit is named E-Port #0 (E3-E0), E-Port #1 (E7-E4), E-Port #2 (E11-E8), E-Port #3 (E15-E12), E-Port #4 (E19-E16), and E-Port #5 (E20) and is indirectly addressed by the Y-register (Port #). 4-bit data in the accumulator is output to an addressed port of E-Ports #0 to #5 by OUTX instruction. 4-bit data on the addressed port is input into the accumulator by INX instruction. (Before IN instruction, the port to be addressed must be set up to "1" state (input) mode.)<br><br>Individual output: A data of the accumulator is output to the each line by ANDX, ORX, and OUTX instruction.<br><br>Refer to Table 3 User mask options for available making option.                                                                                                                                                                                                                                                                                                                                                                                                     |

Table 1 Pin Description (Continued)






| Symbol                             | Pin No.            |                 | Type | Name & Function                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
|------------------------------------|--------------------|-----------------|------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                                    | MB88511<br>MB88513 | MB88512         |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| I/O Ports (Continued)              |                    |                 |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| NC                                 | (11,17,30,41)      | —               | —    | Non connection pin.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| OPEN                               | (19,43)            | —               | —    | <b>Open:</b> This pin should not to be connect.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| A/D Converter Voltage              |                    |                 |      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| AV <sub>CC</sub>                   | 32(6)              | 19              | —    | A/D converter supply voltage.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
| AV <sub>SS</sub>                   | 30(4)              | 17              | —    | A/D converter ground pin.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
| AV <sub>R-</sub>                   | 31(5)              | —               | —    | A/D converter reference voltage.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| AV <sub>R-</sub> /AV <sub>R+</sub> | —                  | 18              | —    | A/D reference voltage. AV <sub>R-</sub> and AV <sub>R+</sub> is selected by mask option.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
| AN3-AN0,<br>AN7-AN4                | 33-36(7-10)<br>—   | 24-27,<br>20-23 | I    | <b>8-bit Resolution A/D Converter Input:</b> Analog input pin are selectable from among the AN7 to AN0 by OUT (Y=D) instruction. Analog data is inputted from selected AN pin, it is Analog-to Digital converted by OUT (Y=9) instruction. And digital data stored into internal memory as 8 bits digital data. Low of 4 bits digital data transfer into the accumulator by IN (Y=E) instruction, and high of 4 bits digital data transfer into the accumulator by IN (Y=F) instruction.<br><br>In the MB88511/513, analog input pins are common to the E19-E16. In the MB88512, AN0 is common to the START pin, AN0 should be select by the mask option. During standby mode, this function doesn't worked, and A/D converted data is not hold. |

Note: Parenthesis number is applied to MB88511-PF and MB88513-PF.

# INPUT/OUTPUT CIRCUITS

All input-only pins are internally pulled up, and all output-only and input/output pins except E-, P-, and R-Ports have push-pull output buffer (standard pull-up). E- and R-Ports can have push-pull (standard or high-current pull-up) or open-drain (standard or high-current, or 12 V interface) buffer using mask option.






Table 2 Input/Output Circuit

| Pin                                                                                                  | Circuit                                                                                                                                                                            | Remarks                                                                                                                                                                                                                                                                                                                                                                                                                                      |
|------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| EX, X                                                                                                | <ul style="list-style-type: none"> <li>Crystal/Ceramic oscillation or external clock*</li> </ul>  | <ol style="list-style-type: none"> <li>Non-hysteresis inverter</li> <li>Feedback resistor:<br/>Approx. 2 M<math>\Omega</math> typ. (at V<sub>CC</sub>=5V)</li> </ol> <p>* When only external clock drive is used, we recommend RC-network oscillation.</p>                                                                                                                                                                                   |
|                                                                                                      | <ul style="list-style-type: none"> <li>RC-Network oscillation or external clock*</li> </ul>      | <ol style="list-style-type: none"> <li>Hysteresis inverter</li> <li>Without feedback resistor</li> </ol> <p>* When only external clock drive is used, we recommend RC-network oscillation.</p>                                                                                                                                                                                                                                               |
| RESET                                                                                                | <ul style="list-style-type: none"> <li>Input/Output pin</li> </ul>                              | <ul style="list-style-type: none"> <li>Output pull-up resistor (P-ch. Tr.):<br/>Approx. 300k<math>\Omega</math> typ. (at V<sub>CC</sub>=5V)</li> </ul>                                                                                                                                                                                                                                                                                       |
| MB88511/513:<br>R15-R11, R7-R0,<br>E10-E0 (Except 12V<br>interface open-drain)<br>MB88512:<br>R11-R0 | <ul style="list-style-type: none"> <li>Input/Output pin</li> </ul>                              | <ul style="list-style-type: none"> <li>Output port options for P-, and R-Ports</li> </ul> <ol style="list-style-type: none"> <li>Standard/high-current pull-up: Pull-up resistor (P-ch. Tr.). Approx. 10k<math>\Omega</math> typ. (at V<sub>CC</sub>=5V)</li> <li>*2: Standard/high-current open-drain: Without P-ch. pull-up resistor</li> </ol> <p>** High-current pull-up/open-drain outputs are only applied to MB88511 and MB88513.</p> |
| MB88511/513:<br>E10-E0 (Except 12V<br>interface open-drain)                                          | <ul style="list-style-type: none"> <li>Output only pin</li> </ul>                               | <ul style="list-style-type: none"> <li>12V interface open-drain</li> </ul>                                                                                                                                                                                                                                                                                                                                                                   |

**Table 2 Input/Output Circuits (Continued)**

| Pin                                           | Circuit                                                            | Remarks                                                                                                                                                                                                                                                                                                                                                                                                                              |
|-----------------------------------------------|--------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| MB88511/513:<br>E14/SO                        | <ul style="list-style-type: none"> <li>Input/Output pin</li> </ul> | <ul style="list-style-type: none"> <li>Output port options: <ul style="list-style-type: none"> <li>1: Standard/high-current pull-up: Pull-up resistor (P-ch. Tr.). Approx. <math>10k\Omega</math> typ. (at <math>V_{cc}=5V</math>)</li> <li>*2: Standard/high-current open-drain: Without P-ch. pull-up resistor</li> </ul> </li> <li>** High-current pull-up/open-drain outputs are only applied to MB88511 and MB88513.</li> </ul> |
| MB88511/513:<br>E13/SI                        | <ul style="list-style-type: none"> <li>Input/Output pin</li> </ul> |                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| MB88511/513:<br>E15/SO                        | <ul style="list-style-type: none"> <li>Input/Output pin</li> </ul> | <ul style="list-style-type: none"> <li>With pull-up resistor P-ch. Tr. approx. <math>10k\Omega</math>:</li> <li>* This additional circuit makes the load MOS FET turn, at the timing when high level is output on the TO line, so that the TO line can go high immediately.</li> </ul>                                                                                                                                               |
| MB88511/513:<br>E12/IRQ<br>MB88512:<br>R8/IRQ | <ul style="list-style-type: none"> <li>Input/Output pin</li> </ul> | <ul style="list-style-type: none"> <li>Output port options: <ul style="list-style-type: none"> <li>1: Standard/high-current pull-up: Pull-up resistor (P-ch. Tr.). Approx. <math>10k\Omega</math> typ. (at <math>V_{cc}=5V</math>)</li> <li>*2: Standard/high-current open-drain: Without P-ch. pull-up resistor</li> </ul> </li> <li>** High-current pull-up/open-drain outputs are only applied to MB88511 and MB88513.</li> </ul> |

Table 2 Input/Output Circuits (Continued)

| Pin                                         | Circuit                                                                                                                                                | Remarks                                                                                                                                                                                                                                                                                                                                                                                     |
|---------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| MB88511/513:<br>E16/AN0–E19/AN3             | <ul style="list-style-type: none"> <li>Input/Output pin</li> </ul>    | <ul style="list-style-type: none"> <li>Open-drain output</li> </ul>                                                                                                                                                                                                                                                                                                                         |
| MB88512:<br>AN0–AN7                         | <ul style="list-style-type: none"> <li>Input/Output pin</li> </ul>    | <ul style="list-style-type: none"> <li>Open-drain output</li> </ul>                                                                                                                                                                                                                                                                                                                         |
| MB88511/513:<br>E11/TC<br>MB88512:<br>R9/TC | <ul style="list-style-type: none"> <li>Input/Output pin</li> </ul>   | <ul style="list-style-type: none"> <li>Output port options: <ol style="list-style-type: none"> <li>Standard/high-current pull-up: Pull-up resistor (P-ch. Tr.). Approx. 10kΩ typ. (at Vcc=5V)</li> <li>Standard/high-current open-drain: Without P-ch. pull-up resistor</li> </ol> </li> <li>** High-current pull-up/open-drain outputs are only applied to MB88511 and MB88513.</li> </ul> |
| MB88511/513:<br>E20/START                   | <ul style="list-style-type: none"> <li>Input/Output pin</li> </ul>  | <p>E20:</p> <ul style="list-style-type: none"> <li>Output port options: <ol style="list-style-type: none"> <li>Standard/high-current pull-up: Pull-up resistor (P-ch. Tr.). Approx. 10kΩ typ. (at Vcc=5V)</li> <li>Standard/high-current open-drain: Without P-ch. pull-up resistor</li> </ol> </li> </ul> <p>START:</p> <p>With N-ch. pull-down resistor approx. 300kΩ</p>                 |
| MB88512:<br>AN0/START                       | <ul style="list-style-type: none"> <li>Input/Output pin</li> </ul>  | <p>AN0:</p> <p>START:</p> <p>With N-ch. pull-down resistor (N-ch. Tr.):<br/>Approx. 300kΩ typ. (at Vcc=5.0V)</p>                                                                                                                                                                                                                                                                            |

## USER MASK OPTIONS

The MB88510 series has the following mask options, which must be specified by the customer on the attached data release form when devices are ordered.

**Table 3 User Mask Options**

| Optional Feature                 | Symbol | Option                                         | Option No. | Note                                                                                   |                                                |
|----------------------------------|--------|------------------------------------------------|------------|----------------------------------------------------------------------------------------|------------------------------------------------|
| Clock Prescaler                  | CLK    | No                                             | 0          | fc=1 MHz to 3 MHz                                                                      |                                                |
|                                  |        | Yes                                            | 1          | fc=2 MHz to 6 MHz                                                                      |                                                |
| Oscillation Type                 | OSC    | Crystal/ceramic oscillation or External clock* | 0          | * When only external clock drive is used, we recommend RC-network oscillation.         |                                                |
|                                  |        | Crystal/ceramic oscillation or External clock  | 1          | We recommended no clock prescaler.                                                     |                                                |
| Output Port Type (R-, E-Ports)   | PORT   | Standard open-drain                            | L          | Except E15.                                                                            | In the MB88511/513, mixed option is available. |
|                                  |        | Standard pull-up                               | M          | Except E19-E16.                                                                        |                                                |
|                                  |        | High-current open-drain                        | K          | Except E15. Only, MB88511/513.                                                         |                                                |
|                                  |        | High-current pull-up                           | T          | Except E19-E15. Only, MB88511/513.                                                     |                                                |
|                                  |        | 12V interface open-drain                       | G          | Only E10-E0. Only, MB88511/513.                                                        |                                                |
| Standby Function                 | STBY   | No                                             | 0          | MB88511/513 : Pin 20(40) is applied to E20.<br>MB88512 : Pin 27 is applied to AN0.     |                                                |
|                                  |        | Yes<br>Software initiation                     | 1          | MB88511/513 : Pin 20(40) is applied to START.<br>MB88512 : Pin 27 is applied to START. |                                                |
| Output Port State During Standby | STATE  | Hold                                           | 0          | Output port state option selected should be the same for all of R-, and E-Ports.       |                                                |
|                                  |        | High-Z                                         | 1          |                                                                                        |                                                |
| Standby Off Reset Function       | SOR    | No                                             | 0          |                                                                                        |                                                |
|                                  |        | Yes                                            | 1          |                                                                                        |                                                |
| Watch-Dog Timer                  | WDR    | No                                             | 0          |                                                                                        |                                                |
|                                  |        | Yes                                            | 1          | Only MB88511/513.                                                                      |                                                |

## NOTES ON OPERATION

### • Latch-up Prevention

Latch-up may occur in CMOS devices when a voltage higher than  $V_{CC}$  or lower than  $V_{SS}$  is applied to input or output pin, or when a voltage exceeding the absolute maximum ratings is applied between  $V_{CC}$  and  $V_{SS}$  pins. If latch-up occurs, the supply current increases greatly, and the device may be thermally destroyed. Therefore, applied voltages should not exceed the maximum ratings.

### • Treatment of Unused Pins

Unused input pins should be externally pulled up or down with resistors because such unused input pins may cause some malfunction if they are left open. (However, the X pin should be open when an external clock oscillator is used.)

### • A/D Converter Supply


Even if the A/D converter function doesn't used,  $AV_{CC}$  and  $AV_{SS}$  A/D converter supply should be connect the supply and ground.

### • Special Function of R12 of MB88511/513 and R11 of MB88512 Pins

The R12 of MB88511/513 and R11 of MB88512 pin has another function as a test terminal, in addition to its normal function R-Port. If the R12 (R11) pin is forced low while the  $\overline{RESET}$  pin is low, the MCU is placed in the test mode. Therefore, the R12 (R11) pin should not be forced low while the  $\overline{RESET}$  pin is low (when all output ports are initialized).

Especially when the open-drain is selected for the output port option, the R12 (R11) pin should be externally pulled up because such open-drain outputs are subject to noise disturbance if left floating.

At least 2 instruction cycles are required to change R12 (R11) from high to low after releasing reset ( $\overline{RESET}$ : Low  $\rightarrow$  High)



### • External Capacitors for Crystal Oscillation

Figure 9 gives an aim of an area where the on-chip oscillator has stable oscillator characteristics and short oscillation stabilization time when an average crystal resonator is used.

The external capacitor should be adjusted to individual crystal resonators when precise oscillation frequency is required. It is recommended to use crystal with a frequency higher than required oscillation frequency, together with the on-chip divided-by-two prescaler, because crystal resonators with lower oscillation frequency generally tends to have longer stabilization time and wider characteristics variation.

### • Supply Voltage

Malfunction may occur even within the recommended operating supply voltage if the supply voltage changes rapidly. Therefore, the supply voltage should be regulated as well as possible. The following conditions are recommended for the power supply:

- (1)  $V_{CC}$  ripple (peak-to-peak value) at commercial frequency (50Hz to 60Hz): Less than 10% of typical  $V_{CC}$  value.
- (2)  $V_{CC}$  transient change rate (such as at switching of power supply): Less than 0.1V/ms.

# INSTRUCTION SET DESCRIPTION

The MB88510 series instructions set includes 79 of MB88511/513, 69 of MB88512 instructions, 78% (83%) of which are single-byte and 20% (15%) two-byte two cycle, and 1% of two byte three cycle. The MB88510 series instruction set is the upward-compatible with the MB88500 series, and is divided into nine functional groups:

- Register-to-register transfer
- Register-to-memory transfer
- Constant transfer
- Arithmetic and logical operations
- Bit manipulation
- Control
- Input/output
- Branch
- Flag manipulation

Table 4 and 5 summarizes the MB88510 series instruction set.

**Table 4 Instruction Set Summary**

|                                          | Mnemonic<br>+Operand | Code<br>(Hex.) | Flag/Status |    |     | Byte/<br>Cycle                    | Operation                                                                                                                                                                              |     |   |   |     |   |   |
|------------------------------------------|----------------------|----------------|-------------|----|-----|-----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|---|---|-----|---|---|
|                                          |                      |                | ZF          | CF | ST  |                                   |                                                                                                                                                                                        |     |   |   |     |   |   |
| Register-<br>to-<br>Register<br>Transfer | TATH                 | 05             | •           | •  | •   | 1/1                               | TH ← (AC)                                                                                                                                                                              |     |   |   |     |   |   |
|                                          | TATL                 | 06             | •           | •  | •   | 1/1                               | TL ← (AC)                                                                                                                                                                              |     |   |   |     |   |   |
|                                          | TAS *4               | 07             | •           | •  | •   | 1/1                               | SB ← (AC)                                                                                                                                                                              |     |   |   |     |   |   |
|                                          | TAY                  | 04             | •           | •  | •   | 1/1                               | Y ← (AC)                                                                                                                                                                               |     |   |   |     |   |   |
|                                          | TSA *4               | 17             | •<br>↕      | •  | •   | 1/1                               | 4-bit mode: AC ← (SBL)<br>8-bit mode: AC ← (SBL), X ← (SBH)                                                                                                                            |     |   |   |     |   |   |
|                                          | TTHA                 | 15             | ↕           | •  | •   | 1/1                               | AC ← (TH)                                                                                                                                                                              |     |   |   |     |   |   |
|                                          | TTLA                 | 16             | ↕           | •  | •   | 1/1                               | AC ← (TL)                                                                                                                                                                              |     |   |   |     |   |   |
|                                          | TYA                  | 14             | ↕           | •  | •   | 1/1                               | AC ← (Y)                                                                                                                                                                               |     |   |   |     |   |   |
| XX                                       | 1B                   | ↕*1            | •           | •  | 1/1 | (AC)↔(X)                          |                                                                                                                                                                                        |     |   |   |     |   |   |
| Register-<br>to-<br>Memory<br>Transfer   | L                    | 0D             | ↕           | •  | •   | 1/1                               | AC ← {M(X,Y)}                                                                                                                                                                          |     |   |   |     |   |   |
|                                          | LS *4                | 2B             | ↕           | •  | •   | 1/1                               | SB ← {M(X,Y)}                                                                                                                                                                          |     |   |   |     |   |   |
|                                          | ST                   | 1D             | •           | •  | •   | 1/1                               | M(X,Y) ← (AC)                                                                                                                                                                          |     |   |   |     |   |   |
|                                          | STDC                 | 1A             | •           | •  | ↓C  | 1/1                               | M(X,Y) ← (AC), Y ← (Y)-1                                                                                                                                                               |     |   |   |     |   |   |
|                                          | STIC                 | 0A             | •           | •  | ↓C  | 1/1                               | M(X,Y) ← (AC), Y ← (Y)+1                                                                                                                                                               |     |   |   |     |   |   |
|                                          | STS *4               | 2A             | ↕           | •  | •   | 1/1                               | M(X,Y) ← (SBL)                                                                                                                                                                         |     |   |   |     |   |   |
|                                          | X                    | 0B             | ↓*1         | •  | •   | 1/1                               | (AC)↔{M(X,Y)}                                                                                                                                                                          |     |   |   |     |   |   |
|                                          | XD D                 | 50-53*         | ↓*1         | •  | •   | 1/1                               | (AC)↔{M(0,D)}; D=0 to 3 (X=0, Y=D)                                                                                                                                                     |     |   |   |     |   |   |
| XYD D                                    | 54-57*               | ↓*2            | •           | •  | 1/1 | (Y)↔{M(0,D)}; D=4 to 7 (X=0, Y=D) |                                                                                                                                                                                        |     |   |   |     |   |   |
| Constant<br>Transfer                     | CLA                  | 90             | ↓           | •  | •   | 1/1                               | AC ← 0 (Included in LI instruction)                                                                                                                                                    |     |   |   |     |   |   |
|                                          | LI imm               | 90-9F*         | ↕           | •  | •   | 1/1                               | AC ← imm; imm=0 to 15                                                                                                                                                                  |     |   |   |     |   |   |
|                                          | LXI imm              | 58-5F*         | ↕           | •  | •   | 1/1                               | X3 ← 0, X2 to X0 ← imm; imm=0 to 7                                                                                                                                                     |     |   |   |     |   |   |
|                                          | LXID                 | 3D90-3D9F*     | ↕           | •  | •   | 2/2                               | X ← imm; imm=0 to 15                                                                                                                                                                   |     |   |   |     |   |   |
|                                          | LRXA imm             | 3D20-3D3F*     | •           | •  | •   | 2/3                               | X ← { ROM ( <table><tr><td>imm</td><td>X</td><td>Y</td></tr></table> ) } d, d=7-4<br>AC ← { ROM ( <table><tr><td>imm</td><td>X</td><td>Y</td></tr></table> ) } d, d=3-0<br>imm=0 to 31 | imm | X | Y | imm | X | Y |
|                                          | imm                  | X              | Y           |    |     |                                   |                                                                                                                                                                                        |     |   |   |     |   |   |
|                                          | imm                  | X              | Y           |    |     |                                   |                                                                                                                                                                                        |     |   |   |     |   |   |
| LYI imm                                  | 80-8F*               | ↕              | •           | •  | 1/1 | Y ← imm; imm=0 to 15              |                                                                                                                                                                                        |     |   |   |     |   |   |
|                                          |                      |                |             |    |     |                                   |                                                                                                                                                                                        |     |   |   |     |   |   |

Table 4 Instruction Set Summary (Continued)


|                                       | Mnemonic<br>+Operand | Code<br>(Hex.) | Flag/Status |    |    | Byte/<br>Cycle | Operation                                                                                                  |
|---------------------------------------|----------------------|----------------|-------------|----|----|----------------|------------------------------------------------------------------------------------------------------------|
|                                       |                      |                | ZF          | CF | ST |                |                                                                                                            |
| Arithmetic &<br>Logical<br>Operations | ADC                  | 0E             | ↕           | ↕  | ↓C | 1/1            | $AC \leftarrow (AC) + \{M(X,Y)\} + (CF)$                                                                   |
|                                       | AI imm               | 3D80–3D8F      | ↕           | ↕  | ↓C | 2/2            | $AC \leftarrow (AC) + \text{imm}; \text{imm}=0 \text{ to } 15$                                             |
|                                       | AND                  | 0F             | ↕           | •  | ↓Z | 1/1            | $AC \leftarrow (AC) \cap \{M(X,Y)\}$                                                                       |
|                                       | C                    | 2E             | ↕           | ↕  | ↓Z | 1/1            | $\{M(X,Y)\} - (AC)$                                                                                        |
|                                       | CI imm               | B0–BF*         | ↕           | ↕  | ↓Z | 1/1            | $\text{imm} - (AC); \text{imm}=0 \text{ to } 15$                                                           |
|                                       | CYL imm              | A0–AF*         | •           | •  | ↓Z | 1/1            | $\text{imm} - (Y); \text{imm}=0 \text{ to } 15$                                                            |
|                                       | DAA                  | 10             | •           | ↕  | ↓C | 1/1            | $AC \leftarrow (AC) + 6 \text{ if } (AC) > 9 \text{ or } (CF)=1$                                           |
|                                       | DAS                  | 11             | •           | ↕  | ↓C | 1/1            | $AC \leftarrow (AC) + 10 \text{ if } (AC) > 9 \text{ or } (CF)=1$                                          |
|                                       | DCA                  | 3D8F           | ↕           | ↕  | ↓C | 2/2            | $AC \leftarrow (AC) + 15 \text{ (Included in AI instruction)}$                                             |
|                                       | DCM                  | 19             | ↕           | •  | ↓C | 1/1            | $M(X,Y) \leftarrow \{M(X,Y)\} - 1$                                                                         |
|                                       | DCY                  | 18             | •           | •  | ↓C | 1/1            | $Y \leftarrow (Y) - 1$                                                                                     |
|                                       | EOR                  | 2F             | ↕           | •  | ↓Z | 1/1            | $AC \leftarrow \{M(X,Y)\} \oplus (AC)$                                                                     |
|                                       | ICA                  | 3D81           | ↕           | ↕  | ↓C | 2/2            | $AC \leftarrow (AC) + 1 \text{ (Included in AI instruction)}$                                              |
|                                       | ICM                  | 09             | ↕           | •  | ↓C | 1/1            | $M(X,Y) \leftarrow \{M(X,Y)\} + 1$                                                                         |
|                                       | ICX                  | 3DAC           | •           | •  | ↓C | 2/2            | $X \leftarrow (X) + 1$                                                                                     |
|                                       | ICY                  | 08             | ↕           | •  | ↓C | 1/1            | $Y \leftarrow (Y) + 1$                                                                                     |
| Bit<br>Manipulation                   | NEG                  | 2D             | •           | •  | ↓Z | 1/1            | $AC \leftarrow (AC) + 1$                                                                                   |
|                                       | OR                   | 1F             | ↕           | •  | ↓Z | 1/1            | $AC \leftarrow \{M(X,Y)\} \cup (AC)$                                                                       |
|                                       | ROL                  | 0C             | ↕           | ↕  | ↓C | 1/1            |                         |
|                                       | ROR                  | 1C             | ↕           | ↕  | ↓C | 1/1            |                        |
|                                       | SBC                  | 1E             | ↕           | ↕  | ↓C | 1/1            | $AC \leftarrow \{M(X,Y)\} - (AC) - (CF)$                                                                   |
|                                       | RBIT bp              | 34–37*         | •           | •  | •  | 1/1            | $\{M(X,Y)\} \text{bp} \leftarrow 0; \text{bp}=0 \text{ to } 3$                                             |
|                                       | SBIT bp              | 30–33*         | •           | •  | •  | 1/1            | $\{M(X,Y)\} \text{bp} \leftarrow 1; \text{bp}=0 \text{ to } 3$                                             |
|                                       | RBA bp               | 3DA4–3DA7*     | •           | •  | •  | 2/2            | $(AC) \text{bp} \leftarrow 0; \text{bp}=0 \text{ to } 3$                                                   |
|                                       | SBA bp               | 3DA0–3DA3*     | •           | •  | •  | 2/2            | $(AC) \text{bp} \leftarrow 1; \text{bp}=0 \text{ to } 3$                                                   |
|                                       | TBA bp               | 4C–4F*         | •           | •  | ↓Z | 1/1            | $(AC) \text{bp} - 1; \text{bp}=0 \text{ to } 3$                                                            |
| Control                               | TBIT bp              | 38–3B*         | •           | •  | ↓Z | 1/1            | $\{M(X,Y)\} \text{bp} - 1; \text{bp}=0 \text{ to } 3$                                                      |
|                                       | EN imm               | 3E00–3EFF*     | •           | •  | •  | 2/2            | Enable the internal resources by the operand byte (2nd byte); *3                                           |
|                                       | DIS imm              | 3F00–3FFF*     | •           | •  | •  | 2/2            | Disable the internal resources by the operand byte (2nd byte); *3                                          |
| Input/<br>Output                      | RST                  | 3DAD           | •           | •  | •  | 2/2            | System initialization                                                                                      |
|                                       | IN                   | 13             | ↕           | •  | •  | 1/1            | $AC \leftarrow (R)Y; Y=0 \text{ to } 3 \text{ (Port \#)}$<br>$AC \leftarrow (REG)Y; Y=9 \text{ to } 15$    |
|                                       | INK *4               | 12             | ↕           | •  | •  | 1/1            | $AC \leftarrow (R15-R12)$                                                                                  |
|                                       | INX *4               | 3DAA           | •           | •  | •  | 2/2            | $AC \leftarrow (E)Y; Y=0 \text{ to } 5 \text{ (Port \#)} *4$                                               |
|                                       | OUT                  | 03             | •           | •  | •  | 1/1            | $(R)Y \leftarrow (AC); Y=0 \text{ to } 3 \text{ (Port \#)}$<br>$(REG)Y \leftarrow (R); Y=9 \text{ to } 15$ |
|                                       | OUTP *4              | 02             | •           | •  | •  | 1/1            | $E3-E0 \leftarrow (AC)$                                                                                    |
|                                       | OUTX *4              | 3DAB           | •           | •  | •  | 2/2            | $(E)Y \leftarrow (AC); Y=0 \text{ to } 5 \text{ (Port \#)} *4$                                             |
|                                       | ANDX *4              | 3DA8           | •           | •  | •  | 2/2            | $(E)Y \leftarrow (AC) \cap E(Y); Y=0 \text{ to } 5 \text{ (Port \#)} *4$                                   |
|                                       | ORX *4               | 3DA9           | •           | •  | •  | 2/2            | $(E)Y \leftarrow (AC) \cup E(Y); Y=0 \text{ to } 5 \text{ (Port \#)} *4$                                   |

Table 4 Instruction Set Summary (Continued)

|                      | Mnemonic<br>+Operand | Code<br>(Hex.) | Flag/Status |    |     | Byte/<br>Cycle | Operation                                                                        |
|----------------------|----------------------|----------------|-------------|----|-----|----------------|----------------------------------------------------------------------------------|
|                      |                      |                | ZF          | CF | ST  |                |                                                                                  |
| Input/<br>Output     | RSTD d               | 44–47*         | •           | •  | •   | 1/1            | (R)d ← 0; d=0 to 3 (Bit # of Port #)                                             |
|                      | RSTR                 | 22             | •           | •  | •   | 1/1            | MB88511/513:(R)Y ← 0; Y=0–7, 11–15 (Bit #)                                       |
|                      | SETD d               | 40–43*         | •           | •  | •   | 1/1            | MB88512:(R)Y ← 0; Y=0 to 11 (Bit #)                                              |
|                      | SETR                 | 20             | •           | •  | •   | 1/1            | (R)d ← 1; d=0 to 3 (Bit # of Port #)                                             |
|                      |                      |                |             |    |     |                | MB88511/513:(R)Y ← 1; Y=0–7, 11–15 (Bit #)                                       |
|                      |                      |                |             |    |     |                | MB88512:(R)Y ← 1; Y=0 to 11 (Bit #)                                              |
| Branch               | TSTD d               | 48–4B*         | •           | •  | ↓C  | 1/1            | MB88511/513:(R)d–1; d=11 (Bit #)                                                 |
|                      | TSTR                 | 24             | •           | •  | ↓C  | 1/1            | MB88512:(R)d–1; d=8 to 11 (Bit #)                                                |
|                      |                      |                |             |    |     |                | MB88511/513:(R)Y–1; d=0–7, 8–15 (Bit #)                                          |
|                      |                      |                |             |    |     |                | MB88512:(R)Y–1; d=0 to 11 (Bit #)                                                |
|                      | CALL addr            | 6000–6FFF*     | •           | •  | •   | 2/2            | If ST=1, Subroutine call for addr; addr=0 to 4095.<br>ST=0, Not subroutine call. |
|                      | JMP addr             | C0–FF*         | •           | •  | •   | 1/1            | If ST=1, Branch to addr; addr=0 to 63<br>ST=0, No branch.                        |
| Flag<br>Manipulation | JPL addr             | 7000–7FFF*     | •           | •  | •   | 2/2            | If ST=1, Branch to addr; addr=0 to 4095.<br>ST=0, No branch.                     |
|                      | JPHY addr            | 3D00–3D1F*     | •           | •  | •   | 2/2            | Branch always to addr on page #n;                                                |
|                      | NOP                  | 00             | •           | •  | •   | 1/1            | No operation                                                                     |
|                      | RTI                  | 3C             | •           | •  | •   | 1/1            | Return from interrupt routine                                                    |
|                      | RTS                  | 2C             | •           | •  | •   | 1/1            | Return from subroutine                                                           |
|                      | RSTC                 | 23             | •           | ↓  | •   | 1/1            | CF ← 0                                                                           |
| Flag<br>Manipulation | SETC                 | 21             | •           | ↑  | •   | 1/1            | CF ← 1                                                                           |
|                      | TSTC                 | 28             | •           | •  | ↓CF | 1/1            | (CF)–1                                                                           |
|                      | TSTI                 | 25             | •           | •  | ↓IF | 1/1            | (IF)–1, (If $\overline{IRQ}=L$ , IF=1)                                           |
|                      | TSTS                 | 27             | •           | •  | ↓SF | 1/1            | (SF)–1, SF ← 0                                                                   |
|                      | TSTV                 | 26             | •           | •  | ↓VF | 1/1            | (VF)–1, VF ← 0                                                                   |
|                      | TSTZ                 | 29             | •           | •  | ↓ZF | 1/1            | (ZF)–1                                                                           |

## Notes:

- \* : Code is variable depending on the operand.
- \*1: ZF is set or reset depending on contents of AC after instruction execution.
- \*2: ZF is set or reset depending on contents of Y after instruction execution.
- \*3: Each bit of the operand (the second byte) functions as follows



\*4: Available only for MB88511 and MB88513.

## Symbols and Abbreviations

| Symbols                       | Meaning                                                                                                                          |
|-------------------------------|----------------------------------------------------------------------------------------------------------------------------------|
| $\leftarrow$                  | Is transferred to                                                                                                                |
| $\leftrightarrow$             | Is exchanged with                                                                                                                |
| +                             | Arithmetic plus                                                                                                                  |
| -                             | Arithmetic minus                                                                                                                 |
| $\oplus$                      | Logical exclusive or                                                                                                             |
| $\cup$                        | Logical OR                                                                                                                       |
| $\cap$                        | Logical AND                                                                                                                      |
| $\overline{\quad}$ (overline) | Negation                                                                                                                         |
| ( )                           | Contents of parenthesis                                                                                                          |
| $\uparrow$                    | Set to "1" always                                                                                                                |
| $\downarrow$                  | Set to "0" always                                                                                                                |
| $\updownarrow$                | Affected (set or reset) by operation results                                                                                     |
| $\downarrow C$                | Set to "0" due to carry (not carry flag)                                                                                         |
| $\downarrow CF$               | Set to "0" due to carry flag                                                                                                     |
| $\downarrow IF$               | Set to "0" due to interrupt flag                                                                                                 |
| $\downarrow SF$               | Set to "0" due to serial buffer full/empty flag                                                                                  |
| $\downarrow VF$               | Set to "0" due to timer/counter overflow flag                                                                                    |
| $\downarrow Z$                | Set to "0" due to zero (not zero flag)                                                                                           |
| $\downarrow ZF$               | Set to "0" due to zero flag                                                                                                      |
| •                             | Not affected                                                                                                                     |
| Abbreviations                 | Meaning                                                                                                                          |
| AC                            | Accumulator                                                                                                                      |
| addr                          | Jump address                                                                                                                     |
| bp                            | Bit pointer (that is part of the instruction code)                                                                               |
| C                             | Carry                                                                                                                            |
| CF                            | Carry flag                                                                                                                       |
| d                             | Direct line number (that is part of the instruction code)                                                                        |
| E                             | E-Port (#0: E3-E0, #1: E7-E4, #2: E11-E8, E3: E15-E12, E4: E19-E16, and #5: E20)<br>E-Port #n specified by Y-register (Y=0 to 5) |
| IF                            | Interrupt flag                                                                                                                   |
| imm                           | Immediate data                                                                                                                   |
| $\overline{IRQ}$              | Interrupt request                                                                                                                |
| LSB                           | Least significant bit                                                                                                            |
| M(X,Y)                        | Data memory (RAM) location indirectly addressed by data pointer (X- and Y-registers)                                             |
| M(0,D)                        | Data memory (RAM) location directly addressed by "D" bits in the instruction code, in page #0 (X=0)                              |
| MSB                           | Most significant bit                                                                                                             |
| R                             | R-Port (#0: R3-R0, #1: R7-R4, #2: R11-R8, #3: R15-R12)                                                                           |
| (R)Y; Y=n                     | 1) R-Port #n specified by Y-register (Y=0 to 3)<br>2) R-Port bit n specified by Y-register (Y=0 to 15)                           |
| (R)d; d=n                     | R-Port bit n specified by "d" bits in the instruction code                                                                       |
| SB                            | Serial buffer register                                                                                                           |
| SF                            | Serial buffer full/empty flag                                                                                                    |
| ST                            | Status flag                                                                                                                      |
| TH                            | Timer/counter high byte                                                                                                          |
| TL                            | Timer/counter low byte                                                                                                           |
| VF                            | Timer/counter overflow flag                                                                                                      |
| X                             | X-register (that indicates page # in data memory RAM)                                                                            |
| Xn                            | The n-th bit of X-register                                                                                                       |
| Y                             | Y-register                                                                                                                       |
| Z                             | Zero                                                                                                                             |
| ZF                            | Zero flag                                                                                                                        |

**Table 5 Instruction Code Summary**

| L<br>H | 0            | 1         | 2          | 3    | 4          | 5    | 6    | 7         | 8          | 9    | A         | B        | C         | D   | E         | F          |
|--------|--------------|-----------|------------|------|------------|------|------|-----------|------------|------|-----------|----------|-----------|-----|-----------|------------|
| 0      | NOP          | Unused    | *1<br>OUTP | OUT  | TAY        | TATH | TATL | *1<br>TAS | ICY        | ICM  | STIC      | X        | ROL       | L   | ADC       | AND        |
| 1      | DAA          | DAS       | *1<br>INK  | IN   | TYA        | TTHA | TTLA | *1<br>TSA | DCY        | DCM  | STDC      | XX       | ROR       | ST  | SBC       | OR         |
| 2      | SETR         | SETC      | RSTR       | RSTC | TSTR       | TSTI | TSTV | TSTS      | TSTC       | TSTZ | *1<br>STS | *1<br>LS | RTS       | NEG | C         | EOR        |
| 3      | SBIT<br>bp   |           |            |      | RBIT<br>bp |      |      |           | TBIT<br>bp |      |           |          | RTI       | EXT | EN<br>imm | DIS<br>imm |
| 4      | SETD<br>d    |           |            |      | RSTD<br>d  |      |      |           | TSTD<br>d  |      |           |          | TBA<br>bp |     |           |            |
| 5      | XD<br>d      |           |            |      | XYD<br>d   |      |      |           | LXI<br>imm |      |           |          |           |     |           |            |
| 6      | CALL<br>addr |           |            |      |            |      |      |           |            |      |           |          |           |     |           |            |
| 7      | JPL<br>addr  |           |            |      |            |      |      |           |            |      |           |          |           |     |           |            |
| 8      | LYI<br>imm   |           |            |      |            |      |      |           |            |      |           |          |           |     |           |            |
| 9      | (CLA)        | LI<br>imm |            |      |            |      |      |           |            |      |           |          |           |     |           |            |
| A      | CYI<br>imm   |           |            |      |            |      |      |           |            |      |           |          |           |     |           |            |
| B      | CI<br>imm    |           |            |      |            |      |      |           |            |      |           |          |           |     |           |            |
| C      | JMP<br>addr  |           |            |      |            |      |      |           |            |      |           |          |           |     |           |            |
| D      |              |           |            |      |            |      |      |           |            |      |           |          |           |     |           |            |
| E      |              |           |            |      |            |      |      |           |            |      |           |          |           |     |           |            |
| F      |              |           |            |      |            |      |      |           |            |      |           |          |           |     |           |            |

Notes:



: 1-byte/1-cycle instruction



: 2-byte/2-cycle instruction



: See the next page.

Table 5 Instruction Code Summary Extended Instruction (Continued)

| <div>3DL<br/>3DH</div> | 0                | 1         | 2 | 3 | 4         | 5 | 6 | 7 | 8                      | 9                     | A                     | B                      | C   | D   | E      | F                |
|------------------------|------------------|-----------|---|---|-----------|---|---|---|------------------------|-----------------------|-----------------------|------------------------|-----|-----|--------|------------------|
| 0                      | JPXY<br>addr     |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| 1                      |                  |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| 2                      | LRXA<br>imm      |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| 3                      |                  |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| 4                      | Unused           |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| 5                      |                  |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| 6                      |                  |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| 7                      |                  |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| 8                      | <div>(ICA)</div> | AI<br>imm |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        | <div>(DCA)</div> |
| 9                      | LXID<br>imm      |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| A                      | SBA<br>bp        |           |   |   | RBA<br>bp |   |   |   | <div>*1<br/>ANDX</div> | <div>*1<br/>ORX</div> | <div>*1<br/>INX</div> | <div>*1<br/>OUTX</div> | ICX | RST | Unused |                  |
| B                      | Unused           |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| C                      |                  |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| D                      |                  |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| E                      |                  |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |
| F                      |                  |           |   |   |           |   |   |   |                        |                       |                       |                        |     |     |        |                  |

Notes:  : 2 byte/2 cycle instruction or 2 byte/3 cycle instruction

\*1 : Available only for MB88511 and MB88513.

# DIFFERENCES BETWEEN MB88500 SERIES AND MB88510 SERIES

Table 6 Difference Between MB88501 and MB88510 Series

| Device<br>Item                                                   | MB88501                                                                                                                                                                                                              | MB88510 Series                                                                                                                                                                                                                                                                                                                                                                                           |
|------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| ROM Size                                                         | <ul style="list-style-type: none"> <li>• 4K x 8 bits</li> </ul>                                                                                                                                                      | <ul style="list-style-type: none"> <li>• MB88511 :4K x 8 bits</li> <li>• MB88512/513 :2K x 8 bits</li> </ul>                                                                                                                                                                                                                                                                                             |
| RAM Size                                                         | <ul style="list-style-type: none"> <li>• 192 x 4 bits</li> </ul>                                                                                                                                                     | <ul style="list-style-type: none"> <li>• MB88511 :256 x 4 bits</li> <li>• MB88512 :128 x 4 bits</li> <li>• MB88513 :192 x 4 bits</li> </ul>                                                                                                                                                                                                                                                              |
| Minimum Instruction Execution Time                               | <ul style="list-style-type: none"> <li>• 2.86<math>\mu</math>s</li> </ul>                                                                                                                                            | <ul style="list-style-type: none"> <li>• 2.0 <math>\mu</math>s</li> </ul>                                                                                                                                                                                                                                                                                                                                |
| I/O Port:<br>-K-Port<br>-P-Port<br>-O-Port<br>-R-Port<br>-E-Port | <ul style="list-style-type: none"> <li>• 36               <ul style="list-style-type: none"> <li>- 4 bits x 1</li> <li>- 4 bits x 1</li> <li>- 8 bits x 1</li> <li>- 4 bits x 4</li> <li>- No</li> </ul> </li> </ul> | <ul style="list-style-type: none"> <li>• MB88511/513:33               <ul style="list-style-type: none"> <li>- No</li> <li>- No</li> <li>- No</li> <li>- 4 bits x 3 and 1 bit x 1</li> <li>- 4 bits x 5 and 1 bit x 1</li> </ul> </li> <li>• MB88512:12               <ul style="list-style-type: none"> <li>- No</li> <li>- No</li> <li>- No</li> <li>- 4 bits x 3</li> <li>- No</li> </ul> </li> </ul> |
| Output PLA                                                       | <ul style="list-style-type: none"> <li>• Yes</li> </ul>                                                                                                                                                              | <ul style="list-style-type: none"> <li>• No</li> </ul>                                                                                                                                                                                                                                                                                                                                                   |
| Serial Buffer                                                    | <ul style="list-style-type: none"> <li>• 4 bits</li> </ul>                                                                                                                                                           | <ul style="list-style-type: none"> <li>• MB88511/513 :4/8 bits software selectable</li> <li>• MB88512 :No</li> </ul>                                                                                                                                                                                                                                                                                     |
| A/D Converter                                                    | <ul style="list-style-type: none"> <li>• No</li> </ul>                                                                                                                                                               | <ul style="list-style-type: none"> <li>• MB88511/513 :8 bits resolution x 4 channel</li> <li>• MB88512 :8 bits resolution x 8 channel</li> </ul>                                                                                                                                                                                                                                                         |
| Low-Voltage Reset Function                                       | <ul style="list-style-type: none"> <li>• Mask option</li> </ul>                                                                                                                                                      | <ul style="list-style-type: none"> <li>• No</li> </ul>                                                                                                                                                                                                                                                                                                                                                   |
| Package                                                          | <ul style="list-style-type: none"> <li>• 42 pin plastic standard DIP</li> <li>• 42 pin plastic shrink DIP</li> <li>• 48 pin plastic flat package</li> </ul>                                                          | <ul style="list-style-type: none"> <li>• 42 pin plastic standard DIP (MB88511/513)</li> <li>• 42 pin plastic shrink DIP (MB88511/513)</li> <li>• 48 pin plastic flat package (MB88511/513)</li> <li>• 28 pin plastic standard DIP (MB88512)</li> </ul>                                                                                                                                                   |
| Instruction Number                                               | <ul style="list-style-type: none"> <li>• 75</li> </ul>                                                                                                                                                               | <ul style="list-style-type: none"> <li>• MB88511/513 :79</li> <li>• MB88512 :69</li> </ul>                                                                                                                                                                                                                                                                                                               |
| Members                                                          | <ul style="list-style-type: none"> <li>• MB88501-P/-P-SH/-PF</li> </ul> <p>A- and L-versions are available for each part above.</p>                                                                                  | <ul style="list-style-type: none"> <li>• MB88511-P/-PSH/-PF</li> <li>• MB88512-P</li> <li>• MB88513-P/-PSH/-PF</li> </ul>                                                                                                                                                                                                                                                                                |

# PRODUCT LINE-UP AND DEVELOPMENT TOOLS

The MB88510 series consists of the MB88511, MB88512, and MB88513. The MB88PG511 are available as piggyback EPROM evaluation devices of the MB88511/513 and MB88PG512 is MB88512. Refer to Table 7.

**Table 7 MB88510 Series Product Line-up & Development Tools**

|                                                               | MB88511-P/-PSH/-PF<br>(MB88513-P/-PSH/-PF)                                                                                                                                                                             | MB88PG511-C-<br>101/-102/-201/-202                                                                                                                             | MB88512-P                                                                                                              | MB88PG512-C-<br>101/-102/-103                                                                                                                     |
|---------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------|
| ROM Size                                                      | 4K x 8 bits (2K x 8 bits)<br>on-chip mask ROM                                                                                                                                                                          | 8K x 8 bits<br>External EPROM                                                                                                                                  | 2K x 8 bits<br>on-chip mask ROM                                                                                        | 4K x 8 bits<br>External EPROM                                                                                                                     |
| RAM Size<br>(Directly addressed<br>locations)                 | 256 x 4 bits (192 x 8 bits)<br>(0-7)                                                                                                                                                                                   | 256 x 4 bits<br>(0-7)                                                                                                                                          | 128 x 4 bits<br>(0-7)                                                                                                  | 128 x 4 bits<br>(0-7)                                                                                                                             |
| I/O Port:                                                     | 34                                                                                                                                                                                                                     | 34                                                                                                                                                             | 12                                                                                                                     | 12                                                                                                                                                |
| -Input only port                                              | 0                                                                                                                                                                                                                      | 0                                                                                                                                                              | 0                                                                                                                      | 0                                                                                                                                                 |
| -Output only port                                             | 0                                                                                                                                                                                                                      | 0                                                                                                                                                              | 0                                                                                                                      | 0                                                                                                                                                 |
| -I/O port                                                     | 34                                                                                                                                                                                                                     | 34                                                                                                                                                             | 12                                                                                                                     | 12                                                                                                                                                |
| -Control port                                                 | 5 (Including serial I/O)                                                                                                                                                                                               |                                                                                                                                                                | 2 (Except serial I/O)                                                                                                  |                                                                                                                                                   |
| Output Port Type                                              | <ul style="list-style-type: none"><li>• Standard pull-up</li><li>• Standard open-drain</li><li>• High-current open-drain</li><li>• High-current pull-up</li><li>• 12V interface open-drain<br/>(Mask option)</li></ul> | <ul style="list-style-type: none"><li>• High-current open-drain<br/>(MB88PG511-C-101/-201)</li><li>• High-current pull-up<br/>(MB88PG511-C-102/-202)</li></ul> | <ul style="list-style-type: none"><li>• Standard pull-up</li><li>• Standard open-drain</li></ul>                       | <ul style="list-style-type: none"><li>• Standard pull-up<br/>(MB88PG512-C-102/-103)</li><li>• Standard open-drain<br/>(MB88PG512-C-101)</li></ul> |
| A/D Converter:<br>-Resolution<br>-Channel                     | 8 bits<br>4 channel                                                                                                                                                                                                    |                                                                                                                                                                | 8 bits<br>8 channel                                                                                                    |                                                                                                                                                   |
| Stack Depth<br>(Nesting level)                                | 8 levels                                                                                                                                                                                                               |                                                                                                                                                                |                                                                                                                        |                                                                                                                                                   |
| Timer/Counter:<br>-Buffer size<br>-Clock source               | Yes<br>8 bits<br>Internal/External                                                                                                                                                                                     |                                                                                                                                                                |                                                                                                                        |                                                                                                                                                   |
| Serial I/O:<br>-Buffer size<br>-Clock source<br>-Output latch | Yes<br>4/8 bits<br>Internal/External<br>Yes                                                                                                                                                                            |                                                                                                                                                                | No<br>-<br>-<br>-                                                                                                      |                                                                                                                                                   |
| Clock Generator:<br>-Oscillator type:                         | Yes <ul style="list-style-type: none"><li>• Crystal/External</li><li>• RC-network/External<br/>(Mask option)</li></ul>                                                                                                 | Yes <ul style="list-style-type: none"><li>• Crystal/External<br/>(Fixed)</li></ul>                                                                             | Yes <ul style="list-style-type: none"><li>• Crystal/External</li><li>• RC-network/External<br/>(Mask option)</li></ul> | Yes <ul style="list-style-type: none"><li>• Crystal/External<br/>(Fixed)</li></ul>                                                                |
| -Clock Frequency<br>(With prescaler)                          | 1 MHz - 3 MHz<br>(2 MHz - 6 MHz)                                                                                                                                                                                       | -<br>(2 MHz - 6 MHz)                                                                                                                                           | 1 MHz - 3 MHz<br>(2 MHz - 6 MHz)                                                                                       | -<br>(2 MHz - 6 MHz)                                                                                                                              |
| Clock Prescaler<br>(Divided by two)                           | Yes/No<br>(Mask option)                                                                                                                                                                                                | Yes<br>(Fixed)                                                                                                                                                 | Yes/No<br>(Mask option)                                                                                                | Yes<br>(Fixed)                                                                                                                                    |
| Interrupt Function:<br>-Nesting level<br>-Interrupt sources   | Yes<br>Single level<br>4 sources                                                                                                                                                                                       |                                                                                                                                                                |                                                                                                                        |                                                                                                                                                   |

# MB88510 SERIES

**Table 7 MB88510 Series Product Line-up & Development Tools (Continued)**

|                                  | <b>MB88511-P/-PSH/-PF<br/>(MB88513-P/-PSH/-PF)</b>                                                                                                                                                                        | <b>MB88PG511-C-<br/>101/-102/-201/-202</b>                                                                                                | <b>MB88512-P</b>                                            | <b>MB88PG512-C-<br/>101/-102/-103</b>                                                                                                                              |
|----------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Standby Function:                | Yes/No (Mask option)                                                                                                                                                                                                      | <ul style="list-style-type: none"> <li>• Yes(MB88PG511-201/-202)</li> <li>• No(MB88PG511-101/-102)</li> </ul>                             | Yes/No (Mask option)                                        | <ul style="list-style-type: none"> <li>• Yes(MB88PG512-101/-102)</li> <li>• No(MB88PG512-103)</li> </ul>                                                           |
| -Initiation method               | Software                                                                                                                                                                                                                  | Software                                                                                                                                  | Software                                                    | Software                                                                                                                                                           |
| -Oscillator state during standby | Idle/Stop<br>(Software selectable)                                                                                                                                                                                        | Idle/Stop<br>(Software selectable)                                                                                                        | Idle/Stop<br>(Software selectable)                          | Idle/Stop<br>(Software selectable)                                                                                                                                 |
| -Output state during standby     | Hold/High-Z (Mask option)                                                                                                                                                                                                 | <ul style="list-style-type: none"> <li>• Hold(MB88G511-202)</li> <li>• High-Z(MB88PG511-201)</li> <li>• No(MB88PG511-201/-202)</li> </ul> | Hold/High-Z (Mask option)                                   | <ul style="list-style-type: none"> <li>• Hold(MB88G512-101)</li> <li>• High-Z(MB88PG512-102)</li> <li>• Yes(MB88PG512-101)</li> <li>• No(MB88PG512-102)</li> </ul> |
| -Standby off reset function      | Yes/No (Mask option)                                                                                                                                                                                                      |                                                                                                                                           | Yes/No (Mask option)                                        |                                                                                                                                                                    |
| Watch Dog Timer Function         | Yes/No<br>(Mask option)                                                                                                                                                                                                   | No<br>(Fixed)                                                                                                                             | No<br>(Fixed)                                               | No<br>(Fixed)                                                                                                                                                      |
| Number of Instructions           | 79                                                                                                                                                                                                                        | 81                                                                                                                                        | 69                                                          | 71                                                                                                                                                                 |
| Instruction Length/Cycle         | 1/1, 2/2, or 2/3                                                                                                                                                                                                          |                                                                                                                                           |                                                             |                                                                                                                                                                    |
| Min. Instruction Execution Time  | 2.0 $\mu$ s at 6 MHz<br>(With prescaler)                                                                                                                                                                                  |                                                                                                                                           |                                                             |                                                                                                                                                                    |
| Power Supply:                    | +5V                                                                                                                                                                                                                       | +5V                                                                                                                                       | +5V                                                         | +5V                                                                                                                                                                |
| -Active                          | 4.5V to 5.5V                                                                                                                                                                                                              | 4.5V to 5.5V                                                                                                                              | 4.5V to 5.5V                                                | 4.5V to 5.5V                                                                                                                                                       |
| -Standby                         | 3.5V to 6.0V                                                                                                                                                                                                              | -                                                                                                                                         | 3.5V to 6.0V                                                | -                                                                                                                                                                  |
| A/D Converter Power Supply:      | +5V                                                                                                                                                                                                                       | +5V                                                                                                                                       | +5V                                                         | +5V                                                                                                                                                                |
| - Reference voltage              | -                                                                                                                                                                                                                         | -                                                                                                                                         | AVR+/AVR- (Mask option)                                     | AVR+ (Fixed)                                                                                                                                                       |
| Operating Temperature Range      | -40°C to +85°C                                                                                                                                                                                                            |                                                                                                                                           |                                                             |                                                                                                                                                                    |
| Process                          | CMOS                                                                                                                                                                                                                      |                                                                                                                                           |                                                             |                                                                                                                                                                    |
| Package                          | <ul style="list-style-type: none"> <li>• DIP-42P</li> <li>• SH-DIP-42P</li> <li>• QFP-48P</li> </ul>                                                                                                                      | <ul style="list-style-type: none"> <li>• MDIP-42C</li> </ul>                                                                              | <ul style="list-style-type: none"> <li>• DIP-28P</li> </ul> | <ul style="list-style-type: none"> <li>• MDIP-28C</li> </ul>                                                                                                       |
| Development Tools:               |                                                                                                                                                                                                                           |                                                                                                                                           |                                                             |                                                                                                                                                                    |
| -Hardware                        | MB2115-01 : CRT unit (Common)<br>MB2115-02 : Monitor board with keyboard (Common)<br>MB2115-04 or MB2115-100: EPROM writer (Common)<br>MB2115-38 : DUE board for MB88511 and MB88513<br>MB2115-44 : DUE board for MB88512 |                                                                                                                                           |                                                             |                                                                                                                                                                    |
| -Software                        | SM07615-AXXX : PC-DOS cross-assembler<br>SM07615-GXXX : PC-DOS host emulator                                                                                                                                              |                                                                                                                                           |                                                             |                                                                                                                                                                    |

# ELECTRICAL CHARACTERISTICS

## ABSOLUTE MAXIMUM RATINGS †

| Parameter                     | Symbol                               | Rating               |     |                       | Unit | Remarks                                                                       |
|-------------------------------|--------------------------------------|----------------------|-----|-----------------------|------|-------------------------------------------------------------------------------|
|                               |                                      | Min                  | Typ | Max                   |      |                                                                               |
| Supply Voltage                | V <sub>CC</sub>                      | V <sub>SS</sub> -0.3 |     | V <sub>SS</sub> +7.0  | V    |                                                                               |
|                               | V <sub>SS</sub>                      |                      | 0   |                       | V    |                                                                               |
| Supply Voltage                | AV <sub>CC</sub>                     | V <sub>SS</sub> -0.3 |     | V <sub>SS</sub> +7.0  | V    | Should not exceed V <sub>CC</sub> .                                           |
|                               | AV <sub>R-</sub><br>AV <sub>R+</sub> |                      | 0   |                       | V    | AV <sub>R-</sub> is only applied to select by the mask option in the MB88512. |
| Input Voltage                 | V <sub>IN</sub>                      | V <sub>SS</sub> -0.3 |     | V <sub>SS</sub> +7.0  | V    | Should not exceed V <sub>CC</sub> +0.3V.                                      |
| Output Voltage                | V <sub>OUT</sub>                     | V <sub>SS</sub> -0.3 |     | V <sub>SS</sub> +7.0  | V    | Should not exceed V <sub>CC</sub> .                                           |
|                               |                                      | V <sub>SS</sub> -0.3 |     | V <sub>SS</sub> +15.0 | V    | 12 V interface open-drain.                                                    |
| Output Low Current            | I <sub>OL</sub>                      |                      |     | 15                    | mA   |                                                                               |
| Total Output Low Current      | ΣI <sub>OL</sub>                     |                      |     | 80                    | mA   |                                                                               |
| Power Dissipation             | P <sub>D</sub>                       |                      |     | 380                   | mW   |                                                                               |
| Operating Ambient Temperature | T <sub>A</sub>                       | -40                  |     | +85                   | °C   |                                                                               |
| Storage Temperature           | T <sub>STG</sub>                     | -55                  |     | +150                  | °C   |                                                                               |

† Permanent device damage may occur if the above ABSOLUTE MAXIMUM RATINGS are exceeded. Functional operation should be restricted to the conditions as detailed in the operational sections of this data sheet. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

## RECOMMENDED OPERATING CONDITIONS

| Parameter                     | Symbol           | Value                |     |                      | Unit | Remarks                                                        |
|-------------------------------|------------------|----------------------|-----|----------------------|------|----------------------------------------------------------------|
|                               |                  | Min                  | Typ | Max                  |      |                                                                |
| Supply Voltage                | V <sub>CC</sub>  | 4.5                  | 5.0 | 5.5                  | V    | Active operation range                                         |
|                               |                  | 3.5                  |     | 6.0                  | V    | Standby operation range                                        |
| Analog Supply Voltage         | AV <sub>CC</sub> | 4.5                  |     | 5.5                  | V    |                                                                |
|                               | AV <sub>R-</sub> |                      |     | 0.2•AV <sub>CC</sub> | V    | MB88511 and MB88513                                            |
|                               | AV <sub>R+</sub> | 0                    |     | AV <sub>R+</sub>     | V    | AV <sub>R+</sub> is selected by the mask option in the MB88512 |
|                               | AV <sub>R-</sub> | AV <sub>R-</sub>     |     | AV <sub>CC</sub>     | V    | AV <sub>R-</sub> is selected by the mask option in the MB88512 |
| Input High Voltage            | V <sub>IH</sub>  | 0.7•V <sub>CC</sub>  |     | V <sub>CC</sub> +0.3 | V    | EX (Crystal/ceramic resonator), R-, E-Ports, SI                |
|                               | V <sub>IHS</sub> | 0.8•V <sub>CC</sub>  |     | V <sub>CC</sub> +0.3 | V    | EX (RC-network), RESET, IRQ, TC, SC/T <sub>O</sub>             |
| Input Low Voltage             | V <sub>IL</sub>  | V <sub>SS</sub> -0.3 |     | 0.3•V <sub>CC</sub>  | V    | EX (Crystal/ceramic resonator), R-, E-Ports, SI                |
|                               | V <sub>ILS</sub> | V <sub>SS</sub> -0.3 |     | 0.2•V <sub>CC</sub>  | V    | EX (RC-network), RESET, IRQ, TC, SC/T <sub>O</sub>             |
| Operating Ambient Temperature | T <sub>A</sub>   | -40                  |     | +85                  | °C   |                                                                |

**DC CHARACTERISTICS** (Recommended operating conditions unless otherwise noted)

| Parameter                                | Symbol            | Pin/Port                                                                                                                                                   | Conditions                                                                                         | Value |     |          | Unit    |
|------------------------------------------|-------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------|-------|-----|----------|---------|
|                                          |                   |                                                                                                                                                            |                                                                                                    | Min   | Typ | Max      |         |
| Output High Voltage                      | V <sub>OH</sub>   | R-Port(High-current/standard pull-up), E-Port (MB8851/513, high-current/standard pull-up), $\overline{SC}/\overline{TO}^*$ (MB88511/513), SO (MB88511/513) | V <sub>CC</sub> = 4.5V<br>I <sub>OH</sub> = -200 $\mu$ A                                           | 2.4   |     |          | V       |
|                                          |                   |                                                                                                                                                            | V <sub>CC</sub> = 4.5V<br>I <sub>OH</sub> = -10 $\mu$ A                                            | 4.0   |     |          | V       |
| Output Low Voltage                       | V <sub>OL</sub>   | R-Ports (All option), $\overline{RESET}$ , SO (MB88511/513), $\overline{SC}/\overline{TO}$ (MB88511/513), E-Port(88512, all option)                        | V <sub>CC</sub> = 4.5V<br>I <sub>OL</sub> = 1.8mA                                                  |       |     | 0.4      | V       |
|                                          |                   |                                                                                                                                                            | V <sub>CC</sub> = 4.5V<br>I <sub>OL</sub> = 3.6mA                                                  |       |     | 0.6      | V       |
|                                          |                   | R-Port(High-current open-drain/pull-up), E-port (MB88511/513, high-current/ open-drain/pull-up)                                                            | V <sub>CC</sub> = 4.5V<br>I <sub>OL</sub> = 10mA                                                   |       |     | 2.0      | V       |
| Input Leakage Current                    | I <sub>IL</sub>   | R-Port(High-current/standard pull-up), E-port (MB88512, high-current/standard pull-up), SI, IRQ, TC, $\overline{SC}/\overline{TO}$ (MB88511/513)           | V <sub>CC</sub> = 5.5V<br>V <sub>IH</sub> = 5.5V                                                   |       |     | -1.8     | mA      |
|                                          |                   | EX, $\overline{RESET}$                                                                                                                                     | V <sub>CC</sub> = 5.5V<br>V <sub>IL</sub> = 0.4V                                                   |       |     | -60      | $\mu$ A |
|                                          | I <sub>IH</sub>   | EX, START                                                                                                                                                  | V <sub>CC</sub> = 5.5V<br>V <sub>IL</sub> = 0.4V                                                   |       |     | 60       | $\mu$ A |
| Open-Drain Output Leakage Current        | I <sub>LEAK</sub> | R-Port(High-current/standard open-drain), E-Port (MB88511/513, high-current/standard open-drain)                                                           | V <sub>CC</sub> = 5.5V<br>V <sub>OH</sub> = 5.5V                                                   |       | 0.1 | 10       | $\mu$ A |
|                                          |                   | E10-E0 (MB88511/513, 12V interface open-drain)                                                                                                             | V <sub>CC</sub> = 5.5V<br>V <sub>OH</sub> = 13.2V                                                  |       |     | 40       | $\mu$ A |
| Total I/O High Impedance Leakage Current | $\Sigma I_{IZ}$   | R-Port(all options), $\overline{IRQ}$ , TC, SI $\overline{SC}/\overline{TO}$ (MB88511/513), SO (MB88511/513), E-Port(MB88511/513)                          | V <sub>CC</sub> = 6.0V<br>V <sub>IN</sub> = 0V to 6.0V (Standby mode)                              |       |     | $\pm 25$ | $\mu$ A |
| Supply Current                           | I <sub>CC</sub>   | V <sub>CC</sub>                                                                                                                                            | V <sub>CC</sub> = 5.0V (Typ),<br>5.5V(Max),<br>f <sub>c</sub> =1MHz(Operation)<br>All outputs open |       | 3   | 6        | mA      |
|                                          | I <sub>CCH</sub>  | V <sub>CC</sub> (standby mode)                                                                                                                             | V <sub>CC</sub> = 6.0V,<br>f <sub>c</sub> =0MHz, (Standby)<br>All outputs open                     |       | 3   | 15       | $\mu$ A |
| Input Capacitance                        | C <sub>IN</sub>   | All pins except V <sub>CC</sub> and V <sub>SS</sub>                                                                                                        | f <sub>c</sub> =1MHz                                                                               |       | 10  | 20       | pF      |

\*: When use serial port at internal clock mode,  $\overline{SC}/\overline{TO}$  output voltage should be over the V<sub>OH</sub>=0.8•V<sub>CC</sub>.

## AC CHARACTERISTICS

| CLOCK TIMING (Recommended operating conditions unless otherwise noted.) |                  |       |                                                                           |       |     |         |                   |
|-------------------------------------------------------------------------|------------------|-------|---------------------------------------------------------------------------|-------|-----|---------|-------------------|
| Parameter                                                               | Symbol           | Pin   | Conditions                                                                | Value |     | Unit    | Remarks           |
|                                                                         |                  |       |                                                                           | Min   | Max |         |                   |
| Clock Frequency                                                         | $f_c$            | EX, X | Crystal/ceramic or RC-network OSC or external clock drive Figures 7 and 8 | 1     | 3   | MHz     | Without prescaler |
|                                                                         |                  |       |                                                                           | 2     | 6   |         | With prescaler    |
| Clock Cycle Time                                                        | $t_{cyc}$        | EX, X | Figures 7 and 8                                                           | 0.33  | 2   | $\mu s$ |                   |
| Input Clock Pulse Width                                                 | PWCH, PWCL       | EX    | External clock drive (with X open) Figures 7 and 8)                       | 100   |     | ns      | Without prescaler |
|                                                                         |                  |       |                                                                           | 50    |     |         | With prescaler    |
| Input Clock Rise/Fall Time                                              | $t_{cr}, t_{cf}$ | EX    | External clock drive (with X open) Figures 7 and 8                        | 5     | 200 | ns      |                   |

Figure 7 Clock Timing






Figure 8 Clock Circuit Configuration


(1) Crystal/Ceramic Oscillation



(2) RC-Network Oscillation\*




(3) External Clock Drive



\*When the RC-network oscillation is used, the following conditions must be met:

- 1) The prescaler is not used.
- 2)  $V_{cc}=5\text{ V} \pm 10\%$
- 3)  $T_A=-40^\circ\text{C}$  to  $+85^\circ\text{C}$
- 4)  $f_c$  does not exceed 3 MHz

Figure 9 RC-Network Oscillation Characteristics (Example)




Note:

When the RC-network oscillations is used, the following conditions must be met:

- 1) The prescaler is not used.
- 2)  $V_{CC} = 5V \pm 10\%$
- 3)  $T_A = -40^\circ C$  to  $+85^\circ C$

Figure 10 Crystal Oscillation Characteristics (Example)




Note:

- 1) The cross-hatched portion shows an area where the on-chip oscillator has stable oscillation characteristics and short oscillation stabilization time when an average crystal resonator is used. This chart gives an aim value of the external capacitor to realize a desired oscillation frequency. When an exact oscillation frequency is needed, a capacitor value should be determined, adjusting to individual crystal resonator characteristics.
- 2) Generally speaking, crystal resonators with lower oscillation frequency tend to have longer oscillation stabilization time and wider characteristic variations which affect on-chip oscillator characteristics. So, we recommend to use high-frequency crystal resonator with on-chip 1/2 prescaler.

| OUTPUT TIMING (MB88511/MB88513) (Recommended operating conditions unless otherwise noted.) |           |                   |            |       |      |      |
|--------------------------------------------------------------------------------------------|-----------|-------------------|------------|-------|------|------|
| Parameter                                                                                  | Symbol    | Pin/Port          | Conditions | Value |      | Unit |
|                                                                                            |           |                   |            | Min   | Max  |      |
| E-, R-Ports Delay Time                                                                     | $t_{PDH}$ | R-Port,<br>E-Port | Figure 11  |       | 1000 | ns   |
|                                                                                            | $t_{PDL}$ |                   |            |       | 350  |      |
| Serial Port Delay Time                                                                     | $t_{SDH}$ | SO                | Figure 11  |       | 1000 | ns   |
|                                                                                            | $t_{SDL}$ |                   |            |       | 350  |      |

Notes:

1. A  $10k\Omega$  pull-up is required when open-drain output is used.
2. All the output loading values are  $50pF + 1TTL$ . See figure below.




**Figure 11 Output Timing**

• Parallel Port

$\overline{SC}/\overline{TO}$   
[ Synchronous  
Output ]


E-, R-Ports



• Serial Port

$\overline{SC}/\overline{TO}$   
[ Shift clock  
input ]


SO



## MB88510 SERIES


| INPUT TIMING (MB88511/513) (Recommended operating conditions unless otherwise noted.) |                                     |                                                                                                                          |            |                           |                        |      |
|---------------------------------------------------------------------------------------|-------------------------------------|--------------------------------------------------------------------------------------------------------------------------|------------|---------------------------|------------------------|------|
| Parameter                                                                             | Symbol                              | Pin/Port                                                                                                                 | Conditions | Value                     |                        | Unit |
|                                                                                       |                                     |                                                                                                                          |            | Min                       | Max                    |      |
| Input Data Setup Time                                                                 | t <sub>DS</sub>                     | E20–E0, R15–R11, R7–R0                                                                                                   | Figure 12  | t <sub>cyc</sub> +1000    |                        | ns   |
| Input Data Hold Time                                                                  | t <sub>DH</sub>                     |                                                                                                                          |            |                           | t <sub>cyc</sub> –50   |      |
| SI Input Setup Time                                                                   | t <sub>SDS</sub>                    | SI                                                                                                                       | Figure 12  | 600                       |                        | ns   |
| SI Input Hold Time                                                                    | t <sub>SDH</sub>                    |                                                                                                                          |            | 600                       |                        |      |
| Device Control Setup Time (Synchronous mode)                                          | t <sub>CS</sub>                     | $\overline{\text{RESET}}$                                                                                                | Figure 12  |                           | 2t <sub>cyc</sub> –200 | ns   |
|                                                                                       |                                     | $\overline{\text{IRQ}}$                                                                                                  |            |                           | 2t <sub>cyc</sub> –200 |      |
| Device Control Hold Time (synchronous mode)                                           | t <sub>CH</sub>                     | $\overline{\text{RESET}}$                                                                                                | Figure 12  | 8t <sub>cyc</sub> +50     |                        | ns   |
|                                                                                       |                                     | $\overline{\text{IRQ}}$                                                                                                  |            | 2t <sub>cyc</sub> +50     |                        |      |
| Timing Input Setup Time (synchronous mode)                                            | t <sub>TS</sub>                     | $\overline{\text{TC}}$                                                                                                   | Figure 12  |                           | 2t <sub>cyc</sub> –200 | ns   |
| Timing Input Hold Time (synchronous mode)                                             | t <sub>TH</sub>                     | $\overline{\text{TC}}$                                                                                                   | Figure 12  | 2t <sub>cyc</sub> +50     |                        | ns   |
| Control Signal Low Level Time (Asynchronous mode)                                     | PWCNL                               | $\overline{\text{SC/TO}}$                                                                                                | Figure 12  | 6t <sub>cyc</sub> +250    |                        | ns   |
|                                                                                       |                                     | $\overline{\text{IRQ}}, \overline{\text{TC}}$                                                                            |            | 6t <sub>cyc</sub> +250    |                        |      |
|                                                                                       |                                     | $\overline{\text{RESET}}$                                                                                                |            | 12t <sub>cyc</sub> +250   |                        |      |
| Control Signal High Level Time (Asynchronous mode)                                    | PWCNH                               | $\overline{\text{SC/TO}}$                                                                                                | Figure 12  | 12t <sub>cyc</sub> +250   |                        | ns   |
|                                                                                       |                                     | $\overline{\text{RESET}}, \overline{\text{IRQ}}, \overline{\text{TC}}$                                                   |            | 6t <sub>cyc</sub> +250    |                        |      |
|                                                                                       |                                     | START                                                                                                                    |            | 500                       |                        |      |
| Control Signal Rise and Fall Time                                                     | t <sub>CNr</sub> , t <sub>CNf</sub> | $\overline{\text{START}}, \overline{\text{SC/TO}}, \overline{\text{IRQ}}, \overline{\text{RESET}}, \overline{\text{TC}}$ | Figure 12  | Should be less than 200ns |                        |      |

Figure 12 Input Timing



| POWER-ON RESET (Recommended operating conditions unless otherwise noted.) |           |            |       |     |      |                                                       |
|---------------------------------------------------------------------------|-----------|------------|-------|-----|------|-------------------------------------------------------|
| Parameter                                                                 | Symbol    | Conditions | Value |     | Unit | Remarks                                               |
|                                                                           |           |            | Min   | Max |      |                                                       |
| Power Supply Rise Time                                                    | $t_r$     | Figure 13  | 0.05  | 50  | ms   | Required for operation of the power-on reset circuit  |
| Power Supply Shut-off Time                                                | $t_{off}$ | Figure 13  | 1     |     | ms   | Required for accurate circuit operation repeatability |

Figure 13 Power-on Reset Timing



Note:  
Power supply should be raised smoothly.

| A/D CONVERTER CHARACTERISTICS (Recommended operating conditions unless otherwise noted.) |                  |                   |                                                                                                                                                                                                                                                                                                                                                                                |                  |       |                      |      |
|------------------------------------------------------------------------------------------|------------------|-------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------|-------|----------------------|------|
| Parameter                                                                                | Symbol           | Pin               | Conditions                                                                                                                                                                                                                                                                                                                                                                     | Value            |       |                      | Unit |
|                                                                                          |                  |                   |                                                                                                                                                                                                                                                                                                                                                                                | Min              | Typ   | Max                  |      |
| Resolution                                                                               |                  |                   |                                                                                                                                                                                                                                                                                                                                                                                |                  |       | 8                    | Bit  |
| Linearity Error                                                                          |                  |                   | Only applied to select AV <sub>R-</sub> (MB88512) <span style="border-left: 1px solid black; padding-left: 5px;">T<sub>A</sub>=25°C, AV<sub>CC</sub>=5.0V, AV<sub>R+</sub>=5.0V</span><br>MB88511/513 and select AV <sub>R+</sub> (MB88512) <span style="border-left: 1px solid black; padding-left: 5px;">T<sub>A</sub>=25°C, AV<sub>CC</sub>=5.0V, AV<sub>R-</sub>=0V</span> |                  |       | ±1.0                 | LSB  |
| Differential Linearity Error                                                             |                  |                   |                                                                                                                                                                                                                                                                                                                                                                                |                  |       | ±0.9                 | LSB  |
| Zero Transition Voltage                                                                  | V <sub>OT</sub>  |                   |                                                                                                                                                                                                                                                                                                                                                                                | -20              | +10   | +40                  | mV   |
| Full Scale Transition Voltage                                                            | V <sub>FST</sub> |                   |                                                                                                                                                                                                                                                                                                                                                                                | +4910            | +4970 | +5030                | mV   |
| Conversion Time                                                                          |                  |                   | 144 x t <sub>CYC</sub>                                                                                                                                                                                                                                                                                                                                                         | 48 *1            |       | 144 *2               | μS   |
| Analog Port Input Current                                                                | I <sub>AIN</sub> | AN3-AN0*, AN7-AN4 |                                                                                                                                                                                                                                                                                                                                                                                |                  |       | 5                    | μA   |
| Analog Input Voltage                                                                     |                  | AN3-AN0*, AN7-AN4 | MB88511/513 and select AV <sub>R-</sub> (MB88512)                                                                                                                                                                                                                                                                                                                              | AV <sub>R-</sub> |       | AV <sub>CC</sub>     | V    |
|                                                                                          |                  | AN3-AN0*, AN7-AN4 | Select AV <sub>R+</sub> (MB88512).                                                                                                                                                                                                                                                                                                                                             | 0                |       | AV <sub>R+</sub>     | V    |
| Reference Voltage                                                                        |                  | AV <sub>R-</sub>  | MB88511/513                                                                                                                                                                                                                                                                                                                                                                    | 0                | 0     | 0.2•AV <sub>CC</sub> | V    |
|                                                                                          |                  | AV <sub>R+</sub>  | Select AV <sub>R+</sub> (MB88512)                                                                                                                                                                                                                                                                                                                                              | 0                |       | AV <sub>R+</sub>     | V    |
|                                                                                          |                  | AV <sub>R-</sub>  | Select AV <sub>R-</sub> (MB88512).                                                                                                                                                                                                                                                                                                                                             | AV <sub>R-</sub> |       | AV <sub>CC</sub>     | V    |
| Reference Voltage Supply Current                                                         | I <sub>R</sub>   |                   | Only applied to the MB88512, AV <sub>R+</sub> :Between AV <sub>R+</sub> and AV <sub>SS</sub> , AV <sub>R-</sub> :Between AV <sub>R-</sub> and AV <sub>CC</sub>                                                                                                                                                                                                                 |                  | 170   |                      | μA   |
| Supply Current                                                                           | I <sub>A</sub>   | AV <sub>CC</sub>  | AV <sub>CC</sub> =5.0V, AV <sub>R-</sub> =0V or AV <sub>R+</sub> =5V, A/D converting                                                                                                                                                                                                                                                                                           |                  | 1.7   |                      | mA   |
|                                                                                          | I <sub>AH1</sub> |                   | AV <sub>CC</sub> =6.0V, AV <sub>R-</sub> =6V or AV <sub>R+</sub> =0V, Standby                                                                                                                                                                                                                                                                                                  |                  |       | 5                    | μA   |
|                                                                                          | I <sub>AH2</sub> |                   | Only applit to the MB88511/513, AV <sub>CC</sub> =6.0V, AV <sub>R-</sub> =0V, Standby and stop A/D converting                                                                                                                                                                                                                                                                  |                  | 250   |                      | μA   |

## Notes:

\* AN7-AN4 is applied to only MB88512.

1. Error between analog inputs is within 1/2 LSB when AV<sub>CC</sub> - AV<sub>R-</sub>=5.0V

2. Full-scale and offset can be adjust by an appropriate setting of AV<sub>CC</sub> and AV<sub>R-</sub>.

3. Error becomes relatively larger as |AV<sub>CC</sub> - AV<sub>R-</sub>| becomes smaller.

\*1 f<sub>c</sub> = 6.0 MHz (with prescaler)

\*2 f<sub>c</sub> = 1.0 MHz (without prescaler)

## MB88510 SERIES

- Resolution


The minimum variation in an analog signal that can be discriminated by the A/D converter. (An analog voltage can be divided into  $2^8 = 256$  parts.)

- Linearity Error

The difference between the line connecting the device zero transition point ("0000 0000" ↔ "0000 0001") with the full scale transition point ("0000 0000" ↔ "0000 0001"), the actual conversion characteristics.

- Differential Linearity Error

The difference from ideal input voltage required to change the output voltage code by 1 LSB.



$$1\text{LSB} = \frac{V_{\text{FST}} - V_{0\text{T}}}{254}$$

$$\text{Linearity Error} = \frac{V_{\text{NT}} - (1\text{LSB} \times N + V_{0\text{T}})}{1\text{LSB}} \quad (\text{LSB})$$


$$\text{Differential Linearity Error} = \frac{V_{(\text{N}+1)\text{T}} - V_{\text{NT}}}{1\text{LSB}} - 1 \quad (\text{LSB})$$

# PACKAGE DIMENSIONS

## MB88511-P and MB88513-P

### 42-LEAD PLASTIC DUAL IN-LINE PACKAGE

(Case No. : DIP-42P-M01)



© 1988 FUJITSU LIMITED D42006S-3C


Dimensions in  
inches (millimeters)

## MB88510 SERIES

### MB88511-PSH and MB88513-PSH

#### 42-LEAD PLASTIC DUAL IN-LINE PACKAGE

(Case No. : DIP-42P-M02)




© 1988 FUJITSU LIMITED D42007S-3C

Dimensions in  
inches (millimeters)

## MB88512-P

28-LEAD PLASTIC DUAL IN-LINE PACKAGE  
(CASE No. : DIP-28P-M02)




© 1988 FUJITSU LIMITED D28006S-2C

Dimensions in  
inches (millimeters)

MB88511-PF and MB88513-PF

48-LEAD PLASTIC FLAT PACKAGE


(Case No. : FPT-48P-M02)



© 1988 FUJITSU LIMITED F48002S-7C




Dimensions in  
inches (millimeters)

## MB88PG511-C



MDP-42C-P04


42-LEAD DUAL IN-LINE PACKAGE MODULE  
(CASE No.: MDP-42C-P04)



© 1988 FUJITSU LIMITED M42005S-2C

Dimension in inches  
and (millimeters)


MB88PG512-C



MDP-28C-P01

28-LEAD CERAMIC DUAL IN-LINE TYPE MODULE

(Case No. : MDP-28C-P01)



© 1990 FUJITSU LIMITED M28001S-2C

Dimensions in  
inches (millimeters)

All Rights Reserved.

Circuit diagrams utilizing Fujitsu products are included as a means of illustrating typical semiconductor applications. Complete Information sufficient for construction purposes is not necessarily given.

The information contained in this document has been carefully checked and is believed to be reliable. However, Fujitsu assumes no responsibility for inaccuracies.

The Information contained in this document does not convey any license under the copyrights, patent rights or trademarks claimed and owned by Fujitsu.

Fujitsu reserves the right to change products or specifications without notice.

No part of this publication may be copied or reproduced in any form or by any means, or transferred to any third party without prior written consent of Fujitsu.