

# **NSP (OTP) Data Sheet**

The information described in this document is the exclusive intellectual property of Nuvoton Technology Corporation and shall not be reproduced without permission from Nuvoton.

Nuvoton is providing this document only for reference purposes of NSP based system design. Nuvoton assumes no responsibility for errors or omissions.

All data and specifications are subject to change without notice.

For additional information or questions, please contact: Nuvoton Technology Corporation.

[www.nuvoton.com](http://www.nuvoton.com)

*Release Date: Jan. 2021*

*Rev 1.1*

## 1. General Description

NSP (OTP) series is an advanced 1-ch Voice IC that equips with Nuvoton 8-bit 65C02 core, embedded OTP (One Time PROM) and new algorithm to implement Voice Prompt applications with high level of sound quality. NSP (OTP) series provide SOP8 and SOP14 with 2 I/Os protocol to communicate with host MCU.

The NSP family contains following chips built-in different size of embedded OTP, shown as below:

Part No.	Package	Duration (Sec) (@ NM4)		Duration (Sec) (@MDM)		V <sub>DD</sub> (V)	LVR (V)	Audio	LVR	WDT
		6KHz	10KHz	6KHz	10KHz			PWM		
NSP075A	SOP8	81	49	69	41	2.0~5.5	1.9	13-bit	Yes	Yes
NSP165A	SOP8	162	97	137	82	2.0~5.5	1.9	13-bit	Yes	Yes
NSP335A	SOP8	324	194	274	164	2.0~5.5	1.9	13-bit	Yes	Yes
NSP075B	SOP14	81	49	69	41	2.0~5.5	1.9	13-bit	Yes	Yes
NSP165B	SOP14	162	97	137	82	2.0~5.5	1.9	13-bit	Yes	Yes
NSP335B	SOP14	324	194	274	164	2.0~5.5	1.9	13-bit	Yes	Yes

## 2. Features

- MCU: 8-bit 65C02
- Operating voltage: 2.0~5.5V
- Oscillator: builds in internal Rosc (TRIM)
  - Frequency deviation: +/-1.5%
- NSP075B~335B has 4 bi-directional I/O pins
- Audio output: 12-bit PWM
- Voice channel: 1-ch Voice
- Algorithm: 4-bit NM4, 5-bit MDM
- Built-in Watch-Dog Timer (WDT)
- Low Voltage Reset (LVR)
- Package form: SOP8, SOP14

### 3. PAD Description

Pin Name	I/O	Function
BP11 BP12	I/O	Interface with host MCU Share with ICPCLK and ICPDATA for program
BP07 BP10 BP13 BP17	I/O	General input/output pins controlled by MCU command Each pin can be set as Input or Output individually For input pin, it can be set as pull-high Only support on NSP075B/165B/335B (SOP14)
VPP	Power	Positive power supply for program
V330	Power	Internal regulator, 0.1uF capacitor is needed
PWM+	O	PWM driver positive output to drive speaker directly
PWM-	O	PWM driver negative output to drive speaker directly
VDD	Power	Positive power supply
VDD_IO	Power	Positive power supply for GPIO
VDD_SPK	Power	Positive power supply for speaker driver Only support on NSP075B/165B/335B (SOP14)
VSS	Power	Negative power supply

### 4. Electrical Characteristics

#### 4.1 Absolute Maximum Ratings

Parameter	Symbol	Conditions	Rated Value	Unit
Input Voltage	VIN	All Inputs	VSS -0.3 to VDD +0.3	V
Storage Temp.	TSTG	-	-55 to +150	°C
Operating Temp.	TOPR	-	-20 to +70	°C

**Note:** Exposure to conditions beyond those listed under the Absolute Maximum Ratings table may adversely affect the life and reliability of the device.

### 4.2 D.C. Characteristics

(VDD – VSS = 4.5V, TA = 25° C, No Load unless otherwise specified)

Parameter	Sym	Conditions	Min	Typ	Max	Unit
Operating Voltage	V <sub>DD</sub>		2.0	-	5.5	V
Operating Current	I <sub>OP1</sub>	No load	-	8	10	mA
Standby Current (STOP)	I <sub>DD1</sub>	No load	-	3	10	μA
Input Low Voltage	V <sub>IL</sub>	All input pins	V <sub>SS</sub>	-	0.3 V <sub>DD</sub>	V
Input High Voltage	V <sub>IH</sub>	All input pins	0.7 V <sub>DD</sub>	-	V <sub>DD</sub>	V
Output Current BP0	I <sub>OL</sub>	V <sub>DD</sub> = 3V, V <sub>OUT</sub> = 0.4V	8	12	-	mA
	I <sub>OH</sub>	V <sub>DD</sub> = 3V, V <sub>OUT</sub> = 2.6V	-4	-6	-	mA
	I <sub>OL</sub>	V <sub>DD</sub> = 4.5V, V <sub>OUT</sub> = 1.0V	-	25	-	mA
	I <sub>OH</sub>	V <sub>DD</sub> = 4.5V, V <sub>OUT</sub> = 3.5V	-	-12	-	mA
Output Current BP1	I <sub>OL</sub>	V <sub>DD</sub> = 3V, V <sub>OUT</sub> = 0.4V	4	6	-	mA
	I <sub>OH</sub>	V <sub>DD</sub> = 3V, V <sub>OUT</sub> = 2.6V	-4	-6	-	mA
	I <sub>OL</sub>	V <sub>DD</sub> = 4.5V, V <sub>OUT</sub> = 1.0V	-	12	-	mA
	I <sub>OH</sub>	V <sub>DD</sub> = 4.5V, V <sub>OUT</sub> = 3.5V	-	-12	-	mA
Output Current PWM+ / PWM-	I <sub>OL1</sub>	RL = 8Ω	+250	-	-	mA
	I <sub>OHI</sub>	[PWM+]---[RL]----[PWM-]	-250	-	-	mA

### 4.3 A.C. Characteristics


(VDD = 4.5V, TA = 25°C, No Load unless otherwise specified)

Parameter	Sym	Conditions	Min	Typ	Max	Unit
Frequency Deviation by Voltage Drop	ΔF/F	(F <sub>max</sub> – F <sub>min</sub> )/F <sub>min</sub> @VDD: 2.4 ~ 5.5V	-	2	-	%

### 5. Typical Application Circuit


NSP075A/165A/335A

3.3V < VDD < 5.5V



**Note:** C1 and C2 need to be close to the NSP chip layout.


2.0V < VDD < 3.6V



**Note:** C1 and C2 need to be close to the NSP chip layout.


**NSP075B/165B/335B**

**3.3V < VDD < 5.5V**




**Note:** C1 and C2 need to be close to the NSP chip layout.

**2.0V < VDD < 3.6V**



**Note:** C1 and C2 need to be close to the NSP chip layout.


### NSP (OTP) Application with N55PA01



## 6. Package Information


### 6.1 Pin Assignment

<b>NSP075A/165A/335A</b> <b>SOP8 (150 mil)</b>	<b>NSP075B/165B/335B</b> <b>SOP14 (150 mil)</b>
---	--



6.2 Package Dimension


SOP8, 150 mil



Control dimensions are in millimeters .

SYMBOL	DIMENSION IN MM		DIMENSION IN INCH	
	MIN.	MAX.	MIN.	MAX.
A	1.35	1.75	0.053	0.069
A1	0.10	0.25	0.004	0.010
b	0.33	0.51	0.013	0.020
c	0.19	0.25	0.008	0.010
E	3.80	4.00	0.150	0.157
D	4.80	5.00	0.188	0.196
e	1.27 BSC		0.050 BSC	
$H_Z$	5.80	6.20	0.228	0.244
Y	—	0.10	—	0.004
L	0.40	1.27	0.016	0.050
$\theta$	0	10	0	10

SOP14, 150 mil



Control demensions are in milimeters .

SYMBOL	DIMENSION IN MM		DIMENSION IN INCH	
	MIN.	MAX.	MIN.	MAX.
A	1.35	1.75	0.053	0.069
A1	0.10	0.25	0.004	0.010
b	0.33	0.51	0.013	0.020
c	0.19	0.25	0.008	0.010
E	3.80	4.00	0.150	0.157
D	8.55	8.75	0.337	0.344
e	1.27 BSC		0.050 BSC	
H <sub>E</sub>	5.80	6.20	0.228	0.244
Y	—	0.10	—	0.004
L	0.40	1.27	0.016	0.050
⌀	0	8	0	8

## 7. Ordering Information

<b>Part No.</b>	<b>Shape</b>	<b>Type</b>	<b>Remark</b>
NSP075A/165A/335A	E	Package: SOP8 (150mil)	Blank
NSP075B/165B/335B	E	Package: SOP14 (150mil)	Blank

## 8. Revision History

Version	Date	Substantial Changes	Page
Rev 0.1	Nov.2019	Preliminary Initial Release	All
Rev 1.0	Feb.2020	First establishment	All
Rev 1.1	Jan.2021	Update PSG and Update SOP14 Pin Assignment Update Application Circuit with N55PA01	3, 8

### Important Notice

Nuvoton Products are neither intended nor warranted for usage in systems or equipment, any malfunction or failure of which may cause loss of human life, bodily injury or severe property damage. Such applications are deemed, “Insecure Usage”.

Insecure usage includes, but is not limited to: equipment for surgical implementation, atomic energy control instruments, airplane or spaceship instruments, the control or operation of dynamic, brake or safety systems designed for vehicular use, traffic signal instruments, all types of safety devices, and other applications intended to support or sustain life.

All Insecure Usage shall be made at customer’s risk, and in the event that third parties lay claims to Nuvoton as a result of customer’s Insecure Usage, customer shall indemnify the damages and liabilities thus incurred by Nuvoton.

---

*Please note that all data and specifications are subject to change without notice.  
All the trademarks of products and companies mentioned in this datasheet belong to their respective owners.*