


SF1173B 374 MHz SAW Filter



PRELIMINARY

- Designed for Wireless LAN Receiver IF Applications
- Balanced Input and Output



See Associated Plots

Characteristic	Sym	Min	Typ	Max	Units	Notes
Nominal Center Frequency	fc		374.000		MHz	1
Passband	Insertion Loss at fc		8.9	10.0	dB	1, 2
	3 dB Passband	BW ₃	17	23	MHz	
	Amplitude Ripple over fc ±7.0 MHz			0.8	1.0	
	Group Delay Variation over fc ±7.0 MHz	GDT		67	100	ns _{P-P}
Rejection	fc-100 to -33 MHz		45	49		dB
	fc-33 to -22 MHz		40	51		
	fc -22 to -16.5 MHz		30	45		
	fc +16.5 to +22 MHz		30	39		
	fc +22 to +43 MHz		35	39		
	fc +43 to +100 MHz		40	45		
Operating Temperature Range	T _A	-10		+85	°C	1

Impedance Matching to Unbalanced 50 Ω	External L-C
Case Style	SMP-03 7 x 5 mm Nominal Footprint
Lid Symbolization (YY = year, WW = week)	RFM SF3745X7 YYWW

Absolute Maximum Ratings

Rating	Value	Units
Maximum Incident Power in Passband	+10	dBm
Max. DC voltage between any 2 terminals	30	VDC
Storage Temperature Range	-40 to +85	°C
Max Soldering Profile	265°C for 10 s	

Electrical Connections

Connection	Terminals
Port 1 Hot	10
Port 1 Gnd Return	1
Port 2 Hot	5
Port 2 Gnd Return	6
Case Ground	All others

Notes:

1. Unless noted otherwise, all specifications apply over the operating temperature range with filter soldered to the specified demonstration board with impedance matching to 50 Ω and measured with 50 Ω network analyzer.
2. Unless noted otherwise, all frequency specifications are referenced to the nominal center frequency, fc.
3. Rejection is measured as attenuation below the minimum IL point in the passband. Rejection in final user application is dependent on PCB layout and external impedance matching design. See Application Note No. 42 for details.
4. "LRIP" or "L" after the part number indicates "low rate initial production" and "ENG" or "E" indicates "engineering prototypes."
5. The design, manufacturing process, and specifications of this filter are subject to change.
6. Either Port 1 or Port 2 may be used for either input or output in the design. However, impedances and impedance matching may vary between Port 1 and Port 2, so that the filter must always be installed in one direction per the circuit design.
7. US and international patents may apply.
8. RFM, stylized RFM logo, and RF Monolithics, Inc. are registered trademarks of RF Monolithics, Inc.
9. ©Copyright 1999, RF Monolithics Inc.
10. Electrostatic Sensitive Device. Observe precautions for handling.



RF Monolithics, Inc.
4347 Sigma Road
Dallas, Texas 75244
USA

Phone: +1(972)233-2903
Fax: +1(972)387-8148
e-mail: info@rfm.com
Home page: www.rfm.com

European Sales Office
44 1963 251383
44 1963 251510