



凌陽科技  
SUNPLUS

Preliminary

**SPCA504A**  
Data Sheet

---

---

## Dual Mode PC Camera Processor

---

---

*Scatch*  
**Sunplus Camera Solution**

**SPCA504A**

**Data Sheet**

Version 0.2.1

---

---

SUNPLUS TECHNOLOGY CO. reserves the right to change this documentation without prior notice. Information provided by SUNPLUS TECHNOLOGY CO. is believed to be accurate and reliable. However, SUNPLUS TECHNOLOGY CO. makes no warranty for any errors which may appear in this document. Contact SUNPLUS TECHNOLOGY CO. to obtain the latest version of device specifications before placing your order. No responsibility is assumed by SUNPLUS TECHNOLOGY CO. for any infringement of patent or other rights of third parties which may result from its use. In addition, SUNPLUS products are not authorized for use as critical components in life support devices/ systems or aviation devices/systems, where a malfunction or failure of the product may reasonably be expected to result in significant injury to the user, without the express written approval of Sunplus.



Table of Contents

<b>1. GENERAL DESCRIPTION</b> .....	<b>3</b>
<b>2. FEATURE</b> .....	<b>3</b>
<b>3. PIN DESCRIPTION</b> .....	<b>4</b>
3.1 PIN ASSIGNMENT FOR 160-PIN PACKAGE .....	4
3.2 PIN ASSIGNMENT FOR 128-PIN PACKAGE .....	10
<b>4. FUNCTIONAL DESCRIPTION</b> .....	<b>15</b>
4.1 BLOCK DIAGRAM .....	15
4.2. CAMERA OPERATION MODES .....	16
<b>5. PACKAGE - 160 PINS</b> .....	<b>17</b>
<b>6. PACKAGE - 128 PINS</b> .....	<b>19</b>
<b>REVISION HISTORY</b> .....	<b>20</b>



## 1. General description

The SPCA504A is a digital camera processor chip that provides a complete solution for dual mode camera applications. This chip integrates image sensor interface, digital video input interface, color image processor, storage media controller, JPEG image compression engine, USB interface, and a built-in micro-controller. The SPCA504A supports both CCD and CMOS image sensors up to 1.1M and 2.0M pixels respectively. It is designed to fulfill all the requirements for the dual mode camera applications. The SPCA504A camera processor chip includes not only the latest technology, but also the full services and support of Sunplus.

## 2. Feature

The main functions of the SPCA504A includes:

- DSC mode : capture one frame each time
- Video clip mode : capture a video with frame rate 15~30 frames/sec
- PC-camera mode : 30 frames/sec for CIF size, 20 frames/sec for VGA size

The SPCA504A chip has many image-processing functions that include:

- High quality color interpolation
- Two-dimensional edge enhancement
- Bad pixels concealment
- AE/AWB parameter windows cover full range of the sensor

The SPCA504A supports image CCD/CMOS sensors up to 1.1M/2.1M pixels. Some of them are listed below.

### CCD

- VGA : Sharp LZ24BP, Sony ICX098AK, Panasonic MN3777
- XGA : Sony ICX204AK
- SXGA : Panasonic MN3778 (progressive)

### CMOS

- VGA: HP HDCS2020, PHOTOBIT PB320, OMMNIVISION OV7620, HYUNDAI HV7131B, SHARP LZ34B10, PIXART PAS202, TASC TAS5130A, BIOMORPHIC BI8602, IC MEDIA ICM205DL, MOTOROLA SCM20014, National Semiconductor LM9627, Century Semiconductor CS2102
- SVGA: HYUNDAI HV7141B
- XGA : PIXELCAM PCS2112
- SXGA: Motorola MCM20027

The DRAM interface supports 16M bits and 64M bits SDRAM modules through a 16-bit data bus.

Audio functions that the SPCA504A supports include audio class, audio capture, audio record and playback.

- It supports bi-directional AC-link for audio record and playback.
- It supports MP3 decoder interface for MP3 decoding and playback.
- It supports microphone interface for audio record.
- It supports an IMA-ADPCM compatible ADPCM compression engine for audio compression.

In addition to the external SDRAM module, the SPCA504A supports many storage media. That include:

- NAND-gate flash memory (smart media card)
- NOR-type flash memory
- ATAPI interface (ATAPI CDRW, compact flash memory)
- SPI serial flash memory, both mode0 and mode 3 supported (MultiMediaCard)
- Next Flash serial flash memory
- SD Card



The SPCA504A supports JPEG image compression at YUV422 and YUV 420 chroma format. It can also compress BW (black-and-white) images. The output data format is compliant with JFIF bitstream format. An automatic scale-down function is included to fit in the display size under playback mode.

The USB interface supports following pipes to PC. They are:

- Video ISO-IN pipe : for video data transmission to the PC
- Audio ISO-IN pipe : for Audio data transmission to the PC
- BULK-IN pipe : for uploading image from the camera to the PC
- BULK-OUT pipe : for download image data, audio data, firmware, and MP3 data to the camera.
- INTERRUPT-IN pipe: For reporting status and events of the camera to the PC

The SPCA504A has a built-in 8032 micro-controller with 6K bytes of internal SRAM.

- It supports *ISP* (in-system-programming with 4K bytes of shadow space).
- It has built-in 64K bytes of mask ROM.
- It supports *LOW-POWER* mode and *IDLE* mode.

The SPCA504A has a built-in PLL to supply on-chip clock sources.

The SPCA504A is packaged in either 128-pin QFP or 160-pin LQFP.

The SPCA504A needs 3.3/2.5 dual power supply.

### 3. Pin description

#### 3.1 Pin assignment for 160-pin package

Pin	Signal	Pin	Signal
1	rgb5	80	fmgpio2
2	rgb6	79	fmgpio3
3	rgb7	78	fmgpio4
4	rgb8	77	fmgpio5 / ma12
5	rgb9	76	fmgpio6 / ma13
6	v1	75	fmgpio7
7	v2	73	fmgpio8
8	v3	73	fmgpio9
9	sg	72	fmgpio10
10	sub	71	fmgpio11
11	fr	70	fmgpio12
12	fh1	69	dvss2
13	fh2	68	dvdd2
14	pb1k	67	md15
15	ovdd4	66	md14
16	ovss4	65	md13
17	rs	64	md12
18	fs	63	md11
19	fedc	62	md10
20	adclp	61	md9
21	obclp	60	md8
22	adck	59	md7
23	sen	58	md6
24	sck	57	md5
25	sdo	56	md4
26	dvdd4	55	md3
27	dvss4	54	md2
28	avssd	53	md1
29	avss	52	md0
30	alc	51	ovss2
31	mic	50	ovdd2
32	opi	49	p35
33	opo	48	p34
34	avdd	47	p31
35	vref	46	p30
36	uvss	45	p17
37	dp	44	p16
38	dm	43	p15
39	uvdd	42	p14
40	suspend	41	p13
41			
42			
43			
44			
45			
46			
47			
48			
49			
50			
51			
52			
53			
54			
55			
56			
57			
58			
59			
60			
61			
62			
63			
64			
65			
66			
67			
68			
69			
70			
71			
72			
73			
74			
75			
76			
77			
78			
79			
80			