

N-Channel Enhancement Mode Field Effect Transistor

Product Summary



• V_{DS}	100V
• I_D	3A
• $R_{DS(ON)}$ (at $V_{GS}=10V$)	< 110 mohm
• $R_{DS(ON)}$ (at $V_{GS}=4.5V$)	< 120 mohm

General Description


- Trench Power MV MOSFET technology
- Excellent package for heat dissipation
- High density cell design for low $R_{DS(ON)}$

Applications

- DC-DC Converters
- Power management functions



SOT-89



■ Absolute Maximum Ratings ($T_A=25^\circ\text{C}$ unless otherwise noted)

Parameter		Symbol	Limit	Unit
Drain-source Voltage		V_{DS}	100	V
Gate-source Voltage		V_{GS}	± 20	V
Drain Current	$T_A=25^\circ\text{C}$	I_D	3	A
	$T_A=70^\circ\text{C}$		2.4	
Pulsed Drain Current ^A		I_{DM}	12	A
Total Power Dissipation	$T_A=25^\circ\text{C}$	P_D	1.5	W
	$T_C=25^\circ\text{C}$		4.0	
Thermal Resistance Junction-to-Ambient ^B		$R_{\theta JA}$	83	$^\circ\text{C}/\text{W}$
Thermal Resistance Junction-to-Case		$R_{\theta JC}$	31	$^\circ\text{C}/\text{W}$
Junction and Storage Temperature Range		T_J, T_{STG}	-55~+150	$^\circ\text{C}$

■ Ordering Information (Example)

PREFERRED P/N	PACKING CODE	Marking	MINIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON QUANTITY(pcs)	DELIVERY MODE
YJH03N10A	F2	1003.	1000	10000	40000	7" reel



YJH03N10A

■ Electrical Characteristics (T_J=25°C unless otherwise noted)

Parameter	Symbol	Conditions	Min	Typ	Max	Units
Static Parameter						
Drain-Source Breakdown Voltage	BV _{DSS}	V _{GS} = 0V, I _D =250μA	100			V
Zero Gate Voltage Drain Current	I _{DSS}	V _{DS} =100V,V _{GS} =0V			1	μA
Gate-Body Leakage Current	I _{GSS}	V _{GS} = ±20V, V _{DS} =0V			±100	nA
Gate Threshold Voltage	V _{GS(th)}	V _{DS} = V _{GS} , I _D =250μA	1	1.8	2.5	V
Static Drain-Source On-Resistance	R _{DS(ON)}	V _{GS} = 10V, I _D =3A		95	110	mΩ
		V _{GS} = 4.5V, I _D =2.4A		100	120	
Diode Forward Voltage	V _{SD}	I _S =3A,V _{GS} =0V		0.8	1.2	V
Maximum Body-Diode Continuous Current	I _S				3	A
Dynamic Parameters						
Input Capacitance	C _{iss}	V _{DS} =50V,V _{GS} =0V,f=1MHZ		785		pF
Output Capacitance	C _{oss}			38		
Reverse Transfer Capacitance	C _{rss}			30		
Switching Parameters						
Total Gate Charge	Q _g	V _{GS} =10V,V _{DS} =50V,I _D =3A		16		nC
Gate-Source Charge	Q _{gs}			2.5		
Gate-Drain Charge	Q _{gd}			2.6		
Turn-on Delay Time	t _{D(on)}	V _{GS} =10V,V _{DD} =50V,R _L =6.4Ω R _{GEN} =3Ω		5		ns
Turn-on Rise Time	t _r			40		
Turn-off Delay Time	t _{D(off)}			20		
Turn-off fall Time	t _f			7		

A. Pulse Test: Pulse Width≤300us, Duty cycle ≤2%.

B. Device mounted on FR-4 PCB, 1 inch x 0.85 inch x 0.062 inch.



■ Typical Performance Characteristics




Figure1. Output Characteristics




Figure2. Transfer Characteristics




Figure3. Capacitance Characteristics




Figure4. Gate Charge




Figure5. Drain-Source on Resistance




Figure6. Drain-Source on Resistance




Figure7. Safe Operation Area





Figure8. Switching wave



■ SOT-89 Package information



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	1.400	1.600	0.055	0.063
b	0.350	0.520	0.013	0.197
b1	0.400	0.580	0.016	0.023
c	0.350	0.440	0.014	0.017
D	4.400	4.600	0.173	0.181
D1	1.550 REF		0.061 REF	
E	2.350	2.550	0.091	0.102
E1	3.940	4.250	0.155	0.167
e	1.500 TYP		0.060TYP	
e1	3.000 TYP		0.118TYP	
L	0.900	1.100	0.035	0.047



Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.