

BLL6H1214-500

www.DataSheet4U.com

LDMOS L-band radar power transistor

Rev. 02 — 1 April 2010

Product data sheet

1. Product profile

1.1 General description

500 W LDMOS power transistor intended for L-band radar applications in the 1.2 GHz to 1.4 GHz range.

Table 1. Test information

Typical RF performance at $T_{case} = 25\text{ °C}$; $t_p = 300\text{ }\mu\text{s}$; $\delta = 10\%$; $I_{DQ} = 150\text{ mA}$; in a class-AB production test circuit.

Mode of operation	f (GHz)	V _{DS} (V)	P _L (W)	G _p (dB)	η_D (%)	t _r (ns)	t _f (ns)
pulsed RF	1.2 to 1.4	50	500	17	50	20	6

CAUTION



This device is sensitive to ElectroStatic Discharge (ESD). Therefore care should be taken during transport and handling.

1.2 Features and benefits

- Typical pulsed RF performance at a frequency of 1.2 GHz to 1.4 GHz, a supply voltage of 50 V, an I_{DQ} of 150 mA, a t_p of 300 μs with δ of 10 %:
 - ◆ Output power = 500 W
 - ◆ Power gain = 17 dB
 - ◆ Efficiency = 50 %
- Easy power control
- Integrated ESD protection
- High flexibility with respect to pulse formats
- Excellent ruggedness
- High efficiency
- Excellent thermal stability
- Designed for broadband operation (1.2 GHz to 1.4 GHz)
- Internally matched for ease of use
- Compliant to Directive 2002/95/EC, regarding restriction of hazardous substances (RoHS)





www.DataSheet4U.com

1.3 Applications

- L-band power amplifiers for radar applications in the 1.2 GHz to 1.4 GHz frequency range

2. Pinning information

Table 2. Pinning

Pin	Description	Simplified outline	Graphic symbol
1	drain1		 <p style="text-align: right; margin-right: 50px;">sym117</p>
2	drain2		
3	gate1		
4	gate2		
5	source		

[1] Connected to flange.

3. Ordering information

Table 3. Ordering information

Type number	Package		
	Name	Description	Version
BLL6H1214-500	-	flanged balanced LDMOST ceramic package; 2 mounting holes; 4 leads	SOT539A

4. Limiting values

Table 4. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134).

Symbol	Parameter	Conditions	Min	Max	Unit
V_{DS}	drain-source voltage		-	100	V
V_{GS}	gate-source voltage		-0.5	+13	V
I_D	drain current		-	45	A
T_{stg}	storage temperature		-65	+150	°C
T_j	junction temperature		-	200	°C

5. Thermal characteristics

Table 5. Thermal characteristics

Symbol	Parameter	Conditions	Typ	Unit
$Z_{th(j-c)}$	transient thermal impedance from junction to case	$T_{case} = 85\text{ °C}; P_L = 500\text{ W}$		
		$t_p = 100\text{ }\mu\text{s}; \delta = 10\text{ }\%$	0.07	K/W
		$t_p = 200\text{ }\mu\text{s}; \delta = 10\text{ }\%$	0.08	K/W
		$t_p = 300\text{ }\mu\text{s}; \delta = 10\text{ }\%$	0.1	K/W
		$t_p = 100\text{ }\mu\text{s}; \delta = 20\text{ }\%$	0.1	K/W

6. Characteristics

Table 6. DC characteristics

$T_j = 25\text{ °C}$; per section unless otherwise specified.

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
$V_{(BR)DSS}$	drain-source breakdown voltage	$V_{GS} = 0\text{ V}; I_D = 2.7\text{ mA}$	100	-	-	V
$V_{GS(th)}$	gate-source threshold voltage	$V_{DS} = 10\text{ V}; I_D = 270\text{ mA}$	1.3	1.8	2.2	V
I_{DSS}	drain leakage current	$V_{GS} = 0\text{ V}; V_{DS} = 50\text{ V}$	-	-	1.4	μA
I_{DSX}	drain cut-off current	$V_{GS} = V_{GS(th)} + 3.75\text{ V}; V_{DS} = 10\text{ V}$	32	42	-	A
I_{GSS}	gate leakage current	$V_{GS} = 11\text{ V}; V_{DS} = 0\text{ V}$	-	-	140	nA
g_{fs}	forward transconductance	$V_{DS} = 10\text{ V}; I_D = 270\text{ mA}$	1.7	3	-	S
$R_{DS(on)}$	drain-source on-state resistance	$V_{GS} = V_{GS(th)} + 3.75\text{ V}; I_D = 9.5\text{ A}$	-	100	164	$\text{m}\Omega$

Table 7. RF characteristics

Mode of operation: pulsed RF; $t_p = 300\text{ }\mu\text{s}; \delta = 10\text{ }\%$; RF performance at $V_{DS} = 50\text{ V}; I_{Dq} = 150\text{ mA}$; $T_{case} = 25\text{ °C}$; unless otherwise specified, in a class-AB production test circuit.

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
P_L	output power		500	-	-	W
V_{DS}	drain-source voltage	$P_L = 500\text{ W}$	-	-	50	V
G_p	power gain	$P_L = 500\text{ W}$	15	17	-	dB
RL_{in}	input return loss	$P_L = 500\text{ W}$	-	10	-	dB
$P_{L(1dB)}$	output power at 1 dB gain compression		-	600	-	W
η_D	drain efficiency	$P_L = 500\text{ W}$	45	50	-	%
$P_{droop(pulse)}$	pulse droop power	$P_L = 500\text{ W}$	-	0	0.3	dB
t_r	rise time	$P_L = 500\text{ W}$	-	20	50	ns
t_f	fall time	$P_L = 500\text{ W}$	-	6	50	ns

6.1 Ruggedness in class-AB operation

The BLL6H1214-500 is capable of withstanding a load mismatch corresponding to $VSWR = 10 : 1$ through all phases under the following conditions: $V_{DS} = 50\text{ V}$; $I_{Dq} = 150\text{ mA}$; $P_L = 500\text{ W}$; $t_p = 300\text{ }\mu\text{s}$; $\delta = 10\text{ }\%$.

7. Application information

7.1 Impedance information

Table 8. Typical impedance

Typical values per section unless otherwise specified.

f GHz	Z_S Ω	Z_L Ω
1.2	1.268 – j2.623	2.987 – j1.664
1.3	2.193 – j2.457	2.162 – j1.326
1.4	2.359 – j2.052	1.604 – j1.887





Fig 1. Definition of transistor impedance

7.2 RF performance


7.2.1 Performance curves measured with $\delta = 10\%$, $t_p = 300 \mu s$ and $T_{hs} = 25^\circ C$



$V_{DS} = 50 V$; $t_p = 300 \mu s$; $\delta = 10\%$; $I_{Dq} = 150 mA$.

- (1) $f = 1200 MHz$
- (2) $f = 1250 MHz$
- (3) $f = 1300 MHz$
- (4) $f = 1350 MHz$
- (5) $f = 1400 MHz$


Fig 2. Output power as a function of input power; typical values



$V_{DS} = 50 V$; $t_p = 300 \mu s$; $\delta = 10\%$; $I_{Dq} = 150 mA$.

- (1) $f = 1200 MHz$
- (2) $f = 1250 MHz$
- (3) $f = 1300 MHz$
- (4) $f = 1350 MHz$
- (5) $f = 1400 MHz$


Fig 3. Power gain as a function of load power; typical values



$V_{DS} = 50\text{ V}$; $t_p = 300\ \mu\text{s}$; $\delta = 10\%$; $I_{Dq} = 150\text{ mA}$.


- (1) $f = 1200\text{ MHz}$
- (2) $f = 1250\text{ MHz}$
- (3) $f = 1300\text{ MHz}$
- (4) $f = 1350\text{ MHz}$
- (5) $f = 1400\text{ MHz}$

Fig 4. Drain efficiency as a function of load power; typical values



$V_{DS} = 50\text{ V}$; $t_p = 300\ \mu\text{s}$; $\delta = 10\%$; $I_{Dq} = 150\text{ mA}$.


Fig 5. Power gain and drain efficiency as function of frequency; typical values



$P_L = 500\text{ W}$; $V_{DS} = 50\text{ V}$; $t_p = 300\ \mu\text{s}$; $\delta = 10\%$; $I_{Dq} = 150\text{ mA}$.


Fig 6. Input return loss as a function of frequency; typical value

7.2.2 Performance curves measured with $\delta = 10\%$, $t_p = 300 \mu s$ and $T_{hs} = 65^\circ C$




$V_{DS} = 50 V$; $t_p = 300 \mu s$; $\delta = 10\%$; $I_{Dq} = 100 mA$.
 (1) $f = 1200 MHz$
 (2) $f = 1300 MHz$
 (3) $f = 1400 MHz$

Fig 7. Output power as a function of input power; typical values




$V_{DS} = 50 V$; $t_p = 300 \mu s$; $\delta = 10\%$; $I_{Dq} = 100 mA$.
 (1) $f = 1200 MHz$
 (2) $f = 1300 MHz$
 (3) $f = 1400 MHz$

Fig 8. Power gain as a function of load power; typical values



$V_{DS} = 50 V$; $t_p = 300 \mu s$; $\delta = 10\%$; $I_{Dq} = 100 mA$.
 (1) $f = 1200 MHz$
 (2) $f = 1300 MHz$
 (3) $f = 1400 MHz$


Fig 9. Drain efficiency as a function of load power; typical values



$P_L = 250 W$; $V_{DS} = 50 V$; $t_p = 300 \mu s$; $\delta = 10\%$; $I_{Dq} = 100 mA$.

Fig 10. Power gain and drain efficiency as function of frequency; typical values


7.2.3 Performance curves measured with $\delta = 10\%$, $t_p = 300\ \mu\text{s}$ and $f = 1300\ \text{MHz}$



$V_{DS} = 50\ \text{V}$; $t_p = 300\ \mu\text{s}$; $\delta = 10\%$; $I_{Dq} = 150\ \text{mA}$; $f = 1300\ \text{MHz}$.

- (1) $T_{hs} = -40^\circ\text{C}$
- (2) $T_{hs} = 25^\circ\text{C}$
- (3) $T_{hs} = 65^\circ\text{C}$


Fig 11. Output power as a function of input power; typical values



$V_{DS} = 50\ \text{V}$; $t_p = 300\ \mu\text{s}$; $\delta = 10\%$; $I_{Dq} = 150\ \text{mA}$; $f = 1300\ \text{MHz}$.

- (1) $T_{hs} = -40^\circ\text{C}$
- (2) $T_{hs} = 25^\circ\text{C}$
- (3) $T_{hs} = 65^\circ\text{C}$

Fig 12. Power gain as a function of load power; typical values




$V_{DS} = 50\ \text{V}$; $t_p = 300\ \mu\text{s}$; $\delta = 10\%$; $I_{Dq} = 150\ \text{mA}$; $f = 1300\ \text{MHz}$.

- (1) $T_{hs} = -40^\circ\text{C}$
- (2) $T_{hs} = 25^\circ\text{C}$
- (3) $T_{hs} = 65^\circ\text{C}$


Fig 13. Drain efficiency as a function of load power; typical values

7.2.4 Performance curves measured with $\delta = 20\%$, $t_p = 500 \mu s$ and $T_{hs} = 25^\circ C$




$V_{DS} = 50 V$; $t_p = 500 \mu s$; $\delta = 20\%$; $I_{Dq} = 150 mA$.
 (1) $f = 1200 MHz$
 (2) $f = 1300 MHz$
 (3) $f = 1400 MHz$

Fig 14. Output power as a function of input power; typical values




$V_{DS} = 50 V$; $t_p = 500 \mu s$; $\delta = 20\%$; $I_{Dq} = 150 mA$.
 (1) $f = 1200 MHz$
 (2) $f = 1300 MHz$
 (3) $f = 1400 MHz$

Fig 15. Power gain as a function of load power; typical values



$V_{DS} = 50 V$; $t_p = 500 \mu s$; $\delta = 20\%$; $I_{Dq} = 150 mA$.
 (1) $f = 1200 MHz$
 (2) $f = 1300 MHz$
 (3) $f = 1400 MHz$


Fig 16. Drain efficiency as a function of load power; typical values



$V_{DS} = 50 V$; $t_p = 500 \mu s$; $\delta = 20\%$; $I_{Dq} = 150 mA$.


Fig 17. Power gain and drain efficiency as function of frequency; typical values

7.2.5 Performance curves measured with $\delta = 20\%$, $t_p = 500 \mu s$ and $T_{hs} = 65^\circ C$




$V_{DS} = 50 V$; $t_p = 500 \mu s$; $\delta = 20\%$; $I_{Dq} = 150 mA$.
 (1) $f = 1200 MHz$
 (2) $f = 1300 MHz$
 (3) $f = 1400 MHz$

Fig 18. Output power as a function of input power; typical values




$V_{DS} = 50 V$; $t_p = 500 \mu s$; $\delta = 20\%$; $I_{Dq} = 150 mA$.
 (1) $f = 1200 MHz$
 (2) $f = 1300 MHz$
 (3) $f = 1400 MHz$

Fig 19. Power gain as a function of load power; typical values



$V_{DS} = 50 V$; $t_p = 500 \mu s$; $\delta = 20\%$; $I_{Dq} = 150 mA$.
 (1) $f = 1200 MHz$
 (2) $f = 1300 MHz$
 (3) $f = 1400 MHz$


Fig 20. Drain efficiency as a function of load power; typical values



$V_{DS} = 50 V$; $t_p = 500 \mu s$; $\delta = 20\%$; $I_{Dq} = 150 mA$.

Fig 21. Power gain and drain efficiency as function of frequency; typical values


7.2.6 Performance curves measured with $\delta = 20\%$, $t_p = 500\ \mu\text{s}$ and $f = 1300\ \text{MHz}$



$V_{DS} = 50\ \text{V}$; $t_p = 500\ \mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\ \text{mA}$; $f = 1300\ \text{MHz}$.

- (1) $T_{hs} = -40\ ^\circ\text{C}$
- (2) $T_{hs} = 25\ ^\circ\text{C}$
- (3) $T_{hs} = 65\ ^\circ\text{C}$


Fig 22. Output power as a function of input power; typical values



$V_{DS} = 50\ \text{V}$; $t_p = 500\ \mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\ \text{mA}$; $f = 1300\ \text{MHz}$.

- (1) $T_{hs} = -40\ ^\circ\text{C}$
- (2) $T_{hs} = 25\ ^\circ\text{C}$
- (3) $T_{hs} = 65\ ^\circ\text{C}$

Fig 23. Power gain as a function of load power; typical values




$V_{DS} = 50\ \text{V}$; $t_p = 500\ \mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\ \text{mA}$; $f = 1300\ \text{MHz}$.

- (1) $T_{hs} = -40\ ^\circ\text{C}$
- (2) $T_{hs} = 25\ ^\circ\text{C}$
- (3) $T_{hs} = 65\ ^\circ\text{C}$


Fig 24. Drain efficiency as a function of load power; typical values

7.2.7 Performance curves measured with $\delta = 10\%$, $t_p = 1\text{ ms}$ and $T_{hs} = 25\text{ }^\circ\text{C}$




$V_{DS} = 50\text{ V}$; $t_p = 500\text{ }\mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\text{ mA}$.
 (1) $f = 1200\text{ MHz}$
 (2) $f = 1300\text{ MHz}$
 (3) $f = 1400\text{ MHz}$

Fig 25. Output power as a function of input power; typical values




$V_{DS} = 50\text{ V}$; $t_p = 500\text{ }\mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\text{ mA}$.
 (1) $f = 1200\text{ MHz}$
 (2) $f = 1300\text{ MHz}$
 (3) $f = 1400\text{ MHz}$

Fig 26. Power gain as a function of load power; typical values



$V_{DS} = 50\text{ V}$; $t_p = 500\text{ }\mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\text{ mA}$.
 (1) $f = 1200\text{ MHz}$
 (2) $f = 1300\text{ MHz}$
 (3) $f = 1400\text{ MHz}$


Fig 27. Drain efficiency as a function of load power; typical values



$V_{DS} = 50\text{ V}$; $t_p = 500\text{ }\mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\text{ mA}$.


Fig 28. Power gain and drain efficiency as function of frequency; typical values

7.2.8 Performance curves measured with $\delta = 10\%$, $t_p = 1\text{ ms}$ and $T_{hs} = 65\text{ }^\circ\text{C}$




$V_{DS} = 50\text{ V}$; $t_p = 500\text{ }\mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\text{ mA}$.
 (1) $f = 1200\text{ MHz}$
 (2) $f = 1300\text{ MHz}$
 (3) $f = 1400\text{ MHz}$

Fig 29. Output power as a function of input power; typical values




$V_{DS} = 50\text{ V}$; $t_p = 500\text{ }\mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\text{ mA}$.
 (1) $f = 1200\text{ MHz}$
 (2) $f = 1300\text{ MHz}$
 (3) $f = 1400\text{ MHz}$

Fig 30. Power gain as a function of load power; typical values



$V_{DS} = 50\text{ V}$; $t_p = 500\text{ }\mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\text{ mA}$.
 (1) $f = 1200\text{ MHz}$
 (2) $f = 1300\text{ MHz}$
 (3) $f = 1400\text{ MHz}$


Fig 31. Drain efficiency as a function of load power; typical values



$V_{DS} = 50\text{ V}$; $t_p = 500\text{ }\mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\text{ mA}$.

Fig 32. Power gain and drain efficiency as function of frequency; typical values


7.2.9 Performance curves measured with $\delta = 10\%$, $t_p = 1\text{ ms}$ and $f = 1300\text{ MHz}$



$V_{DS} = 50\text{ V}$; $t_p = 500\ \mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\text{ mA}$; $f = 1300\text{ MHz}$.

- (1) $T_{hs} = -40^\circ\text{C}$
- (2) $T_{hs} = 25^\circ\text{C}$
- (3) $T_{hs} = 65^\circ\text{C}$


Fig 33. Output power as a function of input power; typical values



$V_{DS} = 50\text{ V}$; $t_p = 500\ \mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\text{ mA}$; $f = 1300\text{ MHz}$.

- (1) $T_{hs} = -40^\circ\text{C}$
- (2) $T_{hs} = 25^\circ\text{C}$
- (3) $T_{hs} = 65^\circ\text{C}$

Fig 34. Power gain as a function of load power; typical values



$V_{DS} = 50\text{ V}$; $t_p = 500\ \mu\text{s}$; $\delta = 20\%$; $I_{Dq} = 150\text{ mA}$; $f = 1300\text{ MHz}$.

- (1) $T_{hs} = -40^\circ\text{C}$
- (2) $T_{hs} = 25^\circ\text{C}$
- (3) $T_{hs} = 65^\circ\text{C}$

Fig 35. Drain efficiency as a function of load power; typical values

8. Test information

Table 9. List of components


For test circuit see [Figure 36](#).

Component	Description	Value	Remarks
C1	multilayer ceramic chip capacitor	22 μ F; 35 V	
C2	multilayer ceramic chip capacitor	51 pF	[1]
C3, C4	multilayer ceramic chip capacitor	100 pF	[1]
C5, C11, C12	multilayer ceramic chip capacitor	1 nF	[2]
C6	multilayer ceramic chip capacitor	47 pF	[1]
C7, C8, C10	multilayer ceramic chip capacitor	51 pF	[3]
C9	multilayer ceramic chip capacitor	100 pF	[3]
C13	electrolytic capacitor	10 μ F; 63 V	
R1	SMD resistor	56 Ω	0603
R2	metal film resistor	51 Ω	

[1] American Technical Ceramics type 100A or capacitor of same quality.

[2] American Technical Ceramics type 100B or capacitor of same quality.

[3] American Technical Ceramics type 800B or capacitor of same quality.



001aa/490

Printed-Circuit Board (PCB): Duroid 6006; $\epsilon_r = 6.15$ F/m; thickness = 0.64 mm; thickness copper plating = 35 μ m.

See [Table 9](#) for a list of components.

Fig 36. Component layout for class-AB production test circuit

9. Package outline

Flanged balanced LDMOST ceramic package; 2 mounting holes; 4 leads

SOT539A




Fig 37. Package outline SOT539A

10. Abbreviations

Table 10. Abbreviations

Acronym	Description
LDMOS	Laterally Diffused Metal-Oxide Semiconductor
LDMOST	Laterally Diffused Metal-Oxide Semiconductor Transistor
RF	Radio Frequency
SMD	Surface Mounted Device
L-band	Long wave Band
VSWR	Voltage Standing-Wave Ratio

11. Revision history

Table 11. Revision history

Document ID	Release date	Data sheet status	Change notice	Supersedes
BLL6H1214-500_2	20100401	Product data sheet	-	BLL6H1214-500_1
Modifications:	<ul style="list-style-type: none"> • The format of this data sheet has been redesigned to comply with the new identity guidelines of NXP Semiconductors. • Legal texts have been adapted to the new company name where appropriate. • The status of this data sheet has been changed to "Product data sheet" • Added Section 7.2.3 on page 8. • Added Section 7.2.4 on page 9. • Added Section 7.2.5 on page 10. • Added Section 7.2.6 on page 11. • Added Section 7.2.7 on page 12. • Added Section 7.2.8 on page 13. • Added Section 7.2.9 on page 14. 			
BLL6H1214-500_1	20090120	Objective data sheet	-	-

12. Legal information

12.1 Data sheet status

Document status ^{[1][2]}	Product status ^[3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions".

[3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL <http://www.nxp.com>.

12.2 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between NXP Semiconductors and its customer, unless NXP Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the NXP Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

12.3 Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in medical, military, aircraft, space or life support equipment, nor in applications where failure or

malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors accepts no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on a weakness or default in the customer application/use or the application/use of customer's third party customer(s) (hereinafter both referred to as "Application"). It is customer's sole responsibility to check whether the NXP Semiconductors product is suitable and fit for the Application planned. Customer has to do all necessary testing for the Application in order to avoid a default of the Application and the product. NXP Semiconductors does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at <http://www.nxp.com/profile/terms>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from national authorities.

Non-automotive qualified products — Unless this data sheet expressly states that this specific NXP Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. NXP Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without NXP Semiconductors' warranty of the

product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond NXP Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies NXP Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond NXP Semiconductors' standard warranty and NXP Semiconductors' product specifications.

12.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

13. Contact information

For more information, please visit: <http://www.nxp.com>

For sales office addresses, please send an email to: salesaddresses@nxp.com

14. Contents

1	Product profile	1
1.1	General description	1
1.2	Features and benefits	1
1.3	Applications	2
2	Pinning information	2
3	Ordering information	2
4	Limiting values	2
5	Thermal characteristics	3
6	Characteristics	3
6.1	Ruggedness in class-AB operation	3
7	Application information	4
7.1	Impedance information	4
7.2	RF performance	5
7.2.1	Performance curves measured with $\delta = 10\%$, $t_p = 300\ \mu\text{s}$ and $T_{hs} = 25\ ^\circ\text{C}$	5
7.2.2	Performance curves measured with $\delta = 10\%$, $t_p = 300\ \mu\text{s}$ and $T_{hs} = 65\ ^\circ\text{C}$	7
7.2.3	Performance curves measured with $\delta = 10\%$, $t_p = 300\ \mu\text{s}$ and $f = 1300\ \text{MHz}$	8
7.2.4	Performance curves measured with $\delta = 20\%$, $t_p = 500\ \mu\text{s}$ and $T_{hs} = 25\ ^\circ\text{C}$	9
7.2.5	Performance curves measured with $\delta = 20\%$, $t_p = 500\ \mu\text{s}$ and $T_{hs} = 65\ ^\circ\text{C}$	10
7.2.6	Performance curves measured with $\delta = 20\%$, $t_p = 500\ \mu\text{s}$ and $f = 1300\ \text{MHz}$	11
7.2.7	Performance curves measured with $\delta = 10\%$, $t_p = 1\ \text{ms}$ and $T_{hs} = 25\ ^\circ\text{C}$	12
7.2.8	Performance curves measured with $\delta = 10\%$, $t_p = 1\ \text{ms}$ and $T_{hs} = 65\ ^\circ\text{C}$	13
7.2.9	Performance curves measured with $\delta = 10\%$, $t_p = 1\ \text{ms}$ and $f = 1300\ \text{MHz}$	14
8	Test information	15
9	Package outline	16
10	Abbreviations	17
11	Revision history	17
12	Legal information	18
12.1	Data sheet status	18
12.2	Definitions	18
12.3	Disclaimers	18
12.4	Trademarks	19
13	Contact information	19
14	Contents	20

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

© NXP B.V. 2010.

All rights reserved.

For more information, please visit: <http://www.nxp.com>

For sales office addresses, please send an email to: salesaddresses@nxp.com

Date of release: 1 April 2010

Document identifier: BLL6H1214-500_2