

COLLMER SEMICONDUCTOR

**14368 PROTON ROAD
DALLAS, TEXAS 75244**

1-800-527-8251

214-233-1589

1 High speed switching transistors

- Suitable for 50kHz class switching regulators.
- Allows transformers to be reduced in size.

Device type	V _{CEO} volts	V _{CEO} volts	V _{CEO} (sus) volts	I _c cont. amps.	P _c watts	h _{FE} min.	I _c amps.	V _{CE} volts	Switching time (Typical)	Package	Net weight grams
2SC2929	500	400	400	3	60	20	0.5	5	0.5 1.0 0.3	TO-220AB	2
2SC2767	300	200	200	5	60	20	1	5	0.5 1.0 0.5	TO-220AB	2
2SC2243	650	400	400	5	120	10	2	5	0.5 1.0 0.3	TO-3	17
2SC2542	650	400	400	5	60	10	2	5	0.5 1.0 0.3	TO-220AB	2
2SC2624	650	400	400	5	100	10	2	5	0.5 1.0 0.3	TO-3P	6
2SC2769	300	200	200	10	100	20	2	5	0.5 1.0 0.3	TO-3P	6
2SC2245	650	400	400	10	120	10	4	5	0.5 1.0 0.3	TO-3	17
2SC2625	650	400	400	10	100	10	2	5	0.5 1.0 0.3	TO-3P	6
2SC2246	650	400	400	15	120	10	6	5	0.5 1.0 0.3	TO-3	17
2SC2623	650	400	400	20	120	10	8	5	0.5 1.0 0.3	TO-3	17
2SC3047	850	500	500	6	40	15	0.5	5	0.5 1.0 0.4	TO-220AB	2
ET206	850	500	500	10	80	15	1	5	0.5 1.5 0.3	TO-3P	6

2 Super high speed switching transistors

- t_{on}: 0.2μsec., t_f: 0.07μsec.
- Suitable for 100KHz class switching regulators

Device type	V _{CBO} volts	V _{CEO} volts	V _{CEO} (sus) volts	I _c cont. amps.	P _c watts	h _{FE} min.	I _c amps.	V _{CE} volts	Switching time (Typical)	Package	Net weight grams
2SC3317	600	400	400	5	60	10	2	5	0.2 1.0 0.07	TO-220AB	2
2SC3318	600	400	400	10	100	10	5	5	0.2 1.0 0.07	TO-3P	6
2SC3319	600	400	400	10	120	10	5	5	0.2 1.0 0.07	TO-3	17
2SC3320	600	400	400	15	100	10	6	5	0.2 1.0 0.07	TO-3P	6
2SC3321	600	400	400	15	120	10	6	5	0.2 1.0 0.07	TO-3	17

3 Large SOA switching transistors

- An especially wide SOA with high-speed switching.
- Excellent surge resistant characteristics
- Suitable for switching regulators, series regulators, electronic ignitors and similar devices.

Device type	V _{CBO} volts	V _{CEO} volts	V _{CEO} (sus) volts	I _c cont. amps.	P _c watts	h _{FE} min.	I _c amps.	V _{CE} volts	Switching time (Typical)	Package	Net weight grams
2SC2437	650	400	400	7	120	10	3	4	1.0 2.0 1.0	TO-3	18
2SC2656	650	400	400	7	100	10	3	4	1.0 2.0 1.0	TO-3P	6

COLLMER SEMICONDUCTOR, INC.
14368 PROTON ROAD
DALLAS, TEXAS 75244
1-800-527-0251 **214-233-1589**

4 High voltage high speed switching transistors

- The V_{CBO} is 900 volts and the transistor is best suited for use with 240VAC input switching regulators.
- Switching time is t_f : $0.8\mu s$.
- Can operate within the 30kHz range.

Device type	V_{CBO} volts	V_{CEO} volts	V_{CEO} (sus) volts	I_c cont. amps.	P_c watts	h_{FE} min.	I_c amps.	V_{CE} volts	Switching time (Max.)	Package	Net weight grams	Darling-ton
2SC3030	900	800	800	7	80	8	3	5	0.5 2.5 0.8	TO-3P	6	Fig. I
2SC3031	900	800	800	7	80	8	3	5	0.5 2.5 0.8	TO-3	17	Fig. I
2SC3032	900	700	700	7	80	8	3	5	0.5 2.5 0.8	TO-3P	6	Fig. I
2SC3033	900	700	700	7	80	8	3	5	0.5 2.5 0.8	TO-3	17	Fig. I
2SC3549	900	800	800	3	40	10	1	5	1.0 4.0 0.8	TO-220AB	2	—
2SC3550	900	800	800	3	80	10	1	5	1.0 4.0 0.8	TO-3P	6	—
2SC3551	900	800	800	5	80	10	2	5	1.0 4.0 0.8	TO-3P	6	—

5 Low voltage high current switching transistors

- High speed switching performance
- V_{CEO} (sus): 80 – 120 volts
- I_c cont: 25 Amps
- Suitable for motor control applications such as DC-DC converters, golf carts, fork-lifts and industrial sewing machines using battery power supply.

Device type	V_{CBO} volts	V_{CEO} volts	V_{CEO} (sus) volts	I_c cont. amps.	P_c watts	h_{FE} min.	I_c amps.	V_{CE} volts	Switching time (Max.)	Package	Net weight grams
2SD913	200	80	80	25	150	20	25	5	0.5 1.5 0.2	TO-3	19
2SD1049	120	80	80	25	100	25	25	5	0.5 1.5 0.2	TO-3P	6
2SD914	200	120	120	25	150	20	25	5	0.5 1.5 0.2	TO-3	19

6 Ultra high β transistors (UBT)

- The DC current gain is extraordinarily high (min. 700).
- h_{FE} – I_c characteristics are linear.
- Transistors for drive use not required.
- Ideally suited for series regulators, color TV, power supplies and similar devices.

Device type	V_{CBO} volts	V_{CEO} volts	V_{CEO} (sus) volts	I_c cont. amps.	P_c watts	h_{FE} min.	I_c amps.	V_{CE} volts	Switching time (Max.)	Package	Net weight grams	Darling-ton
2SD1128	150	100	100	5	40	700	1	4	— — —	TO-220AB	2	Fig. E
2SD920	250	200	200	5	120	700	1	4	— — —	TO-3	17	Fig. E
2SD921	250	200	200	5	100	700	1	4	— — —	TO-3P	6	Fig. E
2SD929	250	200	200	5	100	700	1	4	— — —	TO-3	17	Fig. E
2SD930	250	200	200	5	40	700	0.7	4	— — —	TO-220AB	2	Fig. E
2SD931	250	200	200	5	60	700	1	4	— — —	TO-3	17	Fig. E
2SD981	250	200	200	5	150	700	1	4	— — —	TO-3	13	Fig. E
2SD982	250	200	200	5	60	700	1	4	— — —	TO-220AB	2	Fig. E
2SD983	150	100	100	6	60	700	1	4	— — —	TO-220AB	2	Fig. E
2SD922	150	100	100	10	120	700	3	4	— — —	TO-3	17	Fig. E
2SD923	150	100	100	10	100	700	1	4	— — —	TO-3P	6	Fig. E

Darlington circuit schematic: See page 21