

Power TransformerFor Maxim MAX5074 Isolated PWM Power IC



The C0984-CL transformer is designed specifically for the Maxim MAX5074 isolated PWM power IC in a forward DC-DC converter. It can be used in power supplies for IEEE 802.3af-compliant PoE applications, IP phones, WLAN Access-Points and a variety of other telecom applications with an input voltage range from 36 V to 72 V.

This transformer features very low secondary winding DCR and 1500 Vrms isolation from the primary and bias windings to the secondary.

Coilcraft can also custom engineer a transformer to meet your specific requirements. For free evaluation samples, contact Coilcraft or visit **www.coilcraft.com**.

| Part number ¹ | Power | Inductance ² min (µH) | DCR max (Ohms) | | | Leakage inductance ³ | Turns ratio | | |
|-----------------------------|-------|-------------------------------------|----------------|-------|-------|------------------------------------|-------------|----------|---------------------|
| | | | pri | sec | bias | max (µH) | pri:sec | pri:bias | Output |
| C0984-CL_ | 18 W | 395 | 0.127 | 0.065 | 0.875 | 1.75 | 1:0.88 | 1:0.44 | 12 V, 1.5 A (sec) |
| | | | | | | | | | 14 V, 0.03 A (bias) |

1. When ordering, please specify a packaging code:

C0984-CLD



- B = Less than full reel. In tape, but not machine ready. To have a leader and trailer added (\$25 charge), use code letter D instead.
- Inductance is for the primary, measured at 10 kHz, 0.1 Vrms, 0 Adc.
 Leakage inductance is for the primary winding with the other windings

shorted. 4. Operating temperature range -40° C to $+125^{\circ}$ C.

5. Electrical specifications at 25°C.

Refer to Doc 362 "Soldering Surface Mount Components" before soldering.



www.coilcraft.com

Taiwan +886-2-2264 3646 sales@coilcraft.com.tw China +86-21-6218 8074 sales@coilcraft.com.cn Singapore + 65-6484 8412 sales@coilcraft.com.sg

This product may not be used in medical or high risk applications without prior Coilcraft approval Specification subject to change without notice Please check web site for latest information