


**LA5540****Motor Driver with Regulator, Brake****Features**

- Regulated power supply for motor drive.
- On-chip brake circuit.
- Small-sized package and minimum number of external parts required.

Package Dimensions

unit:mm

3027A-SIP4H**Specifications****Maximum Ratings at Ta = 25°C**

Parameter	Symbol	Conditions	Ratings	Unit
Maximum input voltage	$V_{IN \max}$		20	V
Maximum output current	$I_O \max$	$V_{IN}=10V$, Duty \leq 6%, $t_{ON}=20ms$	2.0	A
Allowable power dissipation	$P_d \max$		1.2	W
Operating temperature	T_{opr}		-20 to +80	°C
Storage temperature	T_{stg}		-30 to +125	°C

Operating Conditions at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Input voltage	V_{IN}		-0.3 to +20	V
MT high level voltage	$V_{MT(H)}$		3 to 20	V
MT low level voltage	$V_{MT(L)}$		-0.3 to +0.7	V

■ Any and all SANYO products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO representative nearest you before using any SANYO products described or contained herein in such applications.

■ SANYO assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO products described or contained herein.

SANYO Electric Co., Ltd. Semiconductor Business Headquarters

TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110-8534 JAPAN


LA5540

Operating Characteristics at $T_a = 25^\circ\text{C}$, $V_{IN}=9\text{V}$, $I_O=200\text{mA}$, $C_O=1\mu\text{F}$


Parameter	Symbol	Conditions	Test Circuit	Ratings			Unit
				min	typ	max	
Output voltage	V_O		1	5.2	5.6	6.0	V
Line regulation	$\Delta V_O \text{ LINE}$	$7.5\text{V} < V_{IN} < 20\text{V}$	2			100	mV
Load regulation	$\Delta V_O \text{ LOAD}$	$10\text{mA} < I_O < 1.0\text{A}$	3			100	mV
Quiescent current	$I_{CC \text{ ON}}$	$V_{MT}=3\text{V}$	4		1.6	3.0	mA
	$I_{CC \text{ OFF}}$	$V_{MT}=0\text{V}$	4		0.3	0.6	mA
Input-output voltage difference		$\Delta V_O=5\%$	5			1.0	V
MT input current	I_{MT}	$V_{MT}=6\text{V}$	6	0.3	0.5	0.9	mA
Breake residual voltage	V_{SAT1}	$I_O=-500\text{mA}$	7			1.2	V
	V_{SAT2}	$I_O=-800\text{mA}$	7			1.4	V

Test Circuits


1. Output Voltage V_O




2. Line Regulation $\Delta V_O \text{ LINE}$




3. Load Regulation $\Delta V_O \text{ LOAD}$




4. Quiescent Current $I_{CC \text{ ON}}, I_{CC \text{ OFF}}$




5. Input-Output Voltage Diff




6. MT Input Current I_{MT}







7. Brake Residual Voltage V_{SAT}



Block Diagram and Sample Application Circuit



MT	V_O	Remarks
H	5.6V typ	Regulator
L	0V	Brake



- Specifications of any and all SANYO products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Electric Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any and all SANYO products described or contained herein fall under strategic products (including services) controlled under the Foreign Exchange and Foreign Trade Control Law of Japan, such products must not be exported without obtaining export license from the Ministry of International Trade and Industry in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Electric Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only ; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of July, 1998. Specifications and information herein are subject to change without notice.