


LMS1B

Low Profile Surface Mount Schottky Bridge Rectifiers Reverse Voltage 100V Output Current 1A

Features

- Low profile, Max Height 1.30mm
- Low forward voltage drop
- Super Low VF Schottky barrier bridge rectifiers
- Moisture sensitivity: level 1, per J-STD-020
- Halogen-free according to IEC 61249-2-21 definition
- High temperature soldering guaranteed: 260°C/10 seconds



LPMB

Typical Applications

For use of fast swiching in RF module, lighting, cellular phone, portable device, power supplies and other consumer applications.

Maximum Ratings (TA = 25 °C unless otherwise noted)							
Parameter	Symbol	LMS1B	Unit				
Maximum repetitive peak reverse voltage	VRRM	100	V				
Maximum RMS voltage	VRMS	70	V				
Maximum DC blocking voltage	VDC	100	V				
Maximum average output rectified current	Io(AV) ¹⁾	1.0	Α				
Peak forward surge current 8.3 ms single half sine- wave superimposed on rated load	IFSM	30	А				
Operating junction temperature range	T_J	- 55 to + 150	°C				
Storage temperature range	T _{STG}	- 55 to + 150	°C				

Electrical Characteristics (TA = 25 °C unless otherwise noted)							
Parameter	Test Conditions	Symbol	LMS1B	Unit			
Maximum instantaneous forward voltage	IF=0.5A,TA=25℃	V _F	0.75	Volts			
Maximum DC reverse current at rated DC blocking voltage	TA=25°C	I _R	200	uA			
Typical thermal resistance ¹⁾	juntion to ambient	$R_{\theta,JA}$	50	°C/W			

Notes:

^{1.} On glass epoxy PCB, mounted on 1.3*1.3mm solder pads

Low Profile Surface Mount Schottky Bridge Rectifiers Reverse Voltage 100V Output Current 1A

Ratings and Characteristics Curves

(TA = 25°C unless otherwise noted)




Figure 1.Output Rectifier Current Derating Curve




Figure 3. Typical Instantaneous Forward Characteristics




Figure 2.Maximum Non-Repetitive Peak Forward Surge Current





Figure 4. Typical Reverse Characteristics

Low Profile Surface Mount Schottky Bridge Rectifiers Reverse Voltage 100V Output Current 1A


Package Outline Dimensions



DIM	Unit: mm		Unit: inch		
	MIN	MAX	MIN	MAX	
Α	1.2	1.3	0.047	0.051	
A1	0	0.1	0.000	0.004	
В	0.5	0.75	0.020	0.030	
С	0.1	0.25	0.004	0.010	
D	2.54	typ.	0.10 typ.		
E1	4.7	4.9	0.185	0.193	
E2	4.7	4.9	0.185	0.193	
L	0.4	0.7	0.016	0.028	
HE	6.65	6.95	0.262	0.274	

Mounting pad layout in mm(inch)






Packing Information

Packing quantities:

4000 pcs/Reel, 15 Reels/Box; 12mm Tape, 13" Reel

Tape & Reel Specification





Low Profile Surface Mount Schottky Bridge Rectifiers

Reverse Voltage 100V Output Current 1A

Disclaimers

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page.(http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.