



SMBRP3045

Schottky Barrier Rectifier

Reverse Voltage 45 Volts Forward Current 30 Amperes


Features

Ultra Low $V_f=0.38V$ at $I_F=10A$ (25°C)/ $V_f=0.50 V$ at $I_F=30A$ (25°C)

- Thin Package:1.0mm
- Low forward voltage drop, low power losses
- High efficiency operation
- Halogen Free Plastic package has underwriters Laboratory Flammability Classification 94V-0

Mechanical Data

- Case: Epoxy, Molded
- Weight: 0.1grams (approximately)
- Finish: All External Surfaces Corrosion Resistant and Terminal Leads are Readily Solderable
- Lead Temperature for Soldering Purposes: 260°C Max. for 10 sec
- Shipped 3000 units per reel



Package: POWER QFN5x6

Maximum Ratings & Electrical Characteristics

($T_A=25^{\circ}C$ unless otherwise noted)

PARAMETER		TEST CONDITIONS		SYMBOL	SMBRP3045	UNIT
Maximum repetitive peak reverse voltage				V_{RRM}	45	V
Working peak reverse voltage				V_{RWM}	45	V
Maximum DC blocking voltage				V_{DC}	45	V
Maximum average forward rectified current at $T_c=105^{\circ}C$ total device per diode				$I_F(AV)$	30	A
Peak forward surge current 8.3ms single half sine-wave superimposed on rated load per diode				I_{FSM}	200	A
Peak repetitive reverse current per leg at $t_p=2.0\mu s$, 1KHz				I_{RRM}	2.0	A
Operating junction temperature range				T_J	-55 to +150	$^{\circ}C$
Storage temperature range				T_{STG}	-55 to +150	$^{\circ}C$
Maximum instantaneous forward voltage per leg		$I_F=30A$ $I_F=30A$	$T_C=25^{\circ}C$ $T_C=125^{\circ}C$	V_F	0.55(0.50 TYP) 0.48	V
Maximum reverse current per leg at working peak Reverse voltage			$T_J=25^{\circ}C$ $T_J=100^{\circ}C$	I_R	500 50	μA mA
Thermal Characteristics $T_A=25^{\circ}C$ unless otherwise noted						
Symbol	Parameter	TYP (POWER QFN 5x6)				Unit
R θ JC	Thermal Resistance, Junction to Case per Leg	2.5				$^{\circ}C/W$
R θ JA	Thermal Resistance, Junction to Ambient per Leg	50				$^{\circ}C/W$

Note: Pulse test:300us pulse width, duty cycle=2%







SMBRP3045

Schottky Barrier Rectifier

Reverse Voltage 45 Volts Forward Current 30 Amperes

Ratings and Characteristics Curves

($T_A = 25^\circ\text{C}$ unless otherwise noted)





SMBRP3045


Schottky Barrier Rectifier

Reverse Voltage 45 Volts Forward Current 30 Amperes

Package Outline Dimensions

Unit: millimeters

POWER QFN 5x6





SMBRP3045

Schottky Barrier Rectifier

Reverse Voltage 45 Volts Forward Current 30 Amperes

Disclaimers

These materials are intended as a reference to assist our customers in the selection of the Suzhou Goo-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd. or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page.
(<http://www.goodark.com>)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.