

# BSS80B,C

CASE 318-02/03, STYLE 6  
SOT-23 (TO-236AA/AB)

GENERAL PURPOSE TRANSISTOR

PNP SILICON

## MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Collector-Emitter Voltage	$V_{CEO}$	40	Vdc
Collector-Base Voltage	$V_{CBO}$	60	Vdc
Emitter-Base Voltage	$V_{EBO}$	5.0	Vdc
Collector Current — Continuous	$I_C$	800	mA

## THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
*Total Device Dissipation, $T_A = 25^\circ\text{C}$ Derate above $25^\circ\text{C}$	$P_D$	350 2.8	mW mW/ $^\circ\text{C}$
Storage Temperature	$T_{stg}$	150	$^\circ\text{C}$
*Thermal Resistance Junction to Ambient	$R_{\theta JA}$	357	$^\circ\text{C/W}$

\*Package mounted on 99.5% alumina  $10 \times 8 \times 0.6$  mm.

## ELECTRICAL CHARACTERISTICS ( $T_A = 25^\circ\text{C}$ unless otherwise noted.)

Characteristic	Symbol	Min	Max	Unit
----------------	--------	-----	-----	------

### OFF CHARACTERISTICS

Collector-Emitter Breakdown Voltage ( $I_C = 10$ mA)	$V_{(BR)CEO}$	40	—	Vdc
Collector-Base Breakdown Voltage ( $I_C = 10$ $\mu\text{A}$ )	$V_{(BR)CBO}$	60	—	Vdc
Emitter-Base Breakdown Voltage ( $I_E = 10$ $\mu\text{A}$ )	$V_{(BR)EBO}$	5.0	—	Vdc
Collector Cutoff Current ( $V_{CB} = 50$ Vdc) ( $V_{CB} = 50$ Vdc, $T_A = 150^\circ\text{C}$ )	$I_{CBO}$	—	10 10	nA $\mu\text{A}$
Emitter Cutoff Current ( $V_{BE} = 3.0$ Vdc)	$I_{EBO}$	—	10	nA

### ON CHARACTERISTICS

DC Current Gain ( $I_C = 150$ mA, $V_{CE} = 10$ Vdc)	B C	$h_{FE}$	40 100	120 300	—
Collector-Emitter Saturation Voltage ( $I_C = 150$ mA, $I_B = 15$ mA) ( $I_C = 500$ mA, $I_B = 50$ mA)		$V_{CE(sat)}$	— —	0.4 1.6	Vdc

### SMALL-SIGNAL CHARACTERISTICS

Current-Gain — Bandwidth Product ( $I_C = 50$ mA, $V_{CE} = 20$ Vdc, $f = 100$ MHz)		$f_T$	200	—	MHz
Output Capacitance ( $V_{CB} = 10$ Vdc, $f = 1.0$ MHz)		$C_{obo}$	—	8.0	pF

### SWITCHING CHARACTERISTICS

Delay Time	( $I_{B1} \approx I_{B2} \approx 15$ mA, $V_{CC} = 30$ V, $I_C = 150$ mA)	$t_d$	—	10	ns
Rise Time		$t_r$	—	40	ns
Storage Time	( $I_{B1} \approx I_{B2} \approx 15$ mA, $V_{CC} = 30$ V, $I_C = 150$ mA)	$t_s$	—	80	ns
Fall Time		$t_f$	—	30	ns

(1) Pulse Test: Pulse Width  $\leq 300$   $\mu\text{s}$ , Duty Cycle  $\leq 2.0\%$ .