

1N4001WA~1N4007WA

RECTIFIER DIODE

REVERSE VOLTAGE 50V TO 1000V FORWARD CURRENT 1A

DESCRIPTION

FEATURES

The 1N4001WA~1N4007WA are available in ● Available in SOD-123FL package SOD-123FL package

ORDERING INFORMATION

Package Type	Part Number
SOD-123FL	1N4001WA
	1N4002WA
	1N4003WA
	1N4004WA
	1N4005WA
	1N4006WA
	1N4007WA
Note	SPQ: 3,000pcs/Reel

AiT provides all RoHS Compliant Products

PIN DESCRIPTION



REV1.0 - APR 2017 RELEASED - - 1 -

1N4001WA~1N4007WA

RECTIFIER DIODE

REVERSE VOLTAGE 50V TO 1000V FORWARD CURRENT 1A

ABSOLUTE MAXIMUM RATINGS

Ratings at 25°C ambient temperature unless otherwise specified. Single phase half-wave 60 Hz, resistive or inductive load, for capacitive load current derate by 20 %.

Paramete	r	Symbol	1N4001WA	1N4002WA	1N4003WA	1N4004WA	1N4005WA	1N4006WA	1N4007WA	Unit
Maximum Repetitive Peak		V _{RRM}	50	100	200	400	600	800	1000	V
Reverse Voltage										
Maximum RMS Volta	V_{RMS}	35	70	140	280	420	560	700	V	
Maximum DC Blockin	Maximum DC Blocking Voltage			100	200	400	600	800	1000	V
Maximum Average Forward		I _{F(AV)}	1							Α
Rectified Current at T	Rectified Current at T _A =65°C			, 						
Peak Forward Surge										
8.3ms Single Half Sir	١.	25							А	
Superimposed on Rated Load										I _{FSM}
(JEDEC Method)										
Maximum Instantaneous Forward		.,,	4.4							\ \/
Voltage at 1A		VF	V _F 1.1							V
Maximum DC										
Reverse Current	verse Current T _A =25°C		5							
at Rated DC	T _A =125°C	I _R	100						uA	
Blocking Voltage										
Typical Junction Capacitance		Cj	4						рF	
Typical Thermal Resi	Reja	180					°C/W			
Operating and Storage		TJ,	-55 ~+150							°C
Temperature Range		Tstg								

NOTE1: Measured at 1MHz and applied reverse voltage of 4 V D.C.

NOTE2: Thermal resistance from junction to ambient at 0.375" (9.5 mm) lead length, P.C.B. mounted

REV1.0 - APR 2017 RELEASED - - 2 -



TYPICAL CHARACTERISTICS

Figure. 1 Forward Current Derating Curve




Figure. 3 Typical Forward Characteristic




Figure. 2 Typical Instantaneous Reverse Characteristics






Figure. 4 Typical Junction Capacitance




REV1.0 - APR 2017 RELEASED -- 3 -

Recommended Condition of Flow Soldering



Recommended Condition of Reflow Soldering



Recommended peak temperature is over 245°C. If peak temperature is below 245°C, you may adjust the following parameters; time length of peak temperature(longer), time length of soldering (longer), thickness of solder paste (thicker)

Condition of hand soldering

Temperature: 370°C

Time: 3s max.
Times: one time

Remark:


Lead free solder paste (96.5Sn/3.0Ag/5Cu)


REV1.0 - APR 2017 RELEASED - - 4 -

PACKAGE INFORMATION


Dimension in SOD-123FL (Unit: mm)

Plastic surface mounted package; 2 leads





The recommended mounting pad size



Unit: mm (mil)

UN	NIT	Α	С	D	Е	е	g	HE	4
mm	Max	1.1	0.20	2.9	1.9	1.1	0.9	3.8	
	Min	0.9	0.12	2.6	1.7	0.8	0.7	3.5	7°
mil	Max	43	7.9	114	75	43	35	150	1
	Min	35	4.7	102	67	31	28	138	

REV1.0 - APR 2017 RELEASED - - 5 -



1N4001WA~1N4007WA

RECTIFIER DIODE

REVERSE VOLTAGE 50V TO 1000V FORWARD CURRENT 1A

IMPORTANT NOTICE

AiT Semiconductor Inc. (AiT) reserves the right to make changes to any its product, specifications, to discontinue any integrated circuit product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

AiT Semiconductor Inc.'s integrated circuit products are not designed, intended, authorized, or warranted to be suitable for use in life support applications, devices or systems or other critical applications. Use of AiT products in such applications is understood to be fully at the risk of the customer. As used herein may involve potential risks of death, personal injury, or servere property, or environmental damage. In order to minimize risks associated with the customer's applications, the customer should provide adequate design and operating safeguards.

AiT Semiconductor Inc. assumes to no liability to customer product design or application support. AiT warrants the performance of its products of the specifications applicable at the time of sale.

REV1.0 - APR 2017 RELEASED - - 6 -