Note: This datasheet may be out of date.

Please download the latest datasheet of BLM15AG700SN1# from the official website of Murata Manufacturing.

Co., Ltd.

https://www.murata.com/en-sg/products/productdetail?partno=BLM15AG700SN1%23

# BLM15AG700SN1#

"#" indicates a package specification code.







< List of part numbers with package codes >

BLM15AG700SN1B BLM15AG700SN1D BLM15AG700SN1J



## Appearance & Shape













The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.
BLM series is effective in circuits without stable ground lines because BLM series does not need a

connection to ground.
The nickel barrier structure of the external electrodes provides excellent solder heat resistance.
BLM\_Aseries generates an impedance from the relatively low frequencies. Therefore BLM\_Aseries is effective in noise suppression in a wide frequency

range (30MHz to several hundred MHz).



## **Applications**

Other Usage

For general



# **Packaging Information**

Packaging	Specifications	Minimum Order Quantity
В	Bulk(Bag)	1000
D	180mm Paper Tape	10000
J	330mm Paper Tape	50000

1 of 3

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2017/11/26



Co., Ltd. https://www.murata.com/en-sg/products/productdetail?partno=BLM15AG700SN1%23

### $\underline{ Please \ download \ the \ latest \ data sheet \ of \ BLM15AG700SN1\# \ from \ the \ official \ website \ of \ Murata \ Manufacturing} }$

# BLM15AG700SN1#

"#" indicates a package specification code.

Note: This datasheet may be out of date



Shape	SMD
Size Code (in mm)	1005
Size Code (in inch)	0402
Length	1.0mm
Length Tolerance	±0.05mm
Width	0.5mm
Width Tolerance	±0.05mm
Thickness	0.5mm
Thickness Tolerance	±0.05mm
Impedance (at 100MHz)	70Ω
Impedance (at 100MHz) Tolerance	(Тур.)
Rated Current (at 85°C)	600mA
Rated Current (at 125℃)	600mA
DC Resistance(max.)	0.15Ω
Operating Temperature Range	-55℃ to 125℃
Mass(typ.)	0.001g
Number of Circuit	1

2 of 3

### Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2017/11/26

<sup>1.</sup> This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.


Note: This datasheet may be out of date.  $\underline{ Please \ download \ the \ latest \ data sheet \ of \ BLM15AG700SN1\# \ from \ the \ official \ website \ of \ Murata \ Manufacturing} }$ 


Co., Ltd. https://www.murata.com/en-sg/products/productdetail?partno=BLM15AG700SN1%23

# BLM15AG700SN1#

"#" indicates a package specification code.







Impedance-Frequency Characteristics

**Equivalent Circuit** 

3 of 3

### Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

<sup>1.</sup> This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.