

NIKO-SEM**Dual N-Channel Enhancement Mode
Field Effect Transistor****PE6R8DX**

PDFN 3x3P

Halogen-Free & Lead-Free

PRODUCT SUMMARY



$V_{(BR)DSS}$	$R_{DS(ON)}$	I_D
40V	15.5m Ω	24A

**Features**

- Pb-Free, Halogen Free and RoHS compliant.
- Low $R_{DS(on)}$ to Minimize Conduction Losses.
- Ohmic Region Good $R_{DS(on)}$ Ratio.
- Optimized Gate Charge to Minimize Switching Losses.

Applications

- Protection Circuits Applications.
- Portable Devices for Battery PACK Applications.



G : GATE
D : DRAIN
S : SOURCE

ABSOLUTE MAXIMUM RATINGS ($T_A = 25^\circ\text{C}$ Unless Otherwise Noted)

PARAMETERS/TEST CONDITIONS	SYMBOL	LIMITS	UNITS
Drain-Source Voltage	V_{DS}	40	V
Gate-Source Voltage	V_{GS}	± 20	V
Continuous Drain Current	I_D	24	A
		15	
		6	
		4.8	
Pulsed Drain Current ¹	I_{DM}	45	
Avalanche Current	I_{AS}	21	
Avalanche Energy	E_{AS}	22	mJ
Power Dissipation	P_D	28	W
		11	
		1.7	
		1	
Operating Junction & Storage Temperature Range	T_j, T_{stg}	-55 to 150	°C

THERMAL RESISTANCE RATINGS

THERMAL RESISTANCE	SYMBOL	TYPICAL	MAXIMUM	UNITS
Junction-to-Ambient ²	$R_{\theta JA}$	75	4.5	°C / W
Junction-to-Case	$R_{\theta JC}$			

¹Pulse width limited by maximum junction temperature.

²The value of $R_{\theta JA}$ is measured with the device mounted on 1in² FR-4 board with 2oz. Copper, in a still air environment with $T_A = 25^\circ\text{C}$

NIKO-SEM
**Dual N-Channel Enhancement Mode
Field Effect Transistor**
PE6R8DX

PDFN 3x3P

Halogen-Free & Lead-Free

ELECTRICAL CHARACTERISTICS ($T_J = 25^\circ\text{C}$, Unless Otherwise Noted)

PARAMETER	SYMBOL	TEST CONDITIONS	LIMITS			UNIT
			MIN	TYP	MAX	
STATIC						
Drain-Source Breakdown Voltage	$V_{(\text{BR})\text{DSS}}$	$V_{\text{GS}} = 0\text{V}, I_D = 250\mu\text{A}$	40			V
Gate Threshold Voltage	$V_{\text{GS}(\text{th})}$	$V_{\text{DS}} = V_{\text{GS}}, I_D = 250\mu\text{A}$	1	1.6	3	
Gate-Body Leakage	I_{GSS}	$V_{\text{DS}} = 0\text{V}, V_{\text{GS}} = \pm 20\text{V}$			± 100	nA
Zero Gate Voltage Drain Current	I_{DSS}	$V_{\text{DS}} = 32\text{V}, V_{\text{GS}} = 0\text{V}$			1	
		$V_{\text{DS}} = 30\text{V}, V_{\text{GS}} = 0\text{V}, T_J = 55^\circ\text{C}$			10	μA
Drain-Source On-State Resistance ¹	$R_{\text{DS}(\text{ON})}$	$V_{\text{GS}} = 4.5\text{V}, I_D = 12\text{A}$		13	20	
		$V_{\text{GS}} = 10\text{V}, I_D = 18\text{A}$		11	15.5	$\text{m}\Omega$
Forward Transconductance ¹	g_{fs}	$V_{\text{DS}} = 10\text{V}, I_D = 18\text{A}$		55		S
DYNAMIC						
Input Capacitance	C_{iss}	$V_{\text{GS}} = 0\text{V}, V_{\text{DS}} = 20\text{V}, f = 1\text{MHz}$		909		pF
Output Capacitance	C_{oss}			116		
Reverse Transfer Capacitance	C_{rss}			75		
Gate Resistance	R_g	$V_{\text{GS}} = 0\text{V}, V_{\text{DS}} = 0\text{V}, f = 1\text{MHz}$		2		Ω
Total Gate Charge ²	$Q_{\text{g}(\text{VGS}=10\text{V})}$	$V_{\text{DS}} = 20\text{V}, I_D = 18\text{A}$		19		nC
	$Q_{\text{g}(\text{VGS}=4.5\text{V})}$			10		
Gate-Source Charge ²	Q_{gs}			2.4		
Gate-Drain Charge ²	Q_{gd}			5.2		
Turn-On Delay Time ²	$t_{\text{d}(\text{on})}$			12		
Rise Time ²	t_r	$V_{\text{DD}} = 0\text{V}$ $I_D \approx 18\text{A}, V_{\text{GEN}} = 10\text{V}, R_G = 6\Omega$		72		nS
Turn-Off Delay Time ²	$t_{\text{d}(\text{off})}$			36		
Fall Time ²	t_f			118		
SOURCE-DRAIN DIODE RATINGS AND CHARACTERISTICS ($T_J = 25^\circ\text{C}$)						
Continuous Current ³	I_S				21	A
Forward Voltage ¹	V_{SD}	$I_F = 18\text{A}, V_{\text{GS}} = 0\text{V}$			1.3	V
Reverse Recovery Time	t_{rr}	$I_F = 18\text{A}, dI_F/dt = 100\text{A} / \mu\text{s}$		9.2		nS
Reverse Recovery Charge	Q_{rr}			2.9		nC


¹Pulse test : Pulse Width $\leq 300 \mu\text{sec}$, Duty Cycle $\leq 2\%$.²Independent of operating temperature.

NIKO-SEM


**Dual N-Channel Enhancement Mode
Field Effect Transistor**

PE6R8DX
PDFN 3x3P
Halogen-Free & Lead-Free


Output Characteristics




Transfer Characteristics




Gate charge Characteristics




Capacitance Characteristic








On-Resistance VS Gate-To-Source Voltage



On-Resistance VS Drain Current




NIKO-SEM
**Dual N-Channel Enhancement Mode
Field Effect Transistor**
PE6R8DX
PDFN 3x3P
Halogen-Free & Lead-Free


NIKO-SEM


**Dual N-Channel Enhancement Mode
Field Effect Transistor**

PE6R8DX
PDFN 3x3P
Halogen-Free & Lead-Free

Safe Operating Area



Single Pulse Maximum Power Dissipation



Transient Thermal Response Curve

