

SKM200GBD126D



SEMITRANS® 3

Trench IGBT Modules

SKM200GBD126D

Features


- Trench = Trenchgate technology
- $V_{CE(sat)}$ with positive temperature coefficient
- High short circuit capability, self limiting to $6 \times I_C$
- UL recognized, file no. E63532

Typical Applications*

- Current source inverter

Remarks

- The Fig.1 to Fig.9 are based on measurements of the SKM200GB126D
- The series diodes (FWD) have the data of the inverse diodes of the SKM300GB126D



GBD

Absolute Maximum Ratings

Symbol	Conditions	Values	Unit
IGBT			
V_{CES}	$T_j = 25\text{ °C}$	1200	V
I_C	$T_j = 150\text{ °C}$	$T_c = 25\text{ °C}$	264
		$T_c = 80\text{ °C}$	186
I_{Cnom}		150	A
I_{CRM}	$I_{CRM} = 2 \times I_{Cnom}$	300	A
V_{GES}		-20 ... 20	V
t_{psc}	$V_{CC} = 900\text{ V}$	$T_j = 125\text{ °C}$	10
	$V_{GE} \leq 15\text{ V}$		
	$V_{CES} \leq 1200\text{ V}$		
T_j		-40 ... 150	°C
Inverse diode			
V_{RRM}	$T_j = 25\text{ °C}$	1200	V
I_F	$T_j = 150\text{ °C}$	$T_c = 25\text{ °C}$	34
		$T_c = 80\text{ °C}$	23
I_{Fnom}		30	A
I_{FRM}	$I_{FRM} = 2 \times I_{Fnom}$	60	A
I_{FSM}	$t_p = 10\text{ ms, sin } 180^\circ, T_j = 25\text{ °C}$	414	A
T_j		-40 ... 150	°C
Freewheeling diode			
V_{RRM}	$T_j = 25\text{ °C}$	1200	V
I_F	$T_j = 150\text{ °C}$	$T_c = 25\text{ °C}$	250
		$T_c = 80\text{ °C}$	169
I_{Fnom}		200	A
I_{FRM}	$I_{FRM} = 2 \times I_{Fnom}$	400	A
I_{FSM}	$t_p = 10\text{ ms, sin } 180^\circ, T_j = 25\text{ °C}$	1656	A
T_j		-40 ... 150	°C
Module			
$I_{t(RMS)}$		500	A
T_{stg}	module without TIM	-40 ... 125	°C
V_{isol}	AC sinus 50 Hz, $t = 1\text{ min}$	4000	V

Characteristics

Symbol	Conditions	min.	typ.	max.	Unit
IGBT					
$V_{CE(sat)}$	$I_C = 150\text{ A}$ $V_{GE} = 15\text{ V}$ chipelevel	$T_j = 25\text{ °C}$	1.71	2.10	V
		$T_j = 125\text{ °C}$	2.00	2.45	V
V_{CE0}	chipelevel	$T_j = 25\text{ °C}$	1.00	1.20	V
		$T_j = 125\text{ °C}$	0.90	1.10	V
r_{CE}	$V_{GE} = 15\text{ V}$ chipelevel	$T_j = 25\text{ °C}$	4.7	6.0	mΩ
		$T_j = 125\text{ °C}$	7.3	9.0	mΩ
$V_{GE(th)}$	$V_{GE} = V_{CE}, I_C = 6\text{ mA}$	5	5.8	6.5	V
I_{CES}	$V_{GE} = 0\text{ V}, V_{CE} = 1200\text{ V}, T_j = 25\text{ °C}$			2.0	mA
C_{ies}	$V_{CE} = 25\text{ V}$ $V_{GE} = 0\text{ V}$	$f = 1\text{ MHz}$	10.7		nF
C_{oes}		$f = 1\text{ MHz}$	0.56		nF
C_{res}		$f = 1\text{ MHz}$	0.48		nF
Q_G	$V_{GE} = -8\text{ V...} + 20\text{ V}$		1530		nC
R_{Gint}	$T_j = 25\text{ °C}$		5.0		Ω



SEMITRANS® 3

Trench IGBT Modules

SKM200GBD126D

Features

- Trench = Trenchgate technology
- $V_{CE(sat)}$ with positive temperature coefficient
- High short circuit capability, self limiting to $6 \times I_C$
- UL recognized, file no. E63532


Typical Applications*

- Current source inverter

Remarks

- The Fig.1 to Fig.9 are based on measurements of the SKM200GB126D
- The series diodes (FWD) have the data of the inverse diodes of the SKM300GB126D

Characteristics						
Symbol	Conditions		min.	typ.	max.	Unit
IGBT						
$t_{d(on)}$	$V_{CC} = 600\text{ V}$	$T_j = 125\text{ °C}$		260		ns
t_r	$I_C = 150\text{ A}$	$T_j = 125\text{ °C}$		40		ns
E_{on}	$V_{GE} = +15/-15\text{ V}$	$T_j = 125\text{ °C}$		18		mJ
$t_{d(off)}$	$R_{G\ on} = 1.5\ \Omega$	$T_j = 125\text{ °C}$		540		ns
t_f	$R_{G\ off} = 1.5\ \Omega$	$T_j = 125\text{ °C}$		110		ns
E_{off}		$T_j = 125\text{ °C}$		24		mJ
$R_{th(j-c)}$	per IGBT				0.13	K/W
$R_{th(c-s)}$	per IGBT ($\lambda_{grease}=0.81\text{ W/(m}^2\text{K)}$)			0.036		K/W
$R_{th(c-s)}$	per IGBT, pre-applied phase change material			0.033		K/W
Inverse diode						
$V_F = V_{EC}$	$I_F = 30\text{ A}$	$T_j = 25\text{ °C}$		2.00	2.50	V
	$V_{GE} = 0\text{ V}$	$T_j = 125\text{ °C}$		1.80	2.30	V
	chipelevel					
V_{F0}		$T_j = 25\text{ °C}$		1.10	1.45	V
	chipelevel	$T_j = 125\text{ °C}$		0.85	1.20	V
r_F		$T_j = 25\text{ °C}$		30	35	m Ω
	chipelevel	$T_j = 125\text{ °C}$		32	37	m Ω
I_{RRM}	$I_F = 15\text{ A}$	$T_j = 125\text{ °C}$		12		A
Q_{rr}	$di/dt_{off} = 150\text{ A}/\mu\text{s}$	$T_j = 125\text{ °C}$		1		μC
E_{rr}	$V_{GE} = \pm 15\text{ V}$	$T_j = 125\text{ °C}$		-		mJ
	$V_{CC} = 600\text{ V}$					
$R_{th(j-c)}$	per diode				1.5	K/W
$R_{th(c-s)}$	per diode ($\lambda_{grease}=0.81\text{ W/(m}^2\text{K)}$)			0.078		K/W
$R_{th(c-s)}$	per diode, pre-applied phase change material			0.076		K/W
Freewheeling diode						
$V_F = V_{EC}$	$I_F = 200\text{ A}$	$T_j = 25\text{ °C}$		1.60	1.80	V
	$V_{GE} = 0\text{ V}$	$T_j = 125\text{ °C}$		1.60	1.80	V
	chipelevel					
V_{F0}		$T_j = 25\text{ °C}$		1.00	1.10	V
	chipelevel	$T_j = 125\text{ °C}$		0.80	0.90	V
r_F		$T_j = 25\text{ °C}$		3.0	3.5	m Ω
	chipelevel	$T_j = 125\text{ °C}$		4.0	4.5	m Ω
I_{RRM}	$I_F = 200\text{ A}$	$T_j = 125\text{ °C}$		290		A
Q_{rr}	$di/dt_{off} = 6200\text{ A}/\mu\text{s}$	$T_j = 125\text{ °C}$		44		μC
E_{rr}	$V_{GE} = \pm 15\text{ V}$	$T_j = 125\text{ °C}$		18		mJ
	$V_{CC} = 600\text{ V}$					
$R_{th(j-c)}$	per diode				0.25	K/W
$R_{th(c-s)}$	per diode ($\lambda_{grease}=0.81\text{ W/(m}^2\text{K)}$)			0.043		K/W
$R_{th(c-s)}$	per diode, pre-applied phase change material			0.041		K/W



GBD

SKM200GBD126D



SEMITRANS® 3

Trench IGBT Modules

SKM200GBD126D

Features

- Trench = Trenchgate technology
- $V_{CE(sat)}$ with positive temperature coefficient
- High short circuit capability, self limiting to $6 \times I_C$
- UL recognized, file no. E63532


Typical Applications*

- Current source inverter

Remarks

- The Fig.1 to Fig.9 are based on measurements of the SKM200GB126D
- The series diodes (FWD) have the data of the inverse diodes of the SKM300GB126D

Characteristics						
Symbol	Conditions		min.	typ.	max.	Unit
Module						
L_{CE}				15		nH
$R_{CC'+EE'}$	measured per switch	$T_C = 25\text{ °C}$		0.35		mΩ
		$T_C = 125\text{ °C}$		0.5		mΩ
$R_{th(c-s)1}$	per module			0.01		K/W
$R_{th(c-s)2}$	including thermal coupling, T_s underneath module ($\lambda_{grease}=0.81\text{ W/(m}^2\text{K)}$)			0.015		K/W
$R_{th(c-s)2}$	including thermal coupling, T_s underneath module, pre-applied phase change material			0.014		K/W
M_s	to heat sink M6		3		5	Nm
M_t	to terminals M6				5	Nm
						Nm
w					325	g



GBD




Fig. 1: Typ. output characteristic, inclusive R_{CC+EE}




Fig. 2: Rated current vs. temperature $I_C = f(T_C)$




Fig. 3: Typ. turn-on /-off energy = $f(I_C)$




Fig. 4: Typ. turn-on /-off energy = $f(R_G)$




Fig. 5: Typ. transfer characteristic




Fig. 6: Typ. gate charge characteristic




Fig. 7: Typ. switching times vs. I_C




Fig. 8: Typ. switching times vs. gate resistor R_G




Fig. 9: Transient thermal impedance of IGBT
 $Z_{th(j-c)} = f(t_p)$; $D = t_p/t_c = t_p * f$




Fig. 10: Transient thermal impedance of FWD
 $Z_{th(j-c)} = f(t_p)$; $D = t_p/t_c = t_p * f$




Fig. 11: CAL diode forward charact., incl. $R_{CC'+EE}$






Fig. 12: Typ. CAL diode peak reverse recovery current

SKM200GBD126D



SEMITRANS 3



This is an electrostatic discharge sensitive device (ESDS), international standard IEC 60747-1, chapter IX.

***IMPORTANT INFORMATION AND WARNINGS**

The specifications of SEMIKRON products may not be considered as guarantee or assurance of product characteristics ("Beschaffenheitsgarantie"). The specifications of SEMIKRON products describe only the usual characteristics of products to be expected in typical applications, which may still vary depending on the specific application. Therefore, products must be tested for the respective application in advance. Application adjustments may be necessary. The user of SEMIKRON products is responsible for the safety of their applications embedding SEMIKRON products and must take adequate safety measures to prevent the applications from causing a physical injury, fire or other problem if any of SEMIKRON products become faulty. The user is responsible to make sure that the application design is compliant with all applicable laws, regulations, norms and standards. Except as otherwise explicitly approved by SEMIKRON in a written document signed by authorized representatives of SEMIKRON, SEMIKRON products may not be used in any applications where a failure of the product or any consequences of the use thereof can reasonably be expected to result in personal injury. No representation or warranty is given and no liability is assumed with respect to the accuracy, completeness and/or use of any information herein, including without limitation, warranties of non-infringement of intellectual property rights of any third party. SEMIKRON does not assume any liability arising out of the applications or use of any product; neither does it convey any license under its patent rights, copyrights, trade secrets or other intellectual property rights, nor the rights of others. SEMIKRON makes no representation or warranty of non-infringement or alleged non-infringement of intellectual property rights of any third party which may arise from applications. Due to technical requirements our products may contain dangerous substances. For information on the types in question please contact the nearest SEMIKRON sales office. This document supersedes and replaces all information previously supplied and may be superseded by updates. SEMIKRON reserves the right to make changes.