



SP988

Simple ORing Controller

DESCRIPTION

The SP988 is an ORing FET Controller for use in a power supply and/or power system. When it is operated in conjunction with an MOSFET, it functions as an ideal diode when connected with a power source. This ORing controller allows MOSFET to replace diode rectifier in power distribution system thus reducing both power loss and voltage drops. The FET may be electrically connected between an input and an output.

With low external component counts, SP988 is a low cost solution for the applications.

SP988 is available in SOT-23-6L package.

FEATURES


- Low saturation voltage
- 500mW power dissipation
- 2A Peak Gate Turnoff Current
- Ideally suited for space / weight critical applications
- SOT-23-6L Package

APPLICATIONS

- Battery Charger
- Open-Frame Switching Power Supply
- LED Power Supply
- Active ORing of Redundant (N+1) Power Supplies


PIN CONFIGURATION

SOT-23-6L



PART MARKING

SOT-23-6L




Y : Year Code
W : Week Code



SP988 Simple ORing Controller


TYPICAL APPLICATION CIRCUIT



PIN DESCRIPTION

Pin	Symbol	Description
1	BIAS	Bias
2	OUT	Voltage sense connection to the external MOSFET Drain pin.
3	NC	Unconnected pin
4	IN	Voltage sense connection to the external MOSFET Source pin.
5	GATE	Gate driver output to drive the external MOSFET.
6	NC	Unconnected pin

BLOCK DIAGRAM



ORDERING INFORMATION

Part Number	Package	Part Marking
SP988S26RGB	SOT-23-6L	988YW

※ SP988S26RGB : Tape Reel ; Pb – Free ; Halogen-Free



SP988

Simple ORing Controller

ABSOLUTE MAXIMUM RATINGS (T_A=25°C, unless otherwise specified.)

The following ratings designate persistent limits beyond which damage to the device may occur.

Symbol	Parameter	Value	Unit
P _D	Power Dissipation @ T _A =85°C (*)	0.3	W
ESD	Human Body Model	2	KV
	Machine Model	200	V
T _J	Operating Junction Temperature Range	-40 ~ 150	°C
T _{STG}	Storage Temperature Range	-40 ~ 150	°C
R _{θJC}	Thermal Resistance Junction – Case (*)	SOT-23-6L 210	°C/W

(*) The power dissipation and thermal resistance are evaluated under copper board mounted with free air conditions.

ELECTRICAL CHARACTERISTICS

(T_A=25°C, unless otherwise specified.)

Symbol	Parameter	Conditions	Min.	Typ.	Max.	Unit
V _{set}	V _{in} -V _{out}	I _{GATE} =I _{BIAS} =1mA		10		mV
V _{IN-BIAS}		Leakage Current	60			V
V _{GATE-IN}		Leakage Current	60			V



SP988

Simple ORing Controller

Information provided is alleged to be exact and consistent. SYNC Power Corporation presumes no responsibility for the penalties of use of such information or for any violation of patents or other rights of third parties that may result from its use. No license is granted by allegation or otherwise under any patent or patent rights of SYNC Power Corporation. Conditions mentioned in this publication are subject to change without notice. This publication surpasses and replaces all information previously supplied. SYNC Power Corporation products are not authorized for use as critical components in life support devices or systems without express written approval of SYNC Power Corporation.

© The SYNC Power logo is a registered trademark of SYNC Power Corporation

© 2023 SYNC Power Corporation – Printed in Taiwan – All Rights Reserved

SYNC Power Corporation

7F-2, No.3-1, Park Street

NanKang District (NKSP), Taipei, Taiwan, 115, R.O.C

Phone: 886-2-2655-8178

Fax: 886-2-2655-8468

<http://www.syncpower.com>