# SPE0521 Single-Line ESD Protection Array

### DESCRIPTION

The SPE0521 are designed by TVS bi-direction device that is to protect sensitive electronics from damage or latch-up due to ESD. They are designed for use in applications where board space is at a premium. SPE0521 will protect single line, and may be used on line where the signal polarities swing above and below ground.

SPE0521 offer desirable characteristics for board level protection including fast response time, low operating and clamping voltage, and no device degradation.

SPE0521 may be used to meet the immunity requirements of IEC 61000-4-2, level 4. The small SOD-523 package makes them ideal for use in portable electronics such as cell phones, PDA's, notebook computers, and digital cameras.

## **APPLICATIONS**

- Cellular Handsets and Accessories
- Cordless Phone
- ♦ PDA
- Notebooks and Handhelds
- Portable Instrumentation
- Digital Cameras
- MP3 Player

## FEATURES

- Transient protection for data lines to IEC 61000-4-2 (ESD) ±15kV (air), ±8kV (contact) IEC 61000-4-4 (EFT) 40A (5/50ns)
- Protects single I/O lines
- ♦ Working voltage: 5V
- Low leakage current
- Low operating and clamping voltages



**PIN CONFIGURATION (SOD-523)** 

#### PART MARKING





### **ORDERING INFORMATION**

Part Number	Package	Part Marking
SPE0521D52RGB	SOD-523	0

X SPE0521D52RGB : Tape Reel ; Pb – Free; Halogen – Free

Date code format on label : YW
Y: year code ( ext. 2011 : 1; 2012: 2)

W: week code (A~Z, a~z,@)

# ABSOULTE MAXIMUM RATINGS

(TA=25°C Unless otherwise noted)

Parameter	Symbol	Typical	Unit
Peak Pulse Power ( $tp = 8/20 \ \mu s$ )	Ppk	250	W
Maximum Peak Pulse Current ( $tp = 8/20 \ \mu s$ )	Ipp	7	А
ESD per ICE 61000 – 4 – 2 (Air )	Vpp	±15	KV
ESD per ICE 61000 – 4 – 2 (Contact )	Vpp	$\pm 8$	KV
Operating Junction Temperature	TJ	-55 ~ 150	°C
Storage Temperature Range	Tstg	-55 ~ 150	°C
Lead Soldering Temperature	TL	260 (10sec)	°C


## ELECTRICAL CHARACTERISTICS

(TA=25°C Unless otherwise noted)

Parameter	Symbol	Conditions	Min.	Тур	Max.	Unit
Reverse Stand – Off Voltage	Vrwm				5	V
Reverse Breakdown Voltage	Vbr	It = 1mA	6			V
Reverse Leakage Current	Ir	$V_{RWM} = 5V$ , $T=25^{\circ}C$		0.01	1	μΑ
Reverse Leakage Current	Ir	$V_{RWM} = 3V$ , $T=25^{\circ}C$		0.01	0.5	μΑ
Clamping Voltage	Vc	Ipp = 1A , tp = $8/20 \ \mu s$			13	V
Clamping Voltage	Vc	Ipp = 7A , tp = $8/20 \ \mu s$			15	V
Junction Capacitance	Cj	Between I/O Pin and GND $V_R = 0V$ , $f = 1MHz$		5	10	pF



## TYPICAL CHARACTERISTICS



2020/06/03 Ver.7

# SPE0521 Single-Line ESD Protection Array

# TYPICAL CHARACTERISTICS




Fig 1 : Junction Capacitance V.S Reverse Voltage Applied




Fig 2 : Peak Plus Power V.S Exponential Plus Duration




Fig 3 : Relative Variation of Peal Plus Power V.S Initial Junction Temperature




Fig 4 : Forward Voltage Drop V.S Peak Forward Current



Information provided is alleged to be exact and consistent. SYNC Power Corporation presumes no responsibility for the penalties of use of such information or for any violation of patents or other rights of third parties which may result from its use. No license is granted by allegation or otherwise under any patent or patent rights of SYNC Power Corporation. Conditions mentioned in this publication are subject to change without notice. This publication surpasses and replaces all information previously supplied. SYNC Power Corporation products are not authorized for use as critical components in life support devices or systems without express written approval of SYNC Power Corporation.

© The SYNC Power logo is a registered trademark of SYNC Power Corporation © 2020 SYNC Power Corporation – Printed in Taiwan – All Rights Reserved SYNC Power Corporation 7F-2, No.3-1, Park Street NanKang District (NKSP), Taipei, Taiwan, 115, R.O.C Phone: 886-2-2655-8178 Fax: 886-2-2655-8468 © http://www.syncpower.com

